

RF Exposure Report

Report No.: SA160205C08H

FCC ID: PY315300322

Test Model: EX6400

Received Date: Nov. 01, 2016

Test Date: Dec. 02 ~ Dec. 27, 2016

Issued Date: Jan. 09, 2017

Applicant: NETGEAR, INC.

Address: 350 East Plumeria Drive San Jose, CA 95134

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan (R.O.C.)

Test Location: No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City 33383, TAIWAN (R.O.C.)



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.

Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
3 Calculation Result of Maximum Conducted Power	6

Release Control Record

Issue No.	Description	Date Issued
SA160205C08H	Original release.	Jan. 09, 2017

1 Certificate of Conformity

Product: AC1900 WiFi Range Extender

Brand: NETGEAR

Test Model: EX6400

Sample Status: Engineering sample

Applicant: NETGEAR, INC.

Test Date: Dec. 02 ~ Dec. 27, 2016

Standards: FCC Part 2 (Section 2.1091)

KDB 447498 D01 General RF Exposure Guidance v06

IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by : Sunt Lee , **Date:** Jan. 09, 2017
Sunt Lee / Specialist

Approved by : Ken Liu , **Date:** Jan. 09, 2017
Ken Liu / Senior Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 26cm away from the body of the user. So, this device is classified as Mobile Device.

3 Calculation Result of Maximum Conducted Power

CDD Mode

Band	Modulation type	Frequency (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2412~2462Hz	802.11b	2412	23.75	5.02	26	0.089	1
		2437	25.48	5.57	26	0.150	1
		2462	23.75	6.25	26	0.118	1
	802.11g	2412	20.96	5.02	26	0.047	1
		2437	25.58	5.57	26	0.153	1
		2462	22.13	6.25	26	0.081	1
	802.11n (HT20)	2412	19.75	5.02	26	0.035	1
		2437	25.76	5.57	26	0.160	1
		2462	19.95	6.25	26	0.049	1
	802.11n (HT40)	2422	17.45	5.12	26	0.021	1
		2437	19.85	5.57	26	0.041	1
		2452	17.85	5.93	26	0.028	1
5180~5240MHz	802.11a	5180	27.13	8.60	26	0.440	1
		5200	28.04	8.76	26	0.563	1
		5240	27.39	9.01	26	0.514	1
	802.11ac (VHT20)	5180	27.11	8.60	26	0.438	1
		5200	27.90	8.76	26	0.546	1
		5240	27.20	9.01	26	0.492	1
	802.11ac (VHT40)	5190	25.66	8.64	26	0.317	1
		5230	27.46	8.89	26	0.508	1
	802.11ac (VHT80)	5210	25.76	8.87	26	0.342	1
5250~5350MHz	802.11a	5260	20.35	9.01	26	0.102	1
		5300	20.43	8.98	26	0.103	1
		5320	20.41	9.08	26	0.105	1
	802.11ac (VHT20)	5260	20.51	9.01	26	0.105	1
		5300	20.54	8.98	26	0.105	1
		5320	20.48	9.08	26	0.106	1
	802.11ac (VHT40)	5270	22.00	9.01	26	0.149	1
		5310	21.44	9.08	26	0.133	1
	802.11ac (VHT80)	5290	21.01	8.98	26	0.117	1
5470~5725MHz	802.11a	5500	20.48	8.97	26	0.104	1
		5580	20.42	9.13	26	0.106	1
		5700	20.49	9.41	26	0.115	1
	802.11ac (VHT20)	5500	20.44	8.97	26	0.103	1
		5580	20.48	9.13	26	0.108	1
		5700	20.47	9.41	26	0.115	1
	802.11ac (VHT40)	5510	21.27	9.05	26	0.127	1
		5550	21.76	9.28	26	0.150	1
		5670	22.22	9.39	26	0.171	1
	802.11ac (VHT80)	5530	23.87	9.17	26	0.237	1
		5610	23.75	9.31	26	0.238	1
5745~5825MHz	802.11a	5745	28.77	9.39	26	0.771	1
		5785	28.76	9.56	26	0.800	1
		5825	28.76	9.63	26	0.813	1
	802.11ac (VHT20)	5745	28.72	9.39	26	0.762	1
		5785	28.73	9.56	26	0.794	1
		5825	28.75	9.63	26	0.811	1
	802.11ac (VHT40)	5755	28.79	9.47	26	0.789	1
		5795	28.80	9.61	26	0.816	1
	802.11ac (VHT80)	5775	28.71	9.56	26	0.790	1

Beamforming Mode

Band	Modulation type	Frequency (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5180~5240MHz	802.11ac (VHT20)	5180	26.99	8.60	26	0.426	1
		5200	26.99	8.76	26	0.442	1
		5240	26.89	9.01	26	0.458	1
	802.11ac (VHT40)	5190	25.43	8.64	26	0.300	1
		5230	27.07	8.89	26	0.464	1
	802.11ac (VHT80)	5210	25.26	8.87	26	0.305	1
5250~5350MHz	802.11ac (VHT20)	5260	20.51	9.01	26	0.105	1
		5300	20.54	8.98	26	0.105	1
		5320	20.48	9.08	26	0.106	1
	802.11ac (VHT40)	5270	20.50	9.01	26	0.105	1
		5310	20.44	9.08	26	0.105	1
	802.11ac (VHT80)	5290	19.73	8.98	26	0.087	1
5470~5725MHz	802.11ac (VHT20)	5500	20.44	8.97	26	0.103	1
		5580	20.48	9.13	26	0.108	1
		5700	20.47	9.41	26	0.115	1
	802.11ac (VHT40)	5510	20.71	9.05	26	0.111	1
		5550	20.66	9.28	26	0.116	1
		5670	20.58	9.39	26	0.117	1
	802.11ac (VHT80)	5530	20.68	9.17	26	0.114	1
		5610	20.63	9.31	26	0.116	1
5745~5825MHz	802.11ac (VHT20)	5745	26.42	9.39	26	0.449	1
		5785	26.43	9.56	26	0.468	1
		5825	26.34	9.63	26	0.465	1
	802.11ac (VHT40)	5755	26.49	9.47	26	0.464	1
		5795	26.38	9.61	26	0.468	1
	802.11ac (VHT80)	5775	26.41	9.56	26	0.465	1

Note:

2412MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.02\text{dBi}$
2437MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.57\text{dBi}$
2462MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 6.25\text{dBi}$
2422MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.12\text{dBi}$
2452MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 5.93\text{dBi}$
5180MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.60\text{dBi}$
5200MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.76\text{dBi}$
5240MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
5190MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.64\text{dBi}$
5230MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.89\text{dBi}$
5210MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.87\text{dBi}$
5260MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
5300MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.98\text{dBi}$
5320MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.08\text{dBi}$
5270MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.01\text{dBi}$
5310MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 9.08\text{dBi}$
5290MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N] = 8.98\text{dBi}$

5500MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 8.97dBi
 5580MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.13dBi
 5700MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.41dBi
 5510MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.05dBi
 5550MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.28dBi
 5670MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.39dBi
 5530MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.17dBi
 5610MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.31dBi
 5745MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.39dBi
 5785MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.56dBi
 5825MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.63dBi
 5755MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.47dBi
 5795MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.61dBi
 5775MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/N]$ = 9.56dBi

Conclusion:

The formula of calculated the MPE is:

CPD1 / LPD1 + CPD2 / LPD2 +etc. < 1

CPD = Calculation power density

LPD = Limit of power density

WLAN 2.4GHz + WLAN 5GHz = 0.160 + 0.816 = 0.976 < 1

---END---