

155940				NOTICE TO PERSONS RECEIVING THIS DRAWING AND/OR TECHNICAL INFORMATION: Checkpoint Systems claims proprietary rights to the material disclosed hereon. This drawing and/or technical information is issued in confidence for engineering information only and may not be reproduced or used to manufacture anything shown or referred to hereon without direct written permission from Checkpoint Systems to the user. This drawing and/or technical information is the property of Checkpoint Systems and is loaned for mutual assistance, to be returned when its purpose has been served. THIS DRAWING AND/OR TECHNICAL INFORMATION IS THE PROPERTY OF CHECKPOINT SYSTEMS, INC.			
Title: TEST PROCEDURE PORTABLE R/O READER PRRO7100							
Revisions				Revisions			
Rev	Description	Date	Engineer	Rev	Description	Date	Approved
*60	CR2478		R. BARBER				



Table of Contents

1.0 INTRODUCTION..... 3

2.0 REQUIRED EQUIPMENT 3

3.0 COMPUTER PREPARATION 3

4.0 SYSTEM TEST..... 3

5.0 TEST DATA SHEET 4

1.0 INTRODUCTION

The purpose of this document is to provide the information necessary to perform a system-level test of the PRRO 7100 Reader.

2.0 REQUIRED EQUIPMENT

- RFID test tag
- Computer with Microsoft hyperterminal
- DB9 to RJ 41 cable (Checkpoint Part # 281876)
- Fully charged PRRO7100 test battery*

3.0 COMPUTER PREPARATION

- 3.1 Connect the serial DB9 to RJ 41 cable to the UUT and computer
- 3.2 Run Microsoft Hyperterminal
- 3.3 Click on File, Properties
- 3.4 Click on "Connect Using" and select Com 2
- 3.5 Click on Configure
- 3.6 Select 9600 8,N,1
- 3.7 Click on OK
- 3.8 Click on Settings
- 3.9 Click on ASCII Setup
- 3.10 Select "Send line ends with linefeeds"
- 3.11 Click on "OK"
- 3.12 Click on "OK"

4.0 SYSTEM TEST

- 4.1 Insert a fully charged PRRO battery into the UUT
- 4.2 Hit enter on the keyboard
- 4.3 Verify that the PRRO7100 Ready light is active (Green LED on)
- 4.4 *Record as pass or fail*
- 4.5 Place a calibrated test tag at 12 inches parallel carry from the antenna
- 4.6 *Verify that the red Tag led is blinking*
- 4.7 *Verify that tag data is seen scrolling across the screen*
- 4.8 *Record Maximum Detection distance*
- 4.9 Enter "B1" followed by enter on the keyboard
- 4.10 Verify that the reader returns the current baud rate
- 4.11 *Record as pass or fail*
- 4.12 Click on Call and select "Disconnect"
- 4.13 *Verify that the reader shuts off (No LEDs lit)*

* Do not use the unit battery. This is to be charged at the customer site only.
--

5.0 TEST DATA SHEET

Line 4.4	Ready light	_____	Pass/Fail
Line 4.6	Red LED blinking	_____	Pass/Fail
Line 4.7	Tag Data scrolling	_____	Pass/Fail
Line 4.8	Maximum detection distance	_____	>12 inches
Line 4.11	Baud rate message	_____	Pass/Fail
Line 4.13	DTR Power Off	_____	Pass/Fail