

SONOFF

DIY D1

User manual V1.0



Wi-Fi Smart Dimmer Switch

·中文-----1-3
·Deutsch-----8-11
·Fran çais-----16-19
·Русский язык-----24-27

·English-----4-7
·Español-----12-15
·Italiano-----20-23

Specifications

Model	D1
Input	100-240V AC 50/60Hz
Output	100-240V AC 50/60Hz
Light Load	Incandescent: 200W LED:150W
Operating systems	(Android 4.1 & iOS 9.0) or higher
Wi-Fi	IEEE 802.11 b/g/n 2.4GHz
Material	PC
Dimension	62x47x32.5mm

Features

D1 is a Wi-Fi smart dimmer switch that is used to adjust the light brightness and set various atmosphere for your room. You can remotely turn on/off light of your home anywhere, schedule it on/off, or share it with your family to control together.




Remote Control



Single/Countdown
Timing



Voice Control



Share Control



Brightness Adjustment



Scene Mode



Sync Status



LAN Control

Buttons	Functions
	On
	Off
	Short press for the low brightness, long press to turn down the brightness
	Short press for the medium brightness, long press to turn down the brightness
	Short press for the higher brightness, long press to turn up the brightness
	Short press for the high brightness, long press to turn up the brightness
	Long press for 5s until you hear "Bi Bi" and release, then the remote controller is cleared successfully. If you need to use, short press any button within 5s after powering on again and you will hear "Bi", which indicates the remote controller is paired successfully.
	Long press for 5s until the connected light enters the breathing mode, which indicates the device enters quick pairing mode (Touch), then you can add the light on eWeLink APP. In quick pairing mode, you can short press any button on the remote controller to exit this mode.

Factory Reset

Turn on and off 3 times on repeatedly or delete the connected light on eWeLink APP until it enters “breathing mode”, then the device is reset successfully and enters quick pairing mode (Touch).



- ⚠ Please reset the switch to factory defaults if you want to use other Wi-Fi networks, then reconnect the network.

FCC Warning

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

Radiation Exposure Statement

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

FCC ID: 2APN5D1

SONOFF

Shenzhen Sonoff Technologies Co., Ltd.

Room 1001, 10F, Building 8, Lianhua Industrial Park,

Longyuan Road, Longhua District, Shenzhen, GD,

China

<https://sonoff.tech>

MADE IN CHINA

