

# Power Bank 4000mAh

## User Manual

### Contents

1.0 INTRODUCTION .....	1
2.0 FEATURES .....	1
3.0 SPECIFICATIONS.....	2
4.0 PACKAGE CONTENTS .....	2
5.0 PRODUCT SHOW .....	3
6.0 OPERATION .....	4

# Power Bank 4000mAh

## DEAR CUSTOMER

Thank you for purchasing this product. For optimum performance and safety, please read these instructions carefully before connecting, operating or using this product. Please keep this manual for future reference.

## 1.0 INTRODUCTION

The fashion design, the TYPE - C - PD&QC charging input design, this product keep your digital devices. It has a 4000 mah lithium-ion batteries, it supports the TYPE - C - PD&QC output and magnetic suction wireless charging output, specifically for your business travel, meetings, adventure, camping, or travel and so on.

## 2.0 FEATURES

- 4000mAh large capacity
- Polymer lithium battery
- TYPE-C-PD&QC Input: 5V/3A 9V/1.67A
- Outputs:
  - Output1: 5V/3A, 9V/2A support PD&QC charging technology
  - Output2: Magnetic suction wireless charger 5 W / 7.5 W / 10 W
- Total output:18W
- Overcharge and over-discharge protection
- Input over voltage protection and output over voltage protection
- Output current protection and short circuit protection
- Automatic power-off
- Intelligent LED battery indicators
- Compliant with CE,FCC,UN38.3

### 3.0 SPECIFICATIONS

Input	TYPE-C-PD&QC:5V/3A 9V/1.67A
Output	Output1: TYPE-C-PD&QC:5V/3A 9V/2A Output2: Magnetic suction wireless charger 5 W / 7.5 W / 10 W Total output:18W
Over Current Protection	Yes
Over Voltage Protection	Yes
Short circuit Protection	Yes
Over Temperature Protection	Yes
Ripple And Noise	≤350mVp-p@5V/9V
Operating Temperature Range	0~ 40°C
Storage Temperature Range	-5~45°C
Operating Humidity	20~90%RH
Storage Humidity	45~85%RH
Color	Black
Size(L*W*H)	107*69.7*15.25mm
Weight	144±10g
Efficiency	≥85%
Certification	CE,FCC,UN38.3
User Manual	English Version

### 4.0 PACKAGE CONTENTS

Before attempting to use this unit, please check the packaging and make sure the following items are contained in the shipping carton:

- Main unit×1
- User Manual×1

## 5.0 PRODUCT SHOW



1. Button: Open the wireless charger and battery indicator
2. Four LED indicator lights:

Press button to start up:

LED indicator status	Battery Percentage	Remark
○○○○	0 %	All LEDs is off
◎○○○	1% ----- 5%	1 the LED flashing
●○○○	5% ----- 25%	1 LED light on
●●○○	25% ----- 50%	2 LEDs light on
●●●○	50% ----- 75%	3 LEDs light on
●●●●	75% ----- 100%	All LEDs light on

During charging:

LED indicator status	Battery Percentage	Remark
◎○○○	1% ----- 24%	The current LED indicator light flashing
●◎○○	25% -----49%	The current LED indicator light flashing
●●◎○	50% ----- 74%	The current LED indicator light flashing
●●●◎	75% ----- 99%	The current LED indicator light flashing
●●●●	100%	The current LED indicator light flashing

During discharging:

LED indicator status	Battery Percentage	Remark
●●●●	100%-----75%	All LED lights on
●●●○	74%-----50%	3 LED lights on
●●○○	49% ----- 25%	2 LED lights on
●○○○	24% ----- 5%	1 LED light on
◎○○○	5% ----- 1%	1 the LED flashing
○○○○	0	All LED lights off

◎ flashing      ● light on      ○ light off

3. TYPE-C Port: Support two-way charging and discharging
4. Magnetic suction wireless charge area

## 6.0 OPERATION

### Operation Procedures

a) Charge the power bank

- Connected to the charger




b) Charge the devices

- Connect your device to TYPE - C port charge



- Put your device in the wireless rechargeable batteries area



Note: Wireless charger after open when you press the buttons, as if using the TYPE - C mouth need to remove the wireless charging device and wait for the 60 s

### Operation Notes

- Please make sure the power bank is full of power before use.
- When charging with this power bank, please light up the screen on your device and check if the charging icon displays correctly.
- Please use a matched cable to charge your power bank
- Under the condition of insufficient battery, LED1 lights flashing,

- please charge as soon as possible.
- When fully charged, please unplug the charging cable timely to avoid losses.
  - When this power bank enters protection mode caused by short circuit or other reasons, please use an external charger to charge it, and then it will back to normal.
  - Do not let the power bank close to fire, such as stove, candles and etc. or expose to high temperature above 60°C.
  - Do not let the power bank soak into liquid, such as swimming pool, bathtub, etc.
  - Do not wash the power bank with corrosive cleaner.
  - Do not disassemble, squeeze, and puncture this power bank to avoid electrolyte leakage of lithium-ion battery.

## **RF exposure statement**

This equipment complies with the FCC RF radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20cm between the radiator and any part of your body.

## **FCC Warning**

This device complies with Part 18 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

P/N