

K297 SPEC

1. Scope:

The MONTEREY Keyboard K297 is 104/105 keys enhanced layout. Especially with new key support for Microsoft Windows key. It is also compatible with IBM PC AT or PS/2 and compatible personal computer.

2. Features:

- ✧ Fashion Styling
- ✧ 107/108 enhanced layout
- ✧ Multifunction keys
- ✧ Microsoft Windows compatible
- ✧ IBM PC/AT, PS/2 compatible
- ✧ Laser engraved printing
- ✧ Compact low profile

3. Specification:

3.1 Electrical Specification

3.1.1. Power Requirement


Input Voltage: DC 4.75V to 5.25V

Input Current: 300 mA max.

3.1.2. Cable Connector


3.1.2.1 DIN standard 5 pin connector pin assignment

PIN	SIGNAL
1	Clock
2	Data
3	Reserve
4	Ground
5	VCC
Shield	Frame Ground



3.1.2.2 MINI DIN 6 pin connector pin assignment

PIN	SIGNAL
1	Data
2	Reserve
3	Ground
4	VCC
5	Clock
6	Reserve
Shield	Frame Ground



3.1.3. Contact Resistance : 500 ohm Max.

3.1.4. Insulation Resistance : 100 ohm, 250V DC

3.1.5. Bounce : 10 MilliSecond

NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIIONS COULD VOID THE USER' S AUTHORITY TO OPERATE THE EQUIPMENT.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are Designed to provide reasonable protection against harmful interference in a Residential installation. This equipment generated, uses and can radiate radio Frequency energy and, if not installed and used in accordance with the Instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the Receiver is connected.

Consult the dealer or an experienced radio / TV technician for help.