









NSCT



































5 **C**

WSCT

World Standardization Certification & Testing Group (Shenzhen) Co., ltd.



W5

W5[

ion& Tes

WSC

'S C 1

Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

7.9 DYNAMIC FREQUENCY SELECTION (DFS) 7.9.1 **DFS OVERVIEW** WSET

WSET

A U-NII network will employ a DFS function to detect signals from radar systems and to avoid co-channel operation with these systems. This applies to the 5250-5350 MHz and/or 5470-5725 MHz bands. Within the context of the operation of the DFS function, a U-NII device will operate in either Master Mode or Client Mode. U-NII devices operating in Client Mode can only operate in a network controlled by a U-NII device operating in Master Mode.

WS CT

WSC7

W5C1

WSC

15 C'i

Tables 1 and 2 shown below summarize the information contained in sections 5.1.1 and 5.1.2

WSET	I

WSI

WS CI

W5

WSCI

Table 1: Applicability of DFS Requirements Prior to Use of a Channel

Requirement	Operational Mode				
	Master	Client Without Radar Detection	Client With Radar Detection		
Non-Occupancy Period	Yes	Not required	Yes		
DFS Detection Threshold	Yes	Not required	Yes		
Channel Availability Check Time	Yes	Not required	Not required		
U-NII Detection Bandwidth	Yes	Not required	Yes		

WSTT / WSFT

Table 2: Applicability of DFS requirements during normal operation

Requirement	Operational	Operational Mode			
	Master Device or Client with Radar Detection	Client Without Radar Detection			
DFS Detection Threshold	Yes	Not required			
Channel Closing Transmission Tim	ne Yes	Yes			
Channel Move Time	Yes	Yes			
U-NII Detection Bandwidth	Yes	Not required			

Additional requirements for devices with	Master Device or Client with	Client Without Radar				
multiple bandwidth modes	Radar Detection	Detection				
U-NII Detection Bandwidth and Statistical	All BW modes must be tested	Not required				
Performance Check						
Channel Move Time and Channel Closing	Test using widest BW mode	Test using the widest				
Transmission Time	available	BW mode available for				
		the link				
All other tests	Any single BW mode	Not required				
Note: Frequencies selected for statistical perfo	ormance check (Section 7.8.4) sho	uld include several				
frequencies within the radar detection bandwidth and frequencies near the edge of the radar						
detection bandwidth. For 802.11 devices it is suggested to select frequencies in each of the						
bonded 20 MHz channels and the chan	nel center frequency.					

WSC

iding A-B,Baoli'an Industrial Park,No.58 and 60,Tangtou Ave an District Shenzhen City, Guangdong Province, China hivan Ste et B 深圳世标检测认证股份有限公司 086-755-26996192 26996053 26996144 FAX:0086-755-8637660

15 E

Page 293 /303



75 L

NSE

World Standardization Certification & Testing Group (Shenzhen) Co., Itd.

WSET

WSET



W5[

WSC

WSE

N 5 C

75 E

Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

The operational behavior and individual DFS requirements that are associated with these modes are as

WSC7

WSCI

WSC7

WS CI

follows:

WSC7

DFS Detection Thresholds

Table 3 below provides the DFS Detection Thresholds for Master Devices as well as Client Devices incorporating In-Service Monitoring. WSCT WSCT W5CT°

Table 3: DFS Detection Thresholds for Master Devices and Client Devices with Radar Detection

Maximum Transmit Power	Value			
	(See Notes 1, 2, and 3)			
$EIRP \ge 200 milliwatt$	-64 dBm			
EIRP < 200 milliwatt and	-62 dBm			
power spectral density < 10 dBm/MHz				
EIRP < 200 milliwatt that do not meet the power spectral density	-64 dBm			
requirement				
Note 1: This is the level at the input of the receiver assuming a 0 dE	3i receive antenna.			
Note 2: Throughout these test procedures an additional 1 dB has be	en added to the amplitude of the			
test transmission waveforms to account for variations in measurement equipment. This will ensure that				
the test signal is at or above the detection threshold level to trigger a DFS response.				
Note3: EIRP is based on the highest antenna gain. For MIMO devi	ces refer to KDB Publication			
662911 D01				

Response Requirements

W5

Table 4 provides the response requirements for Master and Client Devices incorporating DFS.

W/S	Table 4: DFS Response Requirement Values						
	Parameter		V	alue			
	Non-occupancy period		M	inimum 30 minutes			
\sim	Channel Availability Check T	Time	60) seconds			
	Channel Move Time		10) seconds			
ALCO CO			Se	ee Note 1.			
	Channel Closing Transmissio	on Time	20	00 milliseconds + an			
			ag	gregate of 60			
			m	illiseconds over remaining			
			10) second period.			
			Se	ee Notes 1 and 2.			
	U-NII Detection Bandwidth		M	inimum 100% of the U-			
			N	II 99% transmission			
			po	ower bandwidth. See Note			
			3.				
\sim	Note 1: Channel Move Tim	e and the Channel Closing Ir	cansmission Time	should be performed with			
\sim	Radar Type 0. The measurem	nent timing begins at the end o	of the Radar Type	0 burst.			
	Note 2: The Channel Closin	g Iransmission Time is compri	ised of 200 millis	econds starting at the			
	feeilitete e Channel Mo	we time plus any additional in		signals required to			
	naciniale a <i>Channel</i> move (an	aggregate of 60 miniseconds)) during the remains	in between transmissions			
	Note 3: During the UNILD	staction Bandwidth detection to	oun quier perious	hould be used. For each			
	frequency step the minimum	percentage of detection is 90 p	est, latar type 0 s	nould be used. For each			
	no data traffic	percentage of detection is 50 p	percent. Measurer	itents are performed with			
	no data traffic.						
	T WSF		7	WSFT			
	7 1126			in			
				J. S.			
\sim				5			
\sim				3			
A			Anne				

ADD: Building A-B, Baoli'an Industrial Park, No.58 and 60, Tangtou Avenue hiyan Street, Bao'an District, Shenzhen City, Guangdong Province, China Ma 测认证股份有限公司 FAX:0086-755-86376605 TEL:0086-755-26996192 26996053 26996144 E-mail: fengbing w Http://www.wsct-

lember of the WSCT Group (WSC1

Page 294 /303



Sr

World Standardization Certification & Testing Group (Shenzhen) Co., ltd.



WST

Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

RADAR TEST WAVEFORMS

This section provides the parameters for required test waveforms, minimum percentage of successful detections, and the minimum number of trials that must be used for determining DFS conformance. Step 7 intervals of 0.1 microsecond for Pulse Width, 1 microsecond for PRI, 1 MHz for chirp width and 1 for the number of pulses will be utilized for the random determination of specific test waveforms.

WSC

Short Pulse Radar Test Waveforms

			Table 5 – Short Puls	se Radar Test Waveform	15	
	Radar	Pulse Width	PRI	Number of Pulses	Minimum	Minimum
	Type	(µsec)	(µsec)		Percentage of	Number of
W5		-			Successful	Trials
					Detection	
	0	1	1428	18	See Note 1	See Note 1
	1	1	Test A: 15 unique PRI values randomly selected from the list of 23 PRI values in Table	$\operatorname{Roundup} \left\{ \begin{pmatrix} \frac{1}{360} \end{pmatrix}, \\ \left(\frac{19 \cdot 10^6}{200} \right) \right\}$	60%	30
			5a Test B: 15 unique PRI values randomly selected within the range of 518-3066 µsec, with a minimum increment of 1 µsec, excluding PRI values selected in Test A			
	2	1-5	150-230	23-29	60%	30
	3	6-10	200-500	16-18	60%	30
THE	4	11-20	200-500	12-16	60%	30
	Aggregate (I	Radar Types 1-4	4)		80%	120
	Note 1. Sh	art Dulca Dada	" Trme () cheyld he y	and for the detection he	admidth tost ab	annal maria

Note 1: Short Pulse Radar Type 0 should be used for the detection bandwidth test, channel move time, and channel closing time tests.

A minimum of 30 unique waveforms are required for each of the Short Pulse Radar Types 2 through 4. If more than 30 waveforms are used for Short Pulse Radar Types 2 through 4, then each additional waveform must also be unique and not repeated from the previous waveforms. If more than 30 waveforms are used for Short Pulse Radar Type 1, then each additional waveform is generated with Test B and must also be unique and not repeated from the previous waveforms in Tests A or B.

For example if in Short Pulse Radar Type 1 Test B a PRI of 3066 μ sec is selected, the number of pulses would be

Page 295 /303

15 C

$$\left\{ \left(\frac{1}{360}\right), \left(\frac{19\cdot10^2}{3066}\right) \right\}$$

 $J = Round up \{17.2\} = 18.$

ADD: Building A-B, Baoli'an Industrial Park, No.58 and 60, Tangtou Avenue, Shiyan Street, Bao'an District, Shenzhen City, Guangdong Province, China.
REL: 0086-755-26996192 26996053 26996144 FAX: 0086-755-86376605 E-mail: fengbing.wang@wsct-cert.com Http://www.wsct-cert.com World Standard Zation Certification& Testing
World Standard Zation Certification& Testing



World Standardization Certification & Testing Group (Shenzhen) Co., ltd.

WSCT

WSET



WSC

Pulse Repetition

518

538

558

578

598

618

638

658

678

698

718

738

758

778

798

818

838

858

878

898

918

938

WS CT

Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

	Table 5a - Pulse Repetition Intervals Values for Test A						
	Pulse Repetition Frequency Number	Pulse Repetition Frequency (Pulses Per Second)	Pulse Rep Interval (Microsec				
WISITT	1	1930.5	5				
	2	1858.7	5				
	3	1792.1	5				
	4	1730.1	5				
	5	1672.2	5				
	6	1618.1	6				
X	7	1567.4	6				
	8	1519.8	6				
WSET	9	1474.9	6				
	10	1432.7	6				
	11	1392.8	7				
	12	1355	7				
W	13	1319.3	7				



VSC1

W5L









NSC

ion& Tes

WSC1

15 C 1

WSET

ZWSET WS LT **ZWSCT** The aggregate is the average of the percentage of successful detections of Short Pulse Radar Types 1-4. For example, the following table indicates how to compute the aggregate of percentage of successful detections.

	Radar Type	Number of Trials	Number of Successful	Minimum Percentage
			Detections	of Successful
				Detection
	1	35	29	82.9%
	2	30	18	60%
7	3	30	27	90%
	4	50	44	88%
			20/	

WS CT

WSE

Aggregate (82.9% + 60% + 90% + 88%)/4 = 80.2%

NSCI

'S C 1

ADD : Building A-B, Baoli'an Industrial Park, No.58 and 60, Tangtou Avenue, Shiyan Street, Bao'an District, Shenzhen City, Guangdong Province, China. M 深圳世标检测认证股份有限公司 FAX:0086-755-86376605 TEL:0086-755-26996192 26996053 26996144 E-mail: fengbing.wang@wsct-cert.com Http://www.wsct-cert.com

Member of the WSCT Group (WSCT SA

WSC

15 C I

Page 296 /303

IS CI

WSC



World Standardization Certification & Testing Group (Shenzhen) Co., ltd.



Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

Long Pulse Radar Test Waveform

	Table 6 – Long Pulse Radar Test Waveform									
	Radar	Pulse	Chirp	PRI	Number	Number	Minimum	Minimum		
<	Туре	Width (µsec)	Width (MHz)	(µsec)	of Pulses per <i>Burst</i>	of Bursts	Percentage of Successful Detection	Number of Trials		
Ż	5	50-100	5-20	1000- 2000	1-3	8-20	80%	30		

The parameters for this waveform are randomly chosen. Thirty unique waveforms are required for the Long Pulse Radar Type waveforms. If more than 30 waveforms are used for the Long Pulse Radar Type waveforms, then each additional waveform must also be unique and not repeated from the previous waveforms.

Each waveform is defined as follows:

1) The transmission period for the Long Pulse Radar test signal is 12 seconds.

2) There are a total of 8 to 20 *Bursts* in the 12 second period, with the number of *Bursts* being randomly chosen. This number is *Burst Count*.

3) Each *Burst* consists of 1 to 3 pulses, with the number of pulses being randomly chosen. Each *Burst* within the 12 second sequence may have a different number of pulses.

4) The pulse width is between 50 and 100 microseconds, with the pulse width being randomly chosen. Each pulse within a *Burst* will have the same pulse width. Pulses in different *Bursts* may have different pulse widths.

5) Each pulse has a linear frequency modulated chirp between 5 and 20 MHz, with the chirp width being randomly chosen. Each pulse within a *transmission period* will have the same chirp width. The chirp is centered on the pulse. For example, with a radar frequency of 5300 MHz and a 20 MHz chirped signal, the chirp starts at 5290 MHz and ends at 5310 MHz.

6) If more than one pulse is present in a *Burst*, the time between the pulses will be between 1000 and 2000 microseconds, with the time being randomly chosen. If three pulses are present in a *Burst*, the random time interval between the first and second pulses is chosen independently of the random time interval between the second and third pulses.

7) The 12 second transmission period is divided into even intervals. The number of intervals is equal to *Burst Count*. Each interval is of length (12,000,000 / *Burst Count*) microseconds. Each interval contains one *Burst*. The start time for the *Burst*, relative to the beginning of the interval, is between 1 and [(12,000,000 / *Burst Count*) –

(Total *Burst* Length) + (One Random PRI Interval)] microseconds, with the start time being randomly chosen. The step interval for the start time is 1 microsecond. The start time for each *Burst* is chosen randomly.

A representative example of a Long Pulse Radar Type waveform:

1) The total test waveform length is 12 seconds.

2) Eight (8) *Bursts* are randomly generated for the *Burst Count*.

ADD: Building A-B, Baoli'an Industrial Park, No.58 and 60, Tangtou Avenue, Shiyan Street, Bao'an District, Shenzhen City Guangdong Province, China. TEL: 0086-755-26996192 26996053 26996144 FAX: 0086-755-86376605 E-mail: fengbing.wang@wsct-cert.com Http: www.wsct-cert.com World Standard Zation Certification& Testing Group(Shen Member of the WSCT Group (WSCT SA) Page 297 /303





World Standardization Certification & Testing Group (Shenzhen)Co., ltd.

WS ET



WSE

WSE

ion& Test

WSC

WSC

WSC

WSE

Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

Frequency Hopping Radar Test Waveform

	Table 7 – Frequency Hopping Radar Test Waveform								'5 L
\sim	Radar	Pulse	PRI	Pulses	Hopping	Hopping	Minimum	Minimum	
X	Type	Width	(µsec)	per	Rate	Sequence	Percentage of	Number of	
		(µsec)		Нор	(kHz)	Length	Successful	Trials	
WSET		-				(msec)	Detection		
	6	1	333	9	0.333	300	70%	30	

For the Frequency Hopping Radar Type, the same *Burst* parameters are used for each waveform. The hopping sequence is different for each waveform and a 100-length segment is selected from the hopping sequence defined by the following algorithm: ⁴

WSC

The first frequency in a hopping sequence is selected randomly from the group of 475 integer frequencies from

5250 – 5724 MHz. Next, the frequency that was just chosen is removed from the group and a frequency is randomly selected from the remaining 474 frequencies in the group. This process continues until all 475

WSC

75

15 C

frequencies are chosen for the set. For selection of a random frequency, the frequencies remaining within the group are always treated as equally likely.

WSCI

WSC

W5CT

WSE

75/

WSE

WSE

15 E



WSC

'S E



V5 C1

5

WSCI



WSE

75 F



WSC

15 C i

ADD: Building A-B, Baoli'an Industrial Park, No.58 and 60, Tangtou Avenue, Shiyan Street, Bao'an District, Shenzhen City, Guangdong Province, China. TEL: 0086-755-26996192 26996053 26996144 FAX: 0086-755-86376605 E-mail: fengbing.wang@wsct-cert.com Http://www.wsct-cert.com Http://www.wsct-cert.



uato

Traffic Monitoring

The test transmission will always be from the Master Device to the Client Device. While the Client device is set up to associate with the Master device and play the MPEG file (6 y Magic Hours) from

C/S

Master / Client with DFS function

15 C i

WSE

on& Tes

NSC

W 5 [

WSET WSET WSET

15 C

Master device, the designated MPEG test file and instructions are located at:

C/S

luator

Support Unit

http://ntiacsd.ntia.doc.gov/dfs/.

75 C

ADD : Building A-B,Baoli'an Industrial Park,No.58 and 60, Tangtou Avenue, Shiyan Street, Bao'an District, Shenzhen City, Guangdong Province, China. TEL : 0086-755-26996192 26996053 26996144 FAX : 0086-755-86376605 E-mail: fengbing.wang@wsct-cert.com Http: www.wsct-cert.com World Standard zation Certification& Testing Group(Shenzher Member of the WSCT Group (WSCT SA)

Page 300 /303



World Standardization Certification & Testing Group (Shenzhen)Co., ltd.

WSET



Report No.: WSCT-ANAB-R&E240700030A-Wi-Fi2

CALIBRATION OF DFS DETECTION THRESHOLD LEVEL

The measured channel is 5260MHz. The radar signal was the same as transmitted channels, and injected into the antenna port of Client Device with Radar Detection, measured the channel closing transmission time and channel move time.

WSC

SLAVE WITHOUT RADAR DETECTION MODE

The antenna gain is -4dBi and required detection threshold is -65dBm (= -62 +1 - 4)dBm. The calibrated conducted detection threshold level is set to -65dBm.





