

<div data-bbox="506 328 595 379" data-label="Image"></div> <div data-bbox="439 395 672 421" data-label="Section-Header"><h2>Smart Visual Doorbell</h2></div> <div data-bbox="486 434 620 448" data-label="Text"><p>Instruction manual V1.1</p></div> <div data-bbox="398 713 707 727" data-label="Text"><p>Please read it carefully before use and keep it for future reference</p></div>	<div data-bbox="763 287 974 304" data-label="Section-Header"><h3>I. Appearance introduction:</h3></div> <div data-bbox="763 316 1037 523" data-label="Image"></div> <div data-bbox="763 531 1081 574" data-label="Text"><p>Doorbell: 1) MIC 2) Lens 3) Light sensitive 4) Doorbell key 5) Type-C 6) Speaker 7) Anti-theft screw</p></div> <div data-bbox="837 590 969 715" data-label="Image"></div> <div data-bbox="763 721 1104 750" data-label="Text"><p>Ding dong machine 1) Pairing button 2) Volume button 3) Music button 4) USB interface</p></div>	<div data-bbox="1131 282 1335 300" data-label="Section-Header"><h3>II. Download mode of APP:</h3></div> <div data-bbox="1131 309 1473 367" data-label="Text"><p>For Android phones, it can be downloaded from its own app market or App Treasure Search [TUYA Smart]. For IOS phones, search for "TUYA Smart" in the APP Store to download. Note: The function of this doorbell is only supported on APP 4.3.0 and above, for a better user experience, please update or download the latest version.</p></div> <div data-bbox="1256 371 1357 472" data-label="Image"></div> <div data-bbox="1131 489 1285 507" data-label="Section-Header"><h3>III. APP registration:</h3></div> <div data-bbox="1131 515 1485 606" data-label="List-Group"><ol style="list-style-type: none">For the first download and use, please click "Register". If you have an account, click "Login".Click "Register", read "Privacy Policy", and click "Agree". Enter a valid mobile phone number or email address and click Continue. Then enter the verification code to log in to the APP. ("Try Now" login can not add doorbell devices normally, please register and log in.)APP permissions pop-up prompts, such as message push, access geographical location, connect peripheral devices, etc., please set to "Allow".</div> <div data-bbox="1131 622 1281 639" data-label="Section-Header"><h3>IV. Adding a device:</h3></div> <div data-bbox="1131 641 1478 702" data-label="List-Group"><ol style="list-style-type: none">Turn on the bluetooth and location permission functions of the mobile phone.Press the doorbell button to start the device, and the work indicator blinks. The device enters the network mode.Open the APP, enter the "Home page", click "+" on the upper right corner of the page, the APP will automatically scan and discover the device, click "Add".</div>	<div data-bbox="1507 271 1861 454" data-label="Image"></div> <div data-bbox="1507 459 1861 493" data-label="Text"><p>Note: a. If the device is not automatically searched, please click "Turn on Bluetooth" in the picture below and set "Allow device permissions near this application".</p></div> <div data-bbox="1507 497 1861 708" data-label="Image"></div>
<div data-bbox="378 813 730 837" data-label="Text"><p>b. Access permission management, enable WLAN, Bluetooth, and nearby devices, and select Always Allow.</p></div> <div data-bbox="378 841 730 1142" data-label="Image"></div>	<div data-bbox="754 813 1106 868" data-label="Text"><p>4. After adding a doorbell, enter your 2.4ghz wireless network account and password and click "Next". When connecting, keep your router, mobile phone and doorbell as close as possible. After adding a doorbell, click "Finish". (Note: If the connection is not successful, please reset the device and reconnect)</p></div> <div data-bbox="754 873 1106 1099" data-label="Image"></div> <div data-bbox="754 1115 1079 1139" data-label="Text"><p>5. Fully charge the device and install it within the stable and effective range of WIFI signal. The smart doorbell host is successfully added.</p></div>	<div data-bbox="1131 813 1408 833" data-label="Section-Header"><h3>V. Doorbell and ding Dong matching:</h3></div> <div data-bbox="1207 844 1391 997" data-label="Image"></div> <div data-bbox="1131 1003 1473 1059" data-label="List-Group"><ol style="list-style-type: none">Power on the ding Dong machine (left).Long press the pairing button of ding Dong machine for 3 seconds (as shown in the picture), and the indicator blinks.Press the doorbell button (right), ding Dong machine rings, that is, the match is successful.</div> <div data-bbox="1131 1064 1319 1082" data-label="Section-Header"><h3>VI. Mobile message push</h3></div> <div data-bbox="1131 1085 1478 1139" data-label="Text"><p>Enter mobile phone - Settings - notification and status bar - Application notification management, open APP notification permission, enable notification, suspension, lock screen, sound reminder and other notification functions. (Note: Due to different mobile phone models, the operation interface and options are different, please choose independently)</p></div> <div data-bbox="1131 1145 1335 1163" data-label="Section-Header"><h3>VII. Function introduction:</h3></div> <div data-bbox="1131 1165 1473 1252" data-label="List-Group"><ol style="list-style-type: none">Message push: When visitors ring the doorbell, the mobile phone will receive the APP push message, click the push popup to enter the video call.Video call: Hold down the microphone key to talk to each other, open the speaker to listen.Doorbell sharing: Enter the real-time interface of APP, click Settings - Share device - Add Share - enter the registered accountLow battery reminder: When the battery is low, the APP will push low battery reminder, please charge in time.</div>	<div data-bbox="1507 813 1747 831" data-label="Section-Header"><h3>VIII. Matters needing attention</h3></div> <div data-bbox="1507 829 1861 946" data-label="Text"><p>The device is a low-power doorbell. When no one rings the doorbell, the device goes into hibernation and goes offline, which is normal. The push Settings vary according to mobile phone models. Set the Settings as required. Only 2.4g WIFI is supported, but 5G or WIFI with special symbols is not supported. Do not install the device on a metal wall because it may interfere with WIFI signals. The device supports TF card video storage. Do not insert or remove the memory card when it is powered on to avoid loss. Do not use the doorbell while charging.</p></div> <div data-bbox="1507 960 1599 975" data-label="Section-Header"><h4>FCC Statement</h4></div> <div data-bbox="1507 976 1850 1241" data-label="Text"><p>This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: •Reorient or relocate the receiving antenna. •Increase the separation between the equipment and receiver. •Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. •Consult the dealer or an experienced radio/TV technician for help. Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p></div> <div data-bbox="1507 1251 1621 1264" data-label="Section-Header"><h4>RF Exposure Information</h4></div> <div data-bbox="1507 1264 1841 1300" data-label="Text"><p>This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.</p></div>