


Product Overview

ColorFlux Light Bulb LB2202 BR30 Light Bulb is a tunable white, multi-color LED Light Bulb that can be controlled wirelessly via iOS or Android smartphones and tablets, no hub required. You can customize your personal lighting using the VOCOLinc app from anywhere with an active internet connection.



Specifications

Input: AC120V, 60Hz
Base type: E26
Rated power: 9.5W
LED color range: 16 million colors with cool to warm whites

Color temperature: 2200K – 7000K (including 2200K, 2500K, 2700K, 3000K, 3500K, 4000K, 5000K, 5700K, 6500K, 7000K)

Luminous flux: 800 lumens
Beam angle: 100 degrees
Expected LED life: 22.8 years (25000 hours)

Operation frequency band(s): 2412~2462MHz for E26
Max. transmitted RF power: 12±1dBm

What's Included

- LB2202 Smart Wi-Fi BR30 Light Bulb
- User Manual

Features:

- 16 million colors
- Works with Apple HomeKit
- Works with Amazon Alexa
- Works with the Google Assistant
- Remote Access

LB2202 ColorFlux Light Bulb LED status

Status		LB2202
Turning on the first time	Searching Wi-Fi	White light at 5% brightness
Pairing		White light at 5% brightness
Device added successfully		White light at 50% brightness
Identifying the light bulb		White light at 5% brightness quickly blinks 5 times
Firmware update completed		Blinks twice

* If you set the brightness to 0% before turning off the light switch, the smart light bulb will resume to 5% brightness as soon as you turn on the light switch again to indicate that it is in good shape.

Factory Resetting

Resetting the smart light bulb can help you troubleshoot any issues you may have. To reset it to factory defaults:

- Turn the light switch controlling the bulb to the OFF position.
- Flip the light switch on and off 3 times. Time lag between each cycle must not exceed 5 seconds.

The Smart light bulb will blink three times once reset is completed.
Note: all connection data will be cleared. ColorFlux Light Bulb LB2202 must be removed from the app and then added back again.

System Requirements

- Mobile device running iOS latest system or Android OS4.3+
- Existing Wi-Fi network
- Stable Internet with good signal strength

Safety Warnings

- WARNING: RISK OF ELECTRIC SHOCK OR BURNS. Switch OFF the light switch controlling the bulb and WAIT for the bulb to cool down before attempting to change it
- DO NOT install the Smart Wi-Fi LED Bulb with wet hands or when standing on wet or damp surfaces
- Not suitable for use with standard in-wall dimmers. Dimmable via the app only
- Suitable for use in operating environment between 0°C and 40°C

- This device is not intended for use with emergency exit luminaires
- For lamps with a weight significantly higher than that of the lamps for which they are a replacement, attention should be drawn to the fact that the increased weight may reduce the mechanical stability of certain luminaires and lampholders and may impair contact making and lamp retention.
- NOT FOR EMERGENCY LIGHTING
- For indoor use only
- DO NOT disassemble
- DO NOT clean with liquid
- Use in Dry Locations only
- Only use the control provided with or specified by these instructions to control this lamp.
- This lamp will not operate properly when connected to a standard (incandescent) dimmer or dimming control

FCC Declaration

Caution:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct

the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter.

IC Declaration

Caution:


This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions:

(1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

In order to avoid the possibility of exceeding the ISED radio frequency exposure limits, human proximity to the antenna shall not be less than 20cm (8 inches) during normal operation.

Présentation du Produit

Ampoule ColorFlux LB2202 BR30 Ampoule est un blanc réglable multi-couleurs LED ampoule qui peut être contrôlé à distance via iOS ou Android smartphones ou Tablettes, pas de hub requis. Vous pouvez personnaliser votre éclairage personnel en utilisant l'application de VOVOLinc de n'importe où avec une connexion internet active.



Spécifications

Entrée: CA 120V, 60Hz
Type de base: E26
Puissance Nominale: 9.5 W
Gamme de couleurs LED: 16 millions de couleurs avec du blanc Froid au Chaud

Température des couleurs: 2200K – 7000K (incluant 2200K, 2500K, 2700K, 3000K, 3500K, 4000K, 5000K, 5700K, 6500K, 7000K)



VOCOLinc APP

Download on the App Store

ANDROID APP ON Google play

Flux Lumineux: 800 lumens
Angle de Faisceau: 100 Degrés
Durée de vie excepté: 22.8 années (25000 Heures)

Bande(s) de fréquence de fonctionnement: 2412~2462MHz pour E26
Puissance maximale transmise: 12±1dBm

Ce qui est inclus

- LB2202 Ampoule Wi-Fi intelligente BR30
- Manuel de l'Utilisateur

Fonctionnalités

- 16 millions de couleurs
- Fonctionne avec Apple HomeKit
- Fonctionne avec Amzaone Alexa
- Fonctionne avec l'Assistant Google
- Accès à distance

Ampoule ColorFlux LB2202 Ampoule LED

Statut		LB2202
Allumer pour la première fois	Recherche de Réseau Wi-Fi	Lumière blanche à 5% de luminosité
Appariement		Lumière blanche à 5% de luminosité
Appareil ajouté avec succès		Lumière blanche à 50% de luminosité

Identification de l'Ampoule	Lumière blanche à 5% de luminosité et clignote 5 fois rapidement
Mise à jour complète du Firmware	Clignote deux fois

* Si vous mettez la luminosité à 0% avant d'éteindre, l'ampoule intelligente va reprendre à 5% de luminosité dès que vous allumerai la lumière pour indiquer qu'il est en bon état.

Réinitialisation d'usine

Resetting Réinitialiser les paramètres constructeurs peut vous permettre de résoudre tout problème que vous pourrez rencontrer.

Pour réinitialiser aux paramètres usine:

- Mettez l'interrupteur contrôlant l'ampoule en position éteint.
- Mettez l'interrupteur en arrêt et en marche 3 fois. Temps entre chaque cycle ne doit pas dépasser 5 secondes.

L'ampoule intelligente clignotera trois fois dès que la réinitialisation est terminée.

Note: Toutes les données de connexion seront supprimées. ColorFlux Ampoule LB2202 doit être supprimée des applications puis rajoutée.

Configuration requise du système

- Appareil mobile exécutant le dernier système iOS ou Android OS4.3+
- Réseau Wi-Fi disponible
- Une connexion Internet stable avec un bon signal

Avertissement de Sécurité

- Attention: Risque de choc électrique ou brulures, éteignez l'interrupteur contrôlant l'ampoule et attendez jusqu'à ce que l'ampoule se refroidit avec d'essayer de la charger
- N'installez pas l'ampoule Wi-Fi LED intelligente avec des mains mouillés, ou debout sur des surfaces humides ou mouillés
- Non adapté pour être utilisé avec un variateur standard, dimmable via l'application uniquement
- Adapté pour être utilisé dans un environnement d'opération entre 0° et 40°C (32°F et 104°F)
- Cet appareil n'est pas destiné à être utilisé comme luminaires de secours.
- Pour les Ampoules dont le poids est significativement supérieur à celui des ampoules pour lesquelles elles sont remplacées, une attention doit être faite que l'augmentation du poids peut réduire la stabilité mécanique de certains luminaires et supports d'ampoule et peut nuire à l'établissement du contact et la rétention de la lampe
- PAS POUR UN ECLAIRAGE DE SECOURS
- Pour une utilisation à domicile uniquement
- Ne désassembler pas
- Ne PAS nettoyer avec du liquide
- Utiliser dans des endroits sec uniquement
- Utilisez uniquement le contrôleur fourni ou spécifié par ces

instructions pour contrôler l'ampoule.

- Cette ampoule ne fonctionnera pas correctement lorsqu'elle est connectée à un variateur (incandescent) standard ou contrôleur de gradation.

IC Déclaration

Mise en garde:

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

(1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Afin d'éviter la possibilité de dépasser les limites d'exposition aux fréquences radio de la ISED, la proximité humaine à l'antenne ne doit pas être inférieure à 20 cm (8 pouces) pendant le fonctionnement normal.



LB2202


ColorFlux Light Bulb
Ampoule ColorFlux

BR30









PDF
Adobe