

Model: A04162		Test Number: 210120				
MPE Calculator	RF Exposure uses EIRP for calculation. EIRP is based on TX power added to the antenna gain in dBi.					
	dBi = dB gain compared to an isotropic radiator.					
	S = power density in mW/cm <sup>2</sup>					
	Transmitter Output power (mW)	0.3				
	Transmitter Output power (W)	0.0003				
Output Power for % duty Cycle operation (Watts)	100	0.000		Antenna Gain (dBi)	-6.9	
Output Power for 100% duty Cycle operation (Watts)		0.000		Antenna Gain (Numeric)	0.20	
Tx Frequency (MHz)	2441	Calculation power (Watts)	0.000	dBd + 2.17 = dBi	dBi to dBd	2.2
				Antenna Gain (dBd)	-9.07	
Cable Loss (dB)	0.0	Adjusted Power (dBm)	-5.80	Antenna minus cable (dBi)	-6.90	
				Antenna Gain (Numeric)	0.20	
	Calculated ERP (mw)	0.033		EIRP = Po(dBm) + Gain (dB)		
	Calculated EIRP (mw)	0.054		Radiated (EIRP) dBm	-12.700	
	<div style="border: 1px solid black; padding: 5px; width: fit-content;"> <math display="block">\text{Power density (S) mW/cm}^2 = \frac{\text{EIRP}}{4 \pi r^2}</math> <math display="block">r \text{ (cm)} = \sqrt{\frac{\text{EIRP (mW)}}{4 \pi S}}</math> </div>			ERP = EIRP - 2.17 dB		
				Radiated (ERP) dBm	-14.870	
<b>Occupational Limit</b>		FCC radio frequency radiation exposure limits per 1.1310				
5	mW/cm <sup>2</sup>	Frequency (MHz)	Occupational Limit (mW/cm <sup>2</sup> )	Public Limit (mW/cm <sup>2</sup> )		
50	W/m <sup>2</sup>	30-300	1	0.2		
<b>General Public Limit</b>		300-1,500	ƒ/300	ƒ/1500		
1	mW/cm <sup>2</sup>	1,500-10,000	5	1		
10	W/m <sup>2</sup>					
<b>Occupational Limit</b>		IC radio frequency radiation exposure limits per RSS-102				
0.6455f <sup>0.5</sup>	W/m <sup>2</sup>	Frequency (MHz)	Occupational Limit (W/m <sup>2</sup> )	Public Limit (W/m <sup>2</sup> )		
39.7	W/m <sup>2</sup>	100-6,000	0.6455f <sup>0.5</sup>			
<b>General Public Limit</b>		6,000-15,000	50			
0.02619f <sup>0.6834</sup>	W/m <sup>2</sup>	48-300		1.291		
5.4	W/m <sup>2</sup>	300-6,000		0.02619f <sup>0.6834</sup>		
		6,000-15,000	50	10		
f = Transmit Frequency (MHz)				f (MHz) =	2441 MHz	
P <sub>T</sub> = Power Input to Antenna (mW)				P <sub>T</sub> (mW) =	0.2630 mW	
Duty cycle (percentage of operation)				% =	100 %	
P <sub>A</sub> = Adjusted Power due to Duty cycle or Cable Loss (mW)				P <sub>A</sub> (mW) =	0.26 mW	
G <sub>N</sub> = Numeric Gain of the Antenna				G <sub>N</sub> (numeric) =	0.20 numeric	
S <sub>20</sub> = Power Density of device at 20cm (mW/m <sup>2</sup> )		S <sub>20</sub> =(P <sub>A</sub> G <sub>N</sub> )/(4πR <sub>20</sub> ) <sup>2</sup>		S <sub>20</sub> (mW/m <sup>2</sup> ) =	0.00 mW/m <sup>2</sup>	
S <sub>20</sub> = Power Density of device at 20cm (W/m <sup>2</sup> )		S <sub>20</sub> =(P <sub>A</sub> G <sub>N</sub> )/(4πR <sub>20</sub> ) <sup>2</sup>		S <sub>20</sub> (W/m <sup>2</sup> ) =	0.00 W/m <sup>2</sup>	
S <sub>L</sub> = Power Density Limit (W/m <sup>2</sup> )				S <sub>L</sub> (W/m <sup>2</sup> ) =	5.410 W/m <sup>2</sup>	
R <sub>C</sub> = Minimum distance to the Radiating Element for Compliance (cm)		R <sub>C</sub> =√(P <sub>A</sub> G <sub>N</sub> /4πS <sub>L</sub> )		R <sub>C</sub> (cm) =	0.1 cm	
S <sub>C</sub> = Power Density of the device at the Compliance Distance R <sub>C</sub> (W/m <sup>2</sup> )		S <sub>C</sub> =(P <sub>A</sub> G <sub>N</sub> )/(4πR <sub>C</sub> ) <sup>2</sup>		S <sub>C</sub> (W/m <sup>2</sup> ) =	5.41 W/m <sup>2</sup>	
R <sub>20</sub> = 20cm				R <sub>20</sub> =	20 cm	
	For Compliance with Canada General Population Limits, User Manual must indicate a minimum separation distance of				0.1 cm	
	Or in Meters for Compliance with Canada General Population Limits, a minimum separation distance of				0.001 Meters	

Rogers Labs, Inc.  
4405 West 259<sup>th</sup> Terrace  
Louisburg, KS 66053  
Phone/Fax: (913) 837-3214  
Revision 1

Garmin International, Inc.  
Model: A04162  
Test: 210120  
Test to: CFR47 15C, RSS-210  
File: A04162 RF Exemption

SN's: 3356450954, 3356450941  
FCC ID: IPH-04162  
IC: 1792A-04162  
Date: March 18, 2021  
Page 1 of 1