


- 1 x Wireless Keyboard
- 1 x USB Charging Cable
- 1 x User manual

Bluetooth version	Bluetooth 5.1
Dimensions	287x133x20mm/11.3x5.24x0.79 in
Operating Range	< 10 m / 32.8 ft
Lithium Battery Capacity	280 mAh
Charge time	< 2 hours
Uninterrupted Work Time	90 hours
Stand-by time	90 days
Front side of keyboard	ABS
Back side of keyboard	Stainless steel



Press Caps Lock key to switch capital and small letters.  
Inputting Capital Letters: flash in green color.  
Inputting Small Letters: automatically turns off.

(For Android users, the Caps Lock indicator may not appear, but the Caps Lock function is still activated as per normal.)

Will flash green after pressing the "fn + pairing" Keys together.  
It disappears when connected.

### Pairing with the 1st device













- Step 1. On the keyboard, slide the power button on. The green light will be on for 3s and then turn off.
- Step 2. Press "fn + ⌘".
- Step 3. Press "fn + pairing". Bluetooth indicator flash green, starting to search the available bluetooth device.
- Step 4. Find the Bluetooth name "Bluetooth Keyboard" and click for connection.
- Step 5. The Bluetooth indicator will be OFF after successfully paired.

- Step 1. Press "fn + F2".
- Step 2. Press "fn + pairing", Bluetooth indicator flash green, starting to search the available bluetooth device.
- Step 3. Find the Bluetooth name "Bluetooth Keyboard" and click for connection.
- Step 4. The Bluetooth indicator will be OFF after successfully paired.

Step 3. Find the Bluetooth name "Bluetooth Keyboard" and click for connection.

- Three devices can be actively paired at one time, only need to press "fn + ⌘ + Z" key, changing to the accorded paired device.
- Re-connection function: Turn on the keyboard, it can connect with the last used device automatically.
- If connection is failure, delete the pairing record from your device, and try the above procedures again.

For the Windows tablets, press and hold the "Fn" keys while pressing the function keys.

	For Android	For Win	For Windows	For iOS
	N/A	Esc	N/A	N/A
	Home	F4	Web browser	Home
	Switch windows	F5	Switch windows	Switch windows
	Back	F6	N/A	N/A
	Previous track	F7	Previous track	Previous track
	Play/pause	F8	Play/pause	Play/pause
	Next track	F9	Next track	Next track
	Mute	F10	Mute	Mute
	Volume -	F11	Volume -	Volume -
	Volume +	F12	Volume +	Volume +
	Screen shot		Screen shot	Screen shot
	Bluetooth Pairing		Bluetooth Pairing	Bluetooth Pairing

**NOTE:** After connecting with the device, you must press Fn + relative OS key (Q for Android, W for Windows, E for iOS ) to select operating system, otherwise some key's function are invalid.

Samsung Android: shift + Space  
Google Android: ctrl + Space  
Windows: cmd + Space / ctrl+shift  
iOS 8 or below: cmd + Space  
iOS 9 or above: ctrl + Space

- iOS 6.0 and above
- Mac OS X v10.6 to Mac OS X v10.12 and above
- Windows XP / Vista / 7 / 8 / 10, PC computer with a Bluetooth host
- Android 3.0 and above with Bluetooth HID profile (Smartphones and Tablets)
- This keyboard is not compatible with Samsung Smart TV (UE37ES5500, UE55KU6400U, UE48JU6400), Mac mini and Nokia phones.

The keyboard will enter sleep mode after being idle for 30 minutes. To activate it, press any key and wait for 3 seconds.

1. Use the included USB cable for charging. Connect one end to a USB charger, and the other to the keyboard.  
(USB charger is not included)
2. In charging, the power indicator will turn red. Generally, it takes approximately 2 hours for a full charge. (Output: DC 5V/500mA)

**If you are unable to connect the keyboard to your tablet, please try the following:**

1. Starting with a full charge on both devices ensures that process won't be interrupted by a low battery.
2. Check your tablet's Bluetooth is on.
3. Make sure that the keyboard is within the effective operation distance of 32.8 feet (10M ).

**NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates and uses radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.