

Hi98PRO USER MANUAL



产品手册 中文

Hi98PRO 客制化机械键盘 RGB版

莱奥伯格

不拘一格

- ┓ 产品特点 • 时尚的外观设计,101 键布局,Gasket 结构,手感细腻软弹。
- 键帽和机械开关可插拨,用户也可以购买市面上各品牌开关和个性化键帽自由 DIY。 键盘用料扎实,按键反应灵敏。
- 内置 4000mA/8000mA 大容量电池,使用时间更长。
- FN+\|组合键切换 16 种 RGB 灯效(随波逐流、如影随形、正炫光波、旋转风车、七彩瀑布、 花开富贵、自定义、关闭、常亮、呼吸、梦幻彩虹、一触即发、雨中漫步、涟漪扩散、踏雪无痕、
- 配合驱动带音乐律动 RGB 灯效,此灯效下有 10 种灯效模式可选。
- 有线模式配合驱动各键带自定义功能,宏定义。驱动可自定义1600多万种颜色。 键盘人性化设计,与 Fn 配合增加一系列常用快捷功能按键。
- 蓝牙模式下一分钟无任何操作自动进入省电模式,单击按键唤醒键盘。 查看键盘电量连接蓝牙可以在电脑上显示。
- 键盘刷补丁需要切换成有线模式,刷完后重新插拔键盘线和键盘的拨动开关重新开关。 键盘回报率: 有线模式 1000Hz, 蓝牙模式 125Hz。
- 配合驱动可调 5 档键盘响应速度。
- 键盘蓝牙/有线均支持全键无冲。 配合驱动在一般自定义功能上多增加 3 层自定义功能: 支持双 FN 层可编辑, 实现单键双
- 组合功能,增加了 TAP 层实现一键两用,共有 4 层自定义功能。 USB-C 连接性更可靠,性能更稳定。

┓ 产品规格

- 键位: 101键 产品尺寸: 404.13×136.15×47.95±1mm
- 产品重量:4000mAh 电池:约 2120g(不含线材) 8000mAh 电池:约 2272g(不含线材)
- 额定电压 / 电流: DC 3.7V === 230mA
- 充电电压 / 电流:DC 5V/≤1500mA,充电约 11 小时
- 续航时间:约 22/44 小时(默认灯效)/约 250/500 小时(关所有灯光)

■ 标准版快捷键说明

FN+	ESC		1	2	3	Q	W	Е
组合 功能	恢复 默认		蓝牙设备 1#	蓝牙设备 2#	蓝牙设备 3#	Android 系统	Windows 系统	Mac 系统
FN+	-1\	TAB	1	\	←	\rightarrow	WIN-L	Prtsc
	灯光模 式切换	颜色切换	亮度+	亮度-	速度-	速度+	锁WIN	Pause

1. Android 系统,F区单按功能与F区FN 组合功能

键位	F1	F2	F3	F4	F5	F6	F7	F8
单按	屏幕亮度-	屏幕亮度+	转换窗口	返回桌面	亮度-	亮度+	上一曲	播放/暂停
FN 组合	F1	F2	F3	F4	F5	F6	F7	F8
键位	F9	F10	F11	F12				
单按	下一曲	静音	音量-	音量+				
FN 组合	F9	F10	F11	F12				

2. Windows 系统、F区单按功能与F区FN 组合功能

****	IUOWS XX	\$16, F ⊠=	F1X47186-	JI E IN	20 10 70 86			
键位	F1	F2	F3	F4	F5	F6	F7	F8
单按	F1	F2	F3	F4	F5	F6	F7	F8
FN 组合	主页	邮件	转换窗口	打开资源 管理器	亮度-	亮度+	上一曲	播放/暂停
键位	F9	F10	F11	F12				
单按	F9	F10	F11	F12				
FN 组合	下一曲	静音	音量-	音量+				

3. Mac 系统,F 区单按功能与 F 区 FN 组合功能

键位	F1	F2	F3	F4	F5	F6	F7	F8
单按	屏幕亮度-	屏幕亮度+	转换窗口	返回桌面	亮度-	亮度+	上一曲	播放/暂停
FN 组合	F1	F2	F3	F4	F5	F6	F7	F8
键位	F9	F10	F11	F12				
单按	下一曲	静音	音量-	音量+				
FN 组合	F9	F10	F11	F12				

┓ 功能说明

- 开关拨到左边蓝牙模式LEOBOG Hi98PRO 根据终端设备的蓝牙版本随机广播,可以连
- FN+1=蓝牙1 按键下蓝色指示 通道广播时蓝灯快闪,回连/连上蓝色亮3s。 FN+2=蓝牙2 按键下蓝色指示 通道广播时蓝灯快闪,回连/连上蓝色亮3s。
- FN+3=蓝牙3 按键下蓝色指示 通道广播时蓝灯快闪,回连/连上蓝色亮3s。
- 开关切到中间有线模式,4键上白灯亮2s。 · 在不插USB线模式下开关拨到中间,关闭键盘电池。
- · Fn+左WIN=锁定/打开左WIN窗口键 (锁WIN时锁WIN指示灯常亮,在WIN系统下)。
- 指示灯:锁WIN &大写,WIN键 & CAPS键的白灯指示。 切换到Mac系统后左WIN/左ALT位置互换(不锁WIN)
- 低电压电源指示灯闪灯提示,充电时指示灯常亮.充满 提示绿灯灭。
- 按住FN+B 显示电量 1---0显示电量 电量少于30% 1-3亮红灯 大于30% 1-0 亮绿灯。

■ 安装使用说明

- 有线模式: Windows ALL 操作系统 WIN XP, WIN7,WIN8,WIN10 (在 Win95, Win98 系统下,可能需要驱动程序)。
- 有线模式:配置有 USB 1.1 或以上版本端口。

硬件连接 · 有线 USB 支持热插拔 (即插即用)。

*实际续航时间会因环境和使用习惯不同而改变,以实际使用续航为准



产品、技术在不断生产过程中持续优化,说明书可能未及时与产品保持同步 更新、敬请谅解。

■ 保修事项说明

感谢您购买 LEOBOG(莱奥伯格)系列产品!本质保卡是 LEOBOG(莱奥伯格)产品的三

包凭证,由用户自己保存。 凭此质保卡您将享受为您提供的产品售后服务,此质保卡每个产品一份,遗失不补,敬请 妥善保管。

- 、凭此卡您将享受以下权利及服务

- 1、退货服务: 自产品售出之日起七日内, 产品出现质量问题, 根据国家 "三包服务 "规定, 在产品外观与包装完整的情况下,将产品退还给销售商或莱奥伯格指定地点,凭购买时的 有效凭证,退回您支付的产品货款。
- 2、保修服务: 自购买日起 12 月内出现产品性能故障情况经由莱奥伯格售后服务中心检测 确定,可免费享受维修服务。

二、以下情况不属于免费服务范围:

- 1、超出规定的质保期限:
- 、不能出示产品有效质保凭证或产品原序列号标签有涂改、替换、撕毁等现象的;
- 3、产品上没有序列号或质保凭证上的产品型号与产品实物不符的; 4、非正常使用、维护、保管所导致的故障和损坏;
- 5、非我公司授权的维修人员对产品维修、更改或拆卸而造成的故障或损坏; 6、意外事故或其他不可抗力造成的故障或损坏;
- 7、销售人员承诺的产品之外的服务及附加的配件或赠品不在本保修服务范围之列
- 8、因电源、电压不稳而导致的故障或损坏。



Postal Code

Sales Date

邮政编码

销售日期





Dongguan Suoai Electronice CO., LTD 东莞市索艾电子科技有限公司 Village Huangjiang Town Dongguan City 广东省东莞市黄江镇长龙村华裕街索艾产业园 执行标准: GB 4943.1-2022

联系方式: 0769-86911118

Made in China

官网: http://www.leobog.com

- Stylish design, 101 key layout, Gasket structure, feel delicate soft elastic. Key cap and mechanical switch can be inserted and dialed, users can also buy the market
- brand switch and personalized key cap free DIY.
- Keyboard material solid, key responsive.
- Built-in 4000mA/8000mA high capacity battery, longer use time. FN+\| key combination switch 16 kinds of RGB light effect (drift, shadow, is dazzling wave, rotating windmill, colorful waterfall, flowers rich, custom, off, on, breathing, dream rainbow,
- hair-trigger, walk in the rain, ripple spread, snow without trace, flow).
- from under this light effect.
- Keyboard humanized design, with Fn to add a series of commonly used shortcut functio
- cable and switch the keyboard toggle again.
- Keyboard Bluetooth / wired support full key no impact.

■ Product Specification

- - Product size: 404.13×136.15×47.95±1mm
- With the driving music rhythm RGB light effect, there are 10 light effect modes to choose
- Wired mode cooperate to drive each key with custom function, macro definition. The drive can be customized in more than 16 million colors.

- · Adjustable 5-speed ke board response with driver.
- four layers of customization functions.

- - - Charging voltage/current: DC 5V/≤1500mA, charging about 11 hours Battery life: About 22/44 hours (default lighting effect)
- **■** Standard Shortcut Description
- saving mode, click the key to wake up the keyboard.

 Check keyboard battery connection Bluetooth can be displayed on the computer.
- Switch the keyboard patch mode to the wired mode. After brushing, reinsert the keyboard
- Keyboard return rate: Wired mode 1000Hz, Bluetooth mode 125Hz.
- With the driver, three more layers of customization functions are added to the general customization functions: double FN layer can be edited to achieve single-key double combination function, and TAP layer is added to achieve one-key dual use, with a total of
- USB-C connectivity is more reliable and performance is more stable.

- Key: 101 keys
- Product weight: 4000mAh battery: about 2120g (No wire included)
- 8000mAh battery: about 2272g (No wire included)

/About 250/500 hours (all lights off)

FN+	ESC		1	2	3	Q	W	Е
Func- tion	Restore Default		Bluetooth 1#	Bluetooth 2#	Bluetooth 3#	Android mode	Windows mode	Mac mode
FN+	- 1\	TAB	1	Ų.	←	\rightarrow	WIN-L	Prtsc
Func- tion	Light Mode Switching	Color Switching	Brightness +	Brightness	Speed-	Speed+	Lock WIN	Pause

1. Android system, F zone single press function and F zone FN combination function

Key	F1	F2	F3	F4	F5	F6	F7	F8
Single Press	Screen Brightness-	Screen Brightness+	Conversion Window	Back To Desktop	Brightness-	Brightness+	Previous Song	Play/ Pause
Fn Combination	F1	F2	F3	F4	F5	F6	F7	F8
Key	F9	F10	F11	F12				
Single Press	Next Song	Mute	Volume-	Volume+				
Fn Combination	F9	F10	F11	F12				

2. Windows system, F zone single press function and F zone FN combination function

Key	F1	F2	F3	F4	F5	F6	F7	F8
Sing l e Press	F1	F2	F3	F4	F5	F6	F7	F8
Fn Combination	Home	Mail	Conversion Window	Open Explorer	Brightness-	Brightness+	Previous Song	Play/ Pause
Key	F9	F10	F11	F12				
Sing l e Press	F9	F10	F11	F12				
Fn Combination	Next Song	Mute	Volume-	Volume+				

Key	F1	F2	F3	F4	F5	F6	F7	F8
Sing l e Press	Screen Brightness-	Screen Brightness+	Conversion Window	Back To Desktop	Brightness-	Brightness+	Previous Song	Play/ Pause
Fn Combination	F1	F2	F3	F4	F5	F6	F7	F8
Key	F9	F10	F11	F12				
Sing l e Press	Next Song	Mute	Volume-	Volume+				
Fn Combination	F9	F10	F11	F12				

Function Description

to the Bluetooth version of the terminal device, and 3 devices can be connected: Wired USE supports hot swap (plug and play).

blue light flashes quickly, and the blue light is on for 3s.

- FN+2= Bluetooth 2 When the blue indicator channel is broadcast under the button, the blue light flashes quickly, and the blue light is on for 3s. FN+3= Bluetooth 3 When the blue indicator channel is broadcast under the button, the blue light flashes quickly, and the blue light is on for 3s.
- In unplugged USB mode, flip the switch to the middle and turn off the keyboard
- Fn+ Left WIN= Lock/open the left WIN window key (Lock the WIN indicator when the WIN lock is on, in the WIN system). Indicator light: Lock WIN & CAPS, WIN & CAPS
- After switching to Mac OS, the left WIN/ left ALT position is changed (WIN is not The low voltage power indicator blinks, and the indicator is steady on when charging full warning The green light is off.

 Press and hold FN+B to display power 1-- 0 Display power Less than 30% 1-3 Red

light Greater than 30% 1-0 Green light.

■ Listallation And Use Instructions

Wired mode: Windows ALL operating system WIN XP, WIN7, WIN8, WIN10 (In Win95, Win98 systems, drivers may be required).
 Wired mode: equipped with a USB 1.1 or higher port.

abreast of the update, please understand.

Computer System Requirements:

Product, technology in the continuous production process of continuous

optimization, specification may not reach the production products to keep

■ Warranty Description

Thank you for buying LEOBOG products! The Intrinsic Warranty Card is a three-pack certificate for LEOBOG products, which is provided by the user saved. With this warranty card you will enjoy the product after-sales service provided for you his warranty card each product one, lost not up, please keep properly.

With This Card, You Will Enjoy The Following Rights And Services: 1. Return service: within seven days from the date of product sale, product quality

appearance and packaging complete, the product will be returned to the seller or LEOBOG designated place, with the valid proof of purchase, refund you paid for the 2. Warranty service: within 12 months from the date of purchase, the product

problems, the national "three guarantees of service" provisions, in the case of product

- performance failure is determined by the LEOBOG after-sales service center, and you can enjoy free maintenance services.
- The Following Situations Do Not Belong To The Scope Of Free Services:
- 2. Can not produce a valid product warranty certificate or the original serial number label of the product has been altered, replaced, torn and other phenomena;
- 3. There is no serial number on the product or the product model on the warranty certificate is inconsistent with the product:
- 4. Failure and damage caused by abnormal use, maintenance and storage; 5. Failure or damage caused by maintenance, alteration or disassembly of products by

7. Services other than the products promised by the sales staff and additional accessori

non-authorized maintenance personnel of our company: 6. Failure or damage caused by accidents or other force majeure;

or gifts are not included in the scope of this warranty service;

8. Failure or damage caused by unstable power supply and voltage.

— User Warranty Card _____

Sales	Record:		
User	User(Name/Unit)		
User Information	Telephone/E-mail		
ation	Correspondence Address And E-mail		
	Sales Unit		
	Salas I Init Address		

--- 用户保修卡 ----

销售记录:

维修记录:

维修日期

准予出厂。

用户(姓名/单位)

电话/E-mail

通讯地址及邮编

销售单位地址

联系电话

产品型号

销售商印章

维修单位

经检验该产品符合技术标准,

Saller's Seal


Comtact Numbe

Product Model

Date	Unit	ephone Ac	ddress

说明书 尺寸: 80*95m m 材质105克书写纸

印刷颜色:黑色



FCC Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- •Reorient or relocate the receiving antenna.
- •Increase the separation between the equipment and receiver.
- •Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- •Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

RF Exposure Information

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.