双面彩印 105克的铜板纸 打钉

尺寸:90*100mm

使用说明书

IPAD10.9/11寸平板专开的皮套键盘

尊敬顾客您使用本公司为您提供的蓝牙键盘，在使用本产品前请详细阅读本手册。

产品展示

键盘状态	指示灯颜色	指示灯状态
开机状态/蓝牙配对	红色	常亮红灯持续3s
开机状态/蓝牙连接中	蓝色	1秒1闪，1秒熄灭配对进入休眠
大小写状态/大小写锁定	绿色	按Caps Lock键切换大写时红灯亮
充电状态/充电指示灯	红色	电压低于3.3V闪烁1次，低于3.0V常闪烁
充电状态/充电指示灯	红色/绿色	红灯长亮（连接电源指示） 充满后绿灯长亮
电量显示指示灯	红色	按Fn+左方向键电量闪烁次数1次/10%

蓝牙键盘配对连接步骤

第一步. 打开键盘并关闭蓝牙，电源指示灯常亮红色3秒后熄灭，键盘开机。

第二步. 同时长按蓝牙键 1 进入对码状态，此时灯闪烁1次。

第三步. 打开设备的蓝牙进行搜索，设备的蓝牙自行搜索到该键盘名称（Xiangshi Keyboard）点击连接，连接成功后状态指示灯熄灭。

(已经配对过的平板，再保持对光重再次配对，打开时会自动回连)

快捷功能键使用说明

	主页面		查找键盘		复制
	粘贴		语言切换		触摸板开关
	亮度减		亮度加		静音
	音量减		音量加		播放/暂停
	上一曲		下一曲		锁屏
Fn+	蓝牙配对				

七彩背光键盘使用说明

1. 按Fn+ 键打开背光功能，再按一次背光加强。再按第二次关闭。
2. 同时按Fn+ ◀/▶/▲/▼调节背光颜色，三色呼吸。
3. 当键盘12小时内无任何操作或不对键有最低于20mA时，背光功能自动关闭。

注： 当键盘与设备成功连配后，开启背光功能，才能展示背光效果，新键盘没有与设备成功连配，不能开启背光功能，才能展示背光效果。

节能休眠模式

当键盘处于休眠无任何操作指令时，键盘会自动进入休眠模式，需要受用时，只需要按任意键即会唤醒，键盘即对主机工作，键盘开机3分钟未配对，将停止配对，需手动按FN+ C 再次配对。

充电方法

当电压低于3.3V时，低电压指示灯将会闪烁，这时要给键盘充电：

1. 连接原装Type-C数据线给键盘充电接口
2. 连接原装Type-C数据线给平板或配备或者是电脑的USB接口
3. 连接成功，充电状态指示灯会成红色显示。当电量充满时指示灯应绿灯长亮。这说明充电结束。

特别提示

1. 不动机超时，开关机按键动开机，也能进动关机。
2. 对于其他可直流的蓝牙设备，在连接前请仔细阅读其使用说明和兼容性。
3. 为了保障长时间使用效果，我们建议键盘在相应的灯光指示键盘充电。
4. 在连接实际的情况下，删除设备上的配对记录，开再次尝试连接。

触摸板功能示意图

手势图	iOS系统
单指点击	鼠标左键
单指快速点击不松，滑动	左键选中目标拖动
三指敲击	鼠标中键
四指点击	截屏
双指重直/水平移动	滚轮重直、水平滚动
三指同时左/右滑动	滑动窗口左/右滑动切换
滑动单手指	移动鼠标指针
双指点击	鼠标右键
三指同时向上滑动	最近任务窗口切换
三指同时向下滑动	返回主界面

常见疑点解答

1. 中英手机和平板可以使用第三方输入法吗?

答：iOS系统开启第三方键盘需要同时，且主机需单独启用的 “简体拼音”，“中文拼音”，“繁体注音”等其它第三方输入法。

2. 如何使用siri进行语音语音?

答：按住 住一会儿——弹出——弹出键长按语音（打开）
iOS语音指令 键功能: 使用语音键发送消息（打开）
在设置中来开相应无法设置的情。

3. 键盘在开卡顿怎么回事呢?

答：键盘在开卡过程中出现卡顿情况，第一，检查电量是否充足；
第二，是否连接过多设备；第三，电量耗动是否正常。

安全须知

⚠警告：不准将以下安全说明视为可能会导致起火，触电，损坏键盘设备

⚠ 注意（不能导致设备损坏）⚠警告（不按说明设备受损）⚠ 注意（有损害人员）

1. 出现未知
2. 出现未知先改装标准
3. 禁止食物和饮
4. 禁止外出，可保键盘
5. 远离油污，化学品并有有机溶剂。

无线科技 无限生活

User Manual

IPAD10.9/11 inch Tablet Dedicated Leather Keyboard

Thank you for using the keyboard provided by us, please read this manual carefully before using this product.

Product Overview

Keyboard indicator	Indicator color	Indicator status
Power on/ Bluetooth pairing	Red	The red light turn on for 3 seconds and then off
Pairing status/ Bluetooth pairing indicator	Blue	Flash for 1 second, enter sleep without pairing for 3minutes
Caps lock indicator	Green	The green light remains on when entering the uppercase state, and the light is off when entering the lowercase state
Low voltage state: charging indicator	Red	When voltage lower than 3.3V, it flash 1 time per 2 seconds. When the voltage lower than 3.0V, it flash continuously
Charging status: charging indicator	Red/Green	The red indicator light stays on and turn to green light when fully charged.
Battery indicator	Red	Each flash of the light represents 20% of the power, and 4 flashes are fully charged

Keyboard Connection Steps

Step 1. Turn on the keyboard switch and move forward, the power indicator will be steady red for 3 seconds and then go out, the keyboard is turned on.

Step 2. Press the The Bluetooth key 1 to enter the code matching state, the blue light flashes once per second.

Step 3. Turn on the Bluetooth of the device to search, the Bluetooth of the device can be searched by itself or manually to find the keyboard name (Xiangshi Keyboard) and click to connect. After the connection is successful, the status indicator will turn off.

(The tablet that has been paired does not need to be paired again when it is used again, it will automatically connect back when it is turned on.)

Function Key

	HOME		Keyboard display		Copy
	Paste		Screenshot		Touchpad switch
	Brightness -		Brightness +		Mute
	Volume -		Volume +		Play/pause
	Last track		Next track		Lock screen
Fn+	Bluetooth pairing				

Keyboard Specifications

Bluetooth Specification	Bluetooth 4.0
Operating Range	Up to 10 meters
Modulation System	GFSK
Operating Voltage	3.0-4.2V
Reconnect time	≤4S
Wake-up time	≤2S
Charge time	2 hours
Lithium Battery Capacity	280 mAh
Uninterrupted Work Time	≥300 hours(close backlight) ≥2 hours(open backlight)
Standby time	≥365days
Operating temperature	-10℃ ~+50℃
Whether to enter the connection pairing	No pairing password
Charging port	Type-C

Instructions for use of colorful backlit keyboard

1. Backlit on /off : Fn+ E
   Press first time is turning on the light.
   Press second time is increasing brightness.
   Press third time is lighting off.
2. Press Fn+ ◀ ▲ ▼ to change the backlit colors. (7-color backlit)
3. When the battery is less than 20%, the backlit will be off.
4. The backlit won't work until the keyboard paired with device.

Energy-saving sleep mode

When the keyboard has no operation instructions for 30 minutes, the keyboard will automatically enter the sleep mode. When you need to use it, just press any key and the keyboard will be awakened, and the keyboard will work normally; if the keyboard is turned on for 3 minutes without pairing, it will stop pairing. Manually Press FN+ to pair again.

Charging

When the voltage is lower than 3.3V, the low-voltage indicator light will flash, and the keyboard should be charged at the time:

① Connect the B end of the original Type-C cable to the keyboard c hanging port.

② Connect end A of the original USB cable to the power adapter or the USB port of the computer.

③ If the connection is successful, the charging status indicator will turn red. When the power is full, the indicator will turn green and it will turn off when the charging cable is unplugged.

Special Note

1. Manual mechanical switch, turn the switch backward to turn on, turn forward to turn off.
2. Only the Bluetooth devices that can be activated, please carefully check the Bluetooth standards and compatibility before connecting.
3. In order to get a longer battery life, we recommend charging the keyboard when the keyboard low battery indicator light flashes.
4. If the connection fails, delete the pairing record on the device and try to connect again.

Touchpad Function

Gesture Diagram	iOS System
Single finger click	Left mouse button
Double-click quickly for 3 seconds without releasing	Left click to select the target and drag
Three-finger click	Middle mouse button
Four-finger click	Screenshot
Two fingers move vertically Two fingers move horizontally	Middle button vertical scroll Two fingers move horizontally
Three fingers move left/right at the same time	Swipe left/right on the active window to switch
Swipe one finger	Move the mouse pointer
Two-finger click	Key assist function
Swipe up with three fingers at the same time	Task switching in recent window
Swipe down with three fingers at the same time	Show desktop

Frequently Asked Questions

1. Can I use third-party input methods on iPhones and tablets?

Answer: When the iOS system is connected to an external keyboard, it only supports the "Simplified Pinyin" that comes with the Apple system, and does not support other third-party input methods such as Baidu and Sogou Wubi.

2. How to use enter to send messages?

Answer: WeChat Me—Settings—Chat—Enter to send a message (open) First Settings in QQ-Accessibility-Find the Enter key to send a message (open) Some software cannot be set up without upgrading.

3. Why is the keyboard stuck?

Answer: The keyboard freezes during use. First: check whether the battery is sufficient; second: whether too many devices are connected, third: whether the computer driver is normal.

Safety Caution

⚠Warning: It can cause fire, electric shock, damage of keyboard system if disobey the safety notes.

⚠ Dangerous (be careful of highly dangerous)

⚠ Warning (be careful of mid dangerous)

⚠ Caution (slight dangerous should be noted)

1. ⚠Keep the keyboard away from sharp objects.
2. ⚠Do not Microwave the keyboard.
3. ⚠ Do not place heavy object on the keyboard.
4. ⚠ Do not force or distorted the keyboard.
5. ⚠ Keep away from oil, chemical or any other organic liquid.

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the

User is encouraged to try to correct the interference by one or more of the following measures: —Reorient or relocate the receiving antenna.

—Increase the separation between the equipment and receiver.

—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

—Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co - located or operating in conjunction with any other antenna or transmitter.

Wireless Technology, Infinite Life