



# VZM35-SN Instructions

# Next Gen Smart Lighting

We're excited to have you on this journey with us and we're here for you every step of the way. Not only are we smart home owners ourselves, but we build all of our products alongside 1,000's of passionate community members. To see how the project came to life and how everyone contributed, please see Page 52 or visit: [inov.li/zephyr](http://inov.li/zephyr). It's truly amazing working with people of all walks of life and even more humbling to see everyone's dedication to making some of the best smart home products.

Thank you so much for your trust in us and welcome to the next generation of smart lighting with Inovelli.

Eric H. - Founder/CEO

Eric M. - Founder/CTO

Handwritten signatures of Eric H. and Eric M. in blue ink. Eric H.'s signature is on the left, and Eric M.'s signature is on the right.

# Table of Contents

Quick Setup	05	Advanced Features	43
Wiring	11	Switch Parameters	45
Warnings	14	Other Advanced Features	46
Vocabulary	21	Product & Contact Info	47
Steps 1-4	22	FCC/IC Info	49
Step 5 - Installation	30	Product Info	52
Pre-Setup	31	Contact/Warranty Info	53
Example	33	Project New Horizon	54
Configuration & Mode	34		
Hub/Gateway Setup	37		
Amazon Echo	39	Scan for the most	
SmartThings	40	recent instructions or	
Home Assistant	41	visit: <a href="https://inov.li/vzm35sn">inov.li/vzm35sn</a>	
Hubitat	42		



# Navigating this Manual

We designed this manual as if we were installing the switch ourselves. We suggest reviewing the full manual before beginning the installation process. There are five areas this manual covers:

1. Getting to know your switch
2. Figuring out your wiring
3. Pre-programming your switch (after wiring installation)
4. Connecting to your hub/gateway
5. Configuring your switch (optimize the settings)

As we continue to work with hub manufacturers, and improve our products. It may be necessary to periodically update this manual. You can always find the latest version of this manual by visiting: [inov.li/vzm35sn](http://inov.li/vzm35sn)

Rev 1.0 - 2023.05.25

**Quick Setup.**

# Quick Setup Notes

We get it, you're ready to go. No need to flip through the manual, you want the abridged version. **This section assumes you have your switch wired correctly and the blue LED Bar is lit up.**

It also assumes you know how to enter the Zigbee pairing mode on your hub/gateway (and have a Zigbee compatible hub/gateway).

To see which hubs are compatible, please visit: [inov.li/vzm35snhubs](http://inov.li/vzm35snhubs)


While these instructions likely won't change, for the most up-to-date instructions, we recommend scanning the QR code to the right or to visit: [inov.li/vzm35snQS](http://inov.li/vzm35snQS)



# Pairing Your Switch

**Auto-Pairing:** The switch will automatically start pairing when power is restored. To indicate the switch is in pairing mode, the LED Bar (C) will pulse blue. If the LED Bar (C) is not pulsing, pull the air-gap out (located at the bottom left of the switch) and push it back in or flip the breaker off/on. Start the Zigbee pairing process on the hub at any time. If successful, the LED Bar (C) will turn green.

If the switch is unsuccessful in pairing, please hold down the top of the paddle (B) and the Config Button (A) for approximately 20 seconds until the LED Bar (C) flashes/turns red. Let go and the LED Bar (C) should start pulsing blue indicating the pairing process has started.



# Getting to Know Your Switch

Please use the next couple pages to get to know your smart switch.

**A. Fan On / Increase Fan Speed:** Tap 1x to turn on your fan or hold to increase the fan speed (if using for a ceiling fan). In addition, it can be used to activate scene control (multi-taps and holds) where up to 7 scenes can be added\*.

**B. Fan Off / Decrease Fan Speed:** Tap 1x to turn off your fan or hold to decrease the fan speed (if using for a ceiling fan). In addition, it can be used to activate scene control (multi-taps and holds) where up to 7 scenes can be added\*.

**C. RGB LED Bar:** Multi-functional LED bar that shows the speed level  
at  
8



at which your fan is at. In addition, it can be used as a notifier\* for various events (ie: turn red when alarm is armed, pulse purple if garage is left open, etc).

**D. Config / Favorites Button:** Used to configure certain parameters of the switch. In addition, it can be used to activate scene control (multi-taps and holds) where up to 7 scenes can be added\*.

**E. Air Gap:** This can be pulled out to cut power to the load and is there for safety purposes.



\* Hub must support these features. Please see pg. 46.

# Quick Tap Sequences

If you are using your switch for an Exhaust Fan (or a fan that only supports On/Off), please see the quick tap sequences below or visit pages 34-35 for more details. Single-Pole + Exhaust Fan (On/Off Control) is the default.

Wiring Type	Sequence	Confirmation
Single-Pole	Hold on ↓ paddle, tap config 5x, release	Violet
Multi-Way (Aux)	Hold on ↑ paddle, tap config 5x, release	White
Switch Type	Sequence	Confirmation
Ceiling Fan (3-Speed)	Hold on ↓ paddle, tap config 3x, release	Orange
Exhaust Fan (On/Off)	Hold on ↑ paddle, tap config 3x, release	Red

**Wiring.**

# Wiring Notes

Due to the number of ways these switches can be wired, all schematics are housed online and you can access the schematics by scanning the QR Code at the bottom right, or by visiting: [inov.li/vzm35snwiring](http://inov.li/vzm35snwiring)

To work your way through this section, first read the warnings, then familiarize yourself with the vernacular used. Finally, keep notes as you go through the first three (3) steps as you will use them to determine whether or not your wiring is compatible and whether or not you have to pre-program/setup your switch (pg. 28).

Finally, please do not attempt to install these switches if you are unfamiliar with electrical as serious injury can occur.



# Safety Reminder

Consult a qualified electrician if necessary as **we are unable to give wiring advice outside of schematics.**

If you are unsure how electrical circuits work, please do not try installing this device. As exciting as it is to have a smart switch installed, it can be dangerous and even life-threatening if you do not install it correctly. Improper installation will void the product's warranty.

Please read through the warnings on the next few pages before installing your switch. We can't stress enough how dangerous installation can be if you don't know what you're doing.

# Warnings

**Caution - Please Read:** This device (VZM35-SN) is intended for installation in accordance with the National Electric Code and local regulations in the United States, or the Canadian Electrical Code and local regulations in Canada. If you are unsure or uncomfortable about performing this installation consult a qualified electrician. This product is made for indoor use only and is not designed or approved for use on power lines other than 120VAC, 60Hz, single phase. Attempting to use this VZM35-SN on non-approved power lines may have hazardous consequences.

**Attention - Information importante:** Cet appareil (VZM35-SN) est conçu pour être installé conformément au « National Electric Code » et aux réglementations locales aux

États-Unis, ou au Code canadien de l'électricité et aux réglementations locales canadiennes. Si vous ne vous sentez pas à l'aise ou qualifiés pour effectuer cette installation, veuillez consulter un électricien qualifié. Ce produit est conçu pour une utilisation intérieure uniquement et n'est pas conçu ou approuvé pour une utilisation avec une ligne électrique ayant un voltage autre que 120 VCA, 60 Hz, monophasé. L'utilisation du VZM35-SN avec une ligne électrique non approuvée peut avoir des résultats dangereux.

**Other Warnings:** Risk of Fire, Electrical Shock & Burns

**Autres avertissements:** Risque d'incendie, de choc électrique et de brûlures

# Warnings (Continued)

**Recommended Installation Practices:** Use only indoors or in an outdoor rated box. Turn off the circuit breaker. Installing this switch and module with the power on will expose you to dangerous voltages. Connect only copper or copper-clad wire to the switch or module.

To reduce the risk of overheating and possible damage to other equipment, use the VZM35-SN load output to control no more than indicated.

- 2.5 Amps (Resistive Load)
- No more than 2 fans to the same switch
- Use only with split-capacitor or shaded-pole ceiling fan motors

Dimming a lighting load (by connecting to the fan load wire), such as an LED, CFL, Incandescent or anything other than a ceiling or



exhaust fan motor, could cause damage to the fan switch, the load bearing device, or both. To install your Fan Switch (VZM35-SN), you'll need to identify the following four wires (NOTE: Neutral is not mandatory, but recommended):

- **Line:** Usually black and can also be called the, "hot" or "live" and carries 120VAC electricity into the electrical box
- **Neutral\*:** Usually white and is commonly daisy chained from box to box, usually appearing as a white wire bundle.
- **Load:** Usually black, blue or red
- **Ground:** Bare copper wire or metal fixture (if grounded)

\* Neutral is mandatory in certain installations. See page 29 for additional details.

# Warnings (Continued)

If you are having difficulties identifying wires, please consult an electrician.

**Pratiques d'installation recommandées:** Utiliser uniquement à l'intérieur ou à l'extérieur dans une boîte adaptée aux conditions extérieures. Éteignez le disjoncteur. L'installation de cet interrupteur et de ce module alors que le courant est allumé vous exposera à des tensions dangereuses. Connectez uniquement un fil de cuivre ou gainé de cuivre au commutateur ou au module.

Pour réduire le risque de surchauffe et de dommages possibles à d'autres équipements, utilisez la sortie de charge VZM35-SN pour ne pas contrôler plus que ce qui est indiqué, à savoir : 2,5 A (charge résistive), pas plus de 2 ventilateurs sur le même interrupteur,

et utilisez uniquement avec moteurs de ventilateur de plafond à condensateur divisé ou à pôles ombragés.

La gradation d'une charge d'éclairage (en se connectant au fil de charge du ventilateur), telle qu'une LED, une CFL, une incandescence ou tout autre chose qu'un moteur de ventilateur de plafond ou d'extraction, pourrait endommager l'interrupteur du ventilateur, le dispositif de support de charge ou les deux. Pour installer votre interrupteur de ventilateur (VZM35-SN), vous devrez identifier les quatre fils suivants (REMARQUE : le neutre n'est pas obligatoire, mais recommandé) :

- **Ligne:** généralement noire et peut également être appelée « chaud » ou « sous tension » et transporte l'électricité 120 VCA

# Warnings (Continued)

dans le boîtier électrique

- **Neutre:** habituellement blanc et connecté en série d'une boîte à l'autre, les fils sont habituellement attachés ensemble dans la boîte électrique
- **Charge:** habituellement noire, bleue ou rouge
- **Mise à terre:** fil de cuivre nu ou boîtier métallique (si celui-ci est mis à la terre) Si vous rencontrez des difficultés à identifier les fils, veuillez consulter un électricien.

**Équipement médical:** Veuillez ne pas utiliser cet interrupteur pour contrôler de l'équipement médical ou nécessaire à la survie. Les appareils Zigbee ne doivent jamais être utilisés pour contrôler la marche ou l'arrêt d'équipement médical et/ou nécessaires à la survie.

# Vocabulary

Before we go into actual steps, it's important to be familiar with the vernacular used on the following pages. Please see below:

- **Line:** This is your hot wire (120V) - aka: "live" wire
- **Load:** This is the wire that runs from your fan switch to what you're controlling (ie: ceiling fan or exhaust fan)
- **Neutral:** This is the wire that carries current back to the power source (you may not have this in your house)
- **Single-Pole:** One switch controlling one or more load(s)
- **Multi-Way:** Refers to 3-Way (2 switches, 1 load), 4-Way (3 switches, 1 load), or 5-Way setups (4 switches, 1 load)
- **Aux Switch:** Refers to the Inovelli Aux Switch ([inov.li/aux](http://inov.li/aux))

# Step 1 - Determine Wiring Type

The first step is to determine how many switches control your load(s) (aka: fan(s)).


Using the diagram on the next page, please determine what your wiring type is and remember this selection:

- **Single-Pole:** One switch controls one load (load may contain more than one fan, etc).
- **Multi-Way:** Two or more switches control one load (load may contain more than one fan, etc). We will use the term, "multi-way" instead of 3-Way, 4-Way, 5-Way, etc as the programming of the switch is the same regardless.



### **Single-Pole**

One switch controls one (or more) load(s).



### **Multi-Way**

Two or more switches control one (or more) load(s).



# Step 2 - Determine Switch Layout


**NOTE:** If you determined in Step #1 that your switch is single-pole, you can skip this step. This step is for multi-way setups only.

Using the diagram on the next page, please determine what your wiring layout is and remember this selection:

- **Smart Switch + Aux Switch:** One smart switch and one (or more) aux/add-on switch (Model #: AUX01 or [inov.li/aux](http://inov.li/aux)).
- **Smart Switch + Smart Switch:** Two (or more) smart switches.

**Wiring Type (Circle One):** Aux or Smart Switch(es)





### **Smart + Aux Switch**

One Inovelli smart switch & one (or more) Inovelli aux switch (AUX01).



### **Smart Switches**

Two (or more) Inovelli smart switches.

# Step 3 - AC Power Type

In this step, we will determine if you have a neutral wire, which is typically white and located in the back in your switch gang-box (typically in a bundle of wires tied together).

Here are some signs you may have a neutral wire:

- If your house was built in the mid-1980's or later
- If there is an outlet (receptacle) near the switch
- If switches are in the same gang-box (regardless of the year your house was built)

See the next page for details on checking for a neutral wire.



After turning off your breaker, pull out the switches (**WARNING:** there may be multiple circuits in one gang-box -- please ensure all circuits are turned off). Check the back of your gang-box for a bundle of white wires. These are typically neutrals.

# Step 4 - Compatibility Check

In this step, we will determine if your switch can be installed with your current wiring setup. If not, you can see some alternate solutions on how to accomplish compatibility.

Taking the answers you circled in Steps 1-3, please see the chart on the next page to see if your switch is compatible with your setup.

**Example:** If you circled, "Multi-Way", "Aux Switch" and "Neutral", you will see that your wiring is compatible. However, if you circled, "Multi-Way", "No Neutral" and "Smart Switch", you will see that your wiring is not compatible and you will need to purchase an auxiliary switch ([inov.li/aux](http://inov.li/aux)).

Wiring Type		Switch Layout	Power Type	Supported
Single-Pole			Neutral	Yes
			No Neutral	Yes (Ceiling Fan Only)
Multi-Way	Aux (Switch)		Neutral	Yes
			No Neutral	Yes (Ceiling Fan Only)
	Smart (Switch)		Neutral	Yes
			No Neutral	No

**IMPORTANT:** For installations where no neutral wire is present, you will not have the ability to control the, "High" speed. Exhaust fans are not supported in non-neutral setups.

# Step 5 - Switch Installation

The last step is to physically install your switch. After you've determined your wiring type, switch layout, AC Power type and whether or not you have a compatible setup, it's time to look at the wiring schematics and install your switch.

As noted in the beginning of this section, there are many different ways your switch can be wired that if we posted them here, we'd have an encyclopedia of a manual, so all of our schematics are housed online.

Keep note of your answers from the prior steps and either scan the QR Code to the right or go to: [inov.li/vzm35snwiring](http://inov.li/vzm35snwiring) and match up your answers to the correct schematic section.



**Pre-Setup.**

# Pre-Setup Notes

**NOTE: If you plan on using your switch as an exhaust fan switch (On/Off only) and in a single-pole setting, you may skip this step.** If you plan on using your switch as a ceiling fan switch (3-Speed) and/or in a multi-way setup, please continue.

Since this switch has so many different available configurations (exhaust, ceiling fan, smart, aux, neutral, non-neutral, etc), you may need to pre-program the switch to work manually.

Luckily, it's as simple as pressing a couple buttons. Feel free to follow the steps on the next couple of pages, scan the QR Code or visit: [inov.li/vzm35snpresetup](https://inov.li/vzm35snpresetup)

Again, if you are using this switch as an on/off and single-pole setting, you can skip this section.





# Pre-Setup Example

Here's an example of how to use the chart on the next page (pg.34):

Let's say you want your switch to be a ceiling fan switch and you have it wired in a multi-switch setting using an aux switch.


Using the chart on pg. 34, you would first hold down on the bottom part of the paddle (C), while simultaneously tapping the config button (A) 3x and then releasing both the paddle and config button. The LED Bar will confirm the setting by blinking/turning orange.

Next, to program the switch to work in a multi-switch setup using an aux (add-on) switch, you would then hold up on the top part of the paddle (B), while simultaneously tapping the config button (A) 5x and then releasing both the paddle and config button. The LED Bar will confirm the setting by blinking/turning white.

# Switch Configuration

Use the button sequence below to adjust the mode of the switch according to your wiring configuration. The LED bar will flash the associated color to indicate success.


Hubs supporting advanced settings can also update this setting via their respective apps.



Wiring Type	Sequence	Confirmation
Single-pole	Hold on ↓ paddle, tap config 5x, release	Violet
Multi-Way (Aux)	Hold on ↑ paddle, tap config 5x, release	White

# Switch Mode

Use the button sequence below to adjust the mode of the switch according to the type of switch you want. The LED bar will flash the associated color to indicate success. For a visual example of changing to a dimmer, see: [inov.li/vzm35snSMVid](https://inov.li/vzm35snSMVid).



Hubs supporting advanced settings can also update this setting via their respective apps.

Switch Type	Sequence	Confirmation
Ceiling Fan (3-Speed)	Hold on ↓ paddle, tap config 3x, release	Orange
Exhaust Fan (On/Off)	Hold on ↑ paddle, tap config 3x, release	Red

Page intentionally left blank.

**Hub/Gateway Setup.**

# Hub/Gateway Setup Notes

As manufacturers update their hub/gateway platforms, the setup process may change. We recommend checking our website for the latest directions, by scanning the relvant QR code.

If you don't see your hub, please go to: [inov.li/vzm35sn0T](https://inov.li/vzm35sn0T)

**Amazon Echo**



[inov.li/  
vzm35snAE](https://inov.li/vzm35snAE)

**SmartThings**



[inov.li/  
vzm35snST](https://inov.li/vzm35snST)

**Home Asst.  
ZHA**



[inov.li/  
vzm35snZHA](https://inov.li/vzm35snZHA)

**Home Asst.  
Zigbee2mqtt**



[inov.li/  
vzm35snZ2M](https://inov.li/vzm35snZ2M)

**Hubitat**





[inov.li/  
vzm35snHE](https://inov.li/vzm35snHE)

# Amazon Echo Instructions

**COMPATIBLE HUBS:** Echo Plus 1st & 2nd Gen, Echo Show 2nd Gen, and Echo Studio. For a full model list, visit: [inov.li/vzm35snAEHubs](http://inov.li/vzm35snAEHubs).  
(NOTE: Advanced features are not supported by Amazon at this time.)


First, Follow the directions on page 7 to put the switch in pairing mode. When the LED bar (C) is pulsing blue proceed:

- Open the Amazon Alexa app and click on the devices icon 
- Tap on the (+) button and click, "Add Device"
- Tap on the switch icon 
- Scroll to the bottom and select, "Other"
- Click on, "Zigbee"
- Click, "Discover Devices"
- If successful, the LED Bar (C) will turn green and your app will show the new switch (feel free to rename it)

# SmartThings Instructions

**COMPATIBLE HUBS:** Samsung SmartThings Hub V1, V2 and Samsung or Aeotec Hub V3 (NOTE: You may need to install a Device Handler or Edge Driver to ensure full functionality of the switch. For more info, please go to: [inov.li/vzm35snSTPrereqs](http://inov.li/vzm35snSTPrereqs)).

First, Follow the directions on page 7 to put the switch in pairing mode. When the LED bar (C) is pulsing blue proceed:

- Open the SmartThings app and click on the devices icon 
- Tap on the (+) button and click, "Add Device"
- Under the, "Scan for nearby devices", click, "Scan" and your hub will search, find and initialize the device
- If successful, the LED Bar (C) will turn green and your app will show the new switch (feel free to rename it)



# Home Assistant Instructions

**COMPATIBILITY:** We recommend either ZHA or Zigbee2mqtt (NOTE: you will also need a compatible Zigbee stick - a full list can be found here: ZHA = [inov.li/vzm35snZHAsticks](https://inov.li/vzm35snZHAsticks) or Z2M = [inov.li/vzm35snZ2Msticks](https://inov.li/vzm35snZ2Msticks)).

You didn't think we'd be able to fit the HA instructions in here, did you?! Please visit our website :)

## ZHA Instructions



[inov.li/vzm35snZHA](https://inov.li/vzm35snZHA)

## Zigbee2mqtt Instructions




[inov.li/vzm35snZ2M](https://inov.li/vzm35snZ2M)

# Hubitat Instructions

**COMPATIBLE HUBS:** Hubitat C3, C4, C5, C7 & C8 (NOTE: You may need to install a Device Driver to ensure full functionality of the switch. We recommend doing this prior to pairing. For more info, please go to: [inov.li/vzm35snHEPrereqs](http://inov.li/vzm35snHEPrereqs)).

First, Follow the directions on page 7 to put the switch in pairing mode. When the LED bar (C) is pulsing blue proceed:

- Login to your Hubitat portal and click on the devices tab 
- Tap on the (+) Add Device button and click, "Zigbee" under, "Add device manually"
- Click, "Start Zigbee Pairing" and your hub should go into pairing mode, find and initialize the device
- If successful, the LED Bar (C) will turn green and your app will show the new switch (feel free to rename it)

**Advanced Features.**

# Advanced Features Notes

**NOTE:** The advanced features shown below are what is built into the switch firmware, and may or may not be supported by your hub/gateway. We've confirmed they're supported on SmartThings, Hubitat, and Home Assistant (ZHA and Zigbee2MQTT).

These switches are packed with a ton of amazing features, which include scene control (multi-tap), animated notifications, smart bulb mode, energy monitoring, and approximately 60 different parameters to customize your switch.

The manual does not have enough room to list out and explain all the parameters and advanced features. However, the following pages will direct you to the proper URL's. An overview can be found at the QR code to the right or at the following URL: [inov.li/vzm35snAF](https://inov.li/vzm35snAF)



# Switch Parameters

There are approximately 60 different parameters on this switch, making it one of the most customizable switches out there.

Due to the space constraints in this manual, we had to list them all out on our website. You can access these parameters by scanning the QR Code or by visiting: [inov.li/vzm35snparameters](http://inov.li/vzm35snparameters)

If your hub does not support parameter changes, you can program a lot of these directly from the configuration button. Please visit: [inov.li/vzm35snLC](http://inov.li/vzm35snLC)



# Other Advanced Features

To setup some of the other advanced features, such as: Animated Notifications, Scene Control, Smart Fan Mode and Zigbee Binding, please see the URL's below as the instructions will be different depending on the hub you're using.

- **Animated Notifications:** [inov.li/vzm35snAN](http://inov.li/vzm35snAN)
- **Scene Control:** [inov.li/vzm35snSC](http://inov.li/vzm35snSC)
- **Smart Fan Mode:** [inov.li/vzm35snSBM](http://inov.li/vzm35snSBM)
- **Zigbee Binding:** [inov.li/vzm35snZB](http://inov.li/vzm35snZB)

As noted on page 45, your switch has the ability to program parameters from the configuration button. To learn more, please visit: [inov.li/vzm35snLC](http://inov.li/vzm35snLC)

**Product & Contact Info.**

# Product & Contact Info Notes

As mentioned in the beginning of the manual, we're all smart home owners ourselves and have an amazing community of people who are eager to help and share their setups.

If you ever run into any issues, please do not hesitate to submit a ticket, or post in the community. We'd love to hear from you.

**Community Link:** [inov.li/community](https://inov.li/community)

**Submit a Ticket:** [inov.li/support](https://inov.li/support) (or scan the QR Code below)

Thanks again for your support and we look forward to helping you get the most out of our smart home!





# FCC/IC Statements

**FCC Caution:** Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received including interference that may cause undesired operation.

**NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency

# FCC/IC Statements (Cont.)

energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna, increase the separation between the equipment and receiver, connect the equipment into an outlet on a circuit different from that to which the receiver is connected or consult the dealer or an experienced radio/TV technician for help. This equipment should be installed and

operated with minimum distance 8in (20cm) between the radiator and your body.

**IC Caution:** This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

**DECLARATION DE CONFORMITE D'INDUSTRIE CANADA:** Ce périphérique a été testé et reconnu conforme aux limites spécifiées dans RSS-210. Son utilisation est soumise aux deux conditions suivantes: (1) il ne doit pas provoquer d'interférences gênantes et (2) il doit tolérer les interférences, notamment celles susceptibles d'en perturber le fonctionnement.

# Product Info

Name: Smart Fan Switch (Ceiling or Exhaust)

SKU #: VZM35-SN

Power: 120V AC, 60Hz

Signal (Frequency): 2.4GHz

Operating Temperature Range: 32-95° F (0-35° C)

Maximum Load (Watts): 2.5 Amps - No more than two identical fans to the switch. Not to exceed 2.5A resistive load.

Not rated for lighting (LED, CFL, Incandescent, etc).

Range: Up to 100 meters line of sight between the Wireless Controller (HUB) and the closest Zigbee Repeater.

Certifications: ETL Listed, FCC/IC & Zigbee 3.0 Certified

For indoor use. Specifications subject to change without notice due to continuing product improvement.

# Company Info / Warranty

If you run into any issues, feel free to reach out to us at: [contact@inovelli.com](mailto:contact@inovelli.com). We typically answer tickets within 24-48 hours and are staffed by actual smart home owners.

All Inovelli products come with a one (1) year warranty (defined as 365 days). This warranty protects you from breakdowns in the material or workmanship under normal use. This warranty is limited in a couple areas. Purchases must be made from Inovelli or an authorized reseller. The product should be used in the manner directed in the instructions. The product must only be used and/or installed in the United States or Canada.

For full warranty info, please visit: [inov.li/warranty](http://inov.li/warranty)

# Project Zephyr

This project was Inovelli's second Zigbee product which stemmed from the success of our 2-1 Switch launched in late 2022. We chose the name Zephyr because it means, "a soft gentle breeze" which sounds awesome on a hot, summer day.

As we always do, we relied heavily on our amazing community who quickly grasped onto this project and helped us along the way. In fact, many of the signatures you see on the next page are community members, who've stepped up and helped develop and beta tested this product with us. We believe the products should be built by people who actually use them not by some corporate project manager.

To see the origin of this project, as well as the journey scan the code or visit: [inov.li/zephyr](https://inov.li/zephyr)



 George Bay Nathan Proulx  
Eric Cuthing Mark NATE  
 Wang  Don  Robert  Cathy  
Cathy 唐忠清 Rob ADAM's Skat  
王宇坤  Hankin  Rachel  Shun  Dany  
Hankin Rachel

**Thank You.**

inovelli®