1		2	
品牌	BOYA	长丰型号	BY-XM6

7			8	
修改名称	版本	变更内容	变更日期	变更担当

BOYA

Microphone

2.4GHz 迷你双通道无线麦克风系统

BY-XM6-S1
BY-XM6-S2

User Manual
用户手册

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

General Introduction

BOYA BY-XM6 systems are incredibly lightweight, ultracompact and easy-to-use wireless microphone systems for up to 2 people.

The microphone delivers exceptional, broadcast-quality sound to DSLR, mirrorless and video cameras, smartphones, tablets, computers, etc.

It is ideal for content creation, vlogging, mobile journalism, and more.

Available Kits

Model	In the box
BY-XM6-S1	1×BY-XM6 RX
	1×BY-XM6 TX
BY-XM6-S2	1×BY-XM6 RX
	2×BY-XM6 TX

Models: BY-XM6 TX, WMX-2 TX, BY-XM6 TXW, BY-XM6 TX Mini, BY-XM6 TX Mini-W

Models: BY-XM6 RX, WMX-2 RX, BY-XM6 RXW

01

Product Structure

Wireless Receiver BY-XM6 RX



1. OLED display
- For more details, please refer to "OLED Display Operation Guide".
2. Belt clip
3. Charging contacts

02



4. Power/Mute button

Function	Operation
Power ON	Long press
Power OFF	
Mute ON	Short press
Mute OFF	

5. +/SET button

Function	Operation
+	On home screen, short press to increase volume.
	On menu screen, short press to select different functions or values shown on the display.
SET	On home screen, long press to enter the menu screen.
	On menu screen, long press to enter the displayed menu. Then, long press again to confirm your option.

03



6. - button
- On home screen, short press to decrease volume.
- On menu screen, short press to select different functions or values shown on the display.
- long press to return to home screen.

7. USB-C charging port (DC 5V)

8. 3.5mm headphone output
- Connect headphones for audio monitoring.

9. LINE OUT jack
- Connect the BY-XM6 RX to a smartphone, tablet, camera, recorder or mixer with the supplied output cables.

10. Antenna

04

Wireless Transmitter BY-XM6 TX



1. OLED display
- For more details, please refer to "OLED Display Operation Guide".
2. Belt clip
3. Charging contacts

05



4. Power/Mute button

Function	Operation
Power ON	Long press
Power OFF	
Mute ON	Short press
Mute OFF	

5. +/SET button

Function	Operation
+	On home screen, short press to adjust mic gain.
	On menu screen, short press to select different functions or values shown on the display.
SET	On home screen, long press to enter the menu screen.
	On menu screen, long press to enter the displayed menu. Then, long press again to confirm your option.

06

6. - button
- On home screen, short press to adjust mic gain.
- On menu screen, short press to select different functions or values shown on the display.
- long press to return to home screen.

7. USB-C charging port (DC 5V)



8. Built-in microphone

9. MIC/LINE IN jack
- It can be connected to the supplied 3.5mm lavalier microphone, or other 3.5mm TRS microphones or line-in devices.

10. Antenna

07

OLED Display Operation Guide

Wireless Receiver BY-XM6 RX

Home screen

If no operation is performed within 20 seconds on other screens, the display will automatically return to home screen.



1. Pairing indicator
Paired successfully Disconnected Pairing
2. RX's output mode
M: Mono S: Stereo
3. Output volume & Mute indicator
on home screen, press +/- button to adjust the volume.
Mute ON Mute OFF
4. RX's battery level indicator
Displays the RX battery level. Please recharge the device immediately when the indicator starts flashing.
5. Audio input level meter
Displays the audio input level.

08

Menu screen

On home screen, long press SET button to enter menu screen.
On menu screen, long press - button to return to home screen.



Connect Setting
Pair with the transmitter. For details of operation, please refer to "Operation Guide".

Backlight Setting
Set backlight to always on or on for 10/30/60 seconds.
Default is "On".

09



Mute Key Setting
Enable or disable mute key button function.
Default is "Enable".

Output Volume Setting
Output volume can be set from 0 to 6.
Default is "5".



Output Mode Setting
The output mode can be set to either mono or stereo. When in mono mode, the audio from the transmitter, or transmitters will be mixed to both the left and right sides. When in stereo mode, the two transmitters' audio output will be separated to the left and right sides.
Default is mono.

10

Language Setting
English or Chinese are available.
Default is English.



Restore Default Setting

Version of the BY-XM6 RX

11

2.Wireless Transmitter BY-XM6 TX

Home screen

If no operation is performed within 20 seconds on other screens, the display will automatically return to home screen.

1. Pairing indicator
Paired successfully Disconnected Pairing
2. Mic gain & Mute indicator
on home screen, press +/- button to adjust the microphone's input gain level.
Mute ON Mute OFF
3. Audio input level meter
Displays the audio input level.
4. TX's battery level indicator
Displays the TX battery level. Please recharge the device immediately when the indicator starts flashing.

12

Menu screen

On home screen, long press SET button to enter menu screen.
On menu screen, long press - button to return to home screen.

Connect Setting
Pair with the receiver. For details of operation, please refer to "Operation Guide".

Backlight Setting
Set backlight to always on or on for 10/30/60 seconds.
Default is "On".

13

Mute Key Setting
Enable or disable mute key button function.
Default is "Enable".



Mic Gain Setting
Adjust the microphone's input gain level (0–6).
Default is "5".



Input Mode Setting
The input mode can be selected to Mic In or Line In. When Mic In mode selected, the transmitter can be connected to the supplied lavalier microphone, or other microphones with a 3.5mm TRS output. When Line In mode selected, the transmitter can be connected to line-level output devices.
Default is "Mic In".

14



Language Setting
English or Chinese are available.
Default is English.

Restore Default Setting

Version of the BY-XM6 TX

15

Operation Guide

1. Long press the power button to turn on/off the transmitter and the receiver.
2. Pairing
Before leaving factory, the system is pre-paired. Therefore, the connection will be established once they are powered on. If they are disconnected, please follow below steps:
① Long press the SET button to enter menu screen
② Use the + or - button to display the Connect setting menu on both transmitter and receiver.

③ Long press the SET button to select the menu.

④ Select Yes, and long press the SET button to confirm.
⑤ Transmitter and receiver will be successfully paired within 10s.

3. Connect the receiver to the mic input of a camera, recorder or mixer with the supplied 3.5mm TRS cable. Or connect the RX to a smartphone, tablet, or computer with the supplied 3.5mm TRS to TRRS cable.
4. You are ready to record.

16

Features

- 2.4GHz wireless transmission technology
- Ideal for content creation, vlogging, mobile journalism, and more
- Delivers exceptional, broadcast-quality sound
- Ultracompact clip-on transmitter and dual-channel receiver
- Easy-to-use OLED display
- Real-time headphone monitoring
- Operating range of up to 100m
- High-quality built-in microphone
- Lavalier microphone included

IC Caution:
Radio Standards Specification RSS-Gen, issue 5
- English:
This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:
This device may not cause interference.
This device must accept any interference, including interference that may cause undesired operation of the device.

- French:
Cet appareil contient des émetteurs / récepteurs exemptés de licence conformes aux RSS (RSS) d'Innovation, Sciences et Développement économique Canada. Le fonctionnement est soumis aux deux conditions suivantes:
Cet appareil ne doit pas causer d'interférences.
Cet appareil doit accepter toutes les interférences, y compris celles susceptibles de provoquer un fonctionnement indésirable de l'appareil.

17

Specifications

BY-XM6 TX Transmitter

Transmission Type	2.4GHz Digital Frequency
Modulation	GFSK
Operating Range (without obstacle)	Up to 328ft (100m)
RF Output Power	< 10mW
Polar Pattern	Omnidirectional
Frequency Response	50Hz-18kHz
Maximum SPL	Built-in Microphone : 120dB SPL
	Lavalier Microphone : 110dB SPL
Sensitivity	Built-in Microphone : 0dB
	Lavalier Microphone : 0dB
SNR	> 84dB
Power Requirements	Built-in Li-ion Battery or USB-C DC 5V or Charging Contact
Built-in Battery Life	Approx. 7 hours
Antenna	PIFA Antenna
Audio Inputs	3.5mm TRS MIC/LINE IN Jack or Built-in Microphone
Weight	Approx. 32g(1.13oz)
Dimensions	62.1x31.6x16.5mm
Operating Temperature	-10°C to 50°C
Storage Temperature	-20°C to +55°C

18

BY-XM6 RX Receiver

Transmission Type	2.4GHz Digital Frequency
Modulation	GFSK
Operating Range (without obstacle)	Up to 328ft (100m)
Audio Output Connector	3.5mm Headphone Jack
	3.5mm TRS Output Jack
Audio Output Level	>60 dBV@-20dBV
Power Requirements	Built-in Li-ion Battery or USB-C DC 5V or Charging Contact
Built-in Battery Life	Approx. 7 hours
Antenna	PIFA Antenna
Weight	Approx. 32g(1.13oz)
Dimensions	62.1x31.6x16.5mm
Operating Temperature	-10°C to 50°C
Storage Temperature	-20°C to +55°C

19

Packing List

BY-XM6-S1 (1×BY-XM6 RX + 1×BY-XM6 TX)
1x BY-XM6 RX Receiver
1x BY-XM6 TX Transmitter
2x USB-C Charging Cable
1x Lavalier Microphone
1x Mic Clip for Lavalier Microphone
1x Foam Windscreen for Lavalier Microphone
1x Fur Windshield for Built-in Microphone
1x 3.5mm TRS to TRS Output Cable for Cameras
1x 3.5mm TRS to TRRS Output Cable for Smartphones

BY-XM6-S2 (1×BY-XM6 RX + 2×BY-XM6 TX)
1x BY-XM6 RX Receiver
2x BY-XM6 TX Transmitter
3x USB-C Charging Cable
2x Lavalier Microphone
2x Mic Clip for Lavalier Microphone
2x Foam Windscreen for Lavalier Microphone
2x Fur Windshield for Built-in Microphone
1x 3.5mm TRS to TRS Output Cable for Cameras
1x 3.5mm TRS to TRRS Output Cable for Smartphones

20

概述

感谢您选择BOYA！

博雅BY-XM6 系统是迷你双通道无线麦克风系统，提供出色的广播级音质，适用于相机、无反相机、手机、平板电脑等设备，是内容创作、Vlog拍摄、街头采访等场景的理想选择。

BY-XM6组合套装

型号	套装内容
BY-XM6-S1	1×BY-XM6 RX
	1×BY-XM6 TX
BY-XM6-S2	1×BY-XM6 RX
	2×BY-XM6 TX

21

产品结构

无线接收器BY-XM6 RX



1. OLED显示屏
– 详情参考"OLED屏幕操作指南"。
2. 背夹
3. 充电触点

22



4. 电源键/静音键

功能	操作
开机	长按
关机	
静音开启	短按
静音关闭	

5. +/SET键

功能	操作
+	在主界面上，短按+键调大音量； 在菜单界面上，短按+键调整各参数值或功能。
SET	在主界面上，长按设置键进入菜单界面； 在菜单界面，长按设置键进入选定界面，再次长按保存设定。

23



6. - 键
– 在主界面上，短按-键减小音量；
– 在菜单界面上，短按-键调整各参数值或功能；
– 长按-键回到主界面。

7. USB-C充电口（直流电5V）

8. 3.5mm耳机插孔
– 接入耳机进行音频监听。

9. LINE OUT线性输出孔
– 使用随附输出线，将 BY-XM6 RX 连接至手机、平板电脑、相机、录音笔或混音器等设备。

10. 天线

24

无线发射器BY-XM6 TX



1. OLED显示屏
– 详情参考"OLED屏幕操作指南"。
2. 背夹
3. 充电触点

25



4. 电源键/静音键

功能	操作
开机	长按
关机	
静音开启	短按
静音关闭	

5. +/SET键

功能	操作
+	在主界面上，短按+键调节麦克风增益； 在菜单界面上，短按+键调整各参数值或功能。
SET	在主界面上，长按设置键进入菜单界面； 在菜单界面，长按设置键进入选定界面，再次长按保存设定。

26

6. - 键
– 在主界面上，短按-键调节麦克风增益；
– 在菜单界面上，短按-键调整各参数值或功能；
– 长按-键回到主界面。

7. USB-C充电口（直流电5V）



8. 内置麦克风

9. 麦克风/线性输入孔
– 可接入随附的3.5 mm领夹麦或其他 3.5 mm TRS 麦克风或线路输入设备。

10. 天线

27

OLED屏幕操作指南

无线接收器BY-XM6 RX

主界面

若超过20秒不操作，显示屏会自动跳转回主界面上。

1. 配对状态标识
联机成功 未联机 对码中
2. 接收器输出模式
M: 单声道 S: 立体声
3. 输出音量、静音状态指示
在主界面上，短按+/-键可调节音量大小。
静音开启 静音关闭
4. 接收器电量指示
显示接收器电量情况，若图标为空格且开始闪烁，请及时进行充电。
5. 实时输入电平指示
显示实时输入电平大小。

28

菜单界面

在主界面上，长按+/SET键，可进入菜单页面；
在菜单界面，长按-键，可返回到主界面。



连接设置
与发射器配对，具体操作请参考"操作指南"。

背光时间设置
背光灯时间可设置为常亮、10秒、30秒、或60秒，
默认设置为"常亮"。

29

静音按键功能设置
开启或关闭静音按键功能，默认设置为"开启"。

输出音量设置
输出音量调节范围（0-6），默认设置为"5"。



输出模式设置
输出模式可以设置为单声道或立体声。当在单声道模式，音频将混合到左右两边。在立体声模式下，两个发射器的音频输出将左右分开。默认设置为"单声道"。

30

语言设置
English/中文可供选择，默认设置为"English"。



恢复默认设置



BY-XM6 RX版本号

31

无线发射器BY-XM6 TX

主界面

若超过20秒不操作，显示屏会自动跳转回主界面上。

1. 配对状态标识
联机成功 未联机 对码中
2. 麦克风增益、静音状态指示
在主界面上，短按+/-键可调节麦克风增益。
A:静音开启 A:静音关闭
3. 实时输入电平指示
显示实时输入电平大小。
4. 发射器电量指示
显示发射器电量情况，若图标为空格且开始闪烁，请及时进行充电。

32

菜单界面

在主界面上，长按+/SET键，可进入菜单页面；
在菜单界面，长按-键，可返回到主界面。

连接设置
与接收器配对，具体操作请参考"操作指南"。

背光时间设置
背光灯时间可设置为常亮、10秒、30秒、或60秒，
默认设置为"常亮"。

33

静音按键功能设置
开启或关闭静音按键功能，默认设置为"开启"。

麦克风增益设置
麦克风增益调节范围（0-6），默认设置为"5"。



输入模式设置
麦克风输入模式：可接入3.5mm领夹麦克风或其他3.5mm TRS麦克风。（系统默认设置）
线路输入模式：可接入线路输入设备。

34

语言设置
English/中文可供选择，默认设置为"English"。



恢复默认设置

BY-XM6 TX版本号

35

操作指南

1. 长按电源键，将发射器、接收器开机。
2. 配对
发射器和接收器出厂前已配对成功。因此，产品开机之后会自动联机。
若无成功连接，请进行如下配对操作：
① 长按SET键进入菜单界面
② 使用+或-按钮在发射器和接收器上选择"连接请求"菜单

③ 长按SET键进入菜单

④ 选择是，长按SET键确认
⑤ 发射器和接收器将在 10 秒内完成配对

3. 使用随附的 3.5mm TRS转 TRS转接线将接收器连接至相机、录音笔或混音器等设备。或者使用随附的3.5mm TRS 转 TRRS 转接线将 接收器连接至手机、平板电脑等移动设备。
4. 开始录制。

36

特点

- 2.4GHz无线传输技术
- 视频内容创作、移动新闻等的理想选择
- 提供卓越的广播级音质
- 超紧凑型夹式发射器和双通道接收器
- 具有易于操作的OLED 显示屏
- 实时耳机监听功能
- 工作范围可达 100m
- 高品质内置麦克风
- 配备领夹麦克风

37

参数

BY-XM6 TX 发射器

传输方式	2.4GHz数字频段
信号调制	高斯频移键控
操作距离（无障碍）	最远至100米
射频输出功率	< 10mW
极性模式	全向型
频率响应	20Hz–18kHz
最大声压级	内置麦克风：120dB SPL
	领夹麦克风：110dB SPL
灵敏度	内置麦克风：-39dB
	领夹麦克风：-39dB
信噪比	> 84dB
供电方式	内置锂电池 / USB-C直流电5V /充电金触点充电
内置电池续航时间	约7小时
天线	PIFA天线
音频输入源	3.5mm TRS麦克风/线性输入，或内置麦克风
重量	约32g
尺寸	62.1x31.6x16.5mm
工作温度	-10℃ – 50℃
贮存温度	-20℃ – +55℃

38

BY-XM6 RX 接收器

传输方式	2.4GHz数字频段
信号调制	高斯频移键控
操作距离（无障碍）	最远至100米
音频输出口	3.5mm耳机插孔
	3.5mm TRS输出孔
音频输出电平	>60 dBV@-20dBV
供电方式	内置锂电池 / USB-C直流电5V /充电金触点充电
内置电池续航时间	约7小时
天线	PIFA天线
重量	约32g
尺寸	62.1x31.6x16.5mm
工作温度	-10℃ – 50℃
贮存温度	-20℃ – +55℃

39

包装清单

BY-XM6-S1 (1xBY-XM6 RX + 1xBY-XM6 TX)
1x BY-XM6 RX接收器
1x BY-XM6 TX发射器
2x USB-C充电线
1x 领夹麦
1x 麦克风夹子
1x 领夹麦防风海绵
1x 内置麦克风防风毛套
1x 3.5mm TRS转TRS相机输出线
1x 3.5mm TRS转TRRS手机输出线

BY-XM6-S2 (1xBY-XM6 RX + 2xBY-XM6 TX)
1x BY-XM6 RX接收器
2x BY-XM6 TX发射器
3x USB-C充电线
2x 领夹麦
2x 麦克风夹子
2x 领夹麦防风海绵
2x 内置麦克风防风毛套
1x 3.5mm TRS转TRS相机输出线
1x 3.5mm TRS转TRRS手机输出线

40

www.boya-mic.com

SHENZHEN JIAYZ PHOTO INDUSTRIAL., LTD.
The BOYA logo is a trademark which is registered and owned by Shenzhen Jiayz Photo Industrial., Ltd.
深圳市长丰影像器材有限公司
特此广告宣示所生产的无线麦克风系统是符合动力智能终端产品EMI规格

TEL: 400 6110096
Email: sales@boya-mic.com
www.boya-mic.com / www.jiayz.com

技术要求：

1、表面无色差
2、无正负公差
3、包装标注尺寸为内尺寸

长丰影像
2021-8-25
吴蒙蒙

JIAYZ 长丰 深圳市长丰影像器材有限公司					
子件名称	BY-XM6-K系列说明书		版本	V00	
子件编号	1F0300300430	材质	80g书写纸 骑马钉 48p		
尺寸	112x112	比例	1:1	单位	mm
设计/日期	吴蒙蒙 2021-8-25	审核	暂无	核准/日期	赵宏亮