

Duracell

**Portable Power Station
M250**



User Manual

Important Safety Instructions

1. Read all the instructions before using the Duracell Portable Power Station M250 (hereinafter referred as Unit).
2. To reduce the risk of injury, close supervision is necessary when the Unit is used near children.
3. Do not expose the Unit to rain or snow.
4. Use only recommended Duracell accessories and chargers.
5. Do not expose the Unit to fire or excessive temperature. Any such exposure to fire or temperature above 140°F (60°C) may cause explosion. Do not use near flammable gases or fumes.
6. Do not use the Unit with damaged wires or plugs. It may cause an electric shock.
7. Do not use the Unit if it is damaged or modified. Damage or modification of the Unit, including the lithium-ion battery pack within the Unit, may exhibit unpredictable behavior resulting in fire, explosion or risk of injury.
8. Please make sure to use the Unit in a ventilated environment. Do not restrict the ventilation of the Unit in any way during usage.
9. During storage keep the Unit in a dry and ventilated place to avoid moisture and electric shock.
10. Do not disassemble, repair, or modify the Unit or the battery pack. It may cause fire, explosion, injury, and unpredictable risks.
11. This Unit has no serviceable parts. Please visit www.duracell.com or call Duracell Consumer Relations at 800-551-2355 if you experience any problems with the Unit.

Serious injuries include blindness, burns, electric shock, fractures, poisoning, etc., which can lead to complications. Hospitalization, permanent treatment, or death can occur if instructions are not followed.

Instructions de sécurité importantes

- 1.veuillez lire toutes les instructions avant d'utiliser Duracell portable power station 500 (ci - après l'unité).
2. Pour réduire le risque de blessure, une surveillance étroite est nécessaire lors de l'utilisation de cet appareil près des enfants.
3. N'exposez pas l'appareil à la pluie et à la neige.
4. Utilisez uniquement les accessoires et chargeurs Duracell recommandés.
5. N'exposez pas l'appareil au feu ou à une température trop élevée. Un tel incendie ou une température supérieure à 60 ° C (140 ° f) peut provoquer une explosion. Ne pas utiliser à proximité de gaz ou de fumées inflammables.
6. N'utilisez pas cet appareil avec des fils ou des prises endommagés. Cela peut provoquer une électrocution.
7. Ne pas utiliser si l'unité est endommagée ou modifiée. Les dommages ou les modifications à l'appareil, y compris les batteries lithium - ion à l'intérieur de l'appareil, peuvent présenter un comportement imprévisible, entraînant un risque d'incendie, d'explosion ou de blessure.
8. S'il vous plaît assurez - vous d'utiliser cet appareil dans un environnement ventilé. La ventilation de l'appareil ne doit en aucun cas être limitée pendant l'utilisation.
9. Pendant le stockage, veuillez stocker cet appareil dans un endroit sec et ventilé pour éviter l'humidité et l'électrocution.
10. Ne pas démonter, réparer ou modifier l'unité ou la batterie. Il peut provoquer des incendies, des explosions, des blessures et des risques imprévisibles.
11. Il n'y a pas de pièces réparables pour cet appareil. Si vous rencontrez des problèmes avec cette unité, visitez www.duracell.com ou appelez le Service des relations avec les consommateurs de Duracell au 800 - 551 - 2355.

Les blessures graves comprennent la cécité, les brûlures, les électrocutions, les fractures, les intoxications, etc., qui peuvent entraîner des complications. Le non - respect des instructions peut entraîner une hospitalisation, un traitement permanent ou la mort.

WARNING AND HAZARD TYPES

ELECTRIC SHOCK HAZARD

Keep away from children. The unit generates the same potentially lethal AC power as a standard household wall outlet. To reduce the risk of fire or electric shock, do not open the enclosure or expose the Unit to rain or moisture. Do not insert foreign objects into the AC connection or the ventilation holes. All AC plugs must be properly inserted and avoid using damaged cables.

EXPLOSION HAZARD

Do not burn or incinerate this Unit or battery pack. It may explode, causing personal injury or damage. Do not use near flammable gases or fumes or apparatus that produces large amounts of heat.

Avertissements et types de danger

Danger d'électrocution

Tenez - vous loin des enfants. L'appareil produit le même courant alternatif potentiellement mortel qu'une prise murale domestique standard. Pour réduire le risque d'incendie ou d'électrocution, n'ouvrez pas le boîtier ou n'exposez pas l'appareil à la pluie ou à l'humidité. N'insérez pas de corps étranger dans les raccordements de climatisation ou les orifices de ventilation. Toutes les prises AC doivent être branchées correctement et éviter l'utilisation de câbles endommagés.

Danger d'explosion

Ne pas brûler ou incinérer cet appareil ou la batterie. Il peut exploser et causer des blessures ou des dommages corporels. Ne pas utiliser à proximité de gaz inflammables, de fumées ou d'appareils produisant beaucoup de chaleur.

FCC Statement

This device complies with Part 15 of the FCC Rules and Class B Digital Device limits which provide protection against interference in a residential installation. Operation is subject to the following two conditions:

1. This device may not cause harmful interference
2. This device must accept any interference received, including interference that may cause undesired operation.

This device generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause interference to radio/TV communications in which the manufacturer is not responsible. Should interference occur, correct by connecting device to another outlet on a different circuit.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- o Reorient or relocate the receiving antenna.
- o Increase the separation between the equipment and receiver.
- o Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- o Consult the dealer or an experienced radio/TV technician for help.

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- 1) L'appareil ne doit pas produire de brouillage;
- 2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Contents

Product Specifications **Error! Bookmark not defined.**

Packaging Content..... **Error! Bookmark not defined.**

Charging your Powerstation **Error! Bookmark not defined.**

Using your Power Station **2**

Storage and Maintenance..... **2**

Disposal and Recycling **2**

Troubleshooting **Error! Bookmark not defined.**

FAQs..... **Error! Bookmark not defined.**

Warranty Information **Error! Bookmark not defined.**

Specifications

Model	MBA250W-219Wh-120V
Battery	
Chemistry	Li-Ion NMC
Maximum Capacity	219Wh (15Ah@14.6V)
Lifecycles	500 Cycles to 80% capacity
Storage Requirement	Recharge every 3-6 months
Protection Systems	Short Circuit Protection, Over / Under Temperature Protection, Overload Protection, Input Reverse polarity Protection, Input Over Voltage Protection, Input Under Voltage Protection, Battery Under and overvoltage Protection.
Ports	
2x USB-A Port (Output)	5V @ 3A 9V @ 2A 12 @ 1.5A
USB C-1 port (Input and Output)	PD 100W
USB C- 2 port(Output only)	PD 60W
120 AC Inverter (Output, Pure Sine Wave)	120V, 60Hz (1000W continuous, 2000W Peak)
Docking Station/Charging Dock	1 EA. Rated at 60W 24VDC 2.5A
General	
Dimensions	Ø127x236.3mm
Weight	PPS: 1800g Adaptor & DOCK: 290g
Discharging Temperature	14 -104°F (-10-40°C)
Charging Temperature	39.2-104°F (4-40°C)
Storage Temperature	42-85°F (6-29°C)
Certifications	FCC/DOE/UL/RoHS/Prop-65/TSCA
Warranty	24 Months

Included in the Package

1. Duracell Portable Power Station M250
2. Wall Charger + Docking Station

Using your Portable Power Station

(Use Icons)

1. Short Press power on button to turn the unit on. The SOC LED will light up and the battery level indicator will display.
2. Connect your device to the desired port/outlet.
3. AC outlets can only charge/power devices rated less than 250 Watts. Once this limit is exceeded, the Unit will shut off automatically.
4. The AC port output will turn off automatically after 5mins if no load is detected to save battery life.
5. The DC port or car charger port will turn off automatically in 4 hours if no load is detected to save battery life.
6. If the unit won't be used for a long period of time, it should be recharged every 3-6 months and keep the power above 80%. Please keep it in a cool and dry place.

Storage and Maintenance

1. Please keep the unit in a cool and well-ventilated environment, away from any source of water, heat or flammable gases.
2. For long-term storage, please recharge the unit every 3-6 month to make sure it's always above 80%.

If you are still experiencing problems with you Duracell Power Station, please visit www.duracell.com or call Duracell Consumer Relations at 800-551-2355.

Disposal and Recycling

Recycle the unit responsibly and according to local, state and national regulations applicable to lithium-ion rechargeable batteries.

Warranty Information

Duracell offers a 24-month limited warranty from the date of purchase. Keep a copy of your purchase receipt as proof of purchase. Our product's warranty is limited only to the unit itself, when used normally in accordance with the operating instructions and the system environment. Therefore, Customer acknowledges and agrees that:

- Duracell is not liable for damage or loss resulting from the use of this product or for any claim from a third party.
- Duracell is not liable for problems with any electronic devices or home appliances or any other hardware, arising from the use of this product, the suitability of the product for specific hardware, software, or peripherals, operating conflicts with other installed software, data loss or other accidental or unavoidable damages.
- Duracell is not liable for financial damages, lost profits, claims from third parties, etc., arising from the use of this product.

For more information regarding our Product line, customer Service and warranty information please contact Duracell Consumer Relations at 800-551-2355 or visit our Website: www.duracell.com