



UniFi Protect Smart Flood Light



Smart managed floodlight with integrated motion detection and light sensing. Housed in a compact design for low profile mounting, and easily configured with UniFi Protect.

Mechanical

| | |
|---------------------|--|
| Dimensions | 135 x 65 x 50 mm (5.31 x 2.56 x 1.97") |
| Weight | Without Mount: 216 g (7.62 oz) With Flat Wall Mount: 236 g (8.32 oz) With Angle Mount: 273 g (9.63 oz) |
| Enclosure Materials | Plastic, Metal |
| Mount Materials | Flat Wall Mount: Plastic Angle Mount: Plastic |
| Weatherproofing | IPX5 |

Hardware

| | |
|------------------------|--------------------------------|
| Processor | The Qualcomm® QCA9531 SoC |
| Memory Information | 64 MB DDR2 |
| Management Interface | UniFi Protect |
| Networking Interface | 10/100 Mbps RJ45 Ethernet Port |
| Max. Power Consumption | 10.5W |
| Power Method | 802.3af PoE |
| Power Supply | 802.3af PoE, 48VDC, 0.22A Max |
| ESD/EMP Protection | Air: ± 8kV, Contact: ± 8kV |
| Button | Factory Reset |
| RF | Bluetooth 4.0 |
| LEDs | R/B/W |
| Operating Temperature | -10 to 45° C (14 to 113° F) |
| Operating Humidity | 20 to 80% Noncondensing |
| Certifications | FCC, IC, CE |



Specifications are subject to change. Ubiquiti products are sold with a limited warranty described at: www.ui.com/support/warranty
© 2020 Ubiquiti Inc. All rights reserved. Ubiquiti, the Ubiquiti U logo, the Ubiquiti beam logo, UniFi, and UniFi Protect are trademarks or registered trademarks of Ubiquiti Networks, Inc. in the United States and in other countries. Apple and the Apple logo are trademarks of Apple Inc., registered in the U.S. and other countries. All other trademarks are the property of their respective owners.

FCC

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions.

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

"This equipment has been tested and found to comply with the limits for a Class B digital device. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help."

[ISED Canada](#)

[CAN ICES-3\(B\)/NMB-3\(B\)](#)

This device complies with ISED Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions:

1. This device may not cause interference, and
2. This device must accept any interference, including interference that may cause undesired operation of the device.

The device for operation in the band 5150-5250 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems.

[CAN ICES-3\(B\)/NMB-3\(B\)](#)

Le présent appareil est conforme aux CNR d'ISDE Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

1. l'appareil ne doit pas produire de brouillage;
2. l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Les dispositifs fonctionnant dans la bande 5150-5250 MHz sont réservés uniquement pour une utilisation à l'intérieur afin de réduire les risques de brouillage préjudiciable aux systèmes de satellites mobiles utilisant les mêmes canaux.

[RF Exposure Warning](#)

The antennas used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be

located or operating in conjunction with any other antenna or transmitter. Les antennes utilisées pour ce transmetteur doivent être installées en considérant une distance de séparation de toute personnes d'au moins 20 cm et ne doivent pas être localisées ou utilisées en conflit avec tout autre antenne ou transmetteur.