






802.11ax-HE80 Power Spectral Density - Ant 1


Channel 42 (5210MHz)




Channel 58 (5290MHz)




Channel 106 (5530MHz)




Channel 122 (5610MHz)



Channel 138 (5690MHz)




Channel 155 (5775MHz)




802.11a Power Spectral Density - Ant 2


Channel 36 (5180MHz)




Channel 40 (5200MHz)




Channel 48 (5240MHz)




Channel 52 (5260MHz)




Channel 60 (5300MHz)




Channel 64 (5320MHz)




Channel 100 (5500MHz)




Channel 116 (5580MHz)






802.11ac-VHT20 Power Spectral Density - Ant 2


Channel 36 (5180MHz)




Channel 40 (5200MHz)




Channel 48 (5240MHz)




Channel 52 (5260MHz)




Channel 60 (5300MHz)




Channel 64 (5320MHz)




Channel 100 (5500MHz)




Channel 116 (5580MHz)






802.11ac-VHT40 Power Spectral Density - Ant 2


Channel 38 (5190MHz)




Channel 46 (5230MHz)




Channel 54 (5270MHz)




Channel 62 (5310MHz)




Channel 102 (5510MHz)




Channel 110 (5550MHz)



Channel 134 (5670MHz)




Channel 142 (5710MHz)






802.11ac-VHT80 Power Spectral Density - Ant 2


Channel 42 (5210MHz)




Channel 58 (5290MHz)




Channel 106 (5530MHz)




Channel 122 (5610MHz)



Channel 138 (5690MHz)




Channel 155 (5775MHz)




802.11ax-HE20 Power Spectral Density - Ant 2


Channel 36 (5180MHz)




Channel 40 (5200MHz)




Channel 48 (5240MHz)




Channel 52 (5260MHz)




Channel 60 (5300MHz)




Channel 64 (5320MHz)




Channel 100 (5500MHz)




Channel 116 (5580MHz)






802.11ax-HE40 Power Spectral Density - Ant 2


Channel 38 (5190MHz)




Channel 46 (5230MHz)




Channel 54 (5270MHz)




Channel 62 (5310MHz)




Channel 102 (5510MHz)




Channel 110 (5550MHz)




Channel 134 (5670MHz)




Channel 142 (5710MHz)






802.11ax-HE80 Power Spectral Density - Ant 2


Channel 42 (5210MHz)




Channel 58 (5290MHz)



Channel 106 (5530MHz)



Channel 122 (5610MHz)



Channel 138 (5690MHz)



Channel 155 (5775MHz)



7.7. Frequency Stability Measurement

7.7.1. Test Limit

Manufacturers of U-NII devices are responsible for ensuring frequency stability such that an emission is maintained within the band of operation under all conditions of normal operation as specified in the user's manual.

7.7.2. Test Limit

Frequency Stability Under Temperature Variations:


The equipment under test was connected to an external AC or DC power supply and input rated voltage. RF output was connected to a frequency counter or spectrum analyzer via feed through attenuators. The EUT was placed inside the temperature chamber. Set the spectrum analyzer RBW low enough to obtain the desired frequency resolution and measure EUT 20°C operating frequency as reference frequency. Turn EUT off and set the chamber temperature to highest. After the temperature stabilized for approximately 30 minutes recorded the frequency. Repeat step measure with 10°C decreased per stage until the lowest temperature reached.

Frequency Stability Under Voltage Variations:

Set chamber temperature to 20°C. Use a variable AC power supply / DC power source to power the EUT and set the voltage to rated voltage. Set the spectrum analyzer RBW low enough to obtain the desired frequency resolution and recorded the frequency.

Reduce the input voltage to specify extreme voltage variation ($\pm 15\%$) and endpoint, record the maximum frequency change.

7.7.3. Test Setup



7.7.4. Test Result

Grantee ensure that the product meets e-CFR Title 47 section 15.407(g) and KDB 789033 D02v02r01 frequency stability such that the emissions are maintained within the band of operation under all conditions of normal operation as specified in the user's manual.

7.8. Radiated Spurious Emission Measurement

7.8.1. Test Limit

All out of band emissions appearing in a restricted band as specified in Section 15.205 of the Title 47CFR must not exceed the limits shown in Table per Section 15.209.

FCC Part 15 Subpart C Paragraph 15.209		
Frequency [MHz]	Field Strength [uV/m]	Measured Distance [Meters]
0.009 - 0.490	2400/F (kHz)	300
0.490 - 1.705	24000/F (kHz)	30
1.705 - 30	30	30
30 - 88	100	3
88 - 216	150	3
216 - 960	200	3
Above 960	500	3

7.8.2. Test Procedure Used

KDB 789033 D02v02r01- Section II)G)

7.8.3. Test Setting

Table 1 - RBW as a function of frequency

Frequency	RBW
9 ~ 150 kHz	200 ~ 300 Hz
0.15 ~ 30 MHz	9 ~ 10 kHz
30 ~ 1000 MHz	100 ~ 120 kHz
>1000 MHz	1 MHz

Quasi-Peak Measurements below 1GHz

1. Analyzer center frequency was set to the frequency of the radiated spurious emission of interest
2. Span was set greater than 1MHz
3. RBW = as specified in Table 1
4. Detector = CISPR quasi-peak
5. Sweep time = auto couple
6. Trace was allowed to stabilize

Peak Measurements above 1GHz

1. Analyzer center frequency was set to the frequency of the radiated spurious emission of interest
2. RBW = 1MHz
3. VBW = 3MHz
4. Detector = peak
5. Sweep time = auto couple
6. Trace mode = max hold
7. Trace was allowed to stabilize

Average Measurements above 1GHz (Method VB)

1. Analyzer center frequency was set to the frequency of the radiated spurious emission of interest
2. RBW = 1MHz
3. VBW; If the EUT is configured to transmit with duty cycle $\geq 98\%$, set VBW = 10 Hz.
If the EUT duty cycle is $< 98\%$, set VBW $\geq 1/T$. T is the minimum transmission duration.
4. Detector = Peak
5. Sweep time = auto
6. Trace mode = max hold
7. Trace was allowed to stabilize