


# FCC MPE Report

## RF EXPOSURE REPORT

Applicant	Shenzhen Anboqi Technology Co.,Ltd
Address	3F Building B, No.1 Road 1, Shangxue Technology Park Bantian Town, Longgang District, Shenzhen, Guangdong
Manufacturer or Supplier	Shenzhen Anboqi Technology Co.,Ltd
Address	F/9, Building B, No.5, Rd.1, Shangxue Technology Park, Bantian, Longgang Dist., Shenzhen
Product	Battery camera
Trade Mark	/
Model	ABQ-Q9, ABQ-Q1, ABQ-Q2, ABQ-Q3, ABQ-Q5, ABQ-Q6, ABQ-Q7, ABQ-Q8, ABQ-Q10, ABQ-Q11, ABQ-Q12, ABQ-Q13, ABQ-Q14, ABQ-Q15, ABQ-Q16, ABQ-Q17, ABQ-Q18, ABQ-Q19, ABQ-Q20, ABQ-Q21, ABQ-Q22, QXX
Additional Model & Model Difference	These models of PCB boards, structures, and interiors are the same, Just the Different models
Date of tests	Sept.. 29~Oct. 21, 2024
<input checked="" type="checkbox"/> <b>FCC Part 2 (Section 2.1093)</b> <input checked="" type="checkbox"/> <b>KDB 447498 D01</b> <input checked="" type="checkbox"/> <b>IEEE C95.1</b>	
<b>CONCLUSION: The submitted sample was found to <u>COMPLY</u> with the test requirement</b>	

Tested by


:



(Suny Zhuo)

Reviewed by

:



(Blue Hu)

Approved & Authorized Signer

:



(Binglee)

# FCC MPE Report

---

## Table of Contents

1. STANDALONE SAR TEST EXCLUSION CONSIDERATIONS .....	3
2. SAR TEST EXCLUSION THRESHOLDS .....	4

# FCC MPE Report

---

## 1. Standalone SAR test exclusion considerations

Unless specifically required by the published RF exposure KDB procedures, standalone 1-g head or body and 10-g extremity SAR evaluation for general population exposure conditions, by measurement or numerical simulation, is not required when the corresponding SAR Test Exclusion Threshold condition(s), listed below, is (are) satisfied.

These test exclusion conditions are based on source-based time-averaged maximum conducted output power of the RF channel requiring evaluation, adjusted for tune-up tolerance, and the minimum test separation distance required for the exposure conditions.

The minimum test separation distance defined in 4.1 f) is determined by the smallest distance from the antenna and radiating structures or outer surface of the device, according to the host form factor, exposure conditions and platform requirements, to any part of the body or extremity of a user or bystander.

To qualify for SAR test exclusion, the test separation distances applied must be fully explained and justified, typically in the SAR measurement or SAR analysis report, by the operating configurations and exposure conditions of the transmitter and applicable host platform requirements, according to the required published RF exposure KDB procedures.

When no other RF exposure testing or reporting are required, a statement of justification and compliance must be included in the equipment approval, in lieu of the SAR report, to qualify for SAR test exclusion.

When required, the device specific conditions described in the other published RF exposure KDB procedures must be satisfied before applying these SAR test exclusion provisions.

- a) For 100 MHz to 6 GHz and test separation distances  $\leq 50$  mm, the 1-g and 10-g SAR test exclusion thresholds are determined by the following:

$$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR, and } \leq 7.5 \text{ for 10-g extremity SAR,}$$
where

- $f_{(\text{GHz})}$  is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation
- The result is rounded to one decimal place for comparison
- The values 3.0 and 7.5 are referred to as *numeric thresholds* in step b) below

The test exclusions are applicable only when the minimum test separation distance is  $\leq 50$  mm, and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is  $< 5$  mm, a distance of 5 mm according to 4.1 f) is applied to determine SAR test exclusion.

- b) For 100 MHz to 6 GHz and test separation distances  $> 50$  mm, the 1-g and 10-g SAR test exclusion thresholds are determined by the following (also illustrated in Appendix B):

- 1)  $\{[\text{Power allowed at } \textit{numeric threshold} \text{ for } 50 \text{ mm in step a)}] + [(\text{test separation distance} - 50 \text{ mm}) \cdot (f(\text{MHz})/150)]\}$  mW, for 100 MHz to 1500 MHz

# FCC MPE Report

- 
- 2)  $\{[Power\ allowed\ at\ numeric\ threshold\ for\ 50\ mm\ in\ step\ a)] + [(test\ separation\ distance - 50\ mm) \cdot 10]\}$  mW, for  $> 1500\ MHz$  and  $\leq 6\ GHz$
- c) For frequencies below 100 MHz, the following may be considered for SAR test exclusion (also illustrated in Appendix C):
- 1) For test separation distances  $> 50\ mm$  and  $< 200\ mm$ , the power threshold at the corresponding test separation distance at 100 MHz in step b) is multiplied by  $[1 + \log(100/f(MHz))]$
  - 2) For test separation distances  $\leq 50\ mm$ , the power threshold determined by the equation in c) 1) for 50 mm and 100 MHz is multiplied by  $\frac{1}{2}$
  - 3) SAR measurement procedures are not established below 100 MHz.

When SAR test exclusion cannot be applied, a KDB inquiry is required to determine SAR evaluation requirements for any SAR test results below 100 MHz to be acceptable.

## 2. SAR Test Exclusion Thresholds

We use 5mm as separation distance to calculated.

DTS:BLE

Modulation	Channel Freq. (MHz)	Measured Power (dBm)	Tune-up power (dBm)	Max tune-up	Result	1g SAR
				power(dBm)	calculation	
GFSK	2402	1.89	1±1	2	0.4913	3
	2441	2.16	2±1	3	0.6235	3
	2480	1.68	1±1	2	0.4992	3

DTS:2.4G WiFi

Modulation	Channel Freq. (MHz)	Measured Power (dBm)	Tune-up power (dBm)	Max tune-up	Result	1g SAR
				power(dBm)	calculation	
802.11b	2412	6.44	6±1	7	1.5567	3
	2437	5.85	5±1	6	1.2430	3
	2462	6.01	6±1	7	1.5728	3
802.11g	2412	6.74	6±1	7	1.5567	3
	2437	6.78	6±1	7	1.5648	3
	2462	6.07	6±1	7	1.5728	3
802.11n20	2412	6.03	6±1	7	1.5567	3
	2437	6.74	6±1	7	1.5648	3
	2462	6.45	6±1	7	1.5728	3

### Conclusion:

For the max result:  $1.5728 \leq 3.0$  for 1g SAR, No SAR is required.