

S

T

S

L

A

B



# RADIO TEST REPORT

Report No: STS1711314W06

Issued for


Trackimo LLC.

350NE 24th Street, Unit 104, Miami, Florida, United States

<b>Product Name:</b>	GPS Tracker
<b>Brand Name:</b>	trackimo
<b>Model Name:</b>	TRKM015
<b>Series Model:</b>	N/A
<b>FCC ID:</b>	2AAI6-TRKM015
<b>Test Standard:</b>	FCC Part 22H and 24E

Any reproduction of this document must be done in full. No single part of this document may be reproduced without permission from STS, All Test Data Presented in this report is only applicable to presented Test sample.

Shenzhen STS Test Services Co., Ltd.  
1/F., Building B, Zhuoke Science Park, No.190, Chongqing Road,  
Fuyong Street, Bao'an District, Shenzhen, Guangdong, China  
TEL: +86-755 3688 6288 FAX: +86-755 3688 6277 E-mail: sts@stsapp.com



**TEST RESULT CERTIFICATION****Applicant's name** ..... Trackimo LLC.

Address ..... 350NE 24th Street, Unit 104, Miami, Florida, United States

**Manufacture's Name** ..... HUIZHOU QIAOWEI INTELLIGENT OVERSEAS CO.,LTD

Address ..... B2 building, ELing phase 2, wuyi village, chenjiang steet, gaoxin district, Huizhou city, Guangdong Province, China

**Product discription**

Product Name..... GPS Tracker

Brand Name ..... trackimo

Model Name ..... TRKM015

Series Model..... N/A

**Test Standards** ..... FCC Part 22H and 24E

Test procedure ..... ANSI/TIA 603-D (2010)

This device described above has been tested by STS and the test results show that the equipment under test (EUT) is in compliance with the FCC requirements. And it is applicable only to the tested sample identified in the report.

This report shall not be reproduced except in full, without the written approval of STS, this document may be altered or revised by STS, personal only, and shall be noted in the revision of the document.

**Date of Test** .....

Date of performance of tests ..... 30 Nov. 2017~13 Dec. 2017

Date of Issue ..... 14 Dec. 2017

Test Result..... **Pass**

Testing Engineer :

(Sean she)

Technical Manager :

(Hakim.hou)

Authorized Signatory :

(Vita Li)





TABLE OF CONTENTS	Page
<b>1 INTRODUCTION</b>	<b>6</b>
1.1 TEST FACTORY	6
1.2 MEASUREMENT UNCERTAINTY	6
<b>2 PRODUCT INFORMATION</b>	<b>7</b>
<b>3 TEST CONFIGURATION OF EQUIPMENT UNDER TEST</b>	<b>8</b>
<b>4 MEASUREMENT INSTRUMENTS</b>	<b>9</b>
<b>5 TEST ITEMS</b>	<b>10</b>
5.1 CONDUCTED OUTPUT POWER	10
5.2 PEAK TO AVERAGE RATIO	11
5.3 TRANSMITTER RADIATED POWER (EIRP/ERP)	12
5.4 OCCUPIED BANDWIDTH	13
5.5 FREQUENCY STABILITY	14
5.6 SPURIOUS EMISSIONS AT ANTENNA TERMINALS	15
5.7 BAND EDGE	16
5.8 FIELD STRENGTH OF SPURIOUS RADIATION MEASUREMENT	17
<b>APPENDIX A.TESTRESULT</b>	<b>19</b>
A1.CONDUCTED OUTPUT POWER	19
A2. PEAK-TO-AVERAGE RADIO	23
A3. TRANSMITTER RADIATED POWER (EIRP/ERP)	25
A4. OCCUPIED BANDWIDTH (99% OCCUPIED BANDWIDTH/26DB BANDWIDTH)	28
A5.FREQUENCY STABILITY	36
A6. SPURIOUS EMISSIONS AT ANTENNA TERMINALS	39
A7. BAND EDGE	45
A8. FIELD STRENGTH OF SPURIOUS RADIATION MEASUREMENT	51
<b>APPENDIX BPHOTOS OF TEST SETUP</b>	<b>57</b>

**Revision History**

Rev.	Issue Date	Report NO.	Effect Page	Contents
00	14 Dec. 2017	STS1711314W06	ALL	Initial Issue





## SUMMARY OF TEST RESULTS

Test procedures according to the technical standards:

The radiated emission testing was performed according to the procedures of ANSI/TIA-603-D: 2010, KDB 971168 D01 v02r02 and KDB 648474 D03 v01r04

FCC Rules	Test Description	Test Limit	Test Result	Reference
2.1049	Conducted OutputPower	Reporting Only	PASS	
2.0146 24.232	Peak-to-AverageRatio	< 13 dB	PASS	
2.1046 22.913 24.232	Effective Radiated Power/ Equivalent Isotropic Radiated Power	< 7 Watts max. ERP(Part 22) < 2 Watts max. EIRP(Part 24)	PASS	
2.1049 22.917 24.238	Occupied Bandwidth	Reporting Only	PASS	
2.1055 22.355 24.235	Frequency Stability	< 2.5 ppm (Part 22) Emission must remain in band (Part 24)	PASS	
2.1051 22.917 24.238	Spurious Emission at Antenna Terminals	< 43+10log10(P[Watts])	PASS	
2.1053 22.917 24.238	Field Strength of Spurious Radiation	< 43+10log10(P[Watts])	PASS	
2.1051 22.917 24.238	Band Edge	< 43+10log10(P[Watts])	PASS	



## 1 INTRODUCTION

### 1.1 TEST FACTORY

Shenzhen STS Test Services Co., Ltd.

Add. : 1/F., Building B, Zhuoke Science Park, No.190, Chongqing Road,  
Fuyong Street, Bao'an District, Shenzhen, Guangdong, China

CNAS Registration No.: L7649; FCC Registration No.: 625569

IC Registration No.: 12108A; A2LA Certificate No.: 4338.01;

### 1.2 MEASUREMENT UNCERTAINTY

The measurement uncertainties shown below were calculated in accordance with the requirements of ANSI C63.4-2014. All measurement uncertainty values are shown with a coverage factor of  $k = 2$  to indicate a 95% level of confidence. The measurement data shown herein meets or exceeds the CISPR measurement uncertainty values specified in CISPR 16-4-2 and, thus, can be compared directly to specified limits to determine compliance. °

No.	Item	Uncertainty
1	RF power, conducted	$\pm 0.70\text{dB}$
2	Spurious emissions, conducted	$\pm 1.19\text{dB}$
5	All emissions, radiated (<1G) 30MHz-200MHz	$\pm 2.83\text{dB}$
6	All emissions, radiated (<1G) 200MHz-1000MHz	$\pm 2.94\text{dB}$
7	All emissions, radiated (>1G)	$\pm 3.03\text{dB}$
8	Temperature	$\pm 0.5^{\circ}\text{C}$
9	Humidity	$\pm 2\%$



## 2 PRODUCT INFORMATION

Product Name	GPS Tracker
Hardware version number:	CC01_V2.0
Software version number:	2.0
FCC ID:	2AAI6-TRKM015
Tx Frequency:	GPRS/EDGE: 850: 824 MHz ~ 849 MHz 1900: 1850MHz ~ 1910MHz WCDMA: Band V: 824 MHz ~ 849 MHz Band II: 1850 MHz ~ 1910 MHz
Rx Frequency:	GPRS/EDGE: 850: 869 MHz ~ 894 MHz 1900: 1930 MHz ~ 1990 MHz WCDMA: Band V: 869 MHz ~ 894 MHz Band II: 1930 MHz ~ 1990 MHz
Max RF Output Power:	GPRS850(1-Slot):31.48dBm, GPRS1900(1-Slot):27.96dBm GPRS850(2-Slot):31.07dBm, GPRS1900(2-Slot):27.50dBm GPRS850(3-Slot):30.67dBm, GPRS1900(3-Slot):27.03dBm GPRS850(4-Slot):30.23dBm, GPRS1900(4-Slot):26.63dBm EDGE 850(1-Slot):31.42dBm, EDGE 1900(1-Slot):27.93dBm EDGE 850(2-Slot):30.86dBm, EDGE 1900(2-Slot):27.30dBm EDGE 850(3-Slot):30.44dBm, EDGE 1900(3-Slot):26.77dBm EDGE 850(4-Slot):29.95dBm, EDGE 1900(4-Slot):26.37dBm WCDMA Band V:22.97dBm, WCDMA Band II:22.74dBm
Type of Emission:	GPRS(850): 323KGXW; GPRS(1900): 324KGXW EDGE(850): 323KG7W; EDGE(1900): 325KG7W WCDMA850: 4M83F9W WCDMA1900: 4M82F9W
SIM Card:	Support single card only
Antenna:	PIFA Antenna
Antenna gain:	1.34dBi
Power Supply:	DC 3.8V by battery
Battery	Battery(rating): Rated Voltage: 3.8V Charge Limit: 4.3V Capacity: 800mAh
GPRS/EDGE Class:	Multi-Class12
Extreme Vol. Limits:	DC3.4 V to 4.3 V (Nominal DC3.8V )
Extreme Temp. Tolerance:	-30℃ to +50℃
<b>** Note: The High Voltage 4.3 V and Low Voltage 3.4 V was declared by manufacturer, The EUT couldn't be operate normally with higher or lower voltage.</b>	



### 3 TEST CONFIGURATION OF EQUIPMENT UNDER TEST

Antenna port conducted and radiated test items were performed according to KDB 971168 D01 Power Meas. License Digital Systems with maximum output power.

Radiated measurements were performed with rotating EUT in different three orthogonal test planes to find the maximum emission.

Radiated emissions were investigated as following frequency range:

1. 30 MHz to 10th harmonic for GSM850 and WCDMA Band V.
2. 30 MHz to 10th harmonic for GSM1900 and WCDMA Band II.

All modes and data rates and positions were investigated.

Test modes are chosen to be reported as the worst case configuration below:

BAND	TEST MODES	
	RADIATED TCS	CONDUCTED TCS
GSM 850	GPRS/EDGE CLASS 12 LINK	GPRS/EDGE CLASS 12 LINK
GSM 1900	GPRS/EDGE CLASS 12 LINK	GPRS/EDGE CLASS 12 LINK
WCDMA BAND V	RMC 12.2KBPS LINK	RMC 12.2KBPS LINK
WCDMA BAND II	RMC 12.2KBPS LINK	RMC 12.2KBPS LINK





## 4 MEASUREMENT INSTRUMENTS

Kind of Equipment	Manufacturer	Type No.	Serial No.	Last Calibration	Calibrated Until
EMI Test Receiver	R&S	ESW	101535	2017.06.01	2018.05.31
Signal Analyzer	Agilent	N9020A	MY49100060	2017.03.11	2018.03.10
Test Receiver	R&S	ESCI	101427	2017.10.15	2018.10.14
Universal Radio Communication Tester	R&S	CMW500	117239	2017.06.15	2018.06.14
Bilog Antenna	TESEQ	CBL6111D	34678	2017.03.24	2018.03.23
Horn Antenna	Schwarzbeck	BBHA 9120D	9120D-1343	2017.03.06	2018.03.05
SHF-EHF Horn Antenna (15G-40GHz)	BBHA 9170	SCHWARZBECK	BBHA9170367	2017.05.02	2018.05.01
Low frequency cable	EM	R01	N/A	2017.03.12	2018.03.11
Low frequency cable	EM	R06	N/A	2017.03.12	2018.03.11
High frequency cable	SCHWARZBECK	R04	N/A	2017.03.12	2018.03.11
High frequency cable	SCHWARZBECK	R02	N/A	2017.03.12	2018.03.11
Pre-mpifier (0.1M-3GHz)	EM	EM330	60538	2017.03.12	2018.03.11
PreAmplifier (1G-26.5GHz)	Agilent	8449B	60538	2017.10.15	2018.10.14
Pre-mpifier (18G-40G)	MINI-CIRCUITS	AP-040G	1382501	2017.05.15	2018.05.14
Band Reject filter(1920-1980MHz)	COM-MW	ZBSF-1920-1980	0092	2017.10.15	2018.10.14
Band Reject filter(880-915MHz)	COM-MW	ZBSF-C897.5-35	707	2017.10.15	2018.10.14
Band Reject filter(1710-1785MHz)	COM-MW	ZBSF-C1747.5-75	708	2017.10.15	2018.10.14
Band Reject filter(1850-1910MHz)	COM-MW	ZBSF-C1880-60	709	2017.10.15	2018.10.14
Band Reject filter(2500-2570MHz)	COM-MW	ZBSF-C2535-70	710	2017.10.15	2018.10.14
Highpass Filter	WHKX7.0/18G-8SS	Wainwright	18	2017.10.15	2018.10.14
trun table	EM	SC100_1	60531	N/A	N/A
Antnna mast	EM	SC100	N/A	N/A	N/A

Equipment with a calibration date of "NCR" shown in this list was not used to make direct calibrated measurements.



## 5 TEST ITEMS

### 5.1 CONDUCTED OUTPUT POWER

#### Test overview

A system simulator was used to establish communication with the EUT. Its parameters were set to enforce EUT transmitting at the maximum power. The measured power in the radio frequency on the transmitter output terminals shall be reported.

#### Test procedures

1. The transmitter output port was connected to the system simulator.
2. Set eut at maximum power through the system simulator.
3. Select lowest, middle, and highest channels for each band and different modulation.
4. Measure and record the power level from the system simulator.

#### Test setup





## 5.2 PEAK TO AVERAGE RATIO

### TEST OVERVIEW

According to §24.232(d), power measurements for transmissions by stations authorized under this section may be made either in accordance with a commission-approved average power technique or in compliance with paragraph (e) of this section. In both instances, equipment employed must be authorized in accordance with the provisions of §24.51. In measuring transmissions in this band using an average power technique, the peak-to-average ratio (PAR) of the transmission may not exceed 13 db.

### TEST PROCEDURES

1. The testing follows fcckdb 971168 v02r02 section
2. The eut was connected to the and peak and av system simulator& spectrum analysis reads
3. Select lowest, middle, and highest channels for each band and different modulation.
4. Set the test probe and measure average power of the spectrum analysis

### TEST SETUP





### 5.3 TRANSMITTER RADIATED POWER (EIRP/ERP)

#### TEST OVERVIEW

Effective Radiated Power (ERP) and Equivalent Isotropic Radiated Power (EIRP) measurements are performed using the substitution method described in ANSI/TIA-603-D-2010 with the EUT transmitting into an integral antenna. Measurements on signals operating below 1GHz are performed using vertically polarized tuned dipole antennas. Measurements on signals operating above 1GHz are performed using vertically polarized broadband horn antennas. All measurements are performed as RMS average measurements while the EUT is operating at maximum power, and at the appropriate frequencies.

#### TEST PROCEDURE

1. The testing follows FCC KDB 971168 D01 Section 5.2.1. (for CDMA/WCDMA), Section 5.2.2 (for GSM/GPRS/EDGE) and ANSI / TIA-603-D-2010 Section 2.2.17.
2. The transmitter was placed on a wooden turntable, and it was transmitting into a non-radiating load which was also placed on the turntable.
3. The measurement antenna was placed at a distance of 3 meters from the EUT. During the tests, the antenna height and polarization as well as EUT azimuth were varied in order to identify the maximum level of emissions from the EUT. The test was performed by placing the EUT on 3-orthogonal axis.
4. The frequency range up to tenth harmonic of the fundamental frequency was investigated.
5. Remove the EUT and replace it with substitution antenna. A signal generator was connected to the substitution antenna by a nonradiating cable. The absolute levels of the spurious emissions were measured by the substitution.
6. Effective Isotropic Radiated Power (EIRP) was measured by substitution method according to TIA/EIA-603-D. The EUT was replaced by the substitution antenna at same location, and then a known power from S.G. was applied into the dipole antenna through a Tx cable, and then recorded the maximum Analyzer reading through raised and lowered the test antenna. The correction factor (in dB) = S.G. - Tx Cable loss + Substitution antenna gain - Analyzer reading. Then the EUT's EIRP/ERP was calculated with the correction factor,  
$$\text{ERP/EIRP} = \text{P.SG} + \text{GT} - \text{LC}$$
  
ERP/EIRP = effective or equivalent radiated power, respectively (expressed in the same units as P<sub>Meas</sub> as, typically dBW or dBm);  
P<sub>Meas</sub>(PK) = measured transmitter output power or PSD, in dBm or dBW;  
GT = gain of the transmitting antenna, in dBd (ERP) or dBi (EIRP);  
LC = signal attenuation in the connecting cable between the transmitter and antenna, in dB.

## 5.4 OCCUPIED BANDWIDTH

### TEST OVERVIEW

The occupied bandwidth, that is the frequency bandwidth such that, below its lower and above its upper frequency limits, the mean powers radiated are each equal to 0.5 percent of the total mean power radiated by a given emission shall be measured.


The 26 dB emission bandwidth is defined as the frequency range between two points, one above and one below the carrier frequency, at which the spectral density of the emission is attenuated 26 dB below the maximum in-band spectral density of the modulated signal. Spectral density (power per unit bandwidth) is to be measured with a detector of resolution bandwidth equal to approximately 1.0% of the emission bandwidth.

All modes of operation were investigated and the worst case configuration results are reported in this section.

### TEST PROCEDURE

1. The signal analyzer's automatic bandwidth measurement capability was used to perform the 99% occupied bandwidth and the 26dB bandwidth. The bandwidth measurement was not influenced by any intermediate power nulls in the fundamental emission.
2.  $RBW = 1 - 5\%$  of the expected OBW
3.  $VBW \geq 3 \times RBW$
4. Detector = Peak
5. Trace mode = max hold
6. Sweep = auto couple
7. The trace was allowed to stabilize
8. If necessary, steps 2 – 7 were repeated after changing the RBW such that it would be within 1 – 5% of the 99% occupied bandwidth observed in Step 7

### TEST SETUP



## 5.5 FREQUENCY STABILITY

### Test Overview

Frequency stability testing is performed in accordance with the guidelines of ANSI/TIA-603-D-2010. The frequency stability of the transmitter is measured by:

- a.) Temperature: The temperature is varied from -30°C to +50°C in 10°C increments using an environmental chamber.
- b.) Primary Supply Voltage: The primary supply voltage is varied from 85% to 115% of the nominal value for non hand-carried battery and AC powered equipment. For hand-carried, battery-powered equipment, primary supply voltage is reduced to the battery operating end point which shall be specified by the manufacturer.

For Part 22, the frequency stability of the transmitter shall be maintained within  $\pm 0.00025\%$  ( $\pm 2.5$  ppm) of the center frequency. For Part 24 the frequency stability shall be sufficient to ensure that the fundamental emission stays within the authorized frequency block.

### Test Procedure


#### Temperature Variation

1. The testing follows fccdb 971168 D01 section 9.0
2. The EUT was set up in the thermal chamber and connected with the system simulator.
3. With power OFF, the temperature was decreased to -30°C and the EUT was stabilized before testing. Power was applied and the maximum change in frequency was recorded within one minute.
4. With power OFF, the temperature was raised in 10°C steps up to 50°C. The EUT was stabilized at each step for at least half an hour. Power was applied and the maximum frequency change was recorded within one minute.

#### Voltage Variation

1. The testing follows FCC KDB 971168 D01 Section 9.0.
2. The EUT was placed in a temperature chamber at  $25 \pm 5^\circ \text{C}$  and connected with the system simulator.
3. The power supply voltage to the EUT was varied from 85% to 115% of the nominal value measured at the input to the EUT.
4. The variation in frequency was measured for the worst case.

### TEST SETUP



## 5.6 SPURIOUS EMISSIONS AT ANTENNA TERMINALS

### Test Overview


The power of any emission outside of the authorized operating frequency ranges must be lower than the transmitter power (P) by a factor of at least  $43 + 10 \log(P)$  dB.

It is measured by means of a calibrated spectrum analyzer and scanned from 30 MHz up to a frequency including its 10th harmonic.

### Test procedure

1. The testing FCC KDB 971168 D01 v02r02 Section 6.0. and ANSI/TIA-603-D-2010-Section 2.2.13.2(d)
2. The EUT was connected to the spectrum analyzer and system simulator via a power divider.
3. The RF output of EUT was connected to the spectrum analyzer by an RF cable and attenuator. The path loss was compensated to the results for each measurement.
4. The middle channel for the highest RF power within the transmitting frequency was measured.
5. The conducted spurious emission for the whole frequency range was taken.
6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.
7. The limit line is derived from  $43 + 10\log(P)$  dB below the transmitter power P(Watts)  
 $= P(W) - [43 + 10\log(P)]$  (dB)  
 $= [30 + 10\log(P)]$  (dBm) -  $[43 + 10\log(P)]$  (dB)  
 $= -13\text{dBm}$ .

### Test Setup







## 5.7 BAND EDGE

### OVERVIEW

All out of band emissions are measured with a spectrum analyzer connected to the antenna terminal of the EUT while the EUT is operating at maximum power, and at the appropriate frequencies. All data rates were investigated to determine the worst case configuration. All modes of operation were investigated and the worst case configuration results are reported in this section.

The minimum permissible attenuation level of any spurious emission is  $43 + \log_{10}(P[\text{Watts}])$ , where P is the transmitter power in Watts.

### TEST PROCEDURE

1. The testing FCC KDB 971168 D01 v02r02 Section 6.0. and ANSI/TIA-603-D-2010-Section 2.2.13.2(d)
2. Start and stop frequency were set such that the band edge would be placed in the center of the Plot.
3. The EUT was connected to the spectrum analyzer and system simulator via a power divider.
4. The RF output of EUT was connected to the spectrum analyzer by an RF cable and attenuator.

The path loss was compensated to the results for each measurement.

5. The band edges of low and high channels for the highest RF powers were measured.

6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.


7. The limit line is derived from  $43 + 10\log(P)$  dB below the transmitter power P(Watts)

$$= P(W) - [43 + 10\log(P)] \text{ (dB)}$$

$$= [30 + 10\log(P)] \text{ (dBm)} - [43 + 10\log(P)] \text{ (dB)}$$

$$= -13\text{dBm}.$$

### TEST SETUP







## 5.8 FIELD STRENGTH OF SPURIOUS RADIATION MEASUREMENT

### Test overview

Radiated spurious emissions measurements are performed using the substitution method described in ANSI/TIA-603-D-2010 with the EUT transmitting into an integral antenna. Measurements on signals operating below 1GHz are performed using horizontally and vertically polarized tuned dipole antennas. Measurements on signals operating above 1GHz are performed using vertically and horizontally polarized horn antennas. All measurements are performed as peak measurements while the EUT is operating at maximum power and at the appropriate frequencies.


It is measured by means of a calibrated spectrum analyzer and scanned from 30 MHz up to a frequency including its 10th harmonic.

### Test procedure


1. The testing FCC KDB 971168 D01 Section 5.8 and ANSI/TIA-603-D-2010-Section 2.2.12.2(b)
2. RBW = 100kHz for emissions below 1GHz and 1MHz for emissions above 1GHz
3. VBW  $\geq 3 \times$  RBW
4. Span = 1.5 times the OBW
5. No. of sweep points  $> 2 \times$  span/RBW
6. Detector = Peak
7. Trace mode = max hold
8. The trace was allowed to stabilize
9. Effective Isotropic Spurious Radiation was measured by substitution method according to TIA/EIA-603-D. The EUT was replaced by the substitution antenna at same location, and then a known power from S.G. was applied into the dipole antenna through a Tx cable, and then recorded the maximum Analyzer reading through raised and lowered the test antenna. The correction factor (in dB) = S.G. - Tx Cable loss + Substitution antenna gain - Analyzer reading. Then the EUT's EIRP/ERP was calculated with the correction factor,  
$$ERP/EIRP = P.SG + GT - LC$$
  
ERP/EIRP = effective or equivalent radiated power, respectively (expressed in the same units as P<sub>Meas</sub>, typically dBW or dBm);  
P.SG = measured transmitter output power or PSD, in dBm or dBW;  
GT = gain of the transmitting antenna, in dBd (ERP) or dBi (EIRP);  
LC = signal attenuation in the connecting cable between the transmitter and antenna, in dB.

## TEST SETUP

For radiated test from 30MHz to 1GHz



For radiated test from above 1GHz





APPENDIX A.TESTRESULT  
A1.CONDUCTED OUTPUT POWER  
GSM 850:

Mode	Frequency (MHz)	AVG Power(dBm)
GPRS(GMSK,1-Slot)	824.2	<b>31.48</b>
	836.6	31.42
	848.8	31.34
GPRS(GMSK,2-Slot)	824.2	<b>31.07</b>
	836.6	30.96
	848.8	30.94
GPRS(GMSK,3-Slot)	824.2	<b>30.67</b>
	836.6	30.50
	848.8	30.48
GPRS(GMSK,4-Slot)	824.2	<b>30.23</b>
	836.6	30.08
	848.8	29.98
EGPRS(GMSK,1-Slot)	824.2	<b>31.42</b>
	836.6	31.39
	848.8	31.31
EGPRS(GMSK,2-Slot)	824.2	<b>30.86</b>
	836.6	30.75
	848.8	30.65
EGPRS(GMSK,3-Slot)	824.2	<b>30.44</b>
	836.6	30.25
	848.8	30.20
EGPRS(GMSK,4-Slot)	824.2	<b>29.95</b>
	836.6	29.88
	848.8	29.77



PCS 1900:

Mode	Frequency (MHz)	AVG Power(dBm)
GPRS(GMSK,1-Slot)	1850.2	<b>27.96</b>
	1880.0	27.93
	1909.8	27.91
GPRS(GMSK,2-Slot)	1850.2	<b>27.50</b>
	1880.0	27.45
	1909.8	27.50
GPRS(GMSK,3-Slot)	1850.2	27.00
	1880.0	26.97
	1909.8	<b>27.03</b>
GPRS(GMSK,4-Slot)	1850.2	26.52
	1880.0	26.49
	1909.8	<b>26.63</b>
EGPRS(GMSK,1-Slot)	1850.2	<b>27.93</b>
	1880.0	27.91
	1909.8	27.88
EGPRS(GMSK,2-Slot)	1850.2	<b>27.30</b>
	1880.0	27.22
	1909.8	27.22
EGPRS(GMSK,3-Slot)	1850.2	26.73
	1880.0	<b>26.77</b>
	1909.8	26.77
EGPRS(GMSK,4-Slot)	1850.2	26.23
	1880.0	26.29
	1909.8	<b>26.37</b>



## UMTS BAND V

Mode	Frequency(MHz)	AVG Power
WCDMA 850 RMC	826.4	<b>22.97</b>
	836.6	22.96
	846.6	22.95
HSDPA Subtest 1	826.4	22.95
	836.6	22.93
	846.6	22.91
HSDPA Subtest 2	826.4	22.52
	836.6	22.51
	846.6	22.42
HSDPA Subtest 3	826.4	22.13
	836.6	22.08
	846.6	22.02
HSDPA Subtest 4	826.4	21.75
	836.6	21.69
	846.6	21.56
HSUPA Subtest 1	826.4	22.87
	836.6	22.86
	846.6	22.45
HSUPA Subtest 2	826.4	21.89
	836.6	21.89
	846.6	21.51
HSUPA Subtest 3	826.4	21.84
	836.6	21.46
	846.6	21.15
HSUPA Subtest 4	826.4	21.44
	836.6	21.12
	846.6	20.75
HSUPA Subtest 5	826.4	19.94
	836.6	19.62
	846.6	19.26




## UMTS BAND II

Mode	Frequency(MHz)	AVG Power
WCDMA 1900 RMC	1852.4	22.69
	1880	<b>22.74</b>
	1907.6	22.62
HSDPA Subtest 1	1852.4	22.65
	1880	22.72
	1907.6	22.59
HSDPA Subtest 2	1852.4	22.23
	1880	22.31
	1907.6	22.12
HSDPA Subtest 3	1852.4	21.78
	1880	21.86
	1907.6	21.68
HSDPA Subtest 4	1852.4	21.29
	1880	21.37
	1907.6	21.32
HSUPA Subtest 1	1852.4	22.64
	1880	22.68
	1907.6	22.12
HSUPA Subtest 2	1852.4	21.81
	1880	21.73
	1907.6	21.18
HSUPA Subtest 3	1852.4	21.67
	1880	21.30
	1907.6	20.69
HSUPA Subtest 4	1852.4	21.35
	1880	20.82
	1907.6	20.25
HSUPA Subtest 5	1852.4	19.87
	1880	19.39
	1907.6	18.81



## A2. PEAK-TO-AVERAGE RADIO

Mode	Frequency (MHz)	PEAK Power (dBm)	AVG Power (dBm)	PAR (dB)
GPRS850	824.2	<b>31.59</b>	<b>31.48</b>	0.11
	836.6	31.53	31.42	0.11
	848.8	31.44	31.34	0.10
EDGE850	824.2	<b>31.52</b>	<b>31.42</b>	0.10
	836.6	31.51	31.39	0.12
	848.8	31.42	31.31	0.11
GPRS1900	1850.2	<b>28.07</b>	<b>27.96</b>	0.11
	1880	28.05	27.93	0.12
	1909.8	28.02	27.91	0.11
EDGE1900	1850.2	<b>28.03</b>	<b>27.93</b>	0.10
	1880	28.01	27.91	0.10
	1909.8	27.98	27.88	0.10





Mode	Frequency (MHz)	PEAK Power (dBm)	AVG Power (dBm)	PAR (dB)
WCDMA 850 RMC	826.4	<b>25.66</b>	<b>22.97</b>	2.69
	836.6	25.52	22.96	2.56
	846.6	25.55	22.95	2.60
HSDPA 850	826.4	<b>25.70</b>	<b>22.95</b>	2.75
	836.6	25.89	22.93	2.96
	846.6	25.44	22.91	2.53
HSUPA 850	826.4	25.60	<b>22.87</b>	2.73
	836.6	<b>25.82</b>	22.86	2.96
	846.6	24.96	22.45	2.51
WCDMA 1900 RMC	1852.4	<b>25.65</b>	22.69	2.96
	1880	25.53	<b>22.74</b>	2.79
	1907.6	25.26	22.62	2.64
HSDPA 1900	1852.4	25.29	22.65	2.64
	1880	25.25	<b>22.72</b>	2.53
	1907.6	<b>25.42</b>	22.59	2.83
HSUPA 1900	1852.4	25.42	22.64	2.78
	1880	<b>25.46</b>	<b>22.68</b>	2.78
	1907.6	25.07	22.12	2.95





### A3. TRANSMITTER RADIATED POWER (EIRP/ERP)

Radiated Power (ERP) for GSM 850 MHZ							
Mode	Frequency	Result					Conclusion
		S G.Level (dBm)	Cable loss	Gain (dBi)	PMeas E.R.P(dBm)	Polarization Of Max. ERP	
GPRS850	824.2	23.09	0.44	6.5	29.15	Horizontal	Pass
	824.2	24.80	0.44	6.5	<b>30.86</b>	Vertical	Pass
	836.6	22.84	0.45	6.5	28.89	Horizontal	Pass
	836.6	24.68	0.45	6.5	30.73	Vertical	Pass
	848.8	22.91	0.46	6.5	28.95	Horizontal	Pass
	848.8	24.44	0.46	6.5	30.48	Vertical	Pass
EDGE850	824.2	23.18	0.44	6.5	29.24	Horizontal	Pass
	824.2	24.83	0.44	6.5	<b>30.89</b>	Vertical	Pass
	836.6	23.00	0.45	6.5	29.05	Horizontal	Pass
	836.6	24.82	0.45	6.5	30.87	Vertical	Pass
	848.8	22.82	0.46	6.5	28.86	Horizontal	Pass
	848.8	24.49	0.46	6.5	30.53	Vertical	Pass



Radiated Power (EIRP) for PCS 1900 MHZ							
Mode	Frequency	Result					Conclusion
		S G. Level (dBm)	Cable loss	Gain (dBi)	PMeas E.I.R.P.(dBm)	Polarization Of Max. EIRP.	
GPRS1900	1850.2	17.53	2.41	10.35	25.47	Horizontal	Pass
	1850.2	19.37	2.41	10.35	27.31	Vertical	Pass
	1880.0	17.7	2.42	10.35	25.63	Horizontal	Pass
	1880.0	19.43	2.42	10.35	<b>27.36</b>	Vertical	Pass
	1909.8	17.69	2.43	10.35	25.61	Horizontal	Pass
	1909.8	19.36	2.43	10.35	27.28	Vertical	Pass
EDGE1900	1850.2	17.52	2.41	10.35	25.46	Horizontal	Pass
	1850.2	19.48	2.41	10.35	<b>27.42</b>	Vertical	Pass
	1880.0	17.6	2.42	10.35	25.53	Horizontal	Pass
	1880.0	19.3	2.42	10.35	27.23	Vertical	Pass
	1909.8	17.6	2.43	10.35	25.52	Horizontal	Pass
	1909.8	19.32	2.43	10.35	27.24	Vertical	Pass



Radiated Power (ERP) for WCDMA Band V							
Mode	Frequency	Result					Conclusion
		S G. Level (dBm)	Cable loss	Gain (dBi)	PMeas E.R.P (dBm)	Polarization Of Max.ERP	
Band V	826.4	14.49	0.44	6.5	20.55	Horizontal	Pass
	826.4	16.39	0.44	6.5	<b>22.45</b>	Vertical	Pass
	836.6	14.58	0.45	6.5	20.63	Horizontal	Pass
	836.6	16.37	0.45	6.5	22.42	Vertical	Pass
	846.6	14.56	0.46	6.5	20.60	Horizontal	Pass
	846.6	16.37	0.46	6.5	22.41	Vertical	Pass

Radiated Power (EIRP) for WCDMA Band II							
Mode	Frequency	Result					Conclusion
		S G. Level (dBm)	Cable loss	Gain (dBi)	PMeas E.I.R.P.(dBm)	Polarization Of Max.EIRP	
Band II	1852.4	12.43	2.41	10.35	20.37	Horizontal	Pass
	1852.4	14.18	2.41	10.35	22.12	Vertical	Pass
	1880.0	12.52	2.42	10.35	20.45	Horizontal	Pass
	1880.0	14.25	2.42	10.35	<b>22.18</b>	Vertical	Pass
	1907.6	12.46	2.43	10.35	20.38	Horizontal	Pass
	1907.6	14.24	2.43	10.35	22.16	Vertical	Pass



## A4. OCCUPIED BANDWIDTH (99% OCCUPIED BANDWIDTH/26dB BANDWIDTH)

Occupied Bandwidth for GPRS 850 band			
Mode	Frequency(MHz)	Occupied Bandwidth (99%)( kHz)	Emission Bandwidth (-26dBc)( kHz)
Low Channel	824.2	245.31	321.3
Middle Channel	836.6	246.64	322.9
High Channel	848.8	245.39	320.9
Occupied Bandwidth for EGPRS 850 band			
Mode	Frequency(MHz)	Occupied Bandwidth (99%)( kHz)	Emission Bandwidth (-26dBc)( kHz)
Low Channel	824.2	245.03	322.8
Middle Channel	836.6	244.48	312.6
High Channel	848.8	243.26	318.3




Occupied Bandwidth for GPRS 1900 band			
Mode	Frequency(MHz)	Occupied Bandwidth (99%)( kHz)	Emission Bandwidth (-26dBc)( kHz)
Low Channel	1850.2	250.10	324.0
Middle Channel	1880.0	245.23	318.4
High Channel	1909.8	247.24	316.9
Occupied Bandwidth for EDGE 1900 band			
Mode	Frequency(MHz)	Occupied Bandwidth (99%)( kHz)	Emission Bandwidth (-26dBc)( kHz)
Low Channel	1850.2	246.94	319.8
Middle Channel	1880.0	247.65	317.9
High Channel	1909.8	246.22	325.4

Occupied Bandwidth for UMTS band V			
Mode	Frequency(MHz)	Occupied Bandwidth (99%)( MHz)	Emission Bandwidth (-26dBc)( MHz)
Low Channel	826.4	4.2106	4.820
Middle Channel	836.6	4.2076	4.826
High Channel	846.6	4.1943	4.825


Occupied Bandwidth for UMTS band II			
Mode	Frequency(MHz)	Occupied Bandwidth (99%)( MHz)	Emission Bandwidth (-26dBc)( MHz)
Low Channel	1852.4	4.2081	4.823
Middle Channel	1880	4.2073	4.810
High Channel	1907.6	4.2054	4.818




## GPRS 850 CH 128



## GPRS 850 CH 190




## GPRS 850 CH 251







## EDGE 850 CH 128



## EDGE 850 CH 190




## EDGE 850 CH 251







## GPRS 1900 CH 512



## GPRS 1900 CH 661




## GPRS 1900 CH 810









## EDGE 1900 CH 512



## EDGE 1900 CH 661




## EDGE 1900 CH 810







## UMTS BAND V CH 4132



## UMTS BAND V CH 4183




## UMTS BAND V CH 4233







## UMTS BAND II CH 9262



## UMTS BAND II CH 9400



## UMTS BAND II CH 9538





## A5.FREQUENCY STABILITY

Normal Voltage = 3.8V. ; Battery End Point (BEP) = 3.4 V.; Maximum Voltage =4.3 V

GPRS 850 Middle Channel/836.6MHz					
Temperature (°C)	Voltage (Volt)	Freq. Dev. (Hz)	Freq. Dev. (ppm)	Limit	Result
50	Normal Voltage	30.12	0.036	2.5ppm	PASS
40		15.84	0.019		
30		19.24	0.023		
20		12.47	0.015		
10		11.56	0.014		
0		23.07	0.028		
-10		29.03	0.035		
-20		26.89	0.032		
-30		25.97	0.031		
25	Maximum Voltage	19.07	0.023		
25	BEP	22.06	0.026		

EDGE 850 Middle Channel/836.6MHz					
Temperature (°C)	Voltage (Volt)	Freq. Dev. (Hz)	Freq. Dev. (ppm)	Limit	Result
50	Normal Voltage	22.44	0.027	2.5ppm	PASS
40		21.73	0.026		
30		27.28	0.033		
20		29.14	0.035		
10		28.39	0.034		
0		36.12	0.043		
-10		29.85	0.036		
-20		15.38	0.018		
-30		32.52	0.039		
25	Maximum Voltage	18.97	0.023		
25	BEP	14.34	0.017		



GPRS 1900 Middle Channel/1880MHz					
Temperature (°C)	Voltage (Volt)	Freq. Dev. (Hz)	Freq. Dev. (ppm)	Limit	Result
50	Normal Voltage	26.94	0.014	Within Authorized Band	PASS
40		21.74	0.012		
30		13.42	0.007		
20		22.52	0.012		
10		17.68	0.009		
0		12.83	0.007		
-10		28.10	0.015		
-20		21.42	0.011		
-30		23.81	0.013		
25	Maximum Voltage	33.19	0.018		
25	BEP	22.16	0.012		

EDGE 1900 Middle Channel/1880MHz					
Temperature (°C)	Voltage (Volt)	Freq. Dev. (Hz)	Freq. Dev. (ppm)	Limit	Result
50	Normal Voltage	13.06	0.007	Within Authorized Band	PASS
40		24.77	0.013		
30		28.72	0.015		
20		19.35	0.010		
10		17.87	0.010		
0		24.25	0.013		
-10		16.45	0.009		
-20		35.44	0.019		
-30		29.84	0.016		
25	Maximum Voltage	20.71	0.011		
25	BEP	23.52	0.013		



WCDMA V Middle Channel/836.6MHz					
Temperature (°C)	Voltage (Volt)	Freq. Dev. (Hz)	Freq. Dev. (ppm)	Limit	Result
50	Normal Voltage	17.56	0.021	2.5ppm	PASS
40		29.99	0.036		
30		29.02	0.035		
20		11.67	0.014		
10		23.52	0.028		
0		19.06	0.023		
-10		15.50	0.019		
-20		21.43	0.026		
-30		30.19	0.036		
25	Maximum Voltage	25.54	0.031		
25	BEP	33.77	0.040		

1. The frequency fundamental emissions stay within the authorized frequency block based on the frequency deviation measured is small.

WCDMA II Middle Channel/1880MHz					
Temperature (°C)	Voltage (Volt)	Freq. Dev. (Hz)	Freq. Dev. (ppm)	Limit	Result
50	Normal Voltage	30.75	0.016	Within Authorized Band	PASS
40		21.40	0.011		
30		28.27	0.015		
20		13.96	0.007		
10		12.47	0.007		
0		11.54	0.006		
-10		22.33	0.012		
-20		22.28	0.012		
-30		19.20	0.010		
25	Maximum Voltage	17.53	0.009		
25	BEP	22.22	0.012		


1. The frequency fundamental emissions stay within the authorized frequency block based on the frequency deviation measured is small.




## A6. SPURIOUS EMISSIONS AT ANTENNA TERMINALS

## GPRS 850 BAND


## Lowest Channel



## Middle Channel




## Highest Channel






## EDGE 850 BAND


## Lowest Channel



## Middle Channel



## Highest Channel








## GPRS1900 BAND(30M-20G)


## Lowest Channel



## Middle Channel



## Highest Channel






## EDGE 1900 BAND(30M-20G)


## Lowest Channel



## Middle Channel




## Highest Channel






## WCDMA Band V (RMC 12.2Kbps)


## Lowest Channel



## Middle Channel




## Highest Channel






## WCDMA Band II (RMC 12.2Kbps)(30M-20G)


## Lowest Channel



## Middle Channel



## Highest Channel






## A7. BAND EDGE

## GPRS 850

## Lowest Band Edge




## Highest Band Edge





## EDGE 850

## Lowest Band Edge




## Highest Band Edge





## GPRS 1900

## Lowest Band Edge




## Highest Band Edge





## EDGE 1900

## Lowest Band Edge



## Highest Band Edge








## WCDMA Band VRMC 12.2Kbps

## Lowest Band Edge




## Highest Band Edge





## WCDMA Band IIRMC 12.2Kbps

## Lowest Band Edge



## Highest Band Edge





## A8. FIELD STRENGTH OF SPURIOUS RADIATION MEASUREMENT

GPRS 850: (30-9000)MHz

GPRS 850: (30-9000)MHz							
The Worst Test Results Channel 128/824.2 MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1648.12	-40.91	9.40	4.75	-36.26	-13.00	-23.26	H
2472.48	-39.30	10.60	8.39	-37.09	-13.00	-24.09	H
3296.57	-32.17	12.00	11.79	-31.96	-13.00	-18.96	H
1648.27	-43.93	9.40	4.75	-39.28	-13.00	-26.28	V
2472.37	-43.96	10.60	8.39	-41.75	-13.00	-28.75	V
3296.72	-43.43	12.00	11.79	-43.22	-13.00	-30.22	V
The Worst Test Results Channel 190/836.6 MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1673.04	-41.24	9.50	4.76	-36.50	-13.00	-23.50	H
2509.77	-40.66	10.70	8.40	-38.36	-13.00	-25.36	H
3345.98	-32.09	12.20	11.80	-31.69	-13.00	-18.69	H
1673.12	-44.42	9.40	4.75	-39.77	-13.00	-26.77	V
2509.77	-44.88	10.60	8.39	-42.67	-13.00	-29.67	V
3346.10	-43.27	12.20	11.82	-42.89	-13.00	-29.89	V
The Worst Test Results Channel 251/848.8 MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1697.30	-40.48	9.60	4.77	-35.65	-13.00	-22.65	H
2546.17	-40.19	10.80	8.50	-37.89	-13.00	-24.89	H
3395.30	-31.71	12.50	11.90	-31.11	-13.00	-18.11	H
1697.27	-43.41	9.60	4.77	-38.58	-13.00	-25.58	V
2546.42	-44.26	10.80	8.50	-41.96	-13.00	-28.96	V
3395.12	-42.86	12.50	11.90	-42.26	-13.00	-29.26	V

**Note:** (1) Below 30MHz no Spurious found is the worst condition.

(2) Above 3.5GHz amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value



EDGE 850: (30-9000)MHz

EGPRS 850: (30-9000)MHz							
The Worst Test Results Channel 128/824.2 MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1648.15	-41.43	9.40	4.75	-36.78	-13.00	-23.78	H
2472.39	-40.23	10.60	8.39	-38.02	-13.00	-25.02	H
3296.80	-32.34	12.00	11.79	-32.13	-13.00	-19.13	H
1648.47	-44.06	9.40	4.75	-39.41	-13.00	-26.41	V
2472.42	-45.29	10.60	8.39	-43.08	-13.00	-30.08	V
3296.46	-43.23	12.00	11.79	-43.02	-13.00	-30.02	V
The Worst Test Results Channel 190/836.6 MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1673.01	-40.50	9.50	4.76	-35.76	-13.00	-22.76	H
2509.88	-39.49	10.70	8.40	-37.19	-13.00	-24.19	H
3346.30	-31.63	12.20	11.80	-31.23	-13.00	-18.23	H
1672.90	-44.45	9.40	4.75	-39.80	-13.00	-26.80	V
2509.92	-44.76	10.60	8.39	-42.55	-13.00	-29.55	V
3346.13	-43.81	12.20	11.82	-43.43	-13.00	-30.43	V
The Worst Test Results Channel 251/848.8 MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1697.38	-40.95	9.60	4.77	-36.12	-13.00	-23.12	H
2546.38	-40.01	10.80	8.50	-37.71	-13.00	-24.71	H
3395.12	-30.93	12.50	11.90	-30.33	-13.00	-17.33	H
1697.18	-44.61	9.60	4.77	-39.78	-13.00	-26.78	V
2546.55	-44.97	10.80	8.50	-42.67	-13.00	-29.67	V
3394.95	-42.93	12.50	11.90	-42.33	-13.00	-29.33	V

**Note:** (1) Below 30MHz no Spurious found is the worst condition.

(2) Above 3.5GHz amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value



GPRS 1900: (30-20000)MHz

GPRS1900: (30-20000)MHz							
The Worst Test Results for Channel 512/1850.2MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3700.10	-34.40	12.60	12.93	-34.73	-13.00	-21.73	H
5550.43	-34.06	13.10	17.11	-38.07	-13.00	-25.07	H
7400.82	-32.43	11.50	22.20	-43.13	-13.00	-30.13	H
3700.51	-34.86	12.60	12.93	-35.19	-13.00	-22.19	V
5550.51	-34.89	13.10	17.11	-38.90	-13.00	-25.90	V
7400.69	-32.88	11.50	22.20	-43.58	-13.00	-30.58	V
The Worst Test Results for Channel 661/1880.0MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3759.81	-34.43	12.60	12.93	-34.76	-13.00	-21.76	H
5639.85	-34.25	13.10	17.11	-38.26	-13.00	-25.26	H
7520.20	-32.97	11.50	22.20	-43.67	-13.00	-30.67	H
3760.05	-35.03	12.60	12.93	-35.36	-13.00	-22.36	V
5640.08	-35.13	13.10	17.11	-39.14	-13.00	-26.14	V
7520.31	-32.30	11.50	22.20	-43.00	-13.00	-30.00	V
The Worst Test Results for Channel 810/1909.8MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3819.40	-34.86	12.60	12.93	-35.19	-13.00	-22.19	H
5729.44	-35.33	13.10	17.11	-39.34	-13.00	-26.34	H
7639.12	-33.39	11.50	22.20	-44.09	-13.00	-31.09	H
3819.32	-35.96	12.60	12.93	-36.29	-13.00	-23.29	V
5729.33	-35.03	13.10	17.11	-39.04	-13.00	-26.04	V
7638.97	-32.46	11.50	22.20	-43.16	-13.00	-30.16	V

**Note:** (1) Below 30MHz no Spurious found is the worst condition.

(2) Above 8GHz amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value



EDGE 1900: (30-20000)MHz

EGPRS 1900: (30-20000)MHz							
The Worst Test Results for Channel 512/1850.2MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3700.28	-34.26	12.60	12.93	-34.59	-13.00	-21.59	H
5550.36	-34.23	13.10	17.11	-38.24	-13.00	-25.24	H
7400.82	-32.94	11.50	22.20	-43.64	-13.00	-30.64	H
3700.51	-35.56	12.60	12.93	-35.89	-13.00	-22.89	V
5550.27	-34.53	13.10	17.11	-38.54	-13.00	-25.54	V
7400.89	-31.80	11.50	22.20	-42.50	-13.00	-29.50	V
The Worst Test Results for Channel 661/1880.0MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3759.86	-34.40	12.60	12.93	-34.73	-13.00	-21.73	H
5639.95	-34.98	13.10	17.11	-38.99	-13.00	-25.99	H
7520.21	-32.45	11.50	22.20	-43.15	-13.00	-30.15	H
3759.90	-35.43	12.60	12.93	-35.76	-13.00	-22.76	V
5640.24	-35.10	13.10	17.11	-39.11	-13.00	-26.11	V
7520.13	-31.76	11.50	22.20	-42.46	-13.00	-29.46	V
The Worst Test Results for Channel 810/1909.8MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3819.28	-34.30	12.60	12.93	-34.63	-13.00	-21.63	H
5729.08	-35.02	13.10	17.11	-39.03	-13.00	-26.03	H
7638.91	-32.50	11.50	22.20	-43.20	-13.00	-30.20	H
3819.65	-35.34	12.60	12.93	-35.67	-13.00	-22.67	V
5729.17	-34.25	13.10	17.11	-38.26	-13.00	-25.26	V
7639.09	-32.64	11.50	22.20	-43.34	-13.00	-30.34	V

**Note:** (1) Below 30MHz no Spurious found is the worst condition.

(2) Above 8GHz amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has.



UMTS band V(30-9000)MHz

WCDMA Band V: (30-9000)MHz							
The worst testresults channel 4132/826.4MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1652.28	-41.27	9.40	4.75	-36.62	-13.00	-23.62	H
2479.28	-39.82	10.60	8.39	-37.61	-13.00	-24.61	H
3305.90	-32.14	12.00	11.79	-31.93	-13.00	-18.93	H
1652.01	-44.21	9.40	4.75	-39.56	-13.00	-26.56	V
2479.69	-45.41	10.60	8.39	-43.20	-13.00	-30.20	V
3305.64	-43.00	12.00	11.79	-42.79	-13.00	-29.79	V
The Worst Test Results Channel 4183/836.6MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1673.11	-41.03	9.50	4.76	-36.29	-13.00	-23.29	H
2509.67	-39.64	10.70	8.40	-37.34	-13.00	-24.34	H
3345.97	-31.87	12.20	11.80	-31.47	-13.00	-18.47	H
1672.91	-43.68	9.40	4.75	-39.03	-13.00	-26.03	V
2509.81	-44.27	10.60	8.39	-42.06	-13.00	-29.06	V
3346.15	-43.86	12.20	11.82	-43.48	-13.00	-30.48	V
The Worst Test Results Channel 4233/846.6MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
1693.28	-40.18	9.60	4.77	-35.35	-13.00	-22.35	H
2539.33	-39.16	10.80	8.50	-36.86	-13.00	-23.86	H
3386.33	-31.86	12.50	11.90	-31.26	-13.00	-18.26	H
1693.35	-44.21	9.60	4.77	-39.38	-13.00	-26.38	V
2539.08	-44.20	10.80	8.50	-41.90	-13.00	-28.90	V
3386.17	-43.98	12.50	11.90	-43.38	-13.00	-30.38	V

**Note:** (1) Below 30MHz no Spurious found is the worst condition.

(2) Above 3GHz amplitude of spurious emissions which are attenuated by more than 20Db below the permissible value





UMTS band II(30-20000)MHz

WCDMA Band II: (30-20000)MHz							
The Worst Test Results for Channel 9262/1852.4MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3704.44	-33.98	12.60	12.93	-34.31	-13.00	-21.31	H
5557.47	-34.06	13.10	17.11	-38.07	-13.00	-25.07	H
7409.95	-32.21	11.50	22.20	-42.91	-13.00	-29.91	H
3704.02	-35.22	12.60	12.93	-35.55	-13.00	-22.55	V
5557.56	-35.25	13.10	17.11	-39.26	-13.00	-26.26	V
7409.72	-31.83	11.50	22.20	-42.53	-13.00	-29.53	V
The Worst Test Results for Channel 9400/1880MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3760.04	-34.71	12.60	12.93	-35.04	-13.00	-22.04	H
5639.81	-34.54	13.10	17.11	-38.55	-13.00	-25.55	H
7519.99	-33.48	11.50	22.20	-44.18	-13.00	-31.18	H
3760.25	-35.84	12.60	12.93	-36.17	-13.00	-23.17	V
5640.13	-33.88	13.10	17.11	-37.89	-13.00	-24.89	V
7520.04	-32.10	11.50	22.20	-42.80	-13.00	-29.80	V
The Worst Test Results for Channel 9538/1907.6MHz							
Frequency(MHz)	S G.Lev (dBm)	Ant(dBi)	Loss	PMea (dBm)	Limit (dBm)	Margin (dB)	Polarity
3815.64	-34.93	12.60	12.93	-35.26	-13.00	-22.26	H
5722.15	-34.82	13.10	17.11	-38.83	-13.00	-25.83	H
7629.83	-33.01	11.50	22.20	-43.71	-13.00	-30.71	H
3815.56	-35.71	12.60	12.93	-36.04	-13.00	-23.04	V
5722.40	-33.78	13.10	17.11	-37.79	-13.00	-24.79	V
7630.18	-32.94	11.50	22.20	-43.64	-13.00	-30.64	V

**Note:** (1) Below 30MHz no Spurious found is the worst condition.


(2) Above 6GHz amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value





## APPENDIX B PHOTOS OF TEST SETUP

### RADIATED SPURIOUS EMISSION



※※※※※END OF THE REPORT※※※※※