

Model: AA4113		Test Number: 200922			
MPE Calculator	RF Exposure uses EIRP for calculation. EIRP is based on TX power added to the antenna gain in dBi.				
	dBi = dB gain compared to an isotropic radiator.				
	S = power density in mW/cm ²				
	Transmitter Output power (mW)	55.3			
	Transmitter Output power (W)	0.055			
Output Power for % duty Cycle operation (Watts)	100	0.055		Antenna Gain (dBi)	-0.3
Output Power for 100% duty Cycle operation (Watts)		0.055		Antenna Gain (Numeric)	0.93
Tx Frequency (MHz)	2437	Calculation power (Watts)	0.055	dBd + 2.17 = dBi	dBi to dBd
				Antenna Gain (dBd)	-2.47
Cable Loss (dB)	0.0	Adjusted Power (dBm)	17.43	Antenna minus cable (dBi)	-0.30
				Antenna Gain (Numeric)	0.93
	Calculated ERP (mw)	31.333		EIRP = Po(dBm) + Gain (dB)	
	Calculated EIRP (mw)	51.642		Radiated (EIRP) dBm	17.130
	<div style="border: 1px solid black; padding: 5px; width: fit-content;"> $\text{Power density (S) mW/cm}^2 = \frac{\text{EIRP}}{4 \pi r^2}$ $r \text{ (cm)} = \sqrt{\frac{\text{EIRP (mW)}}{4 \pi S}}$ </div>			ERP = EIRP - 2.17 dB	
					Radiated (ERP) dBm
Occupational Limit		FCC radio frequency radiation exposure limits per 1.1310			
5	mW/cm ²	Frequency (MHz)	Occupational Limit (mW/cm ²)	Public Limit (mW/cm ²)	
50	W/m ²	30-300	1	0.2	
General Public Limit		300-1,500	ƒ/300	ƒ/1500	
1	mW/cm ²	1,500-10,000	5	1	
10	W/m ²				
Occupational Limit		IC radio frequency radiation exposure limits per RSS-102			
0.6455f ^{0.5}	W/m ²	Frequency (MHz)	Occupational Limit (W/m ²)	Public Limit (W/m ²)	
39.7	W/m ²	100-6,000	0.6455f ^{0.5}		
General Public Limit		100-6,000			
0.02619f ^{0.6834}	W/m ²	6,000-15,000	50		
5.4	W/m ²	48-300		1.291	
		300-6,000		0.02619f ^{0.6834}	
		6,000-15,000	50	10	
f = Transmit Frequency (MHz)				f (MHz) =	2437 MHz
P _T = Power Input to Antenna (mW)				P _T (mW) =	55.3350 mW
Duty cycle (percentage of operation)				% =	100 %
P _A = Adjusted Power due to Duty cycle or Cable Loss (mW)				P _A (mW) =	55.34 mW
G _N = Numeric Gain of the Antenna				G _N (numeric) =	0.93 numeric
S ₂₀ = Power Density of device at 20cm (mW/m ²)		S ₂₀ =(P _A G _N)/(4πR ₂₀) ²		S ₂₀ (mW/m ²) =	0.01 mW/m ²
S ₂₀ = Power Density of device at 20cm (W/m ²)		S ₂₀ =(P _A G _N)/(4πR ₂₀) ²		S ₂₀ (W/m ²) =	0.10 W/m ²
S _L = Power Density Limit (W/m ²)				S _L (W/m ²)=	5.404 W/m ²
R _C = Minimum distance to the Radiating Element for Compliance (cm)		R _C =√(P _A G _N /4πS _L)		R _C (cm) =	2.8 cm
S _C = Power Density of the device at the Compliance Distance R _C (W/m ²)		S _C =(P _A G _N)/(4πR _C) ²		S _C (W/m ²) =	5.40 W/m ²
R ₂₀ = 20cm				R ₂₀ =	20 cm
For Compliance with Canada General Population Limits, User Manual must indicate a minimum separation distance of					2.8 cm
Or in Meters for Compliance with Canada General Population Limits, a minimum separation distance of					0.03 Meters

Rogers Labs, Inc.
4405 West 259th Terrace
Louisburg, KS 66053
Phone/Fax: (913) 837-3214
Revision 1

Garmin International, Inc.
Model: AA4113
Test: 200922
Test to: CFR47 15C, RSS-247, RSS-Gen
File: AA4113 MPE Exclusion

SN's: 3341634221 / 3341634272
FCC ID: IPH-A4113
IC: 1792A-A4113
Date: December 29, 2020
Page 1 of 1