



DECLARATION OF COMPLIANCE: MPE ASSESSMENT PCII Report Part 2 of 2

Motorola Solutions Inc.
EME Test Laboratory
 Motorola Solutions Malaysia Sdn Bhd
 Plot 2A, Medan Bayan Lepas,
 Mukim 12 SWD 11900 Bayan Lepas Penang, Malaysia.

Date of Report: 4/23/2020
Report Revision: B

Responsible Engineer: Saw Sun Hock (EME Engineer)
Report author: Saw Sun Hock (EME Engineer)
Date(s) Tested: 3/8/2017-3/20/2017; 4/23/2019 - 4/24/2019, 5/7/2019, 5/9/2019, 5/13/2019 - 5/14/2019, 5/29/2019
Manufacturer: Futurecom Systems Group (DVR), Motorola Solutions. Inc (Mobile)
Date submitted for test: 01/13/2017; 04/12/2019
DUT Description: **APX6500 7/800MHz:** Multiple HW Encryption WiFi Interoperability Data Modem Tethering via WiFi or Cable
Companion Device: DVR 800 (806-824 MHz; 851-869MHz), Digital Vehicular Repeater
Test TX mode(s): CW
Max. Power output: **APX6500 7/800MHz:** 36W (762-805 MHz), 42W (806-870 MHz); 11.22 mW (Bluetooth); 6.3 mW (Bluetooth LE); 39.8 mW (WLAN 2.4GHz 802.11b), 15.8 mW (WLAN 2.4GHz 802.11g), 12.6mW (WLAN 2.4GHz 802.11n); 15.8mW (WLAN 5GHz 802.11a/n/ac)
Companion Device: 10W (DVR 800)
TX Frequency Bands: **APX6500 7/800MHz:** 762-806 MHz; 806-870 MHz; WLAN 2412-2462 MHz; WLAN 5180-5825 MHz; BT 2402-2480 MHz
Companion Device: 806-824 MHz; 851-869MHz
Signaling type: FM, TDMA, FHSS (Bluetooth), 802.11b/g/n (WLAN 2.4 GHz), 802.11 a/n/ac (WLAN 5 GHz)
Model(s) Tested: **APX6500 7/800MHz:** M25URS9PW1BN (PMUF1969A)
Companion Device: MOBEXCOM DVRS 800 (DQPM DVRS8000P)
Model(s) Certified: M25URS9PW1BN (PMUF1969A), MOBEXCOM DVRS 800 (DQPM DVRS8000P)
Serial Number(s): 471TVF3314 (APX6500 7/800MHz) , 17010530 (DVR 800)
Classification: Occupational/Controlled Environment
Applicant Name: Motorola Solutions Inc.
Applicant Address: 8000 West Sunrise Boulevard, Fort Lauderdale, Florida 33322
FCC ID: **APX6500 7/800MHz:** AZ492FT7124 (769-775 MHz, 799-824 MHz, 851-869 MHz, 2402-2480 MHz, 2412-2462 MHz; 5180-5825 MHz)
Companion Device: LO6-DVRS800 (806-824 MHz; 851-869MHz)
 This report contains results that are immaterial for FCC equipment approval, which are clearly identified.
IC: **APX6500 7/800MHz:** 109U-92FT7124
Companion Device: 2098B-DVRS800
 This report contains results that are immaterial for ISED Canada equipment approval, which are clearly identified.

The MPE results clearly demonstrate compliance with FCC Occupational/Controlled RF Exposure limits. FCC rules require compliance for Passengers and Bystanders to the FCC General Population/Uncontrolled limits.

Based on the information and the testing results provided herein, the undersigned certifies that when used as stated in the operating instructions supplied, said product complies with the national and international reference standards and guidelines listed in section 4.0 of this report (no deviation from standard methods). This report shall not be reproduced without written approval from an officially designated representative of the Motorola Solutions Inc. EME Laboratory.

I attest to the accuracy of the data and assume full responsibility for the completeness of these measurements.

This reporting format is consistent with the suggested guidelines of the TIA TSB-159 April 2006

The results and statements contained in this report pertain only to the device(s) evaluated herein.

Tiong Nguk Ing
Deputy Technical Manager (Approved Signatory)
Approval Date: 4/23/2020

Appendix D – MPE Test Results Summary for APX6500 7/800 MHz

Table D.1**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS1	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.04	0.51	8.4	0.24	17.5
						35.2	769.0125	0.04	0.51	8.4	0.25	17.5
						35.0	772.0000	0.05	0.51	9.2	0.25	19.1
						34.9	774.9875	0.04	0.52	8.2	0.25	17.1
						34.6	794.0125	0.05	0.53	9.3	0.25	19.6
						35.5	799.0125	0.05	0.53	9.6	0.25	20.3
					42	42.0	811.5000	0.04	0.54	7.3	0.25	15.6
						40.8	823.9875	0.04	0.55	6.8	0.26	14.5
						41.8	851.0125	0.03	0.57	5.1	0.26	11.0
						41.1	860.5000	0.04	0.57	6.9	0.27	14.8
						41.1	868.9875	0.03	0.58	5.4	0.27	11.8
Roof	BS2	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.03	0.51	5.9	0.24	12.2
						35.2	769.0125	0.03	0.51	5.9	0.25	12.2
						35.0	772.0000	0.03	0.51	5.9	0.25	12.3
						34.9	774.9875	0.03	0.52	5.2	0.25	11.0
						34.6	794.0125	0.03	0.53	5.2	0.25	10.9
						35.5	799.0125	0.03	0.53	4.9	0.25	10.4
					42	42.0	811.5000	0.02	0.54	4.4	0.25	9.3
						40.8	823.9875	0.03	0.55	5.4	0.26	11.6
						41.8	851.0125	0.03	0.57	5.0	0.26	10.7
						41.1	860.5000	0.03	0.57	5.7	0.27	12.3
						41.1	868.9875	0.03	0.58	4.5	0.27	9.7

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS3	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	2.3	0.24	4.8
						35.2	769.0125	0.01	0.51	2.3	0.25	4.8
						35.0	772.0000	0.01	0.51	2.2	0.25	4.7
						34.9	774.9875	0.01	0.52	1.9	0.25	4.1
						34.6	794.0125	0.02	0.53	2.9	0.25	6.2
						35.5	799.0125	0.02	0.53	2.8	0.25	6.0
					42	42.0	811.5000	0.01	0.54	2.5	0.25	5.2
						40.8	823.9875	0.02	0.55	2.9	0.26	6.1
						41.8	851.0125	0.01	0.57	2.3	0.26	5.1
						41.1	860.5000	0.01	0.57	2.3	0.27	4.9
						41.1	868.9875	0.01	0.58	2.5	0.27	5.4
Roof	BS4	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.4	0.24	2.9
						35.2	769.0125	0.01	0.51	1.4	0.25	2.9
						35.0	772.0000	0.01	0.51	1.3	0.25	2.7
						34.9	774.9875	0.01	0.52	1.3	0.25	2.8
						34.6	794.0125	0.01	0.53	1.2	0.25	2.5
						35.5	799.0125	0.01	0.53	1.2	0.25	2.4
					42	42.0	811.5000	0.01	0.54	1.0	0.25	2.1
						40.8	823.9875	0.01	0.55	1.2	0.26	2.6
						41.8	851.0125	0.01	0.57	1.1	0.26	2.3
						41.1	860.5000	0.01	0.57	1.4	0.27	3.1
						41.1	868.9875	0.01	0.58	1.1	0.27	2.5

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS5	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.1	0.24	2.2
						35.2	769.0125	0.01	0.51	1.1	0.25	2.2
						35.0	772.0000	0.01	0.51	1.4	0.25	2.9
						34.9	774.9875	0.01	0.52	1.4	0.25	3.0
						34.6	794.0125	0.01	0.53	1.5	0.25	3.1
						35.5	799.0125	0.01	0.53	1.9	0.25	3.9
					42	42.0	811.5000	0.01	0.54	1.8	0.25	3.9
						40.8	823.9875	0.01	0.55	1.0	0.26	2.2
						41.8	851.0125	0.004	0.57	0.7	0.26	1.6
						41.1	860.5000	0.01	0.57	0.9	0.27	1.9
						41.1	868.9875	0.004	0.58	0.7	0.27	1.5
Roof	BS1	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.03	0.51	5.8	0.24	12.1
						35.2	769.0125	0.03	0.51	5.8	0.25	12.1
						35.0	772.0000	0.03	0.51	6.6	0.25	13.7
						34.9	774.9875	0.03	0.52	6.2	0.25	13.0
						34.6	794.0125	0.05	0.53	8.7	0.25	18.4
						35.5	799.0125	0.05	0.53	9.7	0.25	20.5
					42	42.0	811.5000	0.04	0.54	7.9	0.25	16.8
						40.8	823.9875	0.04	0.55	6.7	0.26	14.4
						41.8	851.0125	0.02	0.57	4.1	0.26	8.9
						41.1	860.5000	0.03	0.57	5.0	0.27	10.8
						41.1	868.9875	0.03	0.58	4.4	0.27	9.6

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS2	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.02	0.51	3.5	0.24	7.2
						35.2	769.0125	0.02	0.51	3.3	0.25	7.0
						35.0	772.0000	0.02	0.51	3.6	0.25	7.6
						34.9	774.9875	0.02	0.52	3.8	0.25	8.0
						34.6	794.0125	0.02	0.53	3.9	0.25	8.2
						35.5	799.0125	0.02	0.53	4.0	0.25	8.4
					42	42.0	811.5000	0.02	0.54	3.6	0.25	7.7
						40.8	823.9875	0.03	0.55	5.3	0.26	11.2
						41.8	851.0125	0.03	0.57	4.7	0.26	10.1
						41.1	860.5000	0.03	0.57	5.1	0.27	11.1
						41.1	868.9875	0.02	0.58	3.7	0.27	8.1
Roof	BS3	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.4	0.24	2.9
						35.2	769.0125	0.01	0.51	1.4	0.25	2.9
						35.0	772.0000	0.01	0.51	1.4	0.25	3.0
						34.9	774.9875	0.01	0.52	1.3	0.25	2.6
						34.6	794.0125	0.02	0.53	3.4	0.25	7.2
						35.5	799.0125	0.02	0.53	3.4	0.25	7.2
					42	42.0	811.5000	0.02	0.54	4.6	0.25	9.8
						40.8	823.9875	0.02	0.55	4.2	0.26	8.9
						41.8	851.0125	0.02	0.57	3.9	0.26	8.4
						41.1	860.5000	0.02	0.57	3.0	0.27	6.5
						41.1	868.9875	0.02	0.58	3.7	0.27	8.1

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS4	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.004	0.51	0.9	0.24	1.8
						35.2	769.0125	0.004	0.51	0.9	0.25	1.8
						35.0	772.0000	0.004	0.51	0.8	0.25	1.8
						34.9	774.9875	0.01	0.52	1.2	0.25	2.5
						34.6	794.0125	0.01	0.53	1.4	0.25	3.0
						35.5	799.0125	0.01	0.53	1.3	0.25	2.7
					42	42.0	811.5000	0.01	0.54	1.3	0.25	2.8
						40.8	823.9875	0.01	0.55	1.7	0.26	3.7
						41.8	851.0125	0.01	0.57	2.1	0.26	4.6
						41.1	860.5000	0.01	0.57	2.4	0.27	5.2
						41.1	868.9875	0.01	0.58	1.8	0.27	3.8
Roof	BS5	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.004	0.51	0.8	0.24	1.8
						35.2	769.0125	0.004	0.51	0.8	0.25	1.7
						35.0	772.0000	0.01	0.51	1.3	0.25	2.7
						34.9	774.9875	0.01	0.52	1.3	0.25	2.8
						34.6	794.0125	0.01	0.53	1.8	0.25	3.8
						35.5	799.0125	0.01	0.53	2.7	0.25	5.6
					42	42.0	811.5000	0.01	0.54	2.2	0.25	4.7
						40.8	823.9875	0.01	0.55	2.2	0.26	4.6
						41.8	851.0125	0.01	0.57	1.4	0.26	3.0
						41.1	860.5000	0.01	0.57	1.4	0.27	2.9
						41.1	868.9875	0.01	0.58	1.3	0.27	2.8

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS1	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.04	0.51	8.2	0.24	17.1
						35.2	769.0125	0.04	0.51	8.1	0.25	16.9
						35.0	772.0000	0.04	0.51	8.1	0.25	17.0
						34.9	774.9875	0.04	0.52	8.0	0.25	16.8
						34.6	794.0125	0.05	0.53	9.2	0.25	19.4
						35.5	799.0125	0.05	0.53	9.7	0.25	20.5
					42	42.0	811.5000	0.04	0.54	7.4	0.25	15.6
						40.8	823.9875	0.04	0.55	6.8	0.26	14.5
						41.8	851.0125	0.03	0.57	4.6	0.26	9.9
						41.1	860.5000	0.04	0.57	6.2	0.27	13.5
						41.1	868.9875	0.03	0.58	4.9	0.27	10.6
Roof	BS2	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.03	0.51	5.6	0.24	11.7
						35.2	769.0125	0.03	0.51	5.6	0.25	11.7
						35.0	772.0000	0.03	0.51	5.6	0.25	11.7
						34.9	774.9875	0.03	0.52	5.0	0.25	10.5
						34.6	794.0125	0.03	0.53	5.0	0.25	10.6
						35.5	799.0125	0.03	0.53	4.7	0.25	10.0
					42	42.0	811.5000	0.02	0.54	3.9	0.25	8.4
						40.8	823.9875	0.03	0.55	5.0	0.26	10.7
						41.8	851.0125	0.02	0.57	4.1	0.26	8.9
						41.1	860.5000	0.03	0.57	4.8	0.27	10.3
						41.1	868.9875	0.02	0.58	3.7	0.27	8.0

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS3	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	2.4	0.24	5.0
						35.2	769.0125	0.01	0.51	2.4	0.25	5.0
						35.0	772.0000	0.01	0.51	2.4	0.25	5.0
						34.9	774.9875	0.01	0.52	2.1	0.25	4.5
						34.6	794.0125	0.02	0.53	2.9	0.25	6.2
						35.5	799.0125	0.01	0.53	2.7	0.25	5.8
					42	42.0	811.5000	0.01	0.54	2.5	0.25	5.3
						40.8	823.9875	0.02	0.55	3.0	0.26	6.3
						41.8	851.0125	0.01	0.57	2.1	0.26	4.6
						41.1	860.5000	0.01	0.57	2.4	0.27	5.1
						41.1	868.9875	0.01	0.58	2.5	0.27	5.3
Roof	BS4	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.5	0.24	3.1
						35.2	769.0125	0.01	0.51	1.5	0.25	3.0
						35.0	772.0000	0.01	0.51	1.3	0.25	2.8
						34.9	774.9875	0.01	0.52	1.5	0.25	3.0
						34.6	794.0125	0.01	0.53	1.2	0.25	2.5
						35.5	799.0125	0.01	0.53	1.2	0.25	2.6
					42	42.0	811.5000	0.005	0.54	0.9	0.25	2.0
						40.8	823.9875	0.01	0.55	1.1	0.26	2.4
						41.8	851.0125	0.01	0.57	1.1	0.26	2.3
						41.1	860.5000	0.01	0.57	1.3	0.27	2.9
						41.1	868.9875	0.01	0.58	1.1	0.27	2.4

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS5	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.4	0.24	3.0
						35.2	769.0125	0.01	0.51	1.4	0.25	2.9
						35.0	772.0000	0.01	0.51	1.9	0.25	3.9
						34.9	774.9875	0.01	0.52	1.9	0.25	3.9
						34.6	794.0125	0.01	0.53	1.7	0.25	3.5
						35.5	799.0125	0.01	0.53	2.1	0.25	4.5
					42	42.0	811.5000	0.01	0.54	1.4	0.25	3.1
						40.8	823.9875	0.01	0.55	1.3	0.26	2.8
						41.8	851.0125	0.004	0.57	0.8	0.26	1.6
						41.1	860.5000	0.01	0.57	0.9	0.27	2.0
						41.1	868.9875	0.004	0.58	0.7	0.27	1.6
Roof	BS1	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.05	0.51	9.2	0.24	19.2
						35.2	769.0125	0.05	0.51	9.2	0.25	19.1
						35.0	772.0000	0.05	0.51	10.2	0.25	21.4
						34.9	774.9875	0.05	0.52	9.2	0.25	19.2
						34.6	794.0125	0.06	0.53	11.4	0.25	24.1
						35.5	799.0125	0.07	0.53	12.2	0.25	25.8
					42	42.0	811.5000	0.05	0.54	8.4	0.25	17.8
						40.8	823.9875	0.04	0.55	8.0	0.26	17.0
						41.8	851.0125	0.02	0.57	4.3	0.26	9.3
						41.1	860.5000	0.04	0.57	6.2	0.27	13.4
						41.1	868.9875	0.03	0.58	4.4	0.27	9.6

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS2	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.04	0.51	7.5	0.24	15.6
						35.2	769.0125	0.04	0.51	7.4	0.25	15.4
						35.0	772.0000	0.04	0.51	7.4	0.25	15.5
						34.9	774.9875	0.04	0.52	6.9	0.25	14.3
						34.6	794.0125	0.03	0.53	6.3	0.25	13.2
						35.5	799.0125	0.03	0.53	6.2	0.25	13.1
					42	42.0	811.5000	0.03	0.54	4.8	0.25	10.2
						40.8	823.9875	0.04	0.55	6.5	0.26	14.0
						41.8	851.0125	0.03	0.57	4.6	0.26	10.0
						41.1	860.5000	0.03	0.57	5.9	0.27	12.7
						41.1	868.9875	0.02	0.58	4.1	0.27	9.0
Roof	BS3	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.02	0.51	4.2	0.24	8.7
						35.2	769.0125	0.02	0.51	4.2	0.25	8.9
						35.0	772.0000	0.02	0.51	4.0	0.25	8.3
						34.9	774.9875	0.02	0.52	3.6	0.25	7.6
						34.6	794.0125	0.03	0.53	5.1	0.25	10.8
						35.5	799.0125	0.02	0.53	4.7	0.25	9.9
					42	42.0	811.5000	0.02	0.54	4.1	0.25	8.6
						40.8	823.9875	0.03	0.55	4.9	0.26	10.4
						41.8	851.0125	0.02	0.57	3.1	0.26	6.7
						41.1	860.5000	0.02	0.57	3.6	0.27	7.7
						41.1	868.9875	0.02	0.58	3.2	0.27	7.0

Table D.1 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	BS4	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	2.9	0.24	6.1
						35.2	769.0125	0.01	0.51	2.9	0.25	6.0
						35.0	772.0000	0.01	0.51	2.6	0.25	5.4
						34.9	774.9875	0.02	0.52	2.9	0.25	6.1
						34.6	794.0125	0.01	0.53	2.7	0.25	5.7
						35.5	799.0125	0.01	0.53	2.7	0.25	5.8
					42	42.0	811.5000	0.01	0.54	1.6	0.25	3.4
						40.8	823.9875	0.01	0.55	2.0	0.26	4.3
						41.8	851.0125	0.01	0.57	1.7	0.26	3.6
						41.1	860.5000	0.01	0.57	2.2	0.27	4.7
						41.1	868.9875	0.01	0.58	1.7	0.27	3.6
Roof	BS5	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	2.6	0.24	5.3
						35.2	769.0125	0.01	0.51	2.6	0.25	5.4
						35.0	772.0000	0.02	0.51	3.6	0.25	7.5
						34.9	774.9875	0.02	0.52	3.4	0.25	7.2
						34.6	794.0125	0.02	0.53	3.0	0.25	6.4
						35.5	799.0125	0.02	0.53	3.8	0.25	8.0
					42	42.0	811.5000	0.01	0.54	2.5	0.25	5.3
						40.8	823.9875	0.01	0.55	2.5	0.26	5.3
						41.8	851.0125	0.01	0.57	1.2	0.26	2.6
						41.1	860.5000	0.01	0.57	1.5	0.27	3.2
						41.1	868.9875	0.01	0.58	1.2	0.27	2.7

Table D.2**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	PB	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.02	0.51	3.2	0.24	6.7
						35.2	769.0125	0.02	0.51	3.2	0.25	6.6
						35.0	772.0000	0.02	0.51	3.5	0.25	7.4
						34.9	774.9875	0.02	0.52	3.6	0.25	7.4
						34.6	794.0125	0.02	0.53	3.3	0.25	7.0
						35.5	799.0125	0.02	0.53	2.9	0.25	6.2
					42	42.0	811.5000	0.01	0.54	2.5	0.25	5.2
						40.8	823.9875	0.02	0.55	2.9	0.26	6.1
						41.8	851.0125	0.01	0.57	1.2	0.26	2.7
						41.1	860.5000	0.01	0.57	1.8	0.27	3.9
						41.1	868.9875	0.01	0.58	1.4	0.27	3.1
Roof	PB	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.001	0.51	0.3	0.24	0.6
						35.2	769.0125	0.002	0.51	0.3	0.25	0.6
						35.0	772.0000	0.001	0.51	0.3	0.25	0.6
						34.9	774.9875	0.001	0.52	0.2	0.25	0.5
						34.6	794.0125	0.004	0.53	0.8	0.25	1.6
						35.5	799.0125	0.01	0.53	1.0	0.25	2.2
					42	42.0	811.5000	0.01	0.54	1.9	0.25	4.1
						40.8	823.9875	0.01	0.55	2.3	0.26	5.0
						41.8	851.0125	0.01	0.57	1.9	0.26	4.0
						41.1	860.5000	0.01	0.57	1.3	0.27	2.8
						41.1	868.9875	0.01	0.58	1.8	0.27	4.0

Table D.2 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	PB	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.02	0.51	3.1	0.24	6.5
						35.2	769.0125	0.02	0.51	3.5	0.25	7.3
						35.0	772.0000	0.02	0.51	3.3	0.25	6.8
						34.9	774.9875	0.02	0.52	3.3	0.25	6.8
						34.6	794.0125	0.02	0.53	3.6	0.25	7.6
						35.5	799.0125	0.02	0.53	2.9	0.25	6.2
					42	42.0	811.5000	0.01	0.54	2.2	0.25	4.6
						40.8	823.9875	0.02	0.55	3.4	0.26	7.2
						41.8	851.0125	0.01	0.57	1.6	0.26	3.5
						41.1	860.5000	0.01	0.57	1.5	0.27	3.3
						41.1	868.9875	0.01	0.58	1.6	0.27	3.4
Roof	PB	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.03	0.51	5.8	0.24	12.1
						35.2	769.0125	0.03	0.51	5.2	0.25	10.9
						35.0	772.0000	0.03	0.51	5.5	0.25	11.5
						34.9	774.9875	0.03	0.52	5.5	0.25	11.6
						34.6	794.0125	0.03	0.53	5.4	0.25	11.3
						35.5	799.0125	0.03	0.53	5.0	0.25	10.6
					42	42.0	811.5000	0.02	0.54	3.8	0.25	8.1
						40.8	823.9875	0.02	0.55	3.9	0.26	8.4
						41.8	851.0125	0.01	0.57	2.1	0.26	4.6
						41.1	860.5000	0.02	0.57	3.3	0.27	7.2
						41.1	868.9875	0.01	0.58	2.0	0.27	4.4

Table D.2 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	PF	E	1	HAF4013A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.7	0.24	3.4
						35.2	769.0125	0.01	0.51	2.0	0.25	4.1
						35.0	772.0000	0.01	0.51	1.8	0.25	3.9
						34.9	774.9875	0.01	0.52	1.9	0.25	4.1
						34.6	794.0125	0.01	0.53	1.4	0.25	3.0
						35.5	799.0125	0.01	0.53	1.3	0.25	2.7
					42	42.0	811.5000	0.01	0.54	1.4	0.25	3.0
						40.8	823.9875	0.01	0.55	1.8	0.26	3.9
						41.8	851.0125	0.01	0.57	1.5	0.26	3.2
						41.1	860.5000	0.01	0.57	1.6	0.27	3.4
						41.1	868.9875	0.01	0.58	1.3	0.27	2.8
Roof	PF	E	2	HAF4014A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.002	0.51	0.3	0.24	0.6
						35.2	769.0125	0.002	0.51	0.3	0.25	0.7
						35.0	772.0000	0.002	0.51	0.4	0.25	0.8
						34.9	774.9875	0.002	0.52	0.3	0.25	0.6
						34.6	794.0125	0.003	0.53	0.6	0.25	1.2
						35.5	799.0125	0.004	0.53	0.7	0.25	1.4
					42	42.0	811.5000	0.01	0.54	1.1	0.25	2.4
						40.8	823.9875	0.01	0.55	1.5	0.26	3.2
						41.8	851.0125	0.01	0.57	2.0	0.26	4.4
						41.1	860.5000	0.01	0.57	1.8	0.27	4.0
						41.1	868.9875	0.01	0.58	1.4	0.27	3.1

Table D.2 (Continued)**MPE assessment for APX6500 7/800MHz - roof mounted antenna – Bystander**

Note:

Blue fonts: Frequencies not regulated by FCC.

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit	ISED Limit	% To ISED Spec Limit
Roof	PF	E	3	HAF4016A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.01	0.51	1.8	0.24	3.7
						35.2	769.0125	0.01	0.51	1.9	0.25	4.0
						35.0	772.0000	0.01	0.51	1.4	0.25	3.0
						34.9	774.9875	0.01	0.52	1.6	0.25	3.4
						34.6	794.0125	0.01	0.53	1.3	0.25	2.8
						35.5	799.0125	0.01	0.53	1.3	0.25	2.8
					42	42.0	811.5000	0.01	0.54	1.4	0.25	3.0
						40.8	823.9875	0.01	0.55	1.9	0.26	4.1
						41.8	851.0125	0.01	0.57	1.4	0.26	3.1
						41.1	860.5000	0.01	0.57	1.4	0.27	3.1
						41.1	868.9875	0.01	0.58	1.2	0.27	2.5
Roof	PF	E	4	HAF4017A, 1/4 Wave, (762-870MHz)	36	35.2	762.0125	0.02	0.51	3.5	0.24	7.4
						35.2	769.0125	0.02	0.51	3.4	0.25	7.2
						35.0	772.0000	0.02	0.51	3.3	0.25	6.9
						34.9	774.9875	0.01	0.52	2.8	0.25	5.9
						34.6	794.0125	0.01	0.53	2.8	0.25	5.9
						35.5	799.0125	0.01	0.53	2.3	0.25	4.8
					42	42.0	811.5000	0.01	0.54	2.1	0.25	4.4
						40.8	823.9875	0.02	0.55	3.0	0.26	6.4
						41.8	851.0125	0.01	0.57	2.1	0.26	4.5
						41.1	860.5000	0.01	0.57	2.0	0.27	4.3
						41.1	868.9875	0.01	0.58	1.5	0.27	3.3

Table D.3
APX6500 7/800MHz MPE Results for FCC

Note:

Blue fonts: Frequencies not regulated by FCC.

P_{max} (W)
36, 52P_{initial} (W)FCC Limit (mW/cm²)

35.2	35.2	35.0	34.9	34.6	35.5	42.0	40.8	41.8	41.1	41.1
0.51	0.51	0.51	0.52	0.53	0.53	0.54	0.55	0.57	0.57	0.58

Table	Test Post.	Trunk / Roof	E/H Field	Antenna No.	F1	F2	F3	F4	F5	F6	F7	F8	F9	F10	F11
					762.0125	769.0125	772.0000	774.9875	794.0125	799.0125	811.5000	823.9875	851.0125	860.5000	868.9875
D.1	BS1	Roof	E	1	0.04	0.04	0.05	0.04	0.05	0.05	0.04	0.04	0.03	0.04	0.03
D.1	BS2	Roof	E	1	0.03	0.03	0.03	0.03	0.03	0.03	0.02	0.03	0.03	0.03	0.03
D.1	BS3	Roof	E	1	0.01	0.01	0.01	0.01	0.02	0.02	0.01	0.02	0.01	0.01	0.01
D.1	BS4	Roof	E	1	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01
D.1	BS5	Roof	E	1	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.004	0.01	0.004
D.1	BS1	Roof	E	2	0.03	0.03	0.03	0.03	0.05	0.05	0.04	0.04	0.02	0.03	0.03
D.1	BS2	Roof	E	2	0.02	0.02	0.02	0.02	0.02	0.02	0.02	0.03	0.03	0.03	0.02
D.1	BS3	Roof	E	2	0.01	0.01	0.01	0.01	0.02	0.02	0.02	0.02	0.02	0.02	0.02
D.1	BS4	Roof	E	2	0.004	0.004	0.004	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01
D.1	BS5	Roof	E	2	0.004	0.004	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01
D.1	BS1	Roof	E	3	0.04	0.04	0.04	0.04	0.05	0.05	0.04	0.04	0.03	0.04	0.03
D.1	BS2	Roof	E	3	0.03	0.03	0.03	0.03	0.03	0.03	0.02	0.03	0.02	0.03	0.02
D.1	BS3	Roof	E	3	0.01	0.01	0.01	0.01	0.02	0.01	0.01	0.02	0.01	0.01	0.01
D.1	BS4	Roof	E	3	0.01	0.01	0.01	0.01	0.01	0.01	0.005	0.01	0.01	0.01	0.01
D.1	BS5	Roof	E	3	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.004	0.01	0.004
D.1	BS1	Roof	E	4	0.05	0.05	0.05	0.05	0.06	0.07	0.05	0.04	0.02	0.04	0.03
D.1	BS2	Roof	E	4	0.04	0.04	0.04	0.04	0.03	0.03	0.03	0.04	0.03	0.03	0.02
D.1	BS3	Roof	E	4	0.02	0.02	0.02	0.02	0.03	0.02	0.02	0.03	0.02	0.02	0.02
D.1	BS4	Roof	E	4	0.01	0.01	0.01	0.02	0.01	0.01	0.01	0.01	0.01	0.01	0.01
D.1	BS5	Roof	E	4	0.01	0.01	0.02	0.02	0.02	0.02	0.01	0.01	0.01	0.01	0.01
D.2	PB	Roof	E	1	0.02	0.02	0.02	0.02	0.02	0.02	0.01	0.02	0.01	0.01	0.01
D.2	PB	Roof	E	2	0.001	0.002	0.001	0.001	0.004	0.01	0.01	0.01	0.01	0.01	0.01
D.2	PB	Roof	E	3	0.02	0.02	0.02	0.02	0.02	0.02	0.01	0.02	0.01	0.01	0.01
D.2	PB	Roof	E	4	0.03	0.03	0.03	0.03	0.03	0.03	0.02	0.02	0.01	0.02	0.01
D.2	PF	Roof	E	1	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01
D.2	PF	Roof	E	2	0.002	0.002	0.002	0.002	0.003	0.004	0.01	0.01	0.01	0.01	0.01
D.2	PF	Roof	E	3	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01	0.01
D.2	PF	Roof	E	4	0.02	0.02	0.02	0.01	0.01	0.01	0.01	0.02	0.01	0.01	0.01

Appendix E – MPE Test Results Summary for Companion Device (DVR 800)

Table E.1**MPE assessment for DVR 800 - trunk mounted antenna – Bystander**

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit
Trunk	BS1	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.005	0.54	0.9
						9.95	815.0000	0.006	0.54	1.0
						9.85	824.0000	0.005	0.55	0.8
						9.91	851.0000	0.004	0.57	0.7
						10.00	860.0000	0.003	0.57	0.5
						10.00	869.0000	0.004	0.58	0.6
Trunk	BS2	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.015	0.54	2.8
						9.95	815.0000	0.016	0.54	2.9
						9.85	824.0000	0.012	0.55	2.2
						9.91	851.0000	0.015	0.57	2.7
						10.00	860.0000	0.012	0.57	2.1
						10.00	869.0000	0.011	0.58	1.8
Trunk	BS3	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.014	0.54	2.6
						9.95	815.0000	0.016	0.54	3.0
						9.85	824.0000	0.016	0.55	2.9
						9.91	851.0000	0.016	0.57	2.8
						10.00	860.0000	0.012	0.57	2.2
						10.00	869.0000	0.012	0.58	2.0
Trunk	BS4	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.019	0.54	3.5
						9.95	815.0000	0.024	0.54	4.4
						9.85	824.0000	0.022	0.55	4.0
						9.91	851.0000	0.028	0.57	4.9
						10.00	860.0000	0.018	0.57	3.1
						10.00	869.0000	0.019	0.58	3.3
Trunk	BS5	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.016	0.54	3.0
						9.95	815.0000	0.016	0.54	3.0
						9.85	824.0000	0.012	0.55	2.2
						9.91	851.0000	0.013	0.57	2.3
						10.00	860.0000	0.009	0.57	1.6
						10.00	869.0000	0.010	0.58	1.7

Note: Results in bold font are configurations with highest percentage of limits.

Table E.2

MPE assessment for DVR 800– trunk mounted antenna – Passenger

Trunk / Roof	Test Post.	E/H Field	Antenna No.	Antenna Model	Max Pwr (W)	Initial Pwr (W)	Tx Freq (MHz)	Max Calc. P.D. (mW/cm ²)	FCC Limit	% To FCC Spec Limit
Trunk	PB	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.056	0.54	10.4
						9.95	815.0000	0.060	0.54	11.1
						9.85	824.0000	0.048	0.55	8.7
						9.91	851.0000	0.045	0.57	7.9
						10.00	860.0000	0.039	0.57	6.8
						10.00	869.0000	0.023	0.58	4.0
Trunk	PF	E	9	HAF4016A, 1/4 Wave (764-870MHz)	10.0	10.00	806.0000	0.026	0.54	4.7
						9.95	815.0000	0.026	0.54	4.8
						9.85	824.0000	0.024	0.55	4.4
						9.91	851.0000	0.031	0.57	5.5
						10.00	860.0000	0.028	0.57	4.9
						10.00	869.0000	0.034	0.58	5.8

Note: Results in bold font are configurations with highest percentage of limits.

Table E.3
DVR 800 MPE Results for FCC

Pmax (W)	10	Pinitial (W)	10.00	9.95	9.85	9.91	10.00	10.00
FCCLimit (mW/cm²)			0.54	0.54	0.55	0.57	0.57	0.58

Table	Test Post.	Angle	Trunk / Roof	E/H Field	Antenna No.	f1	f2	f3	f4	f5	f6
						806.0000	815.0000	824.0000	851.0000	860.0000	869.0000
E.1	BS1		Trunk	E	1	0.005	0.006	0.005	0.004	0.003	0.004
E.1	BS2		Trunk	E	1	0.015	0.016	0.012	0.015	0.012	0.011
E.1	BS3		Trunk	E	1	0.014	0.016	0.016	0.016	0.012	0.012
E.11	BS4		Trunk	E	1	0.019	0.024	0.022	0.028	0.018	0.019
E.1	BS5		Trunk	E	1	0.016	0.016	0.012	0.013	0.009	0.010
E 2	PB		Trunk	E	1	0.056	0.060	0.047	0.044	0.039	0.023
E 2	PF		Trunk	E	1	0.026	0.026	0.024	0.031	0.028	0.034

Appendix F – MPE Test Results Summary for APX6500 7/800MHz

Table F.1

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS1	0.0030	0.0120	0.0110	0.0130	0.0210	0.0450	0.0780	0.2120	0.2480	0.2030	0.5	0.083	0.04	0.04
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS1	0.0030	0.0120	0.0110	0.0130	0.0220	0.0440	0.0780	0.2110	0.2500	0.2060	0.5	0.084	0.04	0.04
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS1	0.0030	0.0090	0.0070	0.0110	0.0200	0.0610	0.0990	0.2360	0.2640	0.2170	0.5	0.092	0.05	0.05
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS1	0.0030	0.0070	0.0060	0.0170	0.0190	0.0570	0.0900	0.2200	0.2300	0.1800	0.5	0.082	0.04	0.04
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS1	0.0050	0.0060	0.0100	0.0120	0.0120	0.0440	0.0810	0.2700	0.3100	0.1980	0.5	0.095	0.05	0.05
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS1	0.0040	0.0060	0.0080	0.0100	0.0180	0.0560	0.1110	0.2660	0.3240	0.2050	0.5	0.101	0.05	0.05
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS1	0.0020	0.0070	0.0090	0.0120	0.0110	0.0280	0.0890	0.2080	0.2460	0.1770	0.5	0.079	0.04	0.04
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS1	0.0020	0.0040	0.0050	0.0080	0.0080	0.0300	0.0740	0.1660	0.2280	0.1890	0.5	0.072	0.04	0.04
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS1	0.0010	0.0020	0.0050	0.0110	0.0250	0.0280	0.0300	0.1040	0.1770	0.1760	0.5	0.058	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS1	0.0040	0.0030	0.0040	0.0120	0.0220	0.0390	0.0560	0.1670	0.2170	0.2180	0.5	0.077	0.04	0.04
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS1	0.0030	0.0040	0.0080	0.0150	0.0180	0.0150	0.0480	0.1440	0.1830	0.1550	0.5	0.062	0.03	0.03

Notes:

MPE calculations are defined in section 15.0
 Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS2	0.0020	0.0010	0.0080	0.0130	0.0260	0.0310	0.0670	0.1090	0.1590	0.1750	0.5	0.058	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS2	0.0020	0.0010	0.0080	0.0130	0.0260	0.0300	0.0670	0.1110	0.1610	0.1750	0.5	0.059	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS2	0.0010	0.0030	0.0090	0.0180	0.0250	0.0260	0.0650	0.1260	0.1820	0.1410	0.5	0.059	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS2	0.0000	0.0040	0.0080	0.0130	0.0160	0.0230	0.0520	0.0930	0.1800	0.1410	0.5	0.052	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS2	0.0000	0.0090	0.0080	0.0150	0.0240	0.0200	0.0400	0.0850	0.1480	0.1790	0.5	0.053	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS2	0.0010	0.0060	0.0060	0.0140	0.0280	0.0200	0.0480	0.0940	0.1510	0.1510	0.5	0.052	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS2	0.0010	0.0030	0.0030	0.0070	0.0180	0.0210	0.0450	0.0900	0.1250	0.1560	0.5	0.047	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS2	0.0010	0.0020	0.0030	0.0080	0.0140	0.0230	0.0660	0.1400	0.1660	0.1470	0.5	0.058	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS2	0.0010	0.0030	0.0080	0.0090	0.0090	0.0390	0.0620	0.1250	0.1520	0.1350	0.5	0.056	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS2	0.0010	0.0020	0.0060	0.0110	0.0060	0.0280	0.0530	0.1600	0.2010	0.1470	0.5	0.064	0.03	0.03
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS2	0.0000	0.0010	0.0020	0.0050	0.0100	0.0320	0.0560	0.1180	0.1440	0.1210	0.5	0.051	0.03	0.03

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.			MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)	
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Test Pos.	Bystander (BS) Positions													
											20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm					200 cm
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS3	0.0050	0.0090	0.0110	0.0160	0.0100	0.0070	0.0290	0.0410	0.0430	0.0630	0.5	0.023	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS3	0.0050	0.0100	0.0110	0.0150	0.0110	0.0070	0.0280	0.0410	0.0430	0.0620	0.5	0.023	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS3	0.0060	0.0070	0.0120	0.0130	0.0140	0.0080	0.0210	0.0310	0.0390	0.0760	0.5	0.022	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS3	0.0020	0.0050	0.0110	0.0110	0.0140	0.0110	0.0280	0.0300	0.0330	0.0510	0.5	0.019	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS3	0.0020	0.0080	0.0080	0.0090	0.0100	0.0160	0.0390	0.0560	0.0770	0.0760	0.5	0.030	0.02	0.02	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS3	0.0020	0.0030	0.0060	0.0060	0.0060	0.0150	0.0420	0.0490	0.0720	0.0980	0.5	0.030	0.01	0.02	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS3	0.0030	0.0050	0.0060	0.0060	0.0090	0.0120	0.0330	0.0460	0.0630	0.0820	0.5	0.027	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS3	0.0040	0.0070	0.0100	0.0100	0.0140	0.0170	0.0340	0.0570	0.0710	0.0770	0.5	0.031	0.02	0.02	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS3	0.0030	0.0030	0.0080	0.0130	0.0080	0.0130	0.0310	0.0420	0.0730	0.0630	0.5	0.026	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS3	0.0030	0.0040	0.0070	0.0180	0.0170	0.0160	0.0280	0.0310	0.0580	0.0630	0.5	0.025	0.01	0.01	
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS3	0.0020	0.0040	0.0080	0.0150	0.0120	0.0120	0.0260	0.0310	0.0650	0.0950	0.5	0.028	0.01	0.01	

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS4	0.0030	0.0060	0.0050	0.0100	0.0110	0.0090	0.0080	0.0240	0.0320	0.0330	0.5	0.014	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS4	0.0030	0.0060	0.0050	0.0100	0.0110	0.0090	0.0080	0.0230	0.0330	0.0320	0.5	0.014	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS4	0.0020	0.0050	0.0070	0.0090	0.0100	0.0110	0.0120	0.0230	0.0250	0.0260	0.5	0.013	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS4	0.0030	0.0040	0.0040	0.0090	0.0100	0.0110	0.0120	0.0230	0.0300	0.0300	0.5	0.013	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS4	0.0020	0.0040	0.0040	0.0060	0.0110	0.0120	0.0100	0.0180	0.0230	0.0300	0.5	0.012	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS4	0.0010	0.0060	0.0020	0.0090	0.0100	0.0090	0.0090	0.0260	0.0250	0.0240	0.5	0.012	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS4	0.0010	0.0030	0.0020	0.0050	0.0090	0.0070	0.0110	0.0240	0.0190	0.0260	0.5	0.011	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS4	0.0020	0.0040	0.0040	0.0070	0.0090	0.0050	0.0120	0.0330	0.0270	0.0260	0.5	0.013	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS4	0.0020	0.0030	0.0020	0.0040	0.0100	0.0080	0.0100	0.0270	0.0260	0.0250	0.5	0.012	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS4	0.0020	0.0020	0.0000	0.0040	0.0100	0.0140	0.0130	0.0320	0.0370	0.0400	0.5	0.016	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS4	0.0010	0.0030	0.0040	0.0070	0.0090	0.0080	0.0150	0.0300	0.0240	0.0240	0.5	0.013	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS5	0.0000	0.0030	0.0030	0.0030	0.0060	0.0070	0.0100	0.0230	0.0330	0.0190	0.5	0.011	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS5	0.0000	0.0030	0.0030	0.0030	0.0060	0.0070	0.0100	0.0230	0.0340	0.0180	0.5	0.011	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS5	0.0010	0.0020	0.0010	0.0030	0.0080	0.0130	0.0130	0.0210	0.0450	0.0330	0.5	0.014	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS5	0.0020	0.0010	0.0020	0.0080	0.0130	0.0140	0.0130	0.0170	0.0390	0.0360	0.5	0.014	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS5	0.0010	0.0010	0.0010	0.0050	0.0120	0.0160	0.0140	0.0320	0.0400	0.0290	0.5	0.015	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS5	0.0000	0.0010	0.0020	0.0050	0.0120	0.0180	0.0210	0.0470	0.0540	0.0350	0.5	0.019	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS5	0.0000	0.0010	0.0020	0.0050	0.0120	0.0180	0.0210	0.0470	0.0540	0.0350	0.5	0.020	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS5	0.0000	0.0010	0.0020	0.0090	0.0130	0.0110	0.0090	0.0210	0.0260	0.0180	0.5	0.011	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS5	0.0020	0.0010	0.0010	0.0060	0.0090	0.0110	0.0070	0.0130	0.0170	0.0140	0.5	0.008	0.00	0.00
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS5	0.0010	0.0000	0.0000	0.0040	0.0070	0.0120	0.0050	0.0160	0.0310	0.0190	0.5	0.010	0.00	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS5	0.0010	0.0000	0.0010	0.0030	0.0040	0.0060	0.0060	0.0170	0.0220	0.0150	0.5	0.008	0.00	0.00

Notes:

MPE calculations are defined in section 15.0
 Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.			MPE Measurements									DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)	
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Test Pos.	Bystander (BS) Positions												
											20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm					180 cm
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS1	0.0000	0.0000	0.0000	0.0000	0.0040	0.0000	0.0070	0.0830	0.2440	0.2470	0.5	0.058	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS1	0.0000	0.0000	0.0000	0.0000	0.0040	0.0010	0.0070	0.0820	0.2460	0.2480	0.5	0.058	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS1	0.0000	0.0000	0.0000	0.0000	0.0020	0.0010	0.0130	0.1020	0.2690	0.2780	0.5	0.066	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS1	0.0000	0.0000	0.0000	0.0010	0.0010	0.0020	0.0170	0.1170	0.2600	0.2320	0.5	0.062	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS1	0.0000	0.0010	0.0010	0.0010	0.0040	0.0110	0.0540	0.2500	0.3200	0.2500	0.5	0.089	0.04	0.05
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS1	0.0010	0.0000	0.0000	0.0030	0.0020	0.0130	0.0710	0.2790	0.3750	0.2780	0.5	0.102	0.05	0.05
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS1	0.0010	0.0010	0.0010	0.0060	0.0060	0.0130	0.0790	0.2440	0.2760	0.2250	0.5	0.086	0.04	0.04
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS1	0.0010	0.0020	0.0020	0.0050	0.0100	0.0320	0.1000	0.1990	0.2000	0.1570	0.5	0.072	0.04	0.04
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS1	0.0030	0.0030	0.0100	0.0080	0.0300	0.0380	0.0480	0.1250	0.0870	0.1010	0.5	0.047	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS1	0.0060	0.0030	0.0040	0.0130	0.0190	0.0390	0.0730	0.1460	0.1080	0.1280	0.5	0.056	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS1	0.0020	0.0020	0.0080	0.0150	0.0300	0.0290	0.0600	0.1390	0.0920	0.1070	0.5	0.050	0.03	0.03

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS2	0.0000	0.0000	0.0000	0.0000	0.0000	0.0020	0.0100	0.0380	0.1130	0.1870	0.5	0.034	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS2	0.0000	0.0000	0.0000	0.0000	0.0000	0.0020	0.0090	0.0370	0.1100	0.1820	0.5	0.034	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS2	0.0000	0.0000	0.0000	0.0010	0.0010	0.0030	0.0130	0.0560	0.1300	0.1620	0.5	0.036	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS2	0.0000	0.0000	0.0000	0.0010	0.0020	0.0030	0.0160	0.0590	0.1400	0.1650	0.5	0.038	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS2	0.0000	0.0010	0.0020	0.0030	0.0090	0.0140	0.0360	0.0730	0.1220	0.1380	0.5	0.040	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS2	0.0000	0.0020	0.0020	0.0050	0.0150	0.0140	0.0330	0.0860	0.1420	0.1200	0.5	0.042	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS2	0.0000	0.0010	0.0020	0.0030	0.0090	0.0160	0.0490	0.0900	0.1260	0.0930	0.5	0.039	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS2	0.0000	0.0030	0.0050	0.0060	0.0100	0.0250	0.0730	0.1430	0.1730	0.1150	0.5	0.056	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS2	0.0010	0.0010	0.0030	0.0100	0.0070	0.0380	0.0910	0.1660	0.1160	0.0820	0.5	0.053	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS2	0.0010	0.0020	0.0030	0.0100	0.0070	0.0330	0.0950	0.1890	0.1280	0.0870	0.5	0.058	0.03	0.03
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS2	0.0000	0.0020	0.0090	0.0040	0.0110	0.0400	0.0760	0.1320	0.0820	0.0500	0.5	0.042	0.02	0.02

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS3	0.0000	0.0000	0.0000	0.0020	0.0010	0.0030	0.0120	0.0230	0.0380	0.0610	0.5	0.014	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS3	0.0000	0.0000	0.0000	0.0020	0.0010	0.0030	0.0120	0.0230	0.0390	0.0590	0.5	0.014	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS3	0.0000	0.0000	0.0000	0.0010	0.0000	0.0030	0.0110	0.0220	0.0420	0.0640	0.5	0.014	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS3	0.0010	0.0010	0.0020	0.0020	0.0030	0.0040	0.0110	0.0190	0.0350	0.0490	0.5	0.013	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS3	0.0010	0.0040	0.0050	0.0060	0.0060	0.0130	0.0460	0.0820	0.1090	0.0790	0.5	0.035	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS3	0.0010	0.0030	0.0050	0.0060	0.0070	0.0180	0.0490	0.0690	0.1080	0.0940	0.5	0.036	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS3	0.0020	0.0040	0.0100	0.0080	0.0180	0.0320	0.0660	0.0990	0.1500	0.1060	0.5	0.050	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS3	0.0030	0.0030	0.0090	0.0120	0.0180	0.0380	0.0910	0.0900	0.1110	0.0630	0.5	0.044	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS3	0.0030	0.0060	0.0140	0.0340	0.0210	0.0260	0.0820	0.0970	0.0950	0.0510	0.5	0.044	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS3	0.0050	0.0040	0.0100	0.0190	0.0310	0.0330	0.0580	0.0580	0.0700	0.0370	0.5	0.034	0.02	0.02
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS3	0.0030	0.0040	0.0110	0.0190	0.0220	0.0370	0.0680	0.0790	0.1140	0.0510	0.5	0.043	0.02	0.02

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS4	0.0010	0.0000	0.0010	0.0000	0.0010	0.0010	0.0050	0.0160	0.0260	0.0360	0.5	0.009	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS4	0.0010	0.0000	0.0000	0.0000	0.0010	0.0010	0.0050	0.0160	0.0270	0.0370	0.5	0.009	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS4	0.0010	0.0010	0.0020	0.0020	0.0010	0.0020	0.0070	0.0150	0.0200	0.0350	0.5	0.009	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS4	0.0010	0.0020	0.0010	0.0050	0.0070	0.0090	0.0130	0.0190	0.0240	0.0390	0.5	0.012	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS4	0.0020	0.0030	0.0030	0.0070	0.0110	0.0130	0.0160	0.0260	0.0280	0.0370	0.5	0.015	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS4	0.0010	0.0040	0.0020	0.0040	0.0100	0.0110	0.0180	0.0250	0.0270	0.0300	0.5	0.013	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS4	0.0030	0.0040	0.0040	0.0050	0.0100	0.0090	0.0150	0.0320	0.0280	0.0330	0.5	0.014	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS4	0.0010	0.0020	0.0040	0.0070	0.0070	0.0060	0.0230	0.0520	0.0400	0.0410	0.5	0.019	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS4	0.0020	0.0060	0.0020	0.0110	0.0180	0.0150	0.0360	0.0690	0.0360	0.0400	0.5	0.024	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS4	0.0010	0.0030	0.0030	0.0090	0.0180	0.0230	0.0430	0.0710	0.0430	0.0480	0.5	0.027	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS4	0.0020	0.0030	0.0020	0.0090	0.0130	0.0150	0.0310	0.0530	0.0340	0.0310	0.5	0.020	0.01	0.01

Notes:

MPE calculations are defined in section 15.0
 Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.			MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)	
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Test Pos.	Bystander (BS) Positions													
											20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm					200 cm
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS5	0.0000	0.0000	0.0010	0.0010	0.0010	0.0010	0.0080	0.0230	0.0250	0.0250	0.5	0.008	0.00	0.00	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35	CW	E	0.99	BS5	0.0000	0.0000	0.0010	0.0010	0.0000	0.0020	0.0080	0.0220	0.0250	0.0250	0.5	0.008	0.00	0.00	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS5	0.0000	0.0000	0.0010	0.0010	0.0020	0.0060	0.0150	0.0300	0.0390	0.0380	0.5	0.013	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS5	0.0000	0.0020	0.0010	0.0020	0.0070	0.0130	0.0170	0.0250	0.0340	0.0330	0.5	0.013	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS5	0.0020	0.0010	0.0000	0.0050	0.0120	0.0160	0.0210	0.0530	0.0430	0.0300	0.5	0.018	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS5	0.0010	0.0000	0.0020	0.0080	0.0150	0.0230	0.0390	0.0760	0.0650	0.0500	0.5	0.028	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS5	0.0000	0.0000	0.0020	0.0090	0.0160	0.0200	0.0270	0.0650	0.0550	0.0430	0.5	0.024	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS5	0.0020	0.0010	0.0050	0.0170	0.0220	0.0220	0.0230	0.0540	0.0460	0.0350	0.5	0.023	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS5	0.0020	0.0020	0.0070	0.0130	0.0110	0.0150	0.0130	0.0360	0.0330	0.0220	0.5	0.016	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS5	0.0020	0.0030	0.0050	0.0080	0.0120	0.0150	0.0160	0.0380	0.0280	0.0200	0.5	0.015	0.01	0.01	
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS5	0.0010	0.0030	0.0040	0.0100	0.0100	0.0140	0.0160	0.0380	0.0260	0.0190	0.5	0.015	0.01	0.01	

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35	CW	E	0.98	BS1	0.0030	0.0130	0.0100	0.0140	0.0220	0.0440	0.0770	0.1980	0.2460	0.2000	0.5	0.081	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36	35.2	CW	E	0.99	BS1	0.0030	0.0130	0.0100	0.0140	0.0220	0.0450	0.0760	0.1960	0.2450	0.1990	0.5	0.081	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35	CW	E	0.99	BS1	0.0030	0.0130	0.0100	0.0140	0.0220	0.0450	0.0760	0.1960	0.2450	0.1990	0.5	0.081	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	35	CW	E	0.99	BS1	0.0020	0.0070	0.0050	0.0170	0.0200	0.0580	0.0860	0.2170	0.2240	0.1760	0.5	0.080	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	35	CW	E	1.00	BS1	0.0060	0.0050	0.0110	0.0130	0.0120	0.0400	0.0810	0.2690	0.3020	0.2020	0.5	0.094	0.05	0.05
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	36	CW	E	1.00	BS1	0.0030	0.0060	0.0090	0.0110	0.0160	0.0560	0.1190	0.2750	0.3200	0.2060	0.5	0.102	0.05	0.05
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42	CW	E	1.01	BS1	0.0020	0.0060	0.0090	0.0130	0.0110	0.0270	0.0910	0.2070	0.2480	0.1760	0.5	0.080	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	41	CW	E	1.01	BS1	0.0020	0.0040	0.0060	0.0090	0.0070	0.0320	0.0800	0.1670	0.2290	0.1770	0.5	0.072	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	42	CW	E	1.03	BS1	0.0010	0.0010	0.0050	0.0110	0.0240	0.0300	0.0270	0.0970	0.1560	0.1510	0.5	0.052	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41	CW	E	1.04	BS1	0.0040	0.0030	0.0040	0.0120	0.0220	0.0410	0.0490	0.1540	0.1940	0.1930	0.5	0.070	0.04	0.04
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41	CW	E	1.04	BS1	0.0030	0.0030	0.0060	0.0130	0.0170	0.0130	0.0410	0.1260	0.1700	0.1420	0.5	0.056	0.03	0.03

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35	CW	E	0.98	BS2	0.0020	0.0010	0.0060	0.0130	0.0250	0.0320	0.0670	0.1050	0.1520	0.1630	0.5	0.056	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36	35.2	CW	E	0.99	BS2	0.0020	0.0010	0.0060	0.0120	0.0260	0.0340	0.0660	0.1070	0.1520	0.1640	0.5	0.056	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35	CW	E	0.99	BS2	0.0010	0.0030	0.0080	0.0180	0.0270	0.0280	0.0600	0.1190	0.1760	0.1280	0.5	0.056	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	35	CW	E	0.99	BS2	0.0000	0.0040	0.0080	0.0120	0.0160	0.0220	0.0490	0.0940	0.1750	0.1300	0.5	0.050	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	35	CW	E	1.00	BS2	0.0000	0.0080	0.0090	0.0170	0.0250	0.0190	0.0420	0.0800	0.1360	0.1750	0.5	0.051	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	36	CW	E	1.00	BS2	0.0010	0.0060	0.0080	0.0150	0.0270	0.0170	0.0460	0.0910	0.1460	0.1420	0.5	0.050	0.02	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42	CW	E	1.01	BS2	0.0010	0.0030	0.0030	0.0090	0.0160	0.0160	0.0410	0.0810	0.1140	0.1400	0.5	0.043	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	41	CW	E	1.01	BS2	0.0010	0.0030	0.0020	0.0070	0.0110	0.0250	0.0630	0.1300	0.1540	0.1310	0.5	0.053	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	42	CW	E	1.03	BS2	0.0010	0.0020	0.0060	0.0070	0.0070	0.0330	0.0550	0.1040	0.1230	0.1150	0.5	0.047	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41	CW	E	1.04	BS2	0.0000	0.0020	0.0040	0.0090	0.0050	0.0250	0.0480	0.1360	0.1700	0.1170	0.5	0.053	0.03	0.03
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41	CW	E	1.04	BS2	0.0000	0.0000	0.0020	0.0030	0.0100	0.0280	0.0480	0.0900	0.1180	0.1020	0.5	0.042	0.02	0.02

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35	CW	E	0.98	BS3	0.0060	0.0100	0.0110	0.0160	0.0110	0.0070	0.0280	0.0440	0.0470	0.0630	0.5	0.024	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36	35.2	CW	E	0.99	BS3	0.0060	0.0100	0.0110	0.0150	0.0110	0.0060	0.0280	0.0440	0.0470	0.0630	0.5	0.024	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35	CW	E	0.99	BS3	0.0080	0.0080	0.0110	0.0120	0.0130	0.0060	0.0230	0.0350	0.0460	0.0790	0.5	0.024	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	35	CW	E	0.99	BS3	0.0040	0.0040	0.0130	0.0130	0.0140	0.0100	0.0310	0.0340	0.0380	0.0560	0.5	0.021	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	35	CW	E	1.00	BS3	0.0030	0.0080	0.0120	0.0100	0.0100	0.0170	0.0360	0.0550	0.0760	0.0720	0.5	0.030	0.01	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	36	CW	E	1.00	BS3	0.0030	0.0040	0.0070	0.0050	0.0080	0.0160	0.0380	0.0460	0.0690	0.0920	0.5	0.029	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42	CW	E	1.01	BS3	0.0040	0.0050	0.0070	0.0060	0.0060	0.0120	0.0360	0.0510	0.0650	0.0750	0.5	0.027	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	41	CW	E	1.01	BS3	0.0030	0.0070	0.0090	0.0100	0.0130	0.0180	0.0410	0.0590	0.0740	0.0770	0.5	0.032	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	42	CW	E	1.03	BS3	0.0030	0.0040	0.0080	0.0130	0.0100	0.0110	0.0280	0.0360	0.0620	0.0590	0.5	0.024	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41	CW	E	1.04	BS3	0.0030	0.0060	0.0080	0.0170	0.0160	0.0150	0.0300	0.0350	0.0600	0.0660	0.5	0.027	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41	CW	E	1.04	BS3	0.0020	0.0040	0.0070	0.0130	0.0100	0.0120	0.0290	0.0330	0.0640	0.0940	0.5	0.028	0.01	0.01

Notes:

MPE calculations are defined in section 15.0
 Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35	CW	E	0.98	BS4	0.0030	0.0070	0.0050	0.0110	0.0130	0.0090	0.0090	0.0250	0.0330	0.0330	0.5	0.015	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36	35.2	CW	E	0.99	BS4	0.0030	0.0070	0.0050	0.0110	0.0120	0.0100	0.0080	0.0250	0.0330	0.0340	0.5	0.015	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35	CW	E	0.99	BS4	0.0020	0.0050	0.0070	0.0100	0.0120	0.0110	0.0120	0.0230	0.0250	0.0280	0.5	0.013	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	35	CW	E	0.99	BS4	0.0030	0.0040	0.0040	0.0100	0.0110	0.0110	0.0120	0.0260	0.0330	0.0330	0.5	0.015	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	35	CW	E	1.00	BS4	0.0020	0.0040	0.0040	0.0070	0.0120	0.0120	0.0100	0.0190	0.0210	0.0320	0.5	0.012	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	36	CW	E	1.00	BS4	0.0020	0.0070	0.0030	0.0100	0.0110	0.0090	0.0100	0.0270	0.0250	0.0250	0.5	0.013	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42	CW	E	1.01	BS4	0.0010	0.0020	0.0020	0.0040	0.0080	0.0050	0.0100	0.0240	0.0180	0.0250	0.5	0.010	0.00	0.00
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	41	CW	E	1.01	BS4	0.0020	0.0040	0.0040	0.0060	0.0070	0.0050	0.0120	0.0280	0.0240	0.0240	0.5	0.012	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	42	CW	E	1.03	BS4	0.0010	0.0030	0.0010	0.0050	0.0110	0.0090	0.0110	0.0290	0.0240	0.0240	0.5	0.012	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41	CW	E	1.04	BS4	0.0010	0.0020	0.0000	0.0030	0.0090	0.0120	0.0110	0.0310	0.0370	0.0390	0.5	0.015	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41	CW	E	1.04	BS4	0.0010	0.0020	0.0040	0.0070	0.0090	0.0070	0.0140	0.0290	0.0230	0.0220	0.5	0.012	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.			MPE Measurements									DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)	
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Test Pos.	Bystander (BS) Positions												
											20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm					180 cm
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35	CW	E	0.98	BS5	0.0010	0.0040	0.0050	0.0030	0.0070	0.0100	0.0130	0.0320	0.0440	0.0250	0.5	0.014	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36	35.2	CW	E	0.99	BS5	0.0010	0.0040	0.0040	0.0030	0.0070	0.0100	0.0130	0.0320	0.0420	0.0240	0.5	0.014	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35	CW	E	0.99	BS5	0.0010	0.0040	0.0020	0.0040	0.0120	0.0160	0.0170	0.0310	0.0570	0.0450	0.5	0.019	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	35	CW	E	0.99	BS5	0.0030	0.0030	0.0030	0.0100	0.0150	0.0180	0.0160	0.0230	0.0490	0.0490	0.5	0.019	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	35	CW	E	1.00	BS5	0.0020	0.0010	0.0010	0.0070	0.0130	0.0180	0.0150	0.0360	0.0470	0.0300	0.5	0.017	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	36	CW	E	1.00	BS5	0.0000	0.0010	0.0020	0.0070	0.0150	0.0200	0.0230	0.0540	0.0620	0.0400	0.5	0.022	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42	CW	E	1.01	BS5	0.0010	0.0000	0.0030	0.0100	0.0150	0.0150	0.0140	0.0370	0.0400	0.0200	0.5	0.016	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	41	CW	E	1.01	BS5	0.0010	0.0020	0.0030	0.0110	0.0140	0.0140	0.0110	0.0250	0.0320	0.0240	0.5	0.014	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	42	CW	E	1.03	BS5	0.0020	0.0010	0.0020	0.0060	0.0090	0.0110	0.0060	0.0140	0.0180	0.0140	0.5	0.009	0.00	0.00
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41	CW	E	1.04	BS5	0.0000	0.0010	0.0000	0.0040	0.0060	0.0120	0.0060	0.0170	0.0350	0.0190	0.5	0.010	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41	CW	E	1.04	BS5	0.0010	0.0000	0.0010	0.0030	0.0050	0.0070	0.0060	0.0180	0.0220	0.0170	0.5	0.008	0.00	0.00

Notes:

MPE calculations are defined in section 15.0
 Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS1	0.0040	0.0160	0.0150	0.0270	0.0390	0.0920	0.1520	0.2960	0.2290	0.0590	0.5	0.091	0.05	0.05
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36	35.2	CW	E	0.99	BS1	0.0040	0.0160	0.0150	0.0270	0.0400	0.0920	0.1530	0.2930	0.2290	0.0600	0.5	0.092	0.05	0.05
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS1	0.0040	0.0180	0.0120	0.0210	0.0340	0.1170	0.1850	0.3320	0.2420	0.0700	0.5	0.102	0.05	0.05
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS1	0.0050	0.0150	0.0100	0.0230	0.0340	0.1070	0.1600	0.3280	0.2010	0.0470	0.5	0.092	0.05	0.05
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS1	0.0100	0.0110	0.0180	0.0250	0.0250	0.0740	0.1720	0.4320	0.3160	0.0830	0.5	0.116	0.06	0.06
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS1	0.0070	0.0100	0.0130	0.0190	0.0230	0.0870	0.2260	0.4670	0.3340	0.0970	0.5	0.128	0.06	0.07
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS1	0.0030	0.0090	0.0130	0.0190	0.0180	0.0420	0.1570	0.3250	0.2410	0.0760	0.5	0.091	0.05	0.05
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS1	0.0040	0.0060	0.0090	0.0130	0.0140	0.0620	0.1560	0.2680	0.2240	0.0850	0.5	0.085	0.04	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS1	0.0020	0.0020	0.0070	0.0110	0.0350	0.0470	0.0480	0.1320	0.1320	0.0550	0.5	0.049	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS1	0.0060	0.0030	0.0050	0.0150	0.0310	0.0620	0.0830	0.2020	0.1860	0.0780	0.5	0.070	0.03	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS1	0.0030	0.0030	0.0070	0.0160	0.0230	0.0220	0.0600	0.1620	0.1330	0.0520	0.5	0.050	0.03	0.03

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS2	0.0010	0.0030	0.0140	0.0200	0.0490	0.0640	0.1250	0.1990	0.1880	0.0930	0.5	0.074	0.04	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36	35.2	CW	E	0.99	BS2	0.0010	0.0030	0.0140	0.0200	0.0480	0.0640	0.1250	0.1980	0.1860	0.0900	0.5	0.074	0.04	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS2	0.0020	0.0050	0.0130	0.0300	0.0490	0.0600	0.1190	0.1990	0.2050	0.0690	0.5	0.074	0.04	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS2	0.0000	0.0040	0.0140	0.0220	0.0330	0.0490	0.1040	0.1850	0.2040	0.0790	0.5	0.069	0.03	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS2	0.0000	0.0110	0.0150	0.0260	0.0480	0.0410	0.0830	0.1390	0.1630	0.1150	0.5	0.064	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS2	0.0010	0.0100	0.0140	0.0250	0.0480	0.0330	0.0910	0.1690	0.1680	0.0910	0.5	0.065	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS2	0.0010	0.0040	0.0060	0.0120	0.0240	0.0320	0.0760	0.1350	0.1400	0.0860	0.5	0.052	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS2	0.0010	0.0050	0.0070	0.0130	0.0180	0.0460	0.1160	0.2080	0.1940	0.0810	0.5	0.070	0.03	0.04
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS2	0.0010	0.0030	0.0080	0.0110	0.0090	0.0470	0.0880	0.1530	0.1320	0.0570	0.5	0.052	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS2	0.0010	0.0020	0.0050	0.0150	0.0080	0.0390	0.0900	0.2170	0.1870	0.0700	0.5	0.066	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS2	0.0000	0.0010	0.0050	0.0040	0.0140	0.0420	0.0760	0.1370	0.1180	0.0530	0.5	0.047	0.02	0.02

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS3	0.0130	0.0200	0.0250	0.0320	0.0220	0.0170	0.0590	0.0800	0.0830	0.0730	0.5	0.042	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36	35.2	CW	E	0.99	BS3	0.0130	0.0200	0.0240	0.0310	0.0230	0.0170	0.0600	0.0830	0.0860	0.0740	0.5	0.043	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS3	0.0130	0.0160	0.0240	0.0260	0.0250	0.0170	0.0520	0.0630	0.0730	0.0920	0.5	0.040	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS3	0.0080	0.0090	0.0250	0.0250	0.0230	0.0220	0.0680	0.0670	0.0560	0.0660	0.5	0.037	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS3	0.0060	0.0120	0.0220	0.0160	0.0160	0.0350	0.0830	0.1110	0.1310	0.0900	0.5	0.052	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS3	0.0060	0.0100	0.0150	0.0110	0.0180	0.0350	0.0800	0.0910	0.1120	0.1130	0.5	0.049	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS3	0.0060	0.0080	0.0120	0.0120	0.0130	0.0280	0.0740	0.0890	0.1090	0.0850	0.5	0.044	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS3	0.0050	0.0100	0.0160	0.0200	0.0270	0.0400	0.0800	0.1020	0.1220	0.0900	0.5	0.052	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS3	0.0040	0.0060	0.0140	0.0220	0.0210	0.0210	0.0500	0.0580	0.0840	0.0590	0.5	0.035	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS3	0.0040	0.0080	0.0140	0.0240	0.0250	0.0270	0.0580	0.0610	0.0900	0.0760	0.5	0.040	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS3	0.0030	0.0050	0.0110	0.0170	0.0160	0.0240	0.0480	0.0540	0.0910	0.0840	0.5	0.037	0.02	0.02

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)

APX6500 7/800MHz - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS4	0.0090	0.0110	0.0130	0.0220	0.0310	0.0250	0.0250	0.0550	0.0570	0.0470	0.5	0.029	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36	35.2	CW	E	0.99	BS4	0.0090	0.0110	0.0110	0.0220	0.0310	0.0240	0.0250	0.0530	0.0570	0.0470	0.5	0.029	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS4	0.0070	0.0110	0.0130	0.0160	0.0260	0.0270	0.0300	0.0480	0.0450	0.0390	0.5	0.026	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS4	0.0070	0.0140	0.0120	0.0170	0.0260	0.0270	0.0320	0.0610	0.0530	0.0450	0.5	0.029	0.01	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS4	0.0060	0.0110	0.0100	0.0230	0.0270	0.0200	0.0270	0.0540	0.0530	0.0470	0.5	0.028	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS4	0.0060	0.0130	0.0120	0.0220	0.0250	0.0230	0.0270	0.0540	0.0540	0.0510	0.5	0.029	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS4	0.0030	0.0070	0.0040	0.0110	0.0180	0.0130	0.0230	0.0400	0.0260	0.0260	0.5	0.017	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS4	0.0050	0.0070	0.0040	0.0100	0.0170	0.0100	0.0250	0.0470	0.0400	0.0450	0.5	0.021	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS4	0.0020	0.0060	0.0020	0.0070	0.0170	0.0110	0.0220	0.0480	0.0330	0.0340	0.5	0.019	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS4	0.0020	0.0040	0.0030	0.0050	0.0100	0.0160	0.0340	0.0650	0.0500	0.0480	0.5	0.025	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS4	0.0020	0.0050	0.0030	0.0080	0.0160	0.0140	0.0240	0.0440	0.0330	0.0340	0.5	0.019	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.1 (Continued)**APX6500 7/800MHz - MPE measurement data for Bystander**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35	CW	E	0.98	BS5	0.0030	0.0080	0.0090	0.0100	0.0150	0.0180	0.0230	0.0620	0.0760	0.0340	0.5	0.025	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36	35.2	CW	E	0.99	BS5	0.0030	0.0090	0.0090	0.0090	0.0140	0.0190	0.0240	0.0650	0.0770	0.0340	0.5	0.026	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35	CW	E	0.99	BS5	0.0030	0.0090	0.0060	0.0120	0.0220	0.0310	0.0330	0.0720	0.1120	0.0630	0.5	0.036	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	35	CW	E	0.99	BS5	0.0060	0.0100	0.0070	0.0200	0.0310	0.0350	0.0260	0.0550	0.0940	0.0630	0.5	0.034	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	35	CW	E	1.00	BS5	0.0040	0.0030	0.0040	0.0180	0.0280	0.0330	0.0310	0.0770	0.0770	0.0340	0.5	0.031	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	36	CW	E	1.00	BS5	0.0010	0.0020	0.0050	0.0170	0.0300	0.0410	0.0440	0.1070	0.1050	0.0460	0.5	0.040	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42	CW	E	1.01	BS5	0.0020	0.0010	0.0050	0.0170	0.0240	0.0270	0.0270	0.0700	0.0650	0.0280	0.5	0.027	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	41	CW	E	1.01	BS5	0.0020	0.0030	0.0070	0.0190	0.0280	0.0300	0.0220	0.0500	0.0620	0.0360	0.5	0.026	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	42	CW	E	1.03	BS5	0.0050	0.0020	0.0050	0.0150	0.0130	0.0140	0.0090	0.0250	0.0300	0.0150	0.5	0.014	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41	CW	E	1.04	BS5	0.0030	0.0010	0.0030	0.0080	0.0110	0.0180	0.0130	0.0340	0.0460	0.0220	0.5	0.016	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41	CW	E	1.04	BS5	0.0020	0.0010	0.0030	0.0060	0.0090	0.0130	0.0140	0.0330	0.0340	0.0210	0.5	0.014	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC)						
										Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35.2	CW	E	0.98	PB	0.036	0.024	0.038	0.5	0.032	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35.2	CW	E	0.99	PB	0.033	0.026	0.038	0.5	0.032	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35.0	CW	E	0.99	PB	0.035	0.031	0.041	0.5	0.035	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	34.9	CW	E	0.99	PB	0.036	0.035	0.037	0.5	0.036	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	34.6	CW	E	1.00	PB	0.042	0.036	0.024	0.5	0.034	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	35.5	CW	E	1.00	PB	0.034	0.033	0.025	0.5	0.031	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42.0	CW	E	1.01	PB	0.024	0.031	0.024	0.5	0.027	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	40.8	CW	E	1.01	PB	0.024	0.015	0.052	0.5	0.031	0.02	0.02
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	41.8	CW	E	1.03	PB	0.016	0.012	0.013	0.5	0.014	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41.1	CW	E	1.04	PB	0.021	0.022	0.016	0.5	0.020	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41.1	CW	E	1.04	PB	0.016	0.018	0.013	0.5	0.016	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35.2	CW	E	0.98	PB	0.002	0.004	0.002	0.5	0.003	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35.2	CW	E	0.99	PB	0.002	0.004	0.003	0.5	0.003	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35.0	CW	E	0.99	PB	0.002	0.003	0.003	0.5	0.003	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	34.9	CW	E	0.99	PB	0.002	0.003	0.002	0.5	0.002	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	34.6	CW	E	1.00	PB	0.013	0.005	0.005	0.5	0.008	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	35.5	CW	E	1.00	PB	0.01	0.013	0.01	0.5	0.011	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42.0	CW	E	1.01	PB	0.018	0.027	0.017	0.5	0.021	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	40.8	CW	E	1.01	PB	0.018	0.013	0.043	0.5	0.025	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	41.8	CW	E	1.03	PB	0.024	0.015	0.022	0.5	0.021	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41.1	CW	E	1.04	PB	0.012	0.016	0.014	0.5	0.015	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41.1	CW	E	1.04	PB	0.028	0.017	0.015	0.5	0.021	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35.2	CW	E	0.98	PB	0.037	0.031	0.027	0.5	0.031	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36.0	35.2	CW	E	0.99	PB	0.04	0.027	0.04	0.5	0.035	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35.0	CW	E	0.99	PB	0.033	0.027	0.039	0.5	0.033	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	34.9	CW	E	0.99	PB	0.035	0.022	0.042	0.5	0.033	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	34.6	CW	E	1.00	PB	0.046	0.034	0.031	0.5	0.037	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	35.5	CW	E	1.00	PB	0.035	0.03	0.028	0.5	0.031	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42.0	CW	E	1.01	PB	0.02	0.026	0.024	0.5	0.023	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	40.8	CW	E	1.01	PB	0.022	0.017	0.067	0.5	0.036	0.02	0.02
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	41.8	CW	E	1.03	PB	0.022	0.015	0.016	0.5	0.018	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41.1	CW	E	1.04	PB	0.02	0.019	0.01	0.5	0.017	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41.1	CW	E	1.04	PB	0.025	0.014	0.012	0.5	0.018	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC)						
										Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35.2	CW	E	0.98	PB	0.066	0.04	0.07	0.5	0.058	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35.2	CW	E	0.99	PB	0.066	0.041	0.052	0.5	0.052	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35.0	CW	E	0.99	PB	0.054	0.04	0.073	0.5	0.055	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	34.9	CW	E	0.99	PB	0.055	0.041	0.072	0.5	0.055	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	34.6	CW	E	1.00	PB	0.053	0.058	0.053	0.5	0.055	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	35.5	CW	E	1.00	PB	0.06	0.053	0.045	0.5	0.053	0.03	0.03
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42.0	CW	E	1.01	PB	0.039	0.043	0.041	0.5	0.041	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	40.8	CW	E	1.01	PB	0.055	0.029	0.040	0.5	0.042	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	41.8	CW	E	1.03	PB	0.035	0.019	0.016	0.5	0.024	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41.1	CW	E	1.04	PB	0.040	0.043	0.025	0.5	0.037	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41.1	CW	E	1.04	PB	0.03	0.018	0.018	0.5	0.023	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35.2	CW	E	0.98	PF	0.014	0.019	0.017	0.5	0.016	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35.2	CW	E	0.99	PF	0.016	0.025	0.019	0.5	0.020	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35.0	CW	E	0.99	PF	0.011	0.028	0.017	0.5	0.018	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	34.9	CW	E	0.99	PF	0.018	0.029	0.012	0.5	0.019	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	34.6	CW	E	1.00	PF	0.011	0.025	0.008	0.5	0.015	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	35.5	CW	E	1.00	PF	0.018	0.012	0.01	0.5	0.013	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42.0	CW	E	1.01	PF	0.013	0.018	0.015	0.5	0.015	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	40.8	CW	E	1.01	PF	0.024	0.017	0.017	0.5	0.020	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	41.8	CW	E	1.03	PF	0.02	0.016	0.013	0.5	0.017	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41.1	CW	E	1.04	PF	0.014	0.018	0.019	0.5	0.018	0.01	0.01
Roof	HAF4013A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41.1	CW	E	1.04	PF	0.018	0.014	0.01	0.5	0.015	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35.2	CW	E	0.98	PF	0.002	0.004	0.003	0.5	0.003	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35.2	CW	E	0.99	PF	0.003	0.004	0.003	0.5	0.003	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35.0	CW	E	0.99	PF	0.004	0.004	0.003	0.5	0.004	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	34.9	CW	E	0.99	PF	0.004	0.003	0.002	0.5	0.003	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	34.6	CW	E	1.00	PF	0.006	0.008	0.004	0.5	0.006	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	35.5	CW	E	1.00	PF	0.004	0.010	0.007	0.5	0.007	0.00	0.00
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42.0	CW	E	1.01	PF	0.009	0.019	0.009	0.5	0.012	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	40.8	CW	E	1.01	PF	0.023	0.010	0.014	0.5	0.016	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	41.8	CW	E	1.03	PF	0.029	0.030	0.008	0.5	0.023	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41.1	CW	E	1.04	PF	0.020	0.025	0.015	0.5	0.021	0.01	0.01
Roof	HAF4014A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41.1	CW	E	1.04	PF	0.021	0.014	0.011	0.5	0.016	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	762.0125	36.0	35.2	CW	E	0.98	PF	0.015	0.022	0.017	0.5	0.018	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	769.0125	36.0	35.2	CW	E	0.99	PF	0.017	0.024	0.018	0.5	0.019	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	772.0000	36.0	35.0	CW	E	0.99	PF	0.013	0.016	0.014	0.5	0.014	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	774.9875	36.0	34.9	CW	E	0.99	PF	0.01	0.026	0.013	0.5	0.016	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	794.0125	36.0	34.6	CW	E	1.00	PF	0.013	0.021	0.007	0.5	0.014	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	799.0125	36.0	35.5	CW	E	1.00	PF	0.016	0.016	0.01	0.5	0.014	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	811.5000	42.0	42.0	CW	E	1.01	PF	0.01	0.025	0.011	0.5	0.015	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	823.9875	42.0	40.8	CW	E	1.01	PF	0.023	0.018	0.019	0.5	0.020	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	851.0125	42.0	41.8	CW	E	1.03	PF	0.021	0.016	0.01	0.5	0.016	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	860.5000	42.0	41.1	CW	E	1.04	PF	0.017	0.016	0.014	0.5	0.016	0.01	0.01
Roof	HAF4016A, 1/4 Wave, (762-870MHz)	2.15	868.9875	42.0	41.1	CW	E	1.04	PF	0.016	0.014	0.008	0.5	0.013	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Table F.2 (Continued)**APX6500 7/800MHz - MPE measurement data for Passenger**

D.U.T. Info.							Probe Info.		Test Pos.	MPE Measurements			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	762.0125	36.0	35.2	CW	E	0.98	PF	0.032	0.042	0.033	0.5	0.035	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	769.0125	36.0	35.2	CW	E	0.99	PF	0.033	0.038	0.034	0.5	0.035	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	772.0000	36.0	35.0	CW	E	0.99	PF	0.029	0.038	0.033	0.5	0.033	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	774.9875	36.0	34.9	CW	E	0.99	PF	0.016	0.049	0.021	0.5	0.028	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	794.0125	36.0	34.6	CW	E	1.00	PF	0.026	0.044	0.015	0.5	0.028	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	799.0125	36.0	35.5	CW	E	1.00	PF	0.026	0.027	0.019	0.5	0.024	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	811.5000	42.0	42.0	CW	E	1.01	PF	0.014	0.035	0.018	0.5	0.022	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	823.9875	42.0	40.8	CW	E	1.01	PF	0.046	0.028	0.021	0.5	0.032	0.02	0.02
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	851.0125	42.0	41.8	CW	E	1.03	PF	0.034	0.024	0.011	0.5	0.024	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	860.5000	42.0	41.1	CW	E	1.04	PF	0.022	0.026	0.016	0.5	0.022	0.01	0.01
Roof	HAF4017A, 1/4 Wave, (762-870MHz)	5.15	868.9875	42.0	41.1	CW	E	1.04	PF	0.021	0.017	0.011	0.5	0.017	0.01	0.01

Notes:

MPE calculations are defined in section 15.0

Blue fonts: Frequencies not regulated by FCC.

Appendix G – MPE Test Results Summary for Companion Device (DVR 800)

Table G.1

DVR 800 - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		(5) Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/ cm2)	Calc. P.D. (mW/ cm2)	Max Calc. P.D. (mW/ cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	BS1	0.001	0.001	0.001	0.002	0.002	0.002	0.004	0.008	0.010	0.012	1.0	0.004	0.005	0.005
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	BS1	0.001	0.002	0.002	0.001	0.002	0.003	0.006	0.006	0.012	0.013	1.0	0.005	0.006	0.006
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	BS1	0.001	0.001	0.001	0.001	0.002	0.003	0.007	0.007	0.008	0.009	1.0	0.004	0.005	0.005
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	BS1	0.001	0.002	0.001	0.002	0.002	0.002	0.004	0.007	0.007	0.009	1.0	0.004	0.004	0.004
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	BS1	0.001	0.001	0.001	0.001	0.001	0.002	0.003	0.003	0.008	0.006	1.0	0.003	0.003	0.003
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	BS1	0.001	0.001	0.001	0.002	0.003	0.004	0.004	0.004	0.007	0.006	1.0	0.003	0.004	0.004
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	BS2	0.002	0.002	0.003	0.006	0.009	0.012	0.023	0.025	0.028	0.018	1.0	0.013	0.015	0.015
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	BS2	0.002	0.002	0.003	0.003	0.007	0.012	0.025	0.026	0.027	0.029	1.0	0.014	0.016	0.016
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	BS2	0.002	0.002	0.002	0.003	0.005	0.007	0.020	0.022	0.022	0.018	1.0	0.010	0.012	0.012
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	BS2	0.003	0.004	0.004	0.008	0.009	0.013	0.020	0.027	0.029	0.018	1.0	0.014	0.015	0.015
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	BS2	0.002	0.003	0.003	0.006	0.007	0.010	0.015	0.020	0.022	0.024	1.0	0.011	0.012	0.012
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	BS2	0.002	0.002	0.002	0.005	0.005	0.008	0.013	0.018	0.020	0.023	1.0	0.010	0.011	0.011

MPE calculations are defined in section 15.0.

Table G.1 (Continued)
DVR 800 - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		(5) Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions													
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm				
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	BS3	0.001	0.001	0.002	0.004	0.008	0.011	0.022	0.025	0.025	0.022	1.0	0.012	0.014	0.014
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	BS3	0.001	0.003	0.005	0.005	0.009	0.012	0.026	0.027	0.031	0.023	1.0	0.014	0.016	0.016
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	BS3	0.001	0.002	0.004	0.006	0.011	0.020	0.020	0.027	0.027	0.018	1.0	0.014	0.016	0.016
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	BS3	0.002	0.003	0.006	0.008	0.016	0.018	0.020	0.030	0.021	0.019	1.0	0.014	0.016	0.016
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	BS3	0.002	0.003	0.006	0.005	0.008	0.011	0.018	0.027	0.020	0.013	1.0	0.011	0.012	0.012
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	BS3	0.001	0.003	0.004	0.006	0.008	0.012	0.016	0.024	0.022	0.010	1.0	0.011	0.012	0.012
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	BS4	0.003	0.005	0.008	0.012	0.017	0.020	0.022	0.026	0.025	0.022	1.0	0.016	0.019	0.019
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	BS4	0.003	0.006	0.010	0.016	0.027	0.033	0.023	0.038	0.026	0.023	1.0	0.021	0.024	0.024
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	BS4	0.003	0.006	0.008	0.016	0.024	0.030	0.022	0.032	0.030	0.021	1.0	0.019	0.022	0.022
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	BS4	0.004	0.009	0.012	0.022	0.032	0.033	0.030	0.039	0.041	0.026	1.0	0.025	0.028	0.028
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	BS4	0.004	0.007	0.010	0.009	0.011	0.014	0.019	0.032	0.027	0.028	1.0	0.016	0.018	0.018
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	BS4	0.005	0.007	0.007	0.008	0.014	0.022	0.026	0.033	0.030	0.024	1.0	0.018	0.019	0.019

MPE calculations are defined in section 15.0.

Table G.1 (Continued)
DVR 800 - MPE measurement data for Bystander

D.U.T. Info.							Probe Info.		⁽⁵⁾ Test Pos.	MPE Measurements										DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)	
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Bystander (BS) Positions														
										20 cm	40 cm	60 cm	80 cm	100 cm	120 cm	140 cm	160 cm	180 cm	200 cm					
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	BS5	0.003	0.003	0.007	0.012	0.014	0.015	0.016	0.023	0.022	0.026	1.0	0.014	0.016	0.016	
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	BS5	0.004	0.004	0.010	0.012	0.013	0.015	0.020	0.018	0.022	0.022	1.0	0.014	0.016	0.016	
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	BS5	0.003	0.004	0.006	0.007	0.007	0.013	0.011	0.019	0.018	0.015	1.0	0.010	0.012	0.012	
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	BS5	0.003	0.004	0.008	0.012	0.012	0.015	0.011	0.018	0.019	0.014	1.0	0.012	0.013	0.013	
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	BS5	0.002	0.003	0.003	0.007	0.010	0.011	0.008	0.014	0.015	0.011	1.0	0.008	0.009	0.009	
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	BS5	0.001	0.003	0.006	0.008	0.012	0.011	0.010	0.017	0.012	0.010	1.0	0.009	0.010	0.010	

MPE calculations are defined in section 15.0.

Table G.2
DVR 800 - MPE measurement data for Passenger

D.U.T. Info.							Probe Info.		(5) Test Pos.	MPE Measurement			DUT Max. TX Factor	Avg. over Body (mW/cm2)	Calc. P.D. (mW/cm2)	Max Calc. P.D. (mW/cm2)
Ant Loc.	Ant. Model/ Desc.	Ant. Gain (dBi)	Tx Freq (MHz)	Max Pwr (W)	Initial Pwr (W)	Test Mode	E/H Field	Probe Cal. Factor		Passenger/Operator (MC) Positions						
										Head/ Top 1/3	Chest/ Middle 1/3	Lower Trunk/ Bottom 1/3				
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	PB	0.064	0.053	0.027	1.0	0.048	0.056	0.056
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	PB	0.069	0.049	0.038	1.0	0.052	0.060	0.060
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	PB	0.048	0.042	0.034	1.0	0.041	0.047	0.048
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	PB	0.058	0.032	0.03	1.0	0.040	0.044	0.045
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	PB	0.044	0.03	0.032	1.0	0.035	0.039	0.039
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	PB	0.028	0.021	0.015	1.0	0.021	0.023	0.023
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	806.0000	10.00	10.00	CW	E	1.16	PF	0.022	0.026	0.018	1.0	0.022	0.026	0.026
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	815.0000	10.00	9.95	CW	E	1.15	PF	0.025	0.027	0.016	1.0	0.023	0.026	0.026
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	824.0000	10.00	9.85	CW	E	1.14	PF	0.020	0.027	0.015	1.0	0.021	0.024	0.024
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	851.0000	10.00	9.91	CW	E	1.11	PF	0.046	0.021	0.017	1.0	0.028	0.031	0.031
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	860.0000	10.00	10.00	CW	E	1.10	PF	0.049	0.019	0.009	1.0	0.026	0.028	0.028
Trunk	HAF4016A, 1/4 Wave (764-870MHz)	2.15	869.0000	10.00	10.00	CW	E	1.09	PF	0.048	0.035	0.010	1.0	0.031	0.034	0.034

MPE calculations are defined in section 15.0.