

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A) Limits for Occupational/Controlled Exposure				
0.3-3.0	614	1.63	*100	6
3.0-30	1842/f	4.89/f	*900/f ²	6
30-300	61.4	0.163	1.0	6
300-1,500			f/300	6
1,500-100,000			5	6
(B) Limits for General Population/Uncontrolled Exposure				
0.3-1.34	614	1.63	*100	30
1.34-30	824/f	2.19/f	*180/f ²	30
30-300	27.5	0.073	0.2	30
300-1,500			f/1500	30
1,500-100,000			1.0	30

f = frequency in MHz * = Plane-wave equivalent power density

MPE Calculation Method

$$E \text{ (V/m)} = \frac{\sqrt{30 * P * G}}{d}$$

$$\text{Power Density: } Pd \text{ (W/m}^2\text{)} = \frac{E^2}{377}$$

E = Electric field (V/m)

P = Average RF output power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

The formula can be changed to

$$Pd = \frac{30 * P * G}{377 * D^2}$$

From the EUT RF output power, the minimum mobile separation distance, d=0.2m, as well as the gain of the used antenna, the RF power density can be obtained.

Measurement Result

Jeweller :

Operation Frequency: GFSK: 905 MHz~926.5MHz

Antenna Type: L-inverted antenna

Antenna gain: Antenna: -1 dBi

R=20cm

Channel Freq. (MHz)	modulation	conducted power	Tune-up power (dBm)	Max		Antenna		Evaluation result	Power density Limits
		(dBm)		tune-up power		Gain		(mW/cm2)	(mW/cm2)
				(dBm)	(mW)	(dBi)	Numeric		
905.00	GFSK	9.681	9.5±1	10.5	11.220	-1.00	0.79	0.0018	0.60
915.85	GFSK	9.21	9.5±1	10.5	11.220	-1.00	0.79	0.0018	0.61
926.5	GFSK	8.844	9.5±1	10.5	11.220	-1.00	0.79	0.0018	0.62

interconnect:

Operation Frequency: GFSK: 926MHz

Antenna Type: L-inverted antenna

Antenna gain: Antenna: -1 dBi

R=20cm

Transmit power:

Frequency (MHz)	EIRP power (dBuV/m)	EIRP power (dBm)
926	91.05	-4.21

$$\text{EIRP} = E - 104.8 + 20 \log(D)$$

$$\text{EIRP} = \text{conducted power} + \text{antenna gain}$$

Channel Freq. (MHz)	modulation	conducted power	Tune-up power (dBm)	Max		Antenna		Evaluation result	Power density Limits
		tune-up power		Gain					
		(dBm)		(dBm)	(mW)	(dBi)	Numeric		
926	GFSK	-3.21	-3±1	-2	0.631	-1	0.79	0.0001	0.617333333

Conclusion:

For the max result : $0.0018 \leq 0.60 \text{mW/ cm}^2$ for Max Power density, compliance with RF exposure.



Signature:

Date: 11/18/2024

NAME AND TITLE (Please print or type): Alex Li/Manager

COMPANY (Please print or type): Shenzhen NTEK Testing Technology Co., Ltd./ 1/F, Building E, Fenda Science Park, Sanwei Community, Xixiang Street Bao'an District, Shenzhen P.R. China.