

FCC ID : H38UT-86P

Measurement Result:

(Test Frequency: 794.900MHz , Horizontal , 30 MHz ~ 1 GHz)

Test Conditions:

Testing room : Temperature : 26 °C Humidity : 73 % RH

Testing site : Temperature : 31 °C Humidity : 75 % RH

<i>Frequency</i>	<i>Reading Amplitude</i>	<i>Ant. Height</i>	<i>Table</i>	<i>Correction Factors</i>	<i>Corrected Power</i>	<i>Attenuated below the mean power</i>	<i>minimum Attenuation limit</i>
MHz	dBμV	m	degree	dB/m	dBm	dB	dB

198.727	33.57	1.00	150	-13.32	-50.49	44.80	9.77
397.452	27.91	1.00	27	-19.59	-49.88	44.19	9.77

Note:

1. Margin = Amplitude - limit, *if margin is minus means under limit.*
2. Corrected Amplitude = Reading Amplitude – Correction Factors
3. Correction factor = Antenna factor + (Cable Loss – Amplitude Gain)
(For example :794.900MHz correction Amplitude= 66.59 – (–26.25) = 92.84dBμV/m)
4. FI(Volt) = $10^{FI (dB\mu V/m) / 20} \times 10^{-6}$
FI (Volt) = $10^{92.84/20} \times 10^{-6} = 0. 04385 \text{ V}$
5. P (watt) = $FI^2 (Volt) \times d^2 (meter) / 49.2$
FI (mW) = $(0.04385 \times 3)^2 / 49.2 = 0.351785 \text{ mW}$
FI (dBm) = $10 \log 0.351785 (mW) / 1(mW) = -4.537 (dBm)$
6. Mean Power = $10 \log (p) (dB) = 10 \log (0.27008) = -5.685$
Attenuated below the mean power = P – Corrected Power
(For example : -5.685 – (- 50.49)) = 44.80 (dB)

7. Attenuation required = $43 + 10 \log (0.47564 \text{ mW}) = 9.77$

Measurement Result:

(Test Frequency: 794.900MHz , Horizontal , 1GHz ~ 18GHz)

Radiated Emission				Correction Factors	Corrected Amplitude dBm	Attenuated below the mean power (dB)	minimum Attenuation Limit (dB)
Frequency (GHz)	Amplitude (dBμV/m)	Ant. H. (cm)	Table (°)	(dB)			

1.589	68.03	1.00	64	-8.67	-38.02	32.33	9.77
2.380	64.14	1.00	198	-8.67	-41.91	36.22	9.77
2.770	51.97	1.00	44	-6.84	-52.25	46.56	9.77
2.980	62.81	1.00	10	-6.84	-41.41	35.72	9.77

Radiated Emission Test Result:

(Test Frequency: 794.900MHz , Vertical , 30MHz ~ 1GHz)

<i>Frequency</i>	<i>Reading Amplitude</i>	<i>Ant. Height</i>	<i>Table</i>	<i>Correction Factors</i>	<i>Corrected Power</i>	<i>Attenuated below the mean power</i>	<i>minimum Attenuation limit</i>
MHz	dBμV	m	degree	dB/m	dBm	dB	dB

198.727	30.86	3.96	11	-13.54	44.40	-52.98	9.77
397.451	25.16	1.00	6	-19.14	44.30	-53.08	9.77

Radiated Emission Test Result:

(Test Frequency: 794.900MHz , Vertical , 1GHz ~ 18GHz)

Radiated Emission				Correction Factors	Corrected Amplitude dBm	Attenuated below the mean power (dB)	minimum Attenuation Limit (dB)
Frequency (GHz)	Amplitude (dBμV/m)	Ant. H. (cm)	Table (°)	(dB)			

1.589	64.21	1.00	134	-8.67	-41.84	36.15	9.77
2.380	65.97	1.00	327	-8.67	-40.08	34.39	9.77
2.770	61.97	1.00	50	-6.84	-42.25	36.56	9.77
2.980	74.31	1.00	94	-6.84	-29.91	24.22	9.77

Measurement Result:

(Test Frequency: 800.200MHz , Horizontal , 30MHz ~ 1GHz)

Frequency	Reading Amplitude	Ant. Height	Table	Correction Factors	Corrected Power	Attenuated below the mean power	minimum Attenuation limit
MHz	dBμV	m	degree	dB/m	dBm	dB	dB

200.049	32.79	1.00	150	-13.40	-51.19	44.52	8.22
400.100	22.68	2.47	7	-19.71	-54.99	44.43	8.22
600.148	24.69	1.00	84	-23.25	-51.19	48.23	8.22

Note:

- Margin = Amplitude - limit, *if margin is minus means under limit.*
- Corrected Amplitude = Reading Amplitude – Correction Factors
- Correction factor = Antenna factor + (Cable Loss – Amplitude Gain)
(For example :794.900MHz correction Amplitude= 65.99 – (–26.64) = 92.63dBμV/m)
- $FI(Volt) = 10^{FI (dB\mu V/m) / 20} \times 10^{-6}$
 $FI (Volt) = 10^{92.63/20} \times 10^{-6} = 0. 04281 \text{ V}$
- $P (watt) = FI^2 (Volt) \times d^2 (meter) / 49.2$
 $FI (mW) = (0.04281 \times 3)^2 / 49.2 = 0.335179 \text{ mW}$
 $FI (dBm) = 10 \log 0.335179 (mW)/ 1(mW) = -4.7472 (dBm)$
- Mean Power = $10 \log (p) (dB) = 10 \log (0.21077) = -6.762$
Attenuated below the mean power = P – Corrected Power
(For example : -6.762 – (- 51.19)) = 53.94 (dB))
- Attenuation required = $43 + 10 \log (0.33287 \text{ mW}) = 8.22$

Measurement Result:

(Test Frequency: 800.200MHz , Horizontal , 1GHz ~ 18GHz)

Radiated Emission				Correction Factors	Corrected Amplitude dBm	Attenuated below the mean power (dB)	minimum Attenuation Limit (dB)
Frequency (GHz)	Amplitude (dBμV/m)	Ant. H. (cm)	Table (°)	(dB)			

1.400	72.05	1.00	9	-8.67	-34.00	27.24	8.22
1.600	70.25	1.00	141	-8.67	-35.80	29.04	8.22
2.390	69.97	1.00	95	-8.67	-36.08	29.32	8.22
2.790	61.81	1.00	417	-6.84	-42.41	35.65	8.22
3.000	69.31	1.00	206	-6.84	-34.91	28.15	8.22
3.190	63.64	1.00	4	-6.84	-40.58	33.82	8.22
5.990	38.58	1.00	189	9.72	-49.08	42.32	8.22
6.800	40.91	1.00	206	9.72	-46.75	39.99	8.22
7.410	42.48	1.00	40	9.72	-45.18	38.42	8.22
7.610	42.75	1.00	146	9.72	-44.91	38.15	8.22

Radiated Emission Test Result:

(Test Frequency: 800.200MHz , Vertical , 30MHz ~ 1GHz)

<i>Frequency</i>	<i>Reading Amplitude</i>	<i>Ant. Height</i>	<i>Table</i>	<i>Correction Factors</i>	<i>Corrected Power</i>	<i>Attenuated below the mean power</i>	<i>minimum Attenuation limit</i>
MHz	dBμV	m	degree	dB/m	dBm	dB	dB

200.052	30.39	2.44	56	-13.64	-53.35	46.59	8.22
600.152	22.44	1.00	13	-23.56	-51.38	44.62	8.22

Radiated Emission Test Result:

(Test Frequency: 800.200MHz , Vertical , 1GHz ~ 18GHz)

Radiated Emission				Correction Factors	Corrected Amplitude dBm	Attenuated below the mean power (dB)	minimum Attenuation Limit (dB)
Frequency (GHz)	Amplitude (dBμV/m)	Ant. H. (cm)	Table (°)	(dB)			

1.400	71.20	2.44	10	-8.67	-34.85	28.09	8.22
1.600	62.90	1.00	58	-8.67	-43.15	36.39	8.22
2.390	69.14	1.00	151	-8.67	-36.91	30.15	8.22
2.790	73.81	1.00	206	-6.84	-30.41	23.65	8.22
3.000	75.47	1.00	27	-6.84	-28.75	21.99	8.22
3.190	63.81	1.00	116	-6.84	-40.41	33.65	8.22
5.990	47.41	1.00	237	9.72	-40.25	33.49	8.22
6.800	54.91	1.00	308	9.72	-32.75	25.99	8.22
7.000	51.41	1.00	346	9.72	-36.25	29.49	8.22
7.200	51.25	1.00	15	9.72	-36.41	29.65	8.22
7.410	52.41	1.00	97	9.72	-35.25	28.49	8.22
7.610	57.08	1.00	2	9.72	-30.58	23.82	8.22

Measurement Result:

(Test Frequency: 804.900MHz , Horizontal , 30MHz ~ 1GHz)

Frequency	Reading Amplitude	Ant. Height	Table	Correction Factors	Corrected Power	Attenuated below the mean power	minimum Attenuation limit
MHz	dBμV	m	degree	dB/m	dBm	dB	dB

201.227	34.45	1.00	150	-13.49	-49.44	44.49	9.93
402.452	32.01	1.00	28	-19.81	-45.56	40.61	9.93

Note:

1. Margin = Amplitude - limit, *if margin is minus means under limit.*
2. Corrected Amplitude = Reading Amplitude – Correction Factors
3. Correction factor = Antenna factor + (Cable Loss – Amplitude Gain)
(For example :794.900MHz correction Amplitude= 68.37 – (–26.17) = 94.54dBμV/m)
4. FI(Volt) = $10^{FI (dB\mu V/m) / 20} \times 10^{-6}$
FI (Volt) = $10^{94.54/20} \times 10^{-6} = 0.05333 \text{ V}$
5. P (watt) = $FI^2 (Volt) \times d^2 (meter) / 49.2$
FI (mW) = $(0.05333 \times 3)^2 / 49.2 = 0.520328 \text{ mW}$
FI (dBm) = $10 \log 0.520328 (mW) / 1(mW) = -2.837 (dBm)$
6. Mean Power = $10 \log (p) (dB) = 10 \log (0.31961) = -4.954$
Attenuated below the mean power = P – Corrected Power
(For example : -4.954 – (- 49.44)) = 44.49 (dB)
7. Attenuation required = $43 + 10 \log (0.49349 \text{ mW}) = 9.93$

Report No.: S0774792

Training Research Co., Ltd., TEL: 886-2-26935155, Fax: 886-2-26934440

Measurement Result:

(Test Frequency: 804.900MHz , Horizontal , 1GHz ~ 18GHz)

Radiated Emission				Correction Factors	Corrected Amplitude dBm	Attenuated below the mean power (dB)	minimum Attenuation Limit (dB)
Frequency (GHz)	Amplitude (dBμV/m)	Ant. H. (cm)	Table (°)	(dB)			

1.207	66.14	1.00	64	-8.67	-39.91	34.96	9.93
1.609	68.37	1.00	150	-8.67	-37.68	32.73	9.93
2.010	57.80	1.00	29	-8.67	-48.25	43.3	9.93
2.410	60.11	1.00	146	-8.64	-45.91	40.96	9.93
2.810	60.97	1.00	228	-6.84	-43.25	38.30	9.93
3.010	57.97	1.00	339	-6.84	-46.25	41.30	9.93
3.220	59.31	1.00	8	-6.84	-44.91	39.96	9.93

Radiated Emission Test Result:

(Test Frequency: 804.900MHz , Vertical , 30MHz ~ 1GHz)

<i>Frequency</i>	<i>Reading Amplitude</i>	<i>Ant. Height</i>	<i>Table</i>	<i>Correction Factors</i>	<i>Corrected Power</i>	<i>Attenuated below the mean power</i>	<i>minimum Attenuation limit</i>
MHz	dBμV	m	degree	dB/m	dBm	dB	dB

201.226	31.72	2.47	4	-13.72	-51.94	46.99	9.93
402.452	29.99	1.00	9	-19.36	-48.03	43.08	9.93

Radiated Emission Test Result:

(Test Frequency: 804.900MHz , Vertical , 1GHz ~ 18GHz)

Radiated Emission				Correction Factors	Corrected Amplitude dBm	Attenuated below the mean power (dB)	minimum Attenuation Limit (dB)
Frequency (GHz)	Amplitude (dBμV/m)	Ant. H. (cm)	Table (°)	(dB)			

1.207	59.45	1.00	35	-8.67	50.78	-46.60	41.65
1.609	64.08	1.00	35	-8.67	55.41	-41.97	37.02
2.010	56.97	1.00	39	-8.67	48.30	-49.08	44.13
2.410	63.11	1.00	167	-8.64	54.47	-42.91	37.96
2.810	67.97	1.00	229	-6.84	61.13	-36.25	31.30
3.010	64.97	1.00	64	-6.84	58.13	-39.25	34.30
3.220	61.14	1.00	181	-6.84	54.30	-43.08	38.13
3.420	62.31	1.00	38	-6.84	55.47	-41.91	36.96
3.620	57.61	1.00	239	-5.64	51.97	-45.41	40.46
