RadioShack Corporation

Application For Certification (FCC ID: AAO2101705)

July 28, 2000

WO# 0005315 WL/at July 28, 2000

 The test results reported in this report shall refer only to the sampel actually tested and shall not refer or be deemed a refer to bulk from which such a sample may be said to have been obtained

This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited.

FCC ID: AAO2101705

Intertek Testing Services Hong Kong Ltd.

2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. Tel: (852) 2173 8888 Fax: (852) 2741 1693

INTERTEK TESTING SERVICES

SUMMARY OF CONTENTS

INTRODUCTION

Exhibits 1 through 12

LIST OF EXHIBITS

INTRODUCTION

EXHIBIT 1 _:	General Description
EXHIBIT 2:	System Test Configuration
EXHIBIT 3 _:	RF Power Output
EXHIBIT 4:	Modulation Characteristics
EXHIBIT 5:	Occupied Bandwidth
EXHIBIT 6 _:	Emission Spurious
EXHIBIT 7:	Frequency Stability
EXHIBIT 8:	Technical Specifications
EXHIBIT 9:	Product Labelling
EXHIBIT 10:	Photographs
EXHIBIT 11:	Instruction Manual
EXHBIIT 12:	CB Transmitter Power

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Application:	RadioShack Corporation
Trade Name:	RadioShack
Model No.:	21-1705
Date:	July 28, 2000

This report concerns (check one:)Original Gra	int <u>X</u>	Class II Cha	ange
Equipment Type: <u>CB Radio Station</u> (example	e: computer, pri	nter, moder	n. etc.)
Deferred grant requested per 47 CFR 0.457(d))(1)(ii)?	Yes	No <u>X</u>
	If yes, de	fer until:	
Company Name agrees to notify the Commiss	ion by:		date
	da	ate	
of the intended date of announcement of the pr that date.	da roduct so that t	ate he grant ca	n be issued on
of the intended date of announcement of the pr that date.	da roduct so that t	nte he grant ca	n be issued on

Table of Contents

1.0 General Description	1
1.1 Product Description	2
1.2 Ralated Submittal(s) Grants	3
1.3 Test Methodology	3
1.4 Test Facility	3
2.0 System Test Configuration	. 5
2.1 Justification	6
2.2 EUT Exercising Software	6
2.3 Special Accessories	6
2.4 Equipment Modification	6
3.0 RF Output Power (Section 95.639(d))	8
4.0 <u>Modulation Characteristics (Section 95.637(a))</u>	13
4.1 Modulation Frequeiency Response	14
4.2 Modulation Limiting Characteristic	16
4.3 Over Modulatin Transient Response	18
5.0 Occupied Bandwidth (Section 95.633(c))	21
6.0 Spurious Emission (Section 95.635(b))	23
6.1 Spurious Emission at the Antenna Termianal	24
6.2 Field Strength of Spurious Radiation	28
7.0 <u>Frequency Stanility (Section 95.627)</u>	38
7.1 Frequency Tolerance	39
7.2 Temperature Extreme Condition	42
7.3 Voltage Extreme Condition	47
8.0 Technical Specifications	49
9.0 Product Labelling	51
10.0 Equipment Photographs	53
	-
11.0 Instruction Manual	55
12.0 <u>CB Transmitter Power</u>	57

INTERTEK TESTING SERVICES

Exhibit type	File Description	filename
Cover Letter	Letter of Agency	letter.pdf
Test Report	Test Report	report.doc
Operation Description	Technical Description	descri.pdf
Test Report	Modulation Frequency Response	mfr.pdf
Test Report	Modulation Limiting Characteristics	mlc.pdf
Test Report	Modulation Transient Response	mtr.pdf
Test Report	Bandwidth Plot	bw.pdf
Test Setup Photo	Radiated emission	radiated1.jpg, radiated2.jpg
Test Report	Spurious emission plot	spurious.pdf
External Photo	External Photo	ophoto1.jpg to ophoto2.jpg
Internal Photo	Internal Photo	iphoto1.jpg to iphoto4.jpg
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Operation Description	Electronic Tube specification	power.pdf

List of attached file

STATEMENT OF CONFORMITY

This unit has been found to conform with the following parts of the 47 CFR as detailed below:

- 2.911 This report is certified by a qualified individual. This signature is located in the Measurement Section.
- 2.983 The name of the applicant and identification of the equipment is provided on Form 731. The product will be produced in mass quantities. The technical description information is included in Exhibit 1, Exhibit 8 to 12.
- 2.985 RF power data is located in Exhibit 3.1.
- 2.987 Modulation characteristics are detailed in Exhibit 4.0.
- 2.989 Occupied bandwidth measurements are detailed in Exhibit 5.0.
- 2.993 The field strength of spurious emissions was measured and the data is recorded in Exhibit 6.0.
- 2.995 The frequency stability of the unit, with respect to voltage and temperature variation, was measured and the results are recorded in Exhibit 7.0.
- 2.997 The frequency range investigated was from the lowest frequency present in the device to higher than the tenth harmonic of the carrier frequency.

EXHIBIT 1

GENERAL DESCRIPTION

1.0 General Description

1.1 Product Description

The 21-1705 is a 40 Channel mobile citizen Band (CB) transceiver. The unit is powered from 13.8 Vdc.

Transmitter portion:

- i) Type of emission: 6K00A3E
- ii) Frequency Range: 26.965 MHz to 27.405 MHz
- iii) Maximum Power Rating: 4 Watt
- iv) Source-based Time-averaged Duty Factor: <50% (Push to Talk Device)

Receiver Portion:

- i) Type of Receiver: Superheterodyne receiver
- ii) Tuning Frequency: 26.965 MHz to 27.405 MHz
- iii) Local oscillator: 10.695 MHz and 10.240 MHz
- iv) IF: 10.695 MHz and 455 kHz

For compliance with FCC RF exposure requirements, a separation distance of at least 20 cm must be maintained between the antenna of this device and all persons.

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

1.2 Related Submittal(s) Grants

This is an Application for Certification of the transmitter portion of a CB Transceiver. The receiver section of the CB Transceiver is subject to the vertification process, in accordance with Section 15.101(b).

1.3 Test Methodology

Radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurement were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure of maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna the EUT distance of 3 meters, unless stated otherwise in the "Justification Section" of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the emission data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. The test facility and site measurement data have been fully placed on file with the FCC.

EXHIBIT 2

SYSTEM TEST CONFIGURATION

2.0 System Test Configuration

2.1 Justification

The device was configured for testing in a typical fashion (as a customer would normally use it). The device was mounted to a cardboard box, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes. When the radiated emissions are measured.

The device was powered by a DC power supply adjusted to give 13.8 Vdc.

For measuring spurious and harmonic emissions of the transmitter, a 50Ω load was connected to the antenna terminal.

The frequency range from 25 MHz to 1 GHz was searched for spurious emissions from the device. Harmonic emissions of the transmitter were investigated up to 5 GHz. Only those emissions reported were detected. All other emissions were at least 20 dB below the applicable limits.

2.2 EUT Exercising Software

There was no special software to exercise the device. Once the unit is powered on, a signal is transmitted.

2.3 Special Accessories

There is no special accessory necessary for compliance of this product.

2.4 Equipment Modification

Any modification installed previous to testing by RadioShack Corporation will be incorporated in each production model sold/leased in the United States.

No modification were installed by Intertek Testing Services.

Confirmed by:

Wilson Loke Manager Intertek Testing Services Agent for RadioShack Corporation

_____ Signature

August 7, 2000 Date

EXHIBIT 3

RF POWER OUTPUT

3.0 <u>RF Power Output (Section 2.985(a))</u>

A. Equipment Used

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	35-30L
Voltmeter	Fluke	87
Spectrum Analyzer	Hewlett Packard	8591EM
20dB RF Load	Bird	8304-200-N

- B. Testing Procedure
 - 1) Setup the test equipment in the following configuration:



- 2) Measure the power of all channels (40 channels) by Spectrum Analyzer in Watt.
- Calculate the actual power by times the measured power with a correction factor, 104.7*

ie. Actual Power = measured Power * 104.7

* The Correction Factor is included the 20dB Load and cable loss between EUT and 20dB load.

Table 1

RadioShack Corporation RadioShack 21-1705

Transmission Power

Channel	Frequency	M easured Power	NetPower	Limit	M argin
	(MHz)	(W)	(W)	(W)	(W)
1	26.965	31.00	3.25	4	-0.75
2	26 . 975	30.50	3.19	4	-0.81
3	26.985	30.50	3.19	4	-0.81
4	27.005	30.50	3.19	4	-0.81
5	27.015	30.50	3.19	4	-0.81
б	27.025	30.50	3.19	4	-0.81
7	27.035	30.50	3.19	4	-0.81
8	27.055	30.50	3.19	4	-0.81
9	27.065	30.80	3.22	4	-0.78
10	27.075	30.40	3.18	4	-0.82
11	27.085	30.60	3.20	4	-0.80
12	27.105	30.80	3.22	4	-0.78
13	27.115	30.80	3.22	4	-0.78
14	27.125	30.80	3.22	4	-0.78
15	27.135	30.80	3.22	4	-0.78

Notes: Negative sign in the margin column shows the value below limits.

Test Engineer: H. Y. Vu

Table 1 (Cont'd...)

RadioShack Corporation RadioShack 21-1705

Transmission Power

Channel	Frequency	M easured Power	NetPower	Limit	M argin
	(MHz)	(W)	(W)	(W)	(W)
16	27.155	30.80	3.22	4	-0.78
17	27.165	30.80	3.22	4	-0.78
18	27.175	30.80	3.22	4	-0.78
19	27.185	30.00	3.14	4	-0.86
20	27.205	29.50	3.09	4	-0.91
21	27.215	29.40	3.08	4	-0.92
22	27.225	29.50	3.09	4	-0.91
23	27.255	29.50	3.09	4	-0.91
24	27.235	29.50	3.09	4	-0.91
25	27.245	29.50	3.09	4	-0.91
24	27.265	29.50	3.09	4	-0.91
27	27 . 275	29.50	3.09	4	-0.91
28	27.285	29.50	3.09	4	-0.91
29	27.295	29 . 51	3.09	4	-0.91
30	27.305	29.90	3.13	4	-0.87

Notes: Negative sign in the margin column shows the value below limits.

Test Engineer: Test Engineer

Date of Test: Date of Test

Table 1 (Cont'd...)

RadioShack Corporation RadioShack 21-1705

Transmission Power

Channel	Frequency	M easured Power	NetPower	Limit	M argin
	(MHz)	(W)	(W)	(W)	(W)
31	27.315	29.40	3.08	4	-0.92
32	27.325	29.60	3.10	4	-0.90
33	27.335	29.60	3.10	4	-0.90
34	27.345	29.60	3.10	4	-0.90
35	27.355	29.60	3.10	4	-0.90
36	27.365	29.60	3.10	4	-0.90
37	27.375	29.60	3.10	4	-0.90
38	27.385	29.60	3.10	4	-0.90
39	27.395	29.40	3.08	4	-0.92
40	27.405	29.50	3.09	4	-0.91

Notes: Negative sign in the margin column shows the value below limits.

Test Engineer: H. Y. Vu

EXHIBIT 4

MODULATION CHARACTERISTICS

4.0 Modulation Characteristics

In order to satisfy the 2.987 requirement, Modulation Frequency Response, Modulation Limit Characteristics and Over Modulation Transient Response, are attached in Exhibit 4.1, 4.2 & 4.3.

For electronic filing, the plots are saved with filenames: mfr.pdf, mlc.pdf and mtr.pdf respectively.

4.1 <u>Modulation Frequency Response</u>

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
Audio Signal Generator	Leader	LFG-1300S
dB meter	Leader	LMV-182A
20 dB RF Load	Bird	8304-200-N
Modulation Meter	Marconi Instrument	2945

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Set the audio signal generator frequency to 2kHz and adjust level to obtain 50% modulation. And then adjust the frequency to obtain the maximum audio frequency response of the EUT.
- 3) Adjust the level of audio signal generator to give 50% modulation at the maximum audio frequency response and take this level as the 0dB reference level.
- 4) The frequency of the audio signal generator is changed form 100Hz to 10kHz and adjust the level to obtain the 50% modulation at each frequency.
- 5) Record the level at each frequency reference to 0dB Level.

Table 2

RadioShack Corporation RadioShack 21-1705

Modulation Frequency Response (Section 2.987(a))

Test Channel : 19 0 dB Level : 60.5dBµV Modulation Output : 50%

Modulation Frequency (Hz)	Modulation input relative to max. output. (dB)
100	39.6
200	21.3
300	14.2
400	6.5
500	3.6
600	1.9
700	0.7
800	0.2
900	0.0
1000	0.0
1200	0.0
1500	0.1
2000	1.7
2500	3.7
3000	6.0
4000	10.8
5000	15.1
6000	18.9
7000	22.0
8000	24.9
9000	27.9
10000	30.2

Test Engineer: H. Y. Vu

4.2 <u>Modulation Limiting Characteristics (Section 2.987(b))</u>

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
Audio Signal Generator	Leader	LFG-1300S
dB meter	Leader	LMV-182A
20 dB RF Load	Bird	8304-200-N
Modulation Meter	Marconi	2950

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Set the frequency of the audio signal generator to 400Hz and adjust the level from -70dBm to 0dBm. Record the output modulation index.
- 3) Repeat the above procedure with frequency 1200Hz, 1500Hz, 2500Hz & 5000Hz.

Table 3

RadioShack Corporation RadioShack 21-1705

Modulation Limiting Characteristics

Test Channel : 19

Modulation Input (dBm)	Modulation Index(%) at 400Hz	Modulation Index(%) at 1200Hz	Modulation Index(%) at 1500Hz	Modulation Index(%) at 2500Hz	Modulation Index(%) at 5000Hz
-60	15	33	37	23	8
-50	49	87	86	70	22
-40	86	88	87	83	63
-30	88	89	89	84	85
-20	92	91	92	87	87
-10	95	97	99	91	89
0	90	113	109	95	87
10	97	122	119	99	92

Test Engineer: H. Y. Vu

4.3 <u>Over Modulation Transient Response (Section 2.987(b))</u>

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
Audio Signal Generator	Leader	LFG-1300S
dB meter	Leader	LMV-182A
20 dB RF Load	Bird	8304-200-N
Spectrum Analyzer	Hewlett Packard	8951EM

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Set the frequency of the audio signal generator to 2.5kHz at level 16dB greater than required for 50% modulation.
- 3) Use the other audio signal generator pulse the previous signal at one P.P.S. with pulse width of 0.5 second.
- 4) Tune the spectrum analyzer to the channel on which the transmitter is set and adjust the setting as for the measurement of occupied bandwidth.
- 5) And then tune the spectrum analyser to adjacent channel(+/-10kHz) and use "Zero-scan" to observe the transients caused by the pulsed modulation.

Table 4

RadioShack Corporation RadioShack 21-1705

Over modulation Transient Response

Channel	Adjacent Frequency (MHz)	Transient Level with respect to TP in (dB)	Transient Duration (ms)
1	26.955	-37.3	15.0
1	26.975	-45.3	35.0
19	27.175	-39.9	30.0
19	27.195	-44.3	17.5
40	27.395	-40.8	22.5
40	27.415	-38.2	30.0

Remark: '-' sign in the Transient Level respect to the carrier Level column mean below the carrier level.

Test Engineer: H. Y. Vu

EXHIBIT 5

OCCUPIED BANDWIDTH

5.0 Occupied Bandwidth (Section 2.989 & Section 95.633)

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
Audio Signal Generator	Leader	LFG-1300S
dB meter	Leader	LMV-182A
20 dB RF Load	Bird	8304-200-N
Spectrum Analyzer	Hewlett Packard	8951EM

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Set the level of audio signal generator to obtain 16 dB greater than required for 50% modulation.
- 3) The occupied bandwidth is measured with the spectrum analyzer set at 5kHz/div scan and 10dB/div.

C. Test Result

The occupied Bandwidth is measured to be 6.00 kHz.

For electronic filing, the plot is saved with filename: bw.pdf

Test Engineer: H. Y. Vu

EXHIBIT 6

SPURIOUS EMISSION

6.0 Spurious Emission

In order to satisfy the 2.991 & 2.993 requirement, the spurious emission from the antenna terminal and from the EUT are measured and shown in the Exhibit 6.1 & 6.2

For electronic filing, the spurious emission is saved with filename: spurious.pdf

6.1 <u>Spurious emission at the antenna terminal (Section 2.991 & Section 95.631)</u>

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
Audio Signal Generator	Leader	LFG-1300S
dB meter	Leader	LMV-182A
20 dB RF Load	Bird	8304-200-N
RF Filter	Tailithic	3VF
Spectrum Analyzer	Hewlett Packard	8951EM

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Set the level of audio signal generator to obtain 16 dB greater than required for 50% modulation.
- 3) Plot the graph of emissions with 50kHz span.
- 4) Measure the emissions relative to TP in region CARRIER \pm 4kHz to CARRIER \pm 20kHz from the plot.
- 5) Record the emissions relative to TP from region CARRIER \pm 20kHz to 1000MHz.

RadioShack Corporation RadioShack 21-1705 Table 5(a)

1) Unwanted emission from CARRIER \pm 4kHz to Carrier \pm 20kHz (Refer to the plots)

	Unwanted emission			
Region	Channel 1 Channel 19 Channel 40			
CARRIER \pm 4kHz to \pm 8kHz	< 25dB	< 25dB	< 25dB	
CARRIER \pm 8kHz to \pm 20kHz	< 35dB	< 35dB	< 35dB	

2) Unwanted emission from CARRIER \pm 20kHz to 1000MHz

Table 5(b): Channel 1

Frequency	Em ission relative	Linit	M argin
(MHz)	to TP (dB)	(db)	(dB)
53.930	-61.0	-60	-1.0
80.895	-72 . 9	-60	-12.9
107.860	-85.8	-60	-25.8
134.825	-81.6	-60	-21.6
161.790	-88.6	-60	-28.6
188.755	-87.5	-60	-27.5
215.720	-86.0	-60	-26.0
242.685	-84.9	-60	-24.9
269.650	-74.7	-60	-14.7
296.615	-72.4	-60	-12.4
323.580	-71.7	-60	-11.7
350.545	-75.7	-60	-15.7

Remark: 1. '-' sign in margin column shows the value below the limits.

2. Any emissions and other harmonics which are attenuated more than 20dB below the permissible value need not be recorded.

Test Engineer: H. Y. Vu

Date of Test: July 12, 2000

RadioShack Corporation

RadioShack 21-1705

Frequency	Em ission relative	Linit	M argin
(MHz)	to TP (dB)	(dB)	(dB)
54.370	-61.7	-60	-1.7
81.555	-74.7	-60	-14.7
108.740	-86.9	-60	-26.9
135.925	-81.7	-60	-21.7
163.110	-84.3	-60	-24.3
190.295	-87.7	-60	-27.7
217.480	-90.6	-60	-30.6
244.665	-84.9	-60	-24.9
271.850	-75.2	-60	-15.2
299.035	-73.8	-60	-13.8
326.220	-71.5	-60	-11.5
353.405	-78.9	-60	-18.9

Table 5(c): Channel 19

Remark: 1. '-' sign in margin column shows the value below the limits.

2. Any emissions and any other harmonics which are attenuated more than 20dB below the permissible value need not be recorded.

Test Engineer: H. Y. Vu

Frequency	Em ission relative	Linit	M argin
(MHz)	to TP (dB)	(db)	(dB)
54.810	-61.3	-60	-1.3
82.215	-75.1	-60	-15.1
109.620	-84.7	-60	-24.7
137.025	-84.2	-60	-24.2
164.430	-80.4	-60	-20.4
191.835	-87.5	-60	-27.5
219.240	-91.8	-60	-31.8
246.645	-83.6	-60	-23.6
274.050	-75.1	-60	-15.1
301.455	-76.8	-60	-16.8
328.860	-71.7	-60	-11.7
356.265	-77.6	-60	-17.6

Table 5(d): Channel 40

Remark: 1. '-' sign in margin column shows the value below the limits.

2. Any emissions and any other harmonics which are attenuated more than 20dB below the permissible value need not be recorded.

Test Engineer: H. Y. Vu

6.2 Field Strength of Spurious Radiation (Section 2.993)

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
Antenna	CDI	B100,B200,B300
Test receiver	Rohde & Schwarz	ESVS30
RF Filter	Tailithic	3VF

B. Testing Procedure

Radiated emission measurements were performed according to the procedures in ANSI C63.4(1992). All measurements were performed in Open Area Test Sites located at Roof Top of Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.

INTERTEK TESTING SERVICES

C. Radiated Emission Configuration Photograph

Worst Case Radiated Emission

Front View

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated 1.jpg

INTERTEK TESTING SERVICES

C. Radiated Emission Configuration Photograph (cont.)

Worst Case Radiated Emission

Back View

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated 2.jpg

Table 6

RadioShack Corporation RadioShack 21-1705 Radiated Spurious Emissions

Channel : 1 The output power of transmitter is 35.1 dBm

Antenna	Frequency	Reading	Antenna	Netat	ERP	ERP
Polarity	(MHz)	(dBµV)	Factor	3m	(dBm)	to related
			(dB)	(dBµV/m)		TOP*
V	53.938	31.8	11.7	43.5	-53.9	-89.0
Н	80.895	36.1	6.7	42.8	-54.6	-89.7
Н	107.864	45.4	12.2	57.6	-39.8	-74.9
Н	134.833	37.6	12.3	49.9	-47.5	-82.6
Н	161.802	32.7	13.1	45.8	-51.6	-86.7
Н	188.771	34.6	16.7	51.3	-46.1	-81.2
Н	215.720	43.3	11.8	55.1	-42.3	-77.4
Н	242.685	41.6	11.4	53.0	-44.4	-79.5
Н	269.663	49.2	12.4	61.6	-35.8	-70.9
H	296.628	52.1	13.3	65.4	-32.0	-67.1
Н	323.593	49.1	14.3	63.4	-34.0	-69.1
Н	350.558	50.5	14.9	65.4	-32.0	-67.1

* "TOP" is Transmitter Output Power

Test Engineer: H. Y. Vu

Table 6 (Cont'd...)

RadioShack Corporation RadioShack 21-1705 Radiated Spurious Emissions

Channel : 1 The output power of transmitter is 35.1 dBm

Antenna	Frequency	Reading	Antenna	Netat	ERP	ERP
Polarity	(MHz)	(dBµV)	Factor	3m	(dBm)	to related
			(dB)	(dBµV/m)		TOP*
Н	377 . 523	50.3	15.9	66.2	-31.2	-66.3
Н	404.488	43.7	15.9	59.6	-37.8	-72.9
Н	431.453	38.5	16.3	54.8	-42.6	-77.7
Н	458.418	38.9	16.8	55.7	-41.7	-76.8
Н	485.383	36.3	17.3	53.6	-43.8	-78.9
Н	512.348	35.7	18.0	53.7	-43.7	-78.8
Н	539.307	34.0	18.2	52.2	-45.2	-80.3
Н	566.295	35.5	18.3	53.8	-43.6	-78.7
Н	593.240	38.6	18.6	57.2	-40.2	-75.3
Н	620.245	39.2	18.9	58.1	-39.3	-74.4
Н	647.184	32.3	19.2	51.5	-45.9	-81.0
Н	674,149	19.8	19.6	39.4	-58.0	-93.1

* "TOP" is Transmitter Output Power

Test Engineer: H. Y. Vu

Table 7

RadioShack Corporation RadioShack 21-1705 Radiated Spurious Emissions

Channel : 19 The output power of transmitter is 35.1 dBm

Antenna	Frequency	Reading	Antenna	Netat	ERP	ERP
Polarity	(MHz)	(dBµV)	Factor	3m	(dBm)	to related
			(db)	(dBµV/m)		TOP*
V	54.376	30.3	11.7	42.0	-55.4	-90.5
Н	81 . 553	35.4	6.7	42.1	-55.3	-90.4
Н	108.743	44.6	12.2	56.8	-40.б	-75.7
Н	135.927	38.8	11.9	50.7	-46.7	-81.8
Н	163.118	37.2	13.1	50.3	-47.1	-82.2
Н	190.508	35.4	17.1	52.5	-44.9	-80.0
Н	217.696	43.1	11.8	54.9	-42.5	-77.6
Н	244.884	42.2	11.4	53.6	-43.8	-78.9
Н	272.072	48.4	12.4	60.8	-36.6	-71.7
Н	299.260	51.5	13.3	64.8	-32.6	-67.7
Н	326.448	48.8	14.3	63.1	-34.3	-69.4
Н	353,636	50.3	14.9	65.2	-32.2	-67.3

* "TOP" is Transmitter Output Power

Test Engineer: H. Y. Vu

Table 7 (Cont'd...)

RadioShack Corporation RadioShack 21-1705 Radiated Spurious Emissions

Channel : 19 The output power of transmitter is 35.1 dBm

Antenna	Frequency	Reading	Antenna	Netat	ERP	ERP
Polarity	(MHz)	(dBµV)	Factor	3m	(dBm)	to related
			(db)	(dBµV/m)		TOP*
Н	380.824	50.7	15.4	66.1	-31.3	-66.4
Н	408.012	43.1	15.9	59.0	-38.4	-73.5
Н	435.200	39.3	16.3	55.6	-41.8	-76.9
Н	462.388	38.9	16.8	55.7	-41.7	-76.8
Н	489.576	36.2	17.3	53.5	-43.9	-70.9
Н	516.764	37.1	18.0	55.1	-42.3	-77.4
Н	543.952	35.9	18.2	54.1	-43.3	-78.4
Н	571 . 140	37.5	18.3	55.8	-41.6	-76.7
Н	598.328	36.0	18.6	54.6	-42.8	-77.9
Н	625 . 516	31.7	19.2	50.9	-46.5	-81.6
Н	652.704	28.0	19.6	47.6	-49.8	-84.9
Н	679.892	18.8	20.7	39.5	57.9	-93.1

* "TOP" is Transmitter Output Power

Test Engineer: H. Y. Vu

Table 8

RadioShack Corporation RadioShack 21-1705 Radiated Spurious Emissions

Channel : 40 The output power of transmitter is 35.1 dBm

Antenna	Frequency	Reading	Antenna	Netat	ERP	ERP
Polarity	(MHz)	(dBµV)	Factor	3m	(dBm)	to related
			(db)	(dBµV/m)		TOP*
V	54.814	30.3	11.7	42.0	-55.4	-90.5
Н	53.215	31.1	11.7	42.8	-54.6	-89.7
Н	109.620	43.7	12.2	55.9	-41.5	-76.6
Н	137.029	40.6	11.9	52.5	-44.9	-80.0
Н	164.435	40.8	13.1	53.9	-43.5	-78.6
Н	191.839	33.5	17.1	50.6	-46.8	-81.9
H	219.244	44.4	11.8	56.2	-41.2	-76.3
Н	246.649	42.5	11.4	53.9	-43.5	-78.6
Н	274.054	49.0	12.4	61.4	-36.0	-71.1
Н	301 . 459	53 . 5	14.3	67.8	-29.6	-64.7
Н	328.871	50.2	14.6	64.8	-32.6	-67.7
Н	356.276	43.7	14.9	58.6	-38.8	-67.3

* "TOP" is Transmitter Output Power

Test Engineer: H. Y. Vu

Table 8 (Cont'd...)

RadioShack Corporation RadioShack 21-1705 Radiated Spurious Emissions

Channel : 40 The output power of transmitter is 35.1 dBm

Antenna	Frequency	Reading	Antenna	Netat	ERP	ERP
Polarity	(MHz)	(dBµV)	Factor	3m	(dBm)	to related
			(dB)	(dBµV/m)		TOP*
Н	383.686	50.9	15.4	66.3	-31.1	-66.2
Н	411.093	42.7	15.9	58.6	-38.8	-73.9
Н	438.496	38.4	16.3	54.7	-42.7	-77.8
Н	465.901	38.2	16.8	55.0	-42.4	-77 . 5
Н	493.306	40.8	17.3	58.1	-39.3	-74.4
Н	520.711	36.4	18.0	54.4	-43.0	-78.1
Н	548.116	35.4	18.2	53.6	-43.8	-78.9
Н	575 . 521	38.0	18.6	56.6	-40.8	-75.9
Н	602.926	36.5	18.9	55.4	-42.0	-77.1
Н	630.331	32.6	19.2	51.8	-45.6	-80.7
Н	657.736	28.9	19.6	48.5	-48.9	-84.0
Н	685,143	17.4	20.7	38.1	-59.3	-94.4

* "TOP" is Transmitter Output Power

Test Engineer: H. Y. Vu

EXHIBIT 7

FREQUENCY STABILITY

7.0 Frequency Stability

The frequency tolerance was tested in normal condition & over extreme ambient conditions with respect to voltage and temperature variation.

7.1 Frequency Tolerance (Section 95.625)

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
20 dB RF Load	Bird	8304-200-N
Frequency Counter	Phillips	PM6668

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



2) Measure all transmit channel frequencies in MHz.

Table 9

RadioShack Corporation RadioShack 21-1705 Frequency Tolerance

Channel	Frequency (MHz)	Measured	Tolerance
		Frequency (MHz)	(%)
1	26.96500	26.96488	-0.00045
2	26.97500	26.97485	-0.00056
3	26.98500	26.98489	-0.00042
4	27.00500	27.00483	-0.00065
5	27.01500	27.01481	-0.00069
6	27.02500	27.02486	-0.00051
7	27.03500	27.03484	-0.00060
8	27.05500	27.05481	-0.00069
9	27.06500	27.06485	-0.00055
10	27.07500	27.07484	-0.00060
11	27.08500	27.08485	-0.00055
12	27.10500	27.10483	-0.00065
13	27.11500	27.11481	-0.00069
14	27.12500	27.12483	-0.00065
15	27.13500	27.13486	-0.00050
16	27.15500	27.15480	-0.00074
17	27.16500	27.16484	-0.00060
18	27.17500	27.17483	-0.00064
19	27.18500	27.18480	-0.00074
20	27.20500	27.20484	-0.00060
21	27.21500	27.21479	-0.00078
22	27.22500	27.22484	-0.00060
23	27.25500	27.25483	-0.00064
24	27.23500	27.23484	-0.00059
25	27.24500	27.24484	-0.00059
26	27.26500	27.26483	-0.00064

Table 9 (Cont'd...)

RadioShack Corporation RadioShack 21-1705 Frequency Tolerance

Channel	Frequency (MHz)	Measured	Tolerance
		Frequency (MHz)	(%)
27	27.27500	27.27483	-0.00064
28	27.28500	27.28483	-0.00064
29	27.29500	27.29480	-0.00073
30	27.30500	27.30484	-0.00059
31	27.31500	27.31483	-0.00064
32	27.32500	27.32480	-0.00073
33	27.33500	27.33483	-0.00064
34	27.34500	27.34484	-0.00059
35	27.35500	27.35484	-0.00059
36	27.36500	27.36481	-0.00068
37	27.37500	27.37481	-0.00068
38	27.38500	27.38476	-0.00089
39	27.39500	27.39484	-0.00059
40	27.40500	27.40480	-0.00073

Test Engineer: H. Y. Vu

7.2 <u>Frequency Stability - Temperature (Section 2.995)</u>

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
20 dB RF Load	Bird	8304-200-N
Frequency Counter	Phillips	PM6668

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Set the Temperature Chamber to -30°C and stabilize the EUT temperature for one hour. Apply standard input voltage of 13.8 volts with transmitter ON for two minutes.
- 3) Measure the channel frequency of channel 1, 19, 40 in MHz.
- 4) Turn the EUT OFF
- 5) Repeat the above procedure with 10° C intervals form -30° C to 50° C

Table 10

RadioShack Corporation RadioShack 21-1705

Frequency Deviation with Temperature Variation

Channel: 1

Temperature (°C)	Assigned Frequency (MHz)	Measured Frequency (MHz)	% Deviation
-30	26.96500	26.96469	-0.00116
-20	26.96500	26.96479	-0.00079
-10	26.96500	26.96481	-0.00069
0	26.96500	26.96488	-0.00046
10	26.96500	26.96488	-0.00046
20	26.96500	26.96488	-0.00045
30	26.96500	29.96481	-0.00069
40	26.96500	29.96478	-0.00083
50	26.96500	29.96471	-0.00106

Test Engineer: H. Y. Vu

Table 11

RadioShack Corporation RadioShack 21-1705

Frequency Deviation with Temperature Variation

Channel: 19

Temperature (°C)	Assigned Frequency (MHz)	Measured Frequency (MHz)	% Deviation
-30	27.18500	27.18471	-0.00106
-20	27.18500	27.18478	-0.00083
-10	27.18500	27.18483	-0.00064
0	27.18500	27.18485	-0.00055
10	27.18500	27.18485	-0.00055
20	27.18500	27.18480	-0.00074
30	27.18500	27.18479	-0.00078
40	27.18500	27.18478	-0.00083
50	27.18500	27.18470	-0.00110

Test Engineer: H. Y. Vu

Table 12

RadioShack Corporation RadioShack 21-1705

Frequency Deviation with Temperature Variation

Channel: 40

Temperature (°C)	Assigned Frequency (MHz)	Measured Frequency (MHz)	% Deviation
-30	27.40500	27.40474	-0.00096
-20	27.40500	27.40478	-0.00082
-10	27.40500	27.40484	-0.00059
0	27.40500	27.40486	-0.00050
10	27.40500	27.40486	-0.00050
20	27.40500	27.40480	-0.00073
30	27.40500	27.40480	-0.00073
40	27.40500	27.40479	-0.00077
50	27.40500	27.40474	-0.00096

Test Engineer: H. Y. Vu

7.3 <u>Frequency Stability - Voltage (Section 2.995)</u>

A. Test Equipment

Equipment	Brand Name	Model No.
Regulated Power Supply	PAD	30-35L
20 dB RF Load	Bird	8304-200-N
Voltage meter	Fluke	87
Frequency Counter	Phillips	PM6668

B. Testing Procedure

1) Set-up the test equipment in the following configuration:



- 2) Vary the level of regulated power supply from 85% to 115% of the rated voltage of the EUT.
- 3) Measure the channel frequency of channel 1, 19, 40 in MHz at each input power level.

Table 13

RadioShack Corporation RadioShack 21-1705

Frequency Deviation with Voltage Variation

Channel: 1

Voltage	Assigned Frequency	Measured Frequency	% Deviation
(V)	(MHz)	(MHz)	
11.7	26.96500	26.96485	-0.00056
13.8	26.96500	26.96488	-0.00045
15.9	26.96500	26.96484	-0.00059

Channel: 19

Voltage	Assigned Frequency	Measured Frequency	% Deviation
(V)	(MHz)	(MHz)	
11.7	27.18500	27.18483	-0.00064
13.8	27.18500	27.18480	-0.00074
15.9	27.18500	27.18480	-0.00074

Channel: 40

Voltage	Assigned Frequency	Measured Frequency	% Deviation
(V)	(MHz)	(MHz)	
11.7	27.40500	27.40479	-0.00077
13.8	27.40500	27.40480	-0.00073
15.9	27.40500	27.40480	-0.00073

EXHIBIT 8

TECHNICAL SPECIFICATIONS

8.0 **Technical Specifications**

The circuit diagram and block diagram of the CB radio are attached.

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf respectively.

EXHIBIT 9

PRODUCT LABELLING

9.0 Product Labelling

The label and label location are saved with filename: label.pdf

EXHIBIT 10

PHOTOGRAPHS

10.0 Equipment Photographs

Photographs of the tested EUT are saved with filename: ophoto1.jpg to ophoto2.jpg and iphoto1.jpg to iphoto4.jpg

EXHIBIT 11 INSTRUCTION MANUAL

11.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf .

Please note that the required FCC Information to the User can be found at the front of this manual.

This manual will be provided to the end-user with each unit sold/leased in the United States.

EXHIBIT 12

CB TRANSMITTER POWER

12.0 CB Transmitter Power

The dissipation rating of all the semiconductors or electron tubes which supply RF power to the antenna terminals of each CB transmitter does not exceed 10W. The specification of the semiconductors or electron tubes is saved with filename: power.pdf