

反面



## Instructions

SS-TW003B

True wireless earbudsuser manual  
The parameters may be different between different models.

## Product Overview




Charging dock X1



Earmuffs X3



Wireless earphone X2



Micro-USB charging cable X1



Package content :

- Earphone\*1pair
- USB cable \*1pc
- L & S earmuffs \*1pair (M size on earphone)

Middle size earmuffs is suggested to try first as it suits most people

1

## Brief Introduction



Micro USB charging port

## How to pair for stereo mode

(Connect the two units in series then use them as a pair of stereo earphone)

2

Please follow below steps for the first time using:

- Turn on L & R unites the same time(green indicator flashes)
- Double click L & R unites the same time, the two units will connect with each other after 2-3 seconds ( pairing – green & red indicator flash alternately,paired- green indicator quick flash)
- Turn off one of them, then both of them will be turned off.
- Turn on L unit again until into pairing mode(green & red indicator flash alternately)
- Turn on your mobile phone's Wireless and search for the name "radius HP-T100BT " and connect to it.
- Turn on R unit (green indicator flashes is ok),then R unit will connect to L unit automatically.
- Finally you are wishing to use the TWS now.

After first use, only need to turn on both the units then will re-connect with mobile & re-connect each other.

## Charging the earphone

Put the units into the charging dock (charging contacts should be set properly)

Red indicator will flash to imply the condition of low battery (green light is on to show full charged)

3

Note: red light will flash when the earphone is inserted in the dock, which means the connection works well.

## Charging the dock

Charge it by USB cable Blue indicator will be flash when the dock is charging. There are 4 blue dots totally, they will be full charged one by one.

## Basic operation

Answer phone call--press MFB to answer incoming call , press it again to end  
Reject phone call--hold MFB for 1 second to reject an incoming call

Mute- -double press MFB when you are on the call  
Redial the last outgoing call--double press MFB during stand-by

## Three-way talking

Activate call waiting facility on your phone

- Whenever you are on the phone and there is an incoming

4

call at the same time, please press MFB to answer the second one.

- Supposing you have two incoming calls at the same time, the first one is talking while the second one is holding, you may switch their statuses by double pressing MFB.

### Power-on

Hold MFB for roughly 3S( Green light will be on )  
If the units are charging in the dock, they will be activated whenever you take them out.

### Power-off

Two units are in series connection while the main unit (L) is connected with cellphone, hold MFB of either of them for about 4S, they will be switched off at the same time (red lights are on)

It also can switch off when pull the connected units back to dock.

## Media sharing between two units

Two units are in series connection while the main unit (L) is connected with cellphone, press MFB of either of them to play or pause music and you can enjoy songs by both units together.  
Note: only the main unit (L) is available to answer a call.

5

## Parameters

Model No.	SS-TW003B
Wireless version	V5.0
Battery capacity	3.7V 45mAh*2
Earphone Weight	5G*2pcs
Charge dock weight	45G
Backup battery	450mAh
Working range	10m
Talk Time	2hours
Standby time	100hours
Charging dock size	7.5*3.5*2.5CM

- With the new 5.0 Wireless version,SS-TW003B brings you more HD experience.
- TWS style delivers true wireless stereo sound effect
- Charging dock allows you to charge the device when stored

6

## FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1)this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

7

158g书写纸/单色/双面印刷