



SAR TEST REPORT

For

Hyundai Technology Group, Inc.

Tablet

Test Model: 10LB2

Additional Model No.: HT10LB2MBKLTMO2

Prepared for : Hyundai Technology Group, Inc.
Address : 2601 Walnut Ave. Tustin, California, United States

Prepared by : Shenzhen LCS Compliance Testing Laboratory Ltd.
Address : 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park
Yabianxueziwei, Shajing Street, Baoan District, Shenzhen,
518000, China
Tel : (86)755-82591330
Fax : (86)755-82591332
Web : www.LCS-cert.com
Mail : webmaster@LCS-cert.com

Date of receipt of test sample : July 14, 2023
Number of tested samples : 1
Sample No. : A062823153-1
Serial number : Prototype
Date of Test : July 14, 2023~July 26, 2023
Date of Report : July 31, 2023



**SAR TEST REPORT****Report Reference No. : LCSA062823153EB****Date Of Issue : July 31, 2023****Testing Laboratory Name..... : Shenzhen LCS Compliance Testing Laboratory Ltd.****Address : 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China****Testing Location/ Procedure : Full application of Harmonised standards ■
Partial application of Harmonised standards □
Other standard testing method □****Applicant's Name : Hyundai Technology Group, Inc.****Address : 2601 Walnut Ave. Tustin, California, United States****Test Specification:****Standard : IEEE Std C95.1, 2019/ IEC-IEEE 62209-1528-2020/FCC Part 2.1093****Test Report Form No. : LCSEMC-1.0****TRF Originator..... : Shenzhen LCS Compliance Testing Laboratory Ltd.****Master TRF : Dated 2011-03****Shenzhen LCS Compliance Testing Laboratory Ltd. All rights reserved.**

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen LCS Compliance Testing Laboratory Ltd. is acknowledged as copyright owner and source of the material. Shenzhen LCS Compliance Testing Laboratory Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test Item Description..... : Tablet**Trade Mark : HYUNDAI****Model/Type Reference..... : 10LB2****Operation Frequency : GSM 850,1900;WCDMA II/V;
LTE2,4,5,7;WLAN2.4G,WLAN5.2G,WLAN5.8G and Bluetooth5.0.****Ratings : Input: 5.0V $\pm$ 2.0A
For AC Adapter Input: AC 100-240V, 50/60Hz, 0.5A
Adapter Output: 5V $\pm$ 2.0A, 10.0W
DC 3.8V by Rechargeable Li-ion Battery, 5000mAh****Result : Positive****Compiled by:**

Jay Zhan/ File administrators

Supervised by:

Cary Luo / Technique principal

Approved by:

Gavin Liang/ Manager



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**SAR -- TEST REPORT****Test Report No. :****LCSA062823153EB**July 31, 2023

Date of issue

Type / Model..... : 10LB2

EUT..... : Tablet

Applicant..... : Hyundai Technology Group, Inc.

Address..... : 2601 Walnut Ave. Tustin, California, United States

Telephone..... : /

Fax..... : /

Manufacturer..... : Hyundai Technology Group, Inc.

Address..... : 2601 Walnut Ave. Tustin, California, United States

Telephone..... : /

Fax..... : /

Factory..... : /

Address..... : /

Telephone..... : /

Fax..... : /

Test Result**Positive**

The test report merely corresponds to the test sample.

It is not permitted to copy extracts of these test result without the written permission of the test laboratory.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Revision History

Revision	Issue Date	Revision Content	Revised By
000	July 31, 2023	Initial Issue	---





TABLE OF CONTENTS

1. TEST STANDARDS AND TEST DESCRIPTION.....	6
1.1. TEST STANDARDS	6
1.2. TEST DESCRIPTION.....	6
1.3. GENERAL REMARKS	6
1.4. PRODUCT DESCRIPTION	6
1.5. STATEMENT OF COMPLIANCE	9
2. TEST ENVIRONMENT	10
2.1. TEST FACILITY	10
2.2. ENVIRONMENTAL CONDITIONS	10
2.3. SAR LIMITS	10
2.4. EQUIPMENTS USED DURING THE TEST	11
3. SAR MEASUREMENTS SYSTEM CONFIGURATION	12
3.1. SARMEASUREMENT SET-UP.....	12
3.2. OPENSAR E-FIELD PROBE SYSTEM.....	13
3.3. PHANTOMS.....	14
3.4. DEVICE HOLDER	14
3.5. SCANNING PROCEDURE	15
3.6. DATA STORAGE AND EVALUATION.....	17
3.7. TISSUE DIELECTRIC PARAMETERS FOR HEAD AND BODY PHANTOMS	19
3.8. TISSUE EQUIVALENT LIQUID PROPERTIES	19
3.9. SYSTEM CHECK	20
3.10. SAR MEASUREMENT PROCEDURE	23
3.11. POWER REDUCTION	28
3.12. POWER DRIFT	28
4. TEST CONDITIONS AND RESULTS	29
4.1. CONDUCTED POWER RESULTS	29
4.2. TRANSMIT ANTENNAS AND SAR MEASUREMENT POSITION.....	48
4.3. SAR MEASUREMENT RESULTS	49
4.4. SIMULTANEOUS TX SAR CONSIDERATIONS	53
4.5. SAR MEASUREMENT VARIABILITY	55
4.6. GENERAL DESCRIPTION OF TEST PROCEDURES	56
4.7. MEASUREMENT UNCERTAINTY (450MHz-6GHz).....	56
4.8. SYSTEM CHECK RESULTS	57
4.9. SAR TEST GRAPH RESULTS.....	64
5. CALIBRATION CERTIFICATES	75
5.1. PROBE-EPGO376 CALIBRATION CERTIFICATE.....	75
5.2. SID835DIPOLE CALIBRATION CERITICATE.....	86
5.3. SID1800 DIPOLE CALIBRATION CERTIFICATE	97
5.4. SID1900 DIPOLE CALIBRATION CERTIFICATE	108
5.5. SID2450 DIPOLE CALIBRATION CERTIFICATE.....	119
5.6. SID2600 DIPOLE CALIBRATION CERITICATE.....	130
5.7. SID5-6G DIPOLE CALIBRATION CERITICATE.....	141
6. PHOTOGRAPHS OF THE LIQUID	154
7. PHOTOGRAPHS OF THE TEST	158
8. EUT PHOTOGRAPHS	159





1. TEST STANDARDS AND TEST DESCRIPTION

1.1. Test Standards

[IEEE Std C95.1-2019](#): IEEE Standard for Safety Levels with Respect to Human Exposure to Electric, Magnetic, and Electromagnetic Fields, 0 Hz to 300 GHz. It specifies the maximum exposure limit of 1.6 W/kg as averaged over any 1 gram of tissue for portable devices being used within 20 cm of the user in the uncontrolled environment.

[IEC-IEEE 62209-1528-2020](#): IEEE Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques.

[FCC Part 2.1093 Radiofrequency Radiation Exposure Evaluation](#): Portable Devices

[KDB447498 D01 General RF Exposure Guidance v06](#): Mobile and Portable Device RF Exposure Procedures and Equipment Authorization Policies

[KDB447498 D02 SAR Procedures for Dongle Xmtr v02r01](#): SAR Measurement Procedures For USB Dongle Transmitters.

[KDB865664 D01 SAR Measurement 100 MHz to 6 GHz v01r04](#): SAR Measurement Requirements for 100 MHz to 6 GHz

[KDB865664 D02 RF Exposure Reporting v01r02](#): RF Exposure Compliance Reporting and Documentation Considerations

[KDB 248227 D01 802.11 Wi-Fi SAR v02r02](#): SAR GUIDANCE FOR IEEE 802.11 (Wi-Fi) TRANSMITTERS

[KDB941225 D01 3G SAR Procedures](#): 3G SAR MEAUREMENT PROCEDURES

[KDB 941225 D05 SAR for LTE Devices](#): SAR Evaluation Considerations For LTE Devices

[KDB 616217 D04 SAR for laptop and tablets v01r02](#): SAR Evaluation procedures for umpc mini-tablet devices

[KDB648474 D04](#): Handset SAR v01r03: SAR Evaluation Considerations for Wireless Handsets

1.2. Test Description

The EUT battery must be fully charged and checked periodically during the test to ascertain uniform power. And Test device is identical prototype.

1.3. General Remarks

Date of receipt of test sample	:	July 14, 2023
Testing commenced on	:	July 14, 2023
Testing concluded on	:	July 26, 2023

1.4. Product Description

The Hyundai Technology Group, Inc.'s Model: 10LB2 or the "EUT" as referred to in this report; more general information as follows, for more details, refer to the user's manual of the EUT.

General Description	
EUT :	Tablet
Model/Type reference:	10LB2
Additional Model No.	HT10LB2MBKLTM02
Model Declaration:	PCB board, structure and internal of these model(s) are the same, So no additional models were tested
Hardware Version	P612C2
Software Version:	/
Power supply:	Input: 5.0V $\pm$ 2.0A For AC Adapter Input: AC 100-240V, 50/60Hz, 0.5A Adapter Output: 5V $\pm$ 2.0A, 10.0W DC 3.8V by Rechargeable Li-ion Battery, 5000mAh





The EUT is Tablet. the Tablet is intended for WLAN transmission. It is equipped with Bluetooth, WiFi2.4G WiFi5.2G,5.8G; GSM 850,1900; WCDMA Band II, Band V; LTE 2,4,5,7. For more information see the following datasheet

Technical Characteristics	
LTE	
Support Band:	☒ E-UTRA Band 2(U.S.-Band) ☒ E-UTRA Band 3(Non U.S.-Band) ☒ E-UTRA Band 4(U.S.-Band) ☒ E-UTRA Band 5(U.S.-Band) ☒ E-UTRA Band 7(U.S.-Band) ☒ E-UTRA Band 28(Non U.S.-Band)
Modulation Type:	QPSK/16QAM
Release Version:	R12
Power Class:	Class 3
Antenna Description:	FPC Antenna 1.3dBi (max.) For E-UTRA Band 2 1.5dBi (max.) For E-UTRA Band 4 0.8dBi (max.) For E-UTRA Band 5 1.5dBi (max.) For E-UTRA Band 7
Bluetooth	
Frequency Range:	2402MHz ~ 2480MHz
Chanel Number:	79 channels for Bluetooth V5.0 (DSS) 40 channels for Bluetooth V5.0 (DTS)
Chanel Spacing:	1MHz for Bluetooth V5.0 (DSS) 2MHz for Bluetooth V5.0 (DTS)
Modulation Type;	GFSK, $\pi/4$ -DQPSK, 8-DPSK for Bluetooth V5.0(DSS) GFSK for Bluetooth V5.0 (DTS)
Bluetooth Version:	V5.0
Antenna Description:	FPC Antenna, -2.71dBi (max.)
WIFI 2.4G	
Frequency Range:	2412MHz-2462MHz
Type of Modulation:	IEEE 802.11b: DSSS (CCK, DQPSK, DBPSK) IEEE 802.11g: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11n: OFDM (64QAM, 16QAM, QPSK, BPSK)
Channel number:	11 Channels for 20MHz bandwidth (2412~2462MHz) 7 Channels for 40MHz bandwidth (2422~2452MHz)
Channel separation:	5MHz
Antenna Description:	FPC Antenna, -2.71dBi (max.)
5.2G WLAN	
Frequency Range	5180MHz~5240MHz
Channel Number	4 channels for 20MHz bandwidth(5180MHz~5240MHz) 2 channels for 40MHz bandwidth(5190MHz~5230MHz) 1 channels for 80MHz bandwidth(5210MHz)
Modulation Type	IEEE 802.11a: OFDM (64QAM,16QAM,QPSK,BPSK) IEEE 802.11n: OFDM (64QAM,16QAM,QPSK,BPSK) IEEE 802.11ac: OFDM (256QAM,64QAM,16QAM,QPSK,BPSK)
Antenna Description	FPC Antenna, -2.76dBi (max.)
5.8G WLAN	
Frequency Range	5745MHz~5825MHz
Channel Number	5 channels for 20MHz bandwidth(5745MHz~5825MHz) 2 channels for 40MHz bandwidth(5755MHz~5795MHz) 1 channels for 80MHz bandwidth(5775MHz)
Modulation Type	IEEE 802.11a: OFDM (64QAM,16QAM,QPSK,BPSK) IEEE 802.11n: OFDM (64QAM,16QAM,QPSK,BPSK) IEEE 802.11ac: OFDM (256QAM,64QAM,16QAM,QPSK,BPSK)
Antenna Description	FPC Antenna, -1.27dBi (max.)
UMTS	





Support Band:	☒ WCDMA Band I (EU-Band) ☒ WCDMA Band II (U.S.-Band) ☒ WCDMA Band V (U.S.-Band)
Modulation Type:	QPSK,16QAM
WCDMA Release Version:	R9
Antenna Description:	FPC Antenna 1.3dBi (max.) For WCDMA Band II 0.8dBi (max.) For WCDMA Band V
GSM	
Support Band:	☒ GSM 900 (EU-Band) ☒ DCS 1800 (EU-Band) ☒ GSM 850 (U.S.-Band) ☒ PCS 1900 (U.S.-Band)
Release Version:	R99
GPRS Class	Class 12
EGPRS Class	Class 12
Modulation Type:	GMSK for GSM/GPRS; GMSK/8PSK for EGPRS
Antenna Description:	FPC Antenna 0.8dBi (max.) For GSM 850 1.3dBi (max.) For PCS 1900





1.5. Statement of Compliance

The maximum of results of SAR found during testing for 10LB2 are follows:

<Highest Reported standalone SAR Summary>

Classment Class	Frequency Band	Hotspot (Report SAR _{1-g} (W/kg)	Body-worn (Report SAR _{1-g} (W/kg)
		(Separation Distance 0mm)	
PCB	GSM 850	0.593	0.593
	GSM1900	0.608	0.608
	WCDMA Band V	0.664	0.664
	WCDMA Band II	0.788	0.788
	LTE band 2	0.281	0.281
	LTE band 4	0.662	0.662
	LTE band 5	0.775	0.775
	LTE band 7	0.330	0.330
DTS	WIFI2.4G	0.050	0.050
NII	WIFI 5.2G	0.090	0.090
	WIFI 5.8G	0.022	0.022

This device is in compliance with Specific Absorption Rate (SAR) for general population/uncontrolled exposure limits (1.6 W/kg) specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-2005, and had been tested in accordance with the measurement methods and procedures specified in IEC-IEEE 62209-1528-2020.

<Highest Reported simultaneous SAR Summary>

Exposure Position	Classment Class	Highest Reported Simultaneous Transmission SAR _{1-g} (W/kg)
Body-worn (hotspot open)	PCB	0.878
	NII	





2. TEST ENVIRONMENT

2.1. Test Facility

The test facility is recognized, certified, or accredited by the following organizations:

Site Description

Sar Lab.

: NVLAP Accreditation Code is 600167-0.

FCC Designation Number is CN5024.

CAB identifier is CN0071.

CNAS Registration Number is L4595.

Test Firm Registration Number: 254912

2.2. Environmental conditions

During the measurement the environmental conditions were within the listed ranges:

Temperature:	18-25 ° C
Humidity:	40-65 %
Atmospheric pressure:	950-1050mbar

2.3. SAR Limits

FCC Limit (1g Tissue)

EXPOSURE LIMITS	SAR (W/kg)	
	(General Population / Uncontrolled Exposure Environment)	(Occupational / Controlled Exposure Environment)
Spatial Average(averaged over the whole body)	0.08	0.4
Spatial Peak(averaged over any 1 g of tissue)	1.6	8.0
Spatial Peak(hands/wrists/ feet/ankles averaged over 10 g)	4.0	20.0

Population/Uncontrolled Environments are defined as locations where there is the exposure of individual who have no knowledge or control of their exposure.

Occupational/Controlled Environments are defined as locations where there is exposure that may be incurred by people who are aware of the potential for exposure (i.e. as a result of employment or occupation).



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



2.4. Equipments Used during the Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Cal Date	Due Date
1	PC	Lenovo	G5005	MY42081102	N/A	N/A
2	SAR Measurement system	SATIMO	4014_01	SAR_4014_01	N/A	N/A
3	Signal Generator	Agilent	E4438C	MY49072627	2023-06-09	2024-06-08
4	S-parameter Network Analyzer	Agilent	8753ES	US38432944	2023-06-09	2024-06-08
5	Wideband Radio Communication Tester	R&S	CMW500	103818-1	2022-10-29	2023-10-28
6	E-Field PROBE	MVG	SSE2	SN 25/22 EPGO376	2023-06-22	2024-06-21
7	DIPOLE 750	SATIMO	SID 750	SN 07/14 DIP 0G750-302	2021-09-29	2024-09-28
8	DIPOLE 835	SATIMO	SID 835	SN 07/14 DIP 0G835-303	2021-09-29	2024-09-28
9	DIPOLE 1800	SATIMO	SID 1800	SN 07/14 DIP 1G800-301	2021-09-29	2024-09-28
10	DIPOLE 1900	SATIMO	SID 1900	SN 38/18 DIP 1G900-466	2021-09-22	2024-09-21
11	DIPOLE 2450	SATIMO	SID 2450	SN 07/14 DIP 2G450-306	2021-09-29	2024-09-28
12	DIPOLE 2600	SATIMO	SID 2600	SN 38/18 DIP 2G600-468	2021-09-22	2024-09-21
13	DIPOLE 5000-6000	SATIMO	SWG5500	SN 49/16 WGA 43	2021-09-22	2024-09-21
14	COMOSAR OPENCoaxial Probe	SATIMO	OCPG 68	SN 40/14 OCPG68	2022-10-29	2023-10-28
15	SAR Locator	SATIMO	VPS51	SN 40/14 VPS51	2022-10-29	2023-10-28
16	Communication Antenna	SATIMO	ANTA57	SN 39/14 ANTA57	2022-10-29	2023-10-28
17	FEATURE PHONEPOSITIONING DEVICE	SATIMO	MSH98	SN 40/14 MSH98	N/A	N/A
18	DUMMY PROBE	SATIMO	DP60	SN 03/14 DP60	N/A	N/A
19	SAM PHANTOM	SATIMO	SAM117	SN 40/14 SAM117	N/A	N/A
20	Liquid measurement Kit	HP	85033D	3423A03482	N/A	N/A
21	Power meter	Agilent	E4419B	MY45104493	2022-10-29	2023-10-28
22	Power meter	Agilent	E4419B	MY45100308	2022-10-29	2023-10-28
23	Power sensor	Agilent	E9301H	MY41495616	2022-10-29	2023-10-28
24	Power sensor	Agilent	E9301H	MY41495234	2022-10-29	2023-10-28
25	Directional Coupler	MCLI/USA	4426-20	03746	2023-06-09	2024-06-08

Note:

- 1) Per KDB865664D01 requirements for dipole calibration, the test laboratory has adopted three year extended calibration interval. Each measured dipole is expected to evaluate with following criteria at least on annual interval.
 - a) There is no physical damage on the dipole;
 - b) System check with specific dipole is within 10% of calibrated values;
 - c) The most recent return-loss results, measured at least annually, deviates by no more than 20% from the previous measurement;
 - d) The most recent measurement of the real or imaginary parts of the impedance, measured at least annually is within 5Ω from the previous measurement.
- 2) Network analyzer probe calibration against air, distilled water and a shorting block performed before measuring liquid parameters.



3. SAR MEASUREMENTS SYSTEM CONFIGURATION

3.1. SAR Measurement Set-up

The OPENSAR system for performing compliance tests consist of the following items:

A standard high precision 6-axis robot (KUKA) with controller and software.

KUKA Control Panel (KCP)

A dosimetric probe, i.e., an isotropic E-field probe optimized and calibrated for usage in tissue simulating liquid. The probe is equipped with a Video Positioning System(VPS).

The stress sensor is composed with mechanical and electronic when the electronic part detects a change on the electro-mechanical switch, It sends an “Emergency signal” to the robot controller that to stop robot’s moves

A computer operating Windows XP.

OPENSAR software


Remote control with teaches pendant and additional circuitry for robot safety such as warning lamps, etc.

The SAM phantom enabling testing left-hand right-hand and body usage.

The Position device for handheld EUT

Tissue simulating liquid mixed according to the given recipes .

System validation dipoles to validate the proper functioning of the system.





3.2. OPENSAR E-field Probe System

The SAR measurements were conducted with the dosimetric probe EPGO376 (manufactured by MVG), designed in the classical triangular configuration and optimized for dosimetric evaluation.

Probe Specification

Construction Symmetrical design with triangular core
Interleaved sensors
Built-in shielding against static charges
PEEK enclosure material (resistant to organic solvents, e.g., DGBE)


Calibration ISO/IEC 17025 calibration service available.

Frequency	450 MHz to 6 GHz; Linearity: 0.25dB(450 MHz to 6 GHz)
Directivity	0.25 dB in HSL (rotation around probe axis) 0.5 dB in tissue material (rotation normal to probe axis)
Dynamic Range	0.01W/kg to > 100 W/kg; Linearity: 0.25 dB
Dimensions	Overall length: 330 mm (Tip: 16mm) Tip diameter: 5 mm (Body: 8 mm) Distance from probe tip to sensor centers: 2.5 mm
Application	General dosimetry up to 6 GHz Dosimetry in strong gradient fields Compliance tests of Mobile Phones

Isotropic E-Field Probe

The isotropic E-Field probe has been fully calibrated and assessed for isotropicity, and boundary effect within a controlled environment. Depending on the frequency for which the probe is calibrated the method utilized for calibration will change.


The E-Field probe utilizes a triangular sensor arrangement as detailed in the diagram below:



3.3. Phantoms

The SAM Phantom SAM117 is constructed of a fiberglass shell integrated in a wooden table. The shape of the shell is in compliance with the specification set in IEEE 1528 and EN62209-1, EN62209-2. The phantom enables the dosimetric evaluation of left and right hand phone usage as well as body mounted usage at the flat phantom region. A cover prevents the evaporation of the liquid. Reference markings on the Phantom allow the complete setup of all predefined phantom positions and measurement grids by manually teaching three points in the robot.

System checking was performed using the flat section, whilst Head SAR tests used the left and right head profile sections. Body SAR testing also used the flat section between the head profiles.



SAM Twin Phantom

3.4. Device Holder

In combination with the Generic Twin Phantom SAM117, the Mounting Device enables the rotation of the mounted transmitter in spherical coordinates whereby the rotation points is the ear opening. The devices can be easily, accurately, and repeatedly positioned according to the FCC specifications. The device holder can be locked at different phantom locations (left head, right head, flat phantom).





Device holder supplied by SATIMO

3.5. Scanning Procedure

The procedure for assessing the peak spatial-average SAR value consists of the following steps

Power Reference Measurement

The reference and drift jobs are useful jobs for monitoring the power drift of the device under test in the batch process. Both jobs measure the field at a specified reference position, at a selectable distance from the phantom surface. The reference position can be either the selected section's grid reference point or a user point in this section. The reference job projects the selected point onto the phantom surface, orients the probe perpendicularly to the surface, and approaches the surface using the selected detection method.

Area Scan

The Area Scan is used as a fast scan in two dimensions to find the area of high field values before running a detailed measurement around the hot spot. Before starting the area scan a grid spacing of 15 mm x 15 mm is set. During the scan the distance of the probe to the phantom remains unchanged. After finishing area scan, the field maxima within a range of 2 dB will be ascertained.

	$\leq 3 \text{ GHz}$	$> 3 \text{ GHz}$
Maximum distance from closest measurement point (geometric center of probe sensors) to phantom surface	$5 \text{ mm} \pm 1 \text{ mm}$	$\frac{1}{2} \cdot \delta \cdot \ln(2) \text{ mm} \pm 0.5 \text{ mm}$
Maximum probe angle from probe axis to phantom surface normal at the measurement location	$30^\circ \pm 1^\circ$	$20^\circ \pm 1^\circ$
Maximum area scan spatial resolution: $\Delta x_{\text{Area}}, \Delta y_{\text{Area}}$	$\leq 2 \text{ GHz}: \leq 15 \text{ mm}$ $2 - 3 \text{ GHz}: \leq 12 \text{ mm}$	$3 - 4 \text{ GHz}: \leq 12 \text{ mm}$ $4 - 6 \text{ GHz}: \leq 10 \text{ mm}$
	When the x or y dimension of the test device, in the measurement plane orientation, is smaller than the above, the measurement resolution must be $\leq$ the corresponding x or y dimension of the test device with at least one measurement point on the test device.	

Zoom Scan

Zoom Scans are used to estimate the peak spatial SAR values within a cubic averaging volume containing 1 g and 10 g of simulated tissue. The default Zoom Scan is done by 7x7x7 points within a cube whose base is centered around the maxima found in the preceding area scan.





Maximum zoom scan spatial resolution: $\Delta x_{\text{Zoom}}, \Delta y_{\text{Zoom}}$			$\leq 2 \text{ GHz}: \leq 8 \text{ mm}$ $2 - 3 \text{ GHz}: \leq 5 \text{ mm}^*$	$3 - 4 \text{ GHz}: \leq 5 \text{ mm}^*$ $4 - 6 \text{ GHz}: \leq 4 \text{ mm}^*$
Maximum zoom scan spatial resolution, normal to phantom surface	uniform grid: $\Delta z_{\text{Zoom}}(n)$		$\leq 5 \text{ mm}$	$3 - 4 \text{ GHz}: \leq 4 \text{ mm}$ $4 - 5 \text{ GHz}: \leq 3 \text{ mm}$ $5 - 6 \text{ GHz}: \leq 2 \text{ mm}$
	graded grid	$\Delta z_{\text{Zoom}}(1)$: between 1 st two points closest to phantom surface	$\leq 4 \text{ mm}$	$3 - 4 \text{ GHz}: \leq 3 \text{ mm}$ $4 - 5 \text{ GHz}: \leq 2.5 \text{ mm}$ $5 - 6 \text{ GHz}: \leq 2 \text{ mm}$
		$\Delta z_{\text{Zoom}}(n>1)$: between subsequent points	$\leq 1.5 \cdot \Delta z_{\text{Zoom}}(n-1) \text{ mm}$	
Minimum zoom scan volume	x, y, z		$\geq 30 \text{ mm}$	$3 - 4 \text{ GHz}: \geq 28 \text{ mm}$ $4 - 5 \text{ GHz}: \geq 25 \text{ mm}$ $5 - 6 \text{ GHz}: \geq 22 \text{ mm}$

Note: δ is the penetration depth of a plane-wave at normal incidence to the tissue medium; see IEEE Std 1528-2013 for details.

* When zoom scan is required and the *reported* SAR from the *area scan based 1-g SAR estimation* procedures of KDB Publication 447498 is $\leq 1.4 \text{ W/kg}$, $\leq 8 \text{ mm}$, $\leq 7 \text{ mm}$ and $\leq 5 \text{ mm}$ zoom scan resolution may be applied, respectively, for 2 GHz to 3 GHz, 3 GHz to 4 GHz and 4 GHz to 6 GHz.





Power Drift measurement

The drift job measures the field at the same location as the most recent reference job within the same procedure, and with the same settings. The drift measurement gives the field difference in dB from the reading conducted within the last reference measurement. Several drift measurements are possible for one reference measurement. This allows a user to monitor the power drift of the device under test within a batch process. In the properties of the Drift job, the user can specify a limit for the drift and have OPENSAR software stop the measurements if this limit is exceeded.

3.6. Data Storage and Evaluation

Data Storage

The OPENSAR software stores the acquired data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of incorrect parameter settings. For example, if a measurement has been performed with a wrong crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be re-evaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type ([V/m], [A/m], [°C], [mW/g], [mW/cm²], [dBrel], etc.). Some of these units are not available in certain situations or show meaningless results, e.g., a SAR output in a lossless media will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

Data Evaluation

The OPENSAR software automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

Probe parameters:	- Sensitivity	Normi, ai0, ai1, ai2
	- Conversion factor	ConvFi
	- Diode compression point	Dcpi
Device parameters:	- Frequency	f
	- Crest factor	cf
Media parameters:	- Conductivity	σ
	- Density	ρ

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the OPENSAR components. In the direct measuring mode of the multimeter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power. The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot \frac{cf}{dcp_i}$$

With V_i = compensated signal of channel i ($i = x, y, z$)

U_i = input signal of channel i ($i = x, y, z$)

cf = crest factor of exciting field

dcp_i = diode compression point

From the compensated input signals the primary field data for each channel can be evaluated:



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



$$E - \text{fieldprobes} : \quad E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}$$

$$H - \text{fieldprobes} : \quad H_i = \sqrt{V_i} \cdot \frac{a_{i0} + a_{i1}f + a_{i2}f^2}{f}$$

With V_i = compensated signal of channel i ($i = x, y, z$)
 Norm_i = sensor sensitivity of channel i ($i = x, y, z$)
[mV/(V/m)²] for E-field Probes
 ConvF = sensitivity enhancement in solution
 a_{ij} = sensor sensitivity factors for H-field probes
 f = carrier frequency [GHz]
 E_i = electric field strength of channel i in V/m
 H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$SAR = E_{\text{tot}}^2 \cdot \frac{\sigma}{\rho \cdot 1'000}$$

with SAR = local specific absorption rate in mW/g
 E_{tot} = total field strength in V/m
 σ = conductivity in [mho/m] or [Siemens/m]
 ρ = equivalent tissue density in g/cm³

Note that the density is normally set to 1 (or 1.06), to account for actual brain density rather than the density of the simulation liquid.





3.7. Tissue Dielectric Parameters for Head and Body Phantoms

The liquid is consisted of water,salt,Glycol,Sugar,Preventol and Cellulose.The liquid has previously been proven to be suited for worst-case.It's satisfying the latest tissue dielectric parameters requirements proposed by the KDB865664.

The composition of the tissue simulating liquid

Frequency (MHz)	Bactericide	DGBE	HEC	NaCl	Sucrose	1,2-Propanediol	X100	Water	Conductivity	Permittivity
	%	%	%	%	%	%	%	%	σ	ϵ_r
750	/	/	/	0.79	/	64.81	/	34.40	0.97	41.8
835	/	/	/	0.79	/	64.81	/	34.40	0.97	41.8
900	/	/	/	0.79	/	64.81	/	34.40	0.97	41.8
1800	/	13.84	/	0.35	/	/	30.45	55.36	1.38	41.0
1900	/	13.84	/	0.35	/	/	30.45	55.36	1.38	41.0
2000	/	7.99	/	0.16	/	/	19.97	71.88	1.55	41.1
2450	/	7.99	/	0.16	/	/	19.97	71.88	1.88	40.3
2600	/	7.99	/	0.16	/	/	19.97	71.88	1.88	40.3

Target Frequency (MHz)	Head	
	ϵ_r	$\sigma(\text{S/m})$
450	43.5	0.87
750	41.9	0.89
835	41.5	0.90
900	41.5	0.97
1450	40.5	1.20
1640	40.2	1.31
1800	40.0	1.40
1900	40.0	1.40
2000	40.0	1.40
2450	39.2	1.80
2600	39.0	1.96
3000	38.5	2.40
5200	36.0	4.66
5800	35.3	5.27

3.8. Tissue equivalent liquid properties

Dielectric Performance of Head Tissue Simulating Liquid

Test Engineer: bob.yang									
Tissue Type	Measured Frequency (MHz)	Target Tissue		Measured Tissue				Liquid Temp.	Test Data
		σ	ϵ_r	σ	Dev.	ϵ_r	Dev.		
835H	835	0.90	41.50	0.87	-5.56%	42.65	7.59%	22.2	07/14/2023
1800H	1800	1.40	40.00	1.42	0.71%	39.11	-2.45%	22.5	07/17/2023
1900H	1900	1.40	40.00	1.43	2.14%	38.71	-3.05%	21.7	07/18/2023
2450H	2450	1.80	39.20	1.77	-0.56%	40.24	2.19%	22.3	07/19/2023
2600H	2600	1.96	39.00	1.98	1.02%	37.85	-2.67%	22.2	07/21/2023
5200H	5200	4.66	36.00	4.69	0.21%	35.14	-1.83%	23.0	07/24/2023
5800H	5800	5.27	35.30	5.29	6.07%	35.09	-0.45%	22.5	07/26/2023






3.9. System Check

The purpose of the system check is to verify that the system operates within its specifications at the device test frequency. The system check is simple check of repeatability to make sure that the system works correctly at the time of the compliance test;

System check results have to be equal or near the values determined during dipole calibration with the relevant liquids and test system ($\pm 10\%$).



The output power on dipole port must be calibrated to 20 dBm (100mW) before dipole is connected.



Photo of Dipole Setup



**Justification for Extended SAR Dipole Calibrations**

Referring to KDB 865664D01V01r04, if dipoles are verified in return loss ($< -20\text{dB}$, within 20% of prior calibration), and in impedance (within 5 ohm of prior calibration), the annual calibration is not necessary and the calibration interval can be extended. While calibration intervals not exceed 3 years.

SID835 SN 07/14 DIP 0G835-303 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-24.49		54.9		2.8	
2022-09-29	-24.17	-1.31	54.5	-0.4	2.6	-0.2

SID1800 SN 30/14 DIP 1G800-301 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-20.26		43.1		6.9	
2022-09-29	-20.13	-0.64	42.9	-0.2	6.7	-0.2

SID1900 SN 38/18 DIP 1G900-466 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-26.43		50.5		4.7	
2022-09-22	-26.33	-0.38	50.2	-0.3	4.5	-0.2

SID2450 SN 07/14 DIP 2G450-306 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-25.59		44.7		-1.1	
2022-09-29	-25.68	0.35	44.8	0.1	-1.0	0.1

SID2600 SN 38/18 DIP 2G600-468 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-29.14		49.2		3.4	
2022-09-22	-29.12	-0.07	49.1	-0.1	3.2	-0.1

SID5200 SN 49/16 DIP WGA43 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-8.59		19.38		13.50	
2022-09-22	-8.62	0.35	19.25	-0.13	13.47	-0.03

SID5800 SN 49/16 DIP WGA43 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-11.37		54.79		25.47	
2022-09-22	-11.42	0.44	54.68	-0.11	25.26	-0.21





Mixture Type	Frequency (MHz)	Power	SAR _{1g} (W/Kg)	SAR _{10g} (W/Kg)	Drift (%)	1W Target		Difference percentage		Liquid Temp	Date
						SAR _{1g} (W/Kg)	SAR _{10g} (W/Kg)	1g	10g		
Head	835	100 mW	0.951	0.638	-1.52	9.60	6.20	-0.94%	2.90%	22.2	07/14/2023
		Normalize to 1 Watt	9.51	6.38							
Head	1800	100 mW	3.831	2.044	0.97	38.13	20.20	0.47%	1.19%	22.5	07/17/2023
		Normalize to 1 Watt	38.31	20.44							
Head	1900	100 mW	3.965	2.087	-3.63	40.03	20.55	-0.95%	1.56%	21.7	07/18/2023
		Normalize to 1 Watt	39.65	20.87							
Head	2450	100 mW	5.435	2.557	-1.78	53.89	24.15	0.85%	5.88%	22.3	07/19/2023
		Normalize to 1 Watt	54.35	25.57							
Head	2600	100 mW	5.733	2.274	0.52	56.91	24.69	0.74%	-7.90%	22.2	07/21/2023
		Normalize to 1 Watt	57.33	22.74							
Head	5200	100 mW	17.218	5.900	-4.63	165.77	57.20	3.87%	3.15%	23.0	07/24/2023
		Normalize to 1 Watt	172.18	59.00							
Head	5800	100 mW	18.297	6.166	-1.89	186.77	62.84	-2.03%	-1.88%	22.5	07/26/2023
		Normalize to 1 Watt	182.97	61.66							





3.10. SAR measurement procedure

The measurement procedures are as follows:

3.10.1 Conducted power measurement

- For WWAN power measurement, use base station simulator connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- Read the WWAN RF power level from the base station simulator.
- For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously Transmission, at maximum RF power in each supported wireless interface and frequency band.
- Connect EUT RF port through RF cable to the power meter, and measure WLAN/BT output power.

3.10.2 GSM Test Configuration

SAR tests for GSM 850 and GSM 1900, a communication link is set up with a System Simulator (SS) by air link. Using CMU200 the power level is set to "5" for GSM 850, set to "0" for GSM 1900. Since the GPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 5. the EGPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 5.

SAR test reduction for GPRS and EDGE modes is determined by the source-based time-averaged output power specified for production units, including tune-up tolerance. The data mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested. GSM voice and GPRS data use GMSK, which is a constant amplitude modulation with minimal peak to average power difference within the time-slot burst. For EDGE, GMSK is used for MCS 1 – MCS 4 and 8-PSK is used for MCS 5 – MCS 9; where 8-PSK has an inherently higher peak-to-average power ratio. The GMSK and 8-PSK EDGE configurations are considered separately for SAR compliance. The GMSK EDGE configurations are grouped with GPRS and considered with respect to time-averaged maximum output power to determine compliance. The 3G SAR test reduction procedure is applied to 8-PSK EDGE with GMSK GPRS/EDGE as the primary mode.

3.10.3 UMTS Test Configuration

3G SAR Test Reduction Procedure

In the following procedures, the mode tested for SAR is referred to as the primary mode. The equivalent modes considered for SAR test reduction are denoted as secondary modes. Both primary and secondary modes must be in the same frequency band. When the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq \frac{1}{4}$ dB higher than the primary mode or when the highest reported SAR of the primary mode is scaled by the ratio of specified maximum output power and tune-up tolerance of secondary to primary mode and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for the secondary mode. This is referred to as the 3G SAR test reduction procedure in the following SAR test guidance, where the primary mode is identified in the applicable wireless mode test procedures and the secondary mode is wireless mode being considered for SAR test reduction by that procedure. When the 3G SAR test reduction procedure is not satisfied, it is identified as "otherwise" in the applicable procedures; SAR measurement is required for the secondary mode.

Output power Verification

Maximum output power is verified on the high, middle and low channels according to procedures described in section 5.2 of 3GPP TS 34.121, using the appropriate RMC or AMR with TPC (transmit power control) set to all "1's" for WCDMA/HSDPA or by applying the required inner loop power control procedures to maintain maximum output power while HSUPA is active. Results for all applicable physical channel configurations (DPCCH, DPDCH and spreading codes, HSDPA, HSPA) are required in the SAR report. All configurations that are not supported by the handset or cannot be measured due to technical or equipment limitations must be clearly identified.

Head SAR

SAR for next to the ear head exposure is measured using a 12.2 kbps RMC with TPC bits configured to all "1's". The 3G SAR test reduction procedure is applied to AMR configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for 12.2 kbps AMR in 3.4 kbps SRB (signaling radio bearer) using the highest reported SAR configuration in 12.2 kbps RMC for head exposure.





1) Body-Worn Accessory SAR

SAR for body-worn accessory configurations is measured using a 12.2 kbps RMC with TPC bits configured to all "1's". The 3G SAR test reduction procedure is applied to other spreading codes and multiple DPDCHn configurations supported by the handset with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured using an applicable RMC configuration with the corresponding spreading code or DPDCHn, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When more than 2 DPDCHn are supported by the handset, it may be necessary to configure additional DPDCHn using FTM (Factory Test Mode) or other chipset based test approaches with parameters similar to those used in 384 kbps and 768 kbps RMC.

2) Handsets with Release 5 HSDPA

The 3G SAR test reduction procedure is applied to HSDPA body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSDPA using the HSDPA body SAR procedures in the "Release 5 HSDPA Data Devices" section of this document, for the highest reported SAR body-worn accessory exposure configuration in 12.2 kbps RMC. Handsets with both HSDPA and HSUPA are tested according to Release 6 HSPA test procedures.

HSDPA should be configured according to the UE category of a test device. The number of HSDSCH/ HS-PDSCHs, HARQ processes, minimum inter-TTI interval, transport block sizes and RV coding sequence are defined by the H-set. To maintain a consistent test configuration and stable transmission conditions, QPSK is used in the H-set for SAR testing. HS-DPCCH should be configured with a CQI feedback cycle of 4 ms with a CQI repetition factor of 2 to maintain a constant rate of active CQI slots. DPCCH and DPDCH gain factors (β_c , β_d), and HS-DPCCH power offset parameters (Δ_{ACK} , Δ_{NACK} , Δ_{CQI}) should be set according to values indicated in the Table below. The CQI value is determined by the UE category, transport block size, number of HS-PDSCHs and modulation used in the H-set.

Table 2: Subtests for UMTS Release 5 HSDPA

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	β_{hs} (note 1, note 2)	CM(dB) (note 3)	MPR(dB)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (note 4)	15/15 (note 4)	64	12/15 (note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5

Note1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$
Note2: CM=1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$.
Note3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TFC1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

HSUPA Test Configuration

The 3G SAR test reduction procedure is applied to HSPA (HSUPA/HSDPA with RMC) body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSPA using the HSPA body SAR procedures in the "Release 6 HSPA Data Devices" section of this document, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When VOIP is applicable for next to the ear head exposure in HSPA, the 3G SAR test reduction procedure is applied to HSPA with 12.2 kbps RMC as the primary mode; otherwise, the same HSPA configuration used for body-worn accessory measurements is tested for next to the ear head exposure.

Due to inner loop power control requirements in HSPA, a communication test set is required for output power and SAR tests. The 12.2 kbps RMC, FRC H-set 1 and E-DCH configurations for HSPA are configured according to the β values indicated in Table 2 and other applicable procedures described in the 'WCDMA Handset' and 'Release 5 HSDPA Data Devices' sections of this document.

Table 3: Sub-Test 5 Setup for Release 6 HSUPA

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(1)}$	β_{ec}	β_{ed}	β_{ed} (SF)	β_{ed} (codes)	CM ⁽²⁾ (dB)	MPR (dB)	AG ⁽⁴⁾ Index	E-TFCI
1	11/15 ⁽³⁾	15/15 ⁽³⁾	64	11/15 ⁽³⁾	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1} 47/15$ $\beta_{ed2} 47/15$	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 ⁽⁴⁾	15/15 ⁽⁴⁾	64	15/15 ⁽⁴⁾	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Figure 5.1g.

Note 6: β_{ed} can not be set directly; it is set by Absolute Grant Value.

3.10.4 WIFI Test Configuration

The SAR measurement and test reduction procedures are structured according to either the DSSS or OFDM transmission mode configurations used in each standalone frequency band and aggregated band. For devices that operate in exposure configurations that require multiple test positions, additional SAR test reduction may be applied. The maximum output power specified for production units, including tune-up tolerance, are used to determine initial SAR test requirements for the 802.11 transmission modes in a frequency band. SAR is measured using the highest measured maximum output power channel for the initial test configuration. SAR measurement and test reduction for the remaining 802.11 modes and test channels are determined according to measured or specified maximum output power and reported SAR of the initial measurements. The general test reduction and SAR measurement approaches are summarized in the following:

1. The maximum output power specified for production units are determined for all applicable 802.11 transmission modes in each standalone and aggregated frequency band. Maximum output power is measured for the highest maximum output power configuration(s) in each frequency band according to the default power measurement procedures.
2. For OFDM transmission configurations in the 2.4 GHz and 5 GHz bands, an "initial test configuration" is first determined for each standalone and aggregated frequency band according to the maximum output power and tune-up tolerance specified for production units.
 - a. When the same maximum power is specified for multiple transmission modes in a frequency band, the largest channel bandwidth, lowest order modulation, lowest data rate and lowest order 802.11a/g/n/ac mode is used for SAR measurement, on the highest measured output power channel in the initial test configuration, for each frequency band.
 - b. SAR is measured for OFDM configurations using the initial test configuration procedures. Additional frequency band specific SAR test reduction may be considered for individual frequency bands
 - c. Depending on the reported SAR of the highest maximum output power channel tested in the initial test configuration, SAR test reduction may apply to subsequent highest output channels in the initial test configuration to reduce the number of SAR measurements.
3. The Initial test configuration does not apply to DSSS. The 2.4 GHz band SAR test requirements and 802.11b DSSS procedures are used to establish the transmission configurations required for SAR measurement.
4. An "initial test position" is applied to further reduce the number of SAR tests for devices operating in next to the ear, UMPC mini-tablet or hotspot mode exposure configurations that require multiple test positions.
 - a. SAR is measured for 802.11b according to the 2.4 GHz DSSS procedure using the exposure condition established by the initial test position.
 - b. SAR is measured for 2.4 GHz and 5 GHz OFDM configurations using the initial test configuration. 802.11b/g/n operating modes are tested independently according to the service requirements in each frequency band. 802.11b/g/n modes are tested on the maximum average output channel.
5. The Initial test position does not apply to devices that require a fixed exposure test position. SAR is measured in a fixed exposure test position for these devices in 802.11b according to the 2.4 GHz DSSS procedure or in 2.4 GHz and 5 GHz OFDM configurations using the initial test configuration procedures.
6. The "subsequent test configuration" procedures are applied to determine if additional SAR measurements are required for the remaining OFDM transmission modes that have not been tested in the initial test





configuration. SAR test exclusion is determined according to reported SAR in the initial test configuration and maximum output power specified or measured for these other OFDM configurations.

2.4 GHz and 5GHz SAR Procedures

Separate SAR procedures are applied to DSSS and OFDM configurations in the 2.4 GHz band to simplify DSSS test requirements. For 802.11b DSSS SAR measurements, DSSS SAR procedure applies to fixed exposure test position and initial test position procedure applies to multiple exposure test positions. When SAR measurement is required for an OFDM configuration, the initial test configuration, subsequent test configuration and initial test position procedures are applied. The SAR test exclusion requirements for 802.11g/n OFDM configurations are described in section 5.2.2.

1. 802.11b DSSS SAR Test Requirements

SAR is measured for 2.4 GHz 802.11b DSSS using either a fixed test position or, when applicable, the initial test position procedure. SAR test reduction is determined according to the following:

- When the reported SAR of the highest measured maximum output power channel (section 3.1) for the exposure configuration is ≤ 0.8 W/kg, no further SAR testing is required for 802.11b DSSS in that exposure configuration.
- When the reported SAR is > 0.8 W/kg, SAR is required for that exposure configuration using the next highest measured output power channel. When any reported SAR is > 1.2 W/kg, SAR is required for the third channel; i.e., all channels require testing.

1. 2.4 GHz 802.11g/n OFDM SAR Test Exclusion Requirements

When SAR measurement is required for 2.4 GHz 802.11g/n OFDM configurations, the measurement and test reduction procedures for OFDM are applied (section 5.3). SAR is not required for the following 2.4 GHz OFDM conditions.

- When KDB Publication 447498 SAR test exclusion applies to the OFDM configuration
- When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.

2. SAR Test Requirements for OFDM Configurations

When SAR measurement is required for 802.11 a/g/n/ac OFDM configurations, each standalone and frequency aggregated band is considered separately for SAR test reduction. When the same transmitter and antenna(s) are used for U-NII-1 and U-NII-2A bands, additional SAR test reduction applies. When band gap channels between U-NII-2C band and 5.8 GHz U-NII-3 or §15.247 band are supported, the highest maximum output power transmission mode configuration and maximum output power channel across the bands must be used to determine SAR test reduction, according to the initial test configuration and subsequent test configuration requirements.20 In applying the initial test configuration and subsequent test configuration procedures, the 802.11 transmission configuration with the highest specified maximum output power and the channel within a test configuration with the highest measured maximum output power should be clearly distinguished to apply the procedures.

3. OFDM Transmission Mode SAR Test Configuration and Channel Selection Requirements

The initial test configuration for 2.4 GHz and 5 GHz OFDM transmission modes is determined by the 802.11 configuration with the highest maximum output power specified for production units, including tune-up tolerance, in each standalone and aggregated frequency band. SAR for the initial test configuration is measured using the highest maximum output power channel determined by the default power measurement procedures (section 4). When multiple configurations in a frequency band have the same specified maximum output power, the initial test configuration is determined according to the following steps applied sequentially.

- The largest channel bandwidth configuration is selected among the multiple configurations with the same specified maximum output power.
- If multiple configurations have the same specified maximum output power and largest channel bandwidth, the lowest order modulation among the largest channel bandwidth configurations is selected.
- If multiple configurations have the same specified maximum output power, largest channel bandwidth and lowest order modulation, the lowest data rate configuration among these configurations is selected.
- When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.

After an initial test configuration is determined, if multiple test channels have the same measured maximum output power, the channel chosen for SAR measurement is determined according to the following. These channel selection procedures apply to both the initial test configuration and subsequent test configuration(s), with respect to the default power measurement procedures or additional power measurements required for





further SAR test reduction. The same procedures also apply to subsequent highest output power channel(s) selection.

- a. Channels with measured maximum output power within $\frac{1}{4}$ dB of each other are considered to have the same maximum output.
- b. When there are multiple test channels with the same measured maximum output power, the channel closest to mid-band frequency is selected for SAR measurement.
- c. When there are multiple test channels with the same measured maximum output power and equal separation from mid-band frequency; for example, high and low channels or two mid-band channels, the higher frequency (number) channel is selected for SAR measurement.

Initial Test Configuration Procedures

An initial test configuration is determined for OFDM transmission modes according to the channel bandwidth, modulation and data rate combination(s) with the highest maximum output power specified for production units in each standalone and aggregated frequency band. SAR is measured using the highest measured maximum output power channel. For configurations with the same specified or measured maximum output power, additional transmission mode and test channel selection procedures are required (see section 5.3.2). SAR test reduction of subsequent highest output test channels is based on the reported SAR of the initial test configuration.

For next to the ear, hotspot mode and UMC mini-tablet exposure configurations where multiple test positions are required, the initial test position procedure is applied to minimize the number of test positions required for SAR measurement using the initial test configuration transmission mode.²³ For fixed exposure conditions that do not have multiple SAR test positions, SAR is measured in the transmission mode determined by the initial test configuration. When the reported SAR of the initial test configuration is > 0.8 W/kg, SAR measurement is required for the subsequent next highest measured output power channel(s) in the initial test configuration until the reported SAR is ≤ 1.2 W/kg or all required channels are tested.

4. Subsequent Test Configuration Procedures

SAR measurement requirements for the remaining 802.11 transmission mode configurations that have not been tested in the initial test configuration are determined separately for each standalone and aggregated frequency band, in each exposure condition, according to the maximum output power specified for production units. The initial test position procedure is applied to next to the ear, UMPC mini-tablet and hotspot mode configurations. When the same maximum output power is specified for multiple transmission modes, the procedures in section 5.3.2 are applied to determine the test configuration. Additional power measurements may be required to determine if SAR measurements are required for subsequent highest output power channels in a subsequent test configuration. The subsequent test configuration and SAR measurement procedures are described in the following.

- a. When SAR test exclusion provisions of KDB Publication 447498 are applicable and SAR measurement is not required for the initial test configuration, SAR is also not required for the next highest maximum output power transmission mode subsequent test configuration(s) in that frequency band or aggregated band and exposure configuration.
 - b. When the highest reported SAR for the initial test configuration (when applicable, include subsequent highest output channels), according to the initial test position or fixed exposure position requirements, is adjusted by the ratio of the subsequent test configuration to initial test configuration specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for that subsequent test configuration.
 - c. The number of channels in the initial test configuration and subsequent test configuration can be different due to differences in channel bandwidth. When SAR measurement is required for a subsequent test configuration and the channel bandwidth is smaller than that in the initial test configuration, all channels in the subsequent test configuration that overlap with the larger bandwidth channel tested in the initial test configuration should be used to determine the highest maximum output power channel. This step requires additional power measurement to identify the highest maximum output power channel in the subsequent test configuration to determine SAR test reduction.
- 1). SAR should first be measured for the channel with highest measured output power in the subsequent test configuration.
 - 2). SAR for subsequent highest measured maximum output power channels in the subsequent test configuration is required only when the reported SAR of the preceding higher maximum output power channel(s) in the subsequent test configuration is > 1.2 W/kg or until all required channels are tested.
- a) For channels with the same measured maximum output power, SAR should be measured using the channel closest to the center frequency of the larger channel bandwidth channel in the initial test configuration.





- d. SAR measurements for the remaining highest specified maximum output power OFDM transmission mode configurations that have not been tested in the initial test configuration (highest maximum output) or subsequent test configuration(s) (subsequent next highest maximum output power) is determined by applying the subsequent test configuration procedures in this section to the remaining configurations according to the following:
- 1) replace “subsequent test configuration” with “next subsequent test configuration” (i.e., subsequent next highest specified maximum output power configuration)
 - 2) replace “initial test configuration” with “all tested higher output power configurations.”

3.11. Power Reduction

The product without any power reduction.

3.12. Power Drift

To control the output power stability during the SAR test, SAR system calculates the power drift by measuring the E-field at the same location at the beginning and at the end of the measurement for each test position. This ensures that the power drift during one measurement is within 5%.





4. TEST CONDITIONS AND RESULTS

4.1. Conducted Power Results

According KDB 447498D01 General RF Exposure Guidance v06 Section 4.1 2) states that “Unless it is specified differently in the published RF exposure KDB procedures, these requirements also apply to test reduction and test exclusion considerations. Time-averaged maximum conducted output power applies to SAR and, as required by § 2.1091(c), time-averaged ERP applies to MPE. When an antenna port is not available on the device to support conducted power measurement, such as FRS and certain Part 15 transmitters with built-in integral antennas, the maximum output power allowed for production units should be used to determine RF exposure test exclusion and compliance.”

<GSM Conducted Power>

General Note:

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. According to October 2013TCB Workshop, for GSM / GPRS / EGPRS, the number of time slots to test for SAR should correspond to the highest frame-average maximum output power configuration, considering the possibility of e.g. 3rd party VoIP operation for head and body-worn SAR testing, the EUT was set in GPRS (4Tx slot) for GSM850/GSM1900 band due to their highest frame-average power.
3. For hotspot mode SAR testing, GPRS should be evaluated, therefore the EUT was set in GPRS (4 Tx slots) for GSM850/GSM1900 band due to its highest frame-average power.

Conducted power measurement results for GSM850/PCS1900

GSM 850		Tune -up	Burst Conducted power (dBm)			Division Factors	Tune- up	Average power (dBm)		
			Channel/Frequency(MHz)					Channel/Frequency(MHz)		
		Max	128/ 824.2	190/ 836.6	251/ 848.8		Max	128/ 824.2	190/ 836.6	251/8 48.8
GSM		33.00	32.68	32.73	32.68	-9.03dB	23.97	23.65	23.70	23.65
GPRS (GMSK)	1TX slot	33.00	32.55	32.56	32.49	-9.03dB	23.97	23.52	23.53	23.46
	2TX slot	31.00	30.96	30.99	30.97	-6.02dB	24.98	24.94	24.97	24.95
	3TX slot	29.50	29.47	29.49	29.45	-4.26dB	25.24	25.21	25.23	25.19
	4TX slot	28.00	27.96	27.99	27.97	-3.01dB	24.99	24.95	24.98	24.96
EGPRS (8PSK)	1TX slot	26.50	25.96	26.01	25.96	-9.03dB	17.47	16.93	16.98	16.93
	2TX slot	24.50	24.47	24.48	24.44	-6.02dB	18.48	18.45	18.46	18.42
	3TX slot	23.50	23.01	23.00	22.99	-4.26dB	19.24	18.75	18.74	18.73
	4TX slot	22.00	21.46	21.52	21.46	-3.01dB	18.99	18.45	18.51	18.45
GSM 1900		Tune -up	Burst Conducted power (dBm)			Division Factors	Tune- up	Average power (dBm)		
			Channel/Frequency(MHz)					Channel/Frequency(MHz)		
		Max	512/ 1850.2	661/ 1880	810/ 1909.8		Max.	512/ 1850.2	661/ 1880	810/ 1909. 8
GSM		30.00	29.66	29.71	29.67	-9.03dB	20.97	20.63	20.68	20.64
GPRS (GMSK)	1TX slot	30.00	29.51	29.53	29.50	-9.03dB	20.97	20.48	20.50	20.47
	2TX slot	28.00	27.96	28.00	27.96	-6.02dB	21.98	21.94	21.98	21.94
	3TX slot	26.50	26.46	26.47	26.45	-4.26dB	22.24	22.20	22.21	22.19
	4TX slot	25.50	25.00	25.03	24.97	-3.01dB	22.49	21.99	22.02	21.96
EGPRS (8PSK)	1TX slot	26.00	25.44	25.53	25.43	-9.03dB	16.97	16.41	16.50	16.40
	2TX slot	24.50	23.96	24.03	23.96	-6.02dB	18.48	17.94	18.01	17.94
	3TX slot	23.00	22.44	22.51	22.47	-4.26dB	18.74	18.18	18.25	18.21
	4TX slot	21.00	20.99	21.00	20.95	-3.01dB	17.99	17.98	17.99	17.94

Notes:

1. Division Factors

To average the power, the division factor is as follows:

1TX-slot = 1 transmit time slot out of 8 time slots=> conducted power divided by (8/1) => -9.00dB

2TX-slots = 2 transmit time slots out of 8 time slots=> conducted power divided by (8/2) => -6.00dB

3TX-slots = 3 transmit time slots out of 8 time slots=> conducted power divided by (8/3) => -4.26dB

4TX-slots = 4 transmit time slots out of 8 time slots=> conducted power divided by (8/4) => -3.00dB



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



2. According to the conducted power as above, the GPRS measurements are performed with 3Txslot for GPRS850 and 4Txslot GPRS1900.

<UMTS Conducted Power>

The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification. A summary of these settings are illustrated below:

HSDPA Setup Configuration:

- The EUT was connected to Base Station E5515C referred to the Setup Configuration.
- The RF path losses were compensated into the measurements.
- A call was established between EUT and Base Station with following setting:
 - Set Gain Factors (β_c and β_d) and parameters were set according to each
 - Specific sub-test in the following table, C10.1.4, quoted from the TS 34.121
 - Set RMC 12.2Kbps + HSDPA mode.
 - Set Cell Power = -86 dBm
 - Set HS-DSCH Configuration Type to FRC (H-set 1, QPSK)
 - Select HSDPA Uplink Parameters
 - Set Delta ACK, Delta NACK and Delta CQI = 8
 - Set Ack-Nack Repetition Factor to 3
 - Set CQI Feedback Cycle (k) to 4 ms
 - Set CQI Repetition Factor to 2
 - Power Ctrl Mode = All Up bits
- The transmitted maximum output power was recorded.

Table C.10.1.4: β values for transmitter characteristics tests with HS-DPCCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1, Note 2)	CM (dB) (Note 3)	MPR (dB) (Note 3)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (Note 4)	15/15 (Note 4)	64	12/15 (Note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5
Note 1: Δ_{ACK}, Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$. Note 2: For the HS-DPCCH power mask requirement test in clause 5.2C, 5.7A, and the Error Vector Magnitude (EVM) with HS-DPCCH test in clause 5.13.1A, and HSDPA EVM with phase discontinuity in clause 5.13.1AA, Δ_{ACK} and $\Delta_{NACK} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$, and $\Delta_{CQI} = 24/15$ with $\beta_{HS} = 24/15 * \beta_c$. Note 3: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{HS}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH and HS-DPCCH the MPR is based on the relative CM difference. This is applicable for only UEs that support HSDPA in release 6 and later releases. Note 4: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.							

Setup Configuration

HSUPA Setup Configuration:

- The EUT was connected to Base Station R&S CMU200 referred to the Setup Configuration.
- The RF path losses were compensated into the measurements.
- A call was established between EUT and Base Station with following setting * :
 - Call Configs = 5.2B, 5.9B, 5.10B, and 5.13.2B with QPSK
 - Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.3, quoted from the TS 34.121
 - Set Cell Power = -86 dBm
 - Set Channel Type = 12.2k + HSPA
 - Set UE Target Power
 - Power Ctrl Mode= Alternating bits
 - Set and observe the E-TFCI
 - Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1, and other subtest's E-TFCI
- The transmitted maximum output power was recorded.



Table C.11.1.3: β values for transmitter characteristics tests with HS-DPCCH and E-DCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1)	β_{ec}	β_{ed} (Note 5) (Note 6)	β_{ed} (SF)	β_{ed} (Codes)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 6)	E-TFCI
1	11/15 (Note 3)	15/15 (Note 3)	64	11/15 (Note 3)	22/15	209/25	1309/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	β_{ed1} : 47/15 β_{ed2} : 47/15	4 4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 (Note 4)	15/15 (Note 4)	64	15/15 (Note 4)	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: In case of testing by UE using E-DPDCH Physical Layer category 1, Sub-test 3 is omitted according to TS25.306 Table 5.1g.

Note 6: β_{ed} can not be set directly, it is set by Absolute Grant Value.

General Note

1. Per KDB 941225 D01, RMC 12.2kbps setting is used to evaluate SAR. If AMR 12.2kbps power is < 0.25dB higher than RMC 12.2kbps, SAR tests with AMR 12.2kbps can be excluded.
2. By design, AMR and HSDPA/HSUPA RF power will not be larger than RMC 12.2kbps, detailed information is included in Tune-up Procure exhibit.
3. It is expected by the manufacturer that MPR for some HSDPA/HSUPA subtests may differ from the specification of 3GPP, according to the chipset implementation in this model. The implementation and expected deviation are detailed in tune-up procedure exhibit.

Conducted Power Measurement Results(WCDMA Band II/V)

Item	Band	FDD Band V result (dBm)			FDD Band II result (dBm)		
		Test Channel			Test Channel		
		4132/ 826.4	4183/ 836.6	4233/ 846.6	9262/ 1852.4	9400/ 1880	9538/ 1907.6
RMC	12.2kbps	23.39	23.51	23.43	23.51	23.65	23.49
HSDPA	Subtest 1	22.90	22.78	22.85	22.93	22.91	22.81
	Subtest 2	22.73	22.86	22.83	22.71	22.76	22.82
	Subtest 3	22.79	22.87	22.87	22.80	22.84	22.81
	Subtest 4	22.85	22.71	22.79	22.81	22.81	22.71
HSUPA	Subtest 1	22.71	22.78	22.84	22.81	22.78	22.76
	Subtest 2	22.72	22.74	22.80	22.88	22.72	22.80
	Subtest 3	22.76	22.78	22.87	22.80	22.72	22.74
	Subtest 4	22.76	22.87	22.80	22.75	22.76	22.83
	Subtest 5	22.71	22.71	22.72	22.74	22.71	22.85

Note:1. When the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq 1/2$ dB higher than the primary mode (RMC12.2kbps) or when the highest reported SAR of the primary mode is scaled by the ratio of specified maximum output power and tune-up tolerance of secondary to primary mode and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for the secondary mode.





LTE Band2

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band2	1.4MHz	QPSK	18607	1RB#0	21.88	PASS
Band2	1.4MHz	16QAM	18607	1RB#0	21.09	PASS
Band2	1.4MHz	QPSK	18607	1RB#2	22.10	PASS
Band2	1.4MHz	16QAM	18607	1RB#2	21.21	PASS
Band2	1.4MHz	QPSK	18607	1RB#5	21.90	PASS
Band2	1.4MHz	16QAM	18607	1RB#5	21.07	PASS
Band2	1.4MHz	QPSK	18607	3RB#0	22.03	PASS
Band2	1.4MHz	16QAM	18607	3RB#0	20.88	PASS
Band2	1.4MHz	QPSK	18607	3RB#1	22.02	PASS
Band2	1.4MHz	16QAM	18607	3RB#1	20.86	PASS
Band2	1.4MHz	QPSK	18607	3RB#3	22.02	PASS
Band2	1.4MHz	16QAM	18607	3RB#3	20.88	PASS
Band2	1.4MHz	QPSK	18607	6RB#0	20.96	PASS
Band2	1.4MHz	16QAM	18607	6RB#0	20.01	PASS
Band2	1.4MHz	QPSK	18900	1RB#0	21.94	PASS
Band2	1.4MHz	16QAM	18900	1RB#0	21.04	PASS
Band2	1.4MHz	QPSK	18900	1RB#2	22.07	PASS
Band2	1.4MHz	16QAM	18900	1RB#2	21.19	PASS
Band2	1.4MHz	QPSK	18900	1RB#5	21.92	PASS
Band2	1.4MHz	16QAM	18900	1RB#5	21.06	PASS
Band2	1.4MHz	QPSK	18900	3RB#0	22.03	PASS
Band2	1.4MHz	16QAM	18900	3RB#0	20.89	PASS
Band2	1.4MHz	QPSK	18900	3RB#1	22.02	PASS
Band2	1.4MHz	16QAM	18900	3RB#1	20.90	PASS
Band2	1.4MHz	QPSK	18900	3RB#3	22.07	PASS
Band2	1.4MHz	16QAM	18900	3RB#3	20.87	PASS
Band2	1.4MHz	QPSK	18900	6RB#0	20.89	PASS
Band2	1.4MHz	16QAM	18900	6RB#0	19.97	PASS
Band2	1.4MHz	QPSK	19193	1RB#0	21.48	PASS
Band2	1.4MHz	16QAM	19193	1RB#0	20.59	PASS
Band2	1.4MHz	QPSK	19193	1RB#2	21.58	PASS
Band2	1.4MHz	16QAM	19193	1RB#2	20.80	PASS
Band2	1.4MHz	QPSK	19193	1RB#5	21.42	PASS
Band2	1.4MHz	16QAM	19193	1RB#5	20.60	PASS
Band2	1.4MHz	QPSK	19193	3RB#0	21.55	PASS
Band2	1.4MHz	16QAM	19193	3RB#0	20.44	PASS
Band2	1.4MHz	QPSK	19193	3RB#1	21.53	PASS
Band2	1.4MHz	16QAM	19193	3RB#1	20.42	PASS
Band2	1.4MHz	QPSK	19193	3RB#3	21.58	PASS
Band2	1.4MHz	16QAM	19193	3RB#3	20.41	PASS
Band2	1.4MHz	QPSK	19193	6RB#0	20.44	PASS
Band2	1.4MHz	16QAM	19193	6RB#0	19.38	PASS
Band2	3MHz	QPSK	18615	1RB#0	21.60	PASS
Band2	3MHz	16QAM	18615	1RB#0	20.75	PASS
Band2	3MHz	QPSK	18615	1RB#8	21.51	PASS
Band2	3MHz	16QAM	18615	1RB#8	20.76	PASS
Band2	3MHz	QPSK	18615	1RB#14	21.59	PASS
Band2	3MHz	16QAM	18615	1RB#14	20.82	PASS
Band2	3MHz	QPSK	18615	8RB#0	20.59	PASS
Band2	3MHz	16QAM	18615	8RB#0	19.79	PASS
Band2	3MHz	QPSK	18615	8RB#4	20.90	PASS
Band2	3MHz	16QAM	18615	8RB#4	20.11	PASS
Band2	3MHz	QPSK	18615	8RB#7	21.03	PASS
Band2	3MHz	16QAM	18615	8RB#7	19.89	PASS
Band2	3MHz	QPSK	18615	15RB#0	20.82	PASS
Band2	3MHz	16QAM	18615	15RB#0	19.94	PASS
Band2	3MHz	QPSK	18900	1RB#0	21.99	PASS
Band2	3MHz	16QAM	18900	1RB#0	21.20	PASS
Band2	3MHz	QPSK	18900	1RB#8	21.84	PASS
Band2	3MHz	16QAM	18900	1RB#8	21.05	PASS
Band2	3MHz	QPSK	18900	1RB#14	21.69	PASS
Band2	3MHz	16QAM	18900	1RB#14	21.05	PASS
Band2	3MHz	QPSK	18900	8RB#0	20.73	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band2	3MHz	16QAM	18900	8RB#0	20.04	PASS
Band2	3MHz	QPSK	18900	8RB#4	20.75	PASS
Band2	3MHz	16QAM	18900	8RB#4	19.85	PASS
Band2	3MHz	QPSK	18900	8RB#7	20.87	PASS
Band2	3MHz	16QAM	18900	8RB#7	20.09	PASS
Band2	3MHz	QPSK	18900	15RB#0	21.03	PASS
Band2	3MHz	16QAM	18900	15RB#0	19.96	PASS
Band2	3MHz	QPSK	19185	1RB#0	21.26	PASS
Band2	3MHz	16QAM	19185	1RB#0	20.31	PASS
Band2	3MHz	QPSK	19185	1RB#8	21.11	PASS
Band2	3MHz	16QAM	19185	1RB#8	20.27	PASS
Band2	3MHz	QPSK	19185	1RB#14	21.01	PASS
Band2	3MHz	16QAM	19185	1RB#14	20.18	PASS
Band2	3MHz	QPSK	19185	8RB#0	20.10	PASS
Band2	3MHz	16QAM	19185	8RB#0	19.17	PASS
Band2	3MHz	QPSK	19185	8RB#4	20.10	PASS
Band2	3MHz	16QAM	19185	8RB#4	19.15	PASS
Band2	3MHz	QPSK	19185	8RB#7	20.05	PASS
Band2	3MHz	16QAM	19185	8RB#7	19.10	PASS
Band2	3MHz	QPSK	19185	15RB#0	20.07	PASS
Band2	3MHz	16QAM	19185	15RB#0	19.01	PASS
Band2	5MHz	QPSK	18625	1RB#0	21.42	PASS
Band2	5MHz	16QAM	18625	1RB#0	20.42	PASS
Band2	5MHz	QPSK	18625	1RB#12	21.61	PASS
Band2	5MHz	16QAM	18625	1RB#12	20.53	PASS
Band2	5MHz	QPSK	18625	1RB#24	21.47	PASS
Band2	5MHz	16QAM	18625	1RB#24	20.45	PASS
Band2	5MHz	QPSK	18625	12RB#0	20.40	PASS
Band2	5MHz	16QAM	18625	12RB#0	19.44	PASS
Band2	5MHz	QPSK	18625	12RB#6	20.46	PASS
Band2	5MHz	16QAM	18625	12RB#6	19.63	PASS
Band2	5MHz	QPSK	18625	12RB#13	20.58	PASS
Band2	5MHz	16QAM	18625	12RB#13	19.63	PASS
Band2	5MHz	QPSK	18625	25RB#0	20.51	PASS
Band2	5MHz	16QAM	18625	25RB#0	19.60	PASS
Band2	5MHz	QPSK	18900	1RB#0	21.94	PASS
Band2	5MHz	16QAM	18900	1RB#0	20.62	PASS
Band2	5MHz	QPSK	18900	1RB#12	22.08	PASS
Band2	5MHz	16QAM	18900	1RB#12	20.83	PASS
Band2	5MHz	QPSK	18900	1RB#24	21.48	PASS
Band2	5MHz	16QAM	18900	1RB#24	20.48	PASS
Band2	5MHz	QPSK	18900	12RB#0	20.71	PASS
Band2	5MHz	16QAM	18900	12RB#0	19.81	PASS
Band2	5MHz	QPSK	18900	12RB#6	20.54	PASS
Band2	5MHz	16QAM	18900	12RB#6	20.02	PASS
Band2	5MHz	QPSK	18900	12RB#13	20.84	PASS
Band2	5MHz	16QAM	18900	12RB#13	19.63	PASS
Band2	5MHz	QPSK	18900	25RB#0	20.73	PASS
Band2	5MHz	16QAM	18900	25RB#0	19.74	PASS
Band2	5MHz	QPSK	19175	1RB#0	21.39	PASS
Band2	5MHz	16QAM	19175	1RB#0	20.42	PASS
Band2	5MHz	QPSK	19175	1RB#12	21.13	PASS
Band2	5MHz	16QAM	19175	1RB#12	20.39	PASS
Band2	5MHz	QPSK	19175	1RB#24	20.99	PASS
Band2	5MHz	16QAM	19175	1RB#24	20.22	PASS
Band2	5MHz	QPSK	19175	12RB#0	20.06	PASS
Band2	5MHz	16QAM	19175	12RB#0	19.18	PASS
Band2	5MHz	QPSK	19175	12RB#6	20.09	PASS
Band2	5MHz	16QAM	19175	12RB#6	19.13	PASS
Band2	5MHz	QPSK	19175	12RB#13	20.02	PASS
Band2	5MHz	16QAM	19175	12RB#13	19.08	PASS
Band2	5MHz	QPSK	19175	25RB#0	20.08	PASS
Band2	5MHz	16QAM	19175	25RB#0	19.11	PASS
Band2	10MHz	QPSK	18650	1RB#0	21.45	PASS
Band2	10MHz	16QAM	18650	1RB#0	20.63	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band2	10MHz	QPSK	18650	1RB#24	21.65	PASS
Band2	10MHz	16QAM	18650	1RB#24	20.75	PASS
Band2	10MHz	QPSK	18650	1RB#49	21.53	PASS
Band2	10MHz	16QAM	18650	1RB#49	20.70	PASS
Band2	10MHz	QPSK	18650	25RB#0	20.56	PASS
Band2	10MHz	16QAM	18650	25RB#0	19.60	PASS
Band2	10MHz	QPSK	18650	25RB#12	20.57	PASS
Band2	10MHz	16QAM	18650	25RB#12	19.61	PASS
Band2	10MHz	QPSK	18650	25RB#25	20.63	PASS
Band2	10MHz	16QAM	18650	25RB#25	19.65	PASS
Band2	10MHz	QPSK	18650	50RB#0	20.62	PASS
Band2	10MHz	16QAM	18650	50RB#0	19.63	PASS
Band2	10MHz	QPSK	18900	1RB#0	21.47	PASS
Band2	10MHz	16QAM	18900	1RB#0	20.71	PASS
Band2	10MHz	QPSK	18900	1RB#24	21.57	PASS
Band2	10MHz	16QAM	18900	1RB#24	20.86	PASS
Band2	10MHz	QPSK	18900	1RB#49	21.41	PASS
Band2	10MHz	16QAM	18900	1RB#49	20.61	PASS
Band2	10MHz	QPSK	18900	25RB#0	20.64	PASS
Band2	10MHz	16QAM	18900	25RB#0	19.63	PASS
Band2	10MHz	QPSK	18900	25RB#12	20.60	PASS
Band2	10MHz	16QAM	18900	25RB#12	19.62	PASS
Band2	10MHz	QPSK	18900	25RB#25	20.47	PASS
Band2	10MHz	16QAM	18900	25RB#25	19.48	PASS
Band2	10MHz	QPSK	18900	50RB#0	20.52	PASS
Band2	10MHz	16QAM	18900	50RB#0	19.54	PASS
Band2	10MHz	QPSK	19150	1RB#0	21.19	PASS
Band2	10MHz	16QAM	19150	1RB#0	20.35	PASS
Band2	10MHz	QPSK	19150	1RB#24	21.25	PASS
Band2	10MHz	16QAM	19150	1RB#24	20.46	PASS
Band2	10MHz	QPSK	19150	1RB#49	21.03	PASS
Band2	10MHz	16QAM	19150	1RB#49	20.22	PASS
Band2	10MHz	QPSK	19150	25RB#0	20.38	PASS
Band2	10MHz	16QAM	19150	25RB#0	19.44	PASS
Band2	10MHz	QPSK	19150	25RB#12	20.38	PASS
Band2	10MHz	16QAM	19150	25RB#12	19.43	PASS
Band2	10MHz	QPSK	19150	25RB#25	20.10	PASS
Band2	10MHz	16QAM	19150	25RB#25	19.18	PASS
Band2	10MHz	QPSK	19150	50RB#0	20.22	PASS
Band2	10MHz	16QAM	19150	50RB#0	19.26	PASS
Band2	15MHz	QPSK	18675	1RB#0	21.34	PASS
Band2	15MHz	16QAM	18675	1RB#0	20.47	PASS
Band2	15MHz	QPSK	18675	1RB#38	21.62	PASS
Band2	15MHz	16QAM	18675	1RB#38	20.78	PASS
Band2	15MHz	QPSK	18675	1RB#74	21.38	PASS
Band2	15MHz	16QAM	18675	1RB#74	20.54	PASS
Band2	15MHz	QPSK	18675	38RB#0	20.58	PASS
Band2	15MHz	16QAM	18675	38RB#0	20.55	PASS
Band2	15MHz	QPSK	18675	38RB#18	20.61	PASS
Band2	15MHz	16QAM	18675	38RB#18	20.60	PASS
Band2	15MHz	QPSK	18675	38RB#37	20.55	PASS
Band2	15MHz	16QAM	18675	38RB#37	20.57	PASS
Band2	15MHz	QPSK	18675	75RB#0	20.53	PASS
Band2	15MHz	16QAM	18675	75RB#0	19.54	PASS
Band2	15MHz	QPSK	18900	1RB#0	21.52	PASS
Band2	15MHz	16QAM	18900	1RB#0	20.60	PASS
Band2	15MHz	QPSK	18900	1RB#38	21.47	PASS
Band2	15MHz	16QAM	18900	1RB#38	20.68	PASS
Band2	15MHz	QPSK	18900	1RB#74	21.28	PASS
Band2	15MHz	16QAM	18900	1RB#74	20.48	PASS
Band2	15MHz	QPSK	18900	38RB#0	20.53	PASS
Band2	15MHz	16QAM	18900	38RB#0	20.51	PASS
Band2	15MHz	QPSK	18900	38RB#18	20.52	PASS
Band2	15MHz	16QAM	18900	38RB#18	20.51	PASS
Band2	15MHz	QPSK	18900	38RB#37	20.51	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band2	15MHz	16QAM	18900	38RB#37	20.52	PASS
Band2	15MHz	QPSK	18900	75RB#0	20.62	PASS
Band2	15MHz	16QAM	18900	75RB#0	19.49	PASS
Band2	15MHz	QPSK	19125	1RB#0	21.14	PASS
Band2	15MHz	16QAM	19125	1RB#0	20.39	PASS
Band2	15MHz	QPSK	19125	1RB#38	21.13	PASS
Band2	15MHz	16QAM	19125	1RB#38	20.42	PASS
Band2	15MHz	QPSK	19125	1RB#74	20.88	PASS
Band2	15MHz	16QAM	19125	1RB#74	20.16	PASS
Band2	15MHz	QPSK	19125	38RB#0	20.17	PASS
Band2	15MHz	16QAM	19125	38RB#0	20.15	PASS
Band2	15MHz	QPSK	19125	38RB#18	20.16	PASS
Band2	15MHz	16QAM	19125	38RB#18	20.19	PASS
Band2	15MHz	QPSK	19125	38RB#37	20.17	PASS
Band2	15MHz	16QAM	19125	38RB#37	20.16	PASS
Band2	15MHz	QPSK	19125	75RB#0	20.17	PASS
Band2	15MHz	16QAM	19125	75RB#0	19.21	PASS
Band2	20MHz	QPSK	18700	1RB#0	21.37	PASS
Band2	20MHz	16QAM	18700	1RB#0	20.32	PASS
Band2	20MHz	QPSK	18700	1RB#49	21.85	PASS
Band2	20MHz	16QAM	18700	1RB#49	20.84	PASS
Band2	20MHz	QPSK	18700	1RB#99	21.36	PASS
Band2	20MHz	16QAM	18700	1RB#99	20.32	PASS
Band2	20MHz	QPSK	18700	50RB#0	20.59	PASS
Band2	20MHz	16QAM	18700	50RB#0	19.59	PASS
Band2	20MHz	QPSK	18700	50RB#25	20.55	PASS
Band2	20MHz	16QAM	18700	50RB#25	19.60	PASS
Band2	20MHz	QPSK	18700	50RB#50	20.63	PASS
Band2	20MHz	16QAM	18700	50RB#50	19.67	PASS
Band2	20MHz	QPSK	18700	100RB#0	20.64	PASS
Band2	20MHz	16QAM	18700	100RB#0	19.63	PASS
Band2	20MHz	QPSK	18900	1RB#0	21.89	PASS
Band2	20MHz	16QAM	18900	1RB#0	20.77	PASS
Band2	20MHz	QPSK	18900	1RB#49	21.79	PASS
Band2	20MHz	16QAM	18900	1RB#49	20.79	PASS
Band2	20MHz	QPSK	18900	1RB#99	21.24	PASS
Band2	20MHz	16QAM	18900	1RB#99	20.22	PASS
Band2	20MHz	QPSK	18900	50RB#0	20.79	PASS
Band2	20MHz	16QAM	18900	50RB#0	19.92	PASS
Band2	20MHz	QPSK	18900	50RB#25	20.94	PASS
Band2	20MHz	16QAM	18900	50RB#25	19.85	PASS
Band2	20MHz	QPSK	18900	50RB#50	20.72	PASS
Band2	20MHz	16QAM	18900	50RB#50	19.50	PASS
Band2	20MHz	QPSK	18900	100RB#0	20.54	PASS
Band2	20MHz	16QAM	18900	100RB#0	19.57	PASS
Band2	20MHz	QPSK	19100	1RB#0	21.62	PASS
Band2	20MHz	16QAM	19100	1RB#0	20.36	PASS
Band2	20MHz	QPSK	19100	1RB#49	21.42	PASS
Band2	20MHz	16QAM	19100	1RB#49	20.65	PASS
Band2	20MHz	QPSK	19100	1RB#99	20.87	PASS
Band2	20MHz	16QAM	19100	1RB#99	20.02	PASS
Band2	20MHz	QPSK	19100	50RB#0	20.34	PASS
Band2	20MHz	16QAM	19100	50RB#0	19.36	PASS
Band2	20MHz	QPSK	19100	50RB#25	20.31	PASS
Band2	20MHz	16QAM	19100	50RB#25	19.38	PASS
Band2	20MHz	QPSK	19100	50RB#50	19.98	PASS
Band2	20MHz	16QAM	19100	50RB#50	19.02	PASS
Band2	20MHz	QPSK	19100	100RB#0	20.19	PASS
Band2	20MHz	16QAM	19100	100RB#0	19.15	PASS





LTE Band4

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band4	1.4MHz	QPSK	19957	1RB#0	21.96	PASS
Band4	1.4MHz	16QAM	19957	1RB#0	21.03	PASS
Band4	1.4MHz	QPSK	19957	1RB#2	22.15	PASS
Band4	1.4MHz	16QAM	19957	1RB#2	21.21	PASS
Band4	1.4MHz	QPSK	19957	1RB#5	21.96	PASS
Band4	1.4MHz	16QAM	19957	1RB#5	21.06	PASS
Band4	1.4MHz	QPSK	19957	3RB#0	22.05	PASS
Band4	1.4MHz	16QAM	19957	3RB#0	20.86	PASS
Band4	1.4MHz	QPSK	19957	3RB#1	22.01	PASS
Band4	1.4MHz	16QAM	19957	3RB#1	20.90	PASS
Band4	1.4MHz	QPSK	19957	3RB#3	22.03	PASS
Band4	1.4MHz	16QAM	19957	3RB#3	20.90	PASS
Band4	1.4MHz	QPSK	19957	6RB#0	21.00	PASS
Band4	1.4MHz	16QAM	19957	6RB#0	20.06	PASS
Band4	1.4MHz	QPSK	20175	1RB#0	22.10	PASS
Band4	1.4MHz	16QAM	20175	1RB#0	21.26	PASS
Band4	1.4MHz	QPSK	20175	1RB#2	22.23	PASS
Band4	1.4MHz	16QAM	20175	1RB#2	21.41	PASS
Band4	1.4MHz	QPSK	20175	1RB#5	22.09	PASS
Band4	1.4MHz	16QAM	20175	1RB#5	21.25	PASS
Band4	1.4MHz	QPSK	20175	3RB#0	22.23	PASS
Band4	1.4MHz	16QAM	20175	3RB#0	21.08	PASS
Band4	1.4MHz	QPSK	20175	3RB#1	22.23	PASS
Band4	1.4MHz	16QAM	20175	3RB#1	21.09	PASS
Band4	1.4MHz	QPSK	20175	3RB#3	22.24	PASS
Band4	1.4MHz	16QAM	20175	3RB#3	21.08	PASS
Band4	1.4MHz	QPSK	20175	6RB#0	21.14	PASS
Band4	1.4MHz	16QAM	20175	6RB#0	20.04	PASS
Band4	1.4MHz	QPSK	20393	1RB#0	21.83	PASS
Band4	1.4MHz	16QAM	20393	1RB#0	20.87	PASS
Band4	1.4MHz	QPSK	20393	1RB#2	21.95	PASS
Band4	1.4MHz	16QAM	20393	1RB#2	20.91	PASS
Band4	1.4MHz	QPSK	20393	1RB#5	21.85	PASS
Band4	1.4MHz	16QAM	20393	1RB#5	20.86	PASS
Band4	1.4MHz	QPSK	20393	3RB#0	21.90	PASS
Band4	1.4MHz	16QAM	20393	3RB#0	20.77	PASS
Band4	1.4MHz	QPSK	20393	3RB#1	21.90	PASS
Band4	1.4MHz	16QAM	20393	3RB#1	20.79	PASS
Band4	1.4MHz	QPSK	20393	3RB#3	21.97	PASS
Band4	1.4MHz	16QAM	20393	3RB#3	20.74	PASS
Band4	1.4MHz	QPSK	20393	6RB#0	20.87	PASS
Band4	1.4MHz	16QAM	20393	6RB#0	19.91	PASS
Band4	3MHz	QPSK	19965	1RB#0	22.02	PASS
Band4	3MHz	16QAM	19965	1RB#0	21.21	PASS
Band4	3MHz	QPSK	19965	1RB#8	22.03	PASS
Band4	3MHz	16QAM	19965	1RB#8	21.20	PASS
Band4	3MHz	QPSK	19965	1RB#14	22.00	PASS
Band4	3MHz	16QAM	19965	1RB#14	21.19	PASS
Band4	3MHz	QPSK	19965	8RB#0	21.01	PASS
Band4	3MHz	16QAM	19965	8RB#0	20.12	PASS
Band4	3MHz	QPSK	19965	8RB#4	21.04	PASS
Band4	3MHz	16QAM	19965	8RB#4	20.12	PASS
Band4	3MHz	QPSK	19965	8RB#7	21.09	PASS
Band4	3MHz	16QAM	19965	8RB#7	20.09	PASS
Band4	3MHz	QPSK	19965	15RB#0	20.99	PASS
Band4	3MHz	16QAM	19965	15RB#0	20.06	PASS
Band4	3MHz	QPSK	20175	1RB#0	22.21	PASS
Band4	3MHz	16QAM	20175	1RB#0	21.36	PASS
Band4	3MHz	QPSK	20175	1RB#8	22.24	PASS
Band4	3MHz	16QAM	20175	1RB#8	21.34	PASS
Band4	3MHz	QPSK	20175	1RB#14	22.17	PASS
Band4	3MHz	16QAM	20175	1RB#14	21.24	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band4	3MHz	QPSK	20175	8RB#0	21.22	PASS
Band4	3MHz	16QAM	20175	8RB#0	20.29	PASS
Band4	3MHz	QPSK	20175	8RB#4	21.21	PASS
Band4	3MHz	16QAM	20175	8RB#4	20.24	PASS
Band4	3MHz	QPSK	20175	8RB#7	21.19	PASS
Band4	3MHz	16QAM	20175	8RB#7	20.23	PASS
Band4	3MHz	QPSK	20175	15RB#0	21.15	PASS
Band4	3MHz	16QAM	20175	15RB#0	20.14	PASS
Band4	3MHz	QPSK	20385	1RB#0	21.89	PASS
Band4	3MHz	16QAM	20385	1RB#0	21.05	PASS
Band4	3MHz	QPSK	20385	1RB#8	21.90	PASS
Band4	3MHz	16QAM	20385	1RB#8	20.99	PASS
Band4	3MHz	QPSK	20385	1RB#14	21.87	PASS
Band4	3MHz	16QAM	20385	1RB#14	20.99	PASS
Band4	3MHz	QPSK	20385	8RB#0	20.92	PASS
Band4	3MHz	16QAM	20385	8RB#0	19.96	PASS
Band4	3MHz	QPSK	20385	8RB#4	20.92	PASS
Band4	3MHz	16QAM	20385	8RB#4	19.97	PASS
Band4	3MHz	QPSK	20385	8RB#7	20.93	PASS
Band4	3MHz	16QAM	20385	8RB#7	19.94	PASS
Band4	3MHz	QPSK	20385	15RB#0	20.86	PASS
Band4	3MHz	16QAM	20385	15RB#0	19.89	PASS
Band4	5MHz	QPSK	19975	1RB#0	21.96	PASS
Band4	5MHz	16QAM	19975	1RB#0	20.92	PASS
Band4	5MHz	QPSK	19975	1RB#12	22.08	PASS
Band4	5MHz	16QAM	19975	1RB#12	21.02	PASS
Band4	5MHz	QPSK	19975	1RB#24	21.97	PASS
Band4	5MHz	16QAM	19975	1RB#24	21.00	PASS
Band4	5MHz	QPSK	19975	12RB#0	20.93	PASS
Band4	5MHz	16QAM	19975	12RB#0	19.99	PASS
Band4	5MHz	QPSK	19975	12RB#6	20.96	PASS
Band4	5MHz	16QAM	19975	12RB#6	19.94	PASS
Band4	5MHz	QPSK	19975	12RB#13	20.99	PASS
Band4	5MHz	16QAM	19975	12RB#13	19.99	PASS
Band4	5MHz	QPSK	19975	25RB#0	20.95	PASS
Band4	5MHz	16QAM	19975	25RB#0	20.04	PASS
Band4	5MHz	QPSK	20175	1RB#0	22.07	PASS
Band4	5MHz	16QAM	20175	1RB#0	21.34	PASS
Band4	5MHz	QPSK	20175	1RB#12	22.24	PASS
Band4	5MHz	16QAM	20175	1RB#12	21.42	PASS
Band4	5MHz	QPSK	20175	1RB#24	22.04	PASS
Band4	5MHz	16QAM	20175	1RB#24	21.19	PASS
Band4	5MHz	QPSK	20175	12RB#0	21.10	PASS
Band4	5MHz	16QAM	20175	12RB#0	20.15	PASS
Band4	5MHz	QPSK	20175	12RB#6	21.16	PASS
Band4	5MHz	16QAM	20175	12RB#6	20.21	PASS
Band4	5MHz	QPSK	20175	12RB#13	21.06	PASS
Band4	5MHz	16QAM	20175	12RB#13	20.14	PASS
Band4	5MHz	QPSK	20175	25RB#0	21.15	PASS
Band4	5MHz	16QAM	20175	25RB#0	20.13	PASS
Band4	5MHz	QPSK	20375	1RB#0	21.82	PASS
Band4	5MHz	16QAM	20375	1RB#0	20.76	PASS
Band4	5MHz	QPSK	20375	1RB#12	21.92	PASS
Band4	5MHz	16QAM	20375	1RB#12	20.88	PASS
Band4	5MHz	QPSK	20375	1RB#24	21.79	PASS
Band4	5MHz	16QAM	20375	1RB#24	20.74	PASS
Band4	5MHz	QPSK	20375	12RB#0	20.84	PASS
Band4	5MHz	16QAM	20375	12RB#0	19.82	PASS
Band4	5MHz	QPSK	20375	12RB#6	20.82	PASS
Band4	5MHz	16QAM	20375	12RB#6	19.82	PASS
Band4	5MHz	QPSK	20375	12RB#13	20.80	PASS
Band4	5MHz	16QAM	20375	12RB#13	19.75	PASS
Band4	5MHz	QPSK	20375	25RB#0	20.80	PASS
Band4	5MHz	16QAM	20375	25RB#0	19.88	PASS
Band4	10MHz	QPSK	20000	1RB#0	21.96	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band4	10MHz	16QAM	20000	1RB#0	21.14	PASS
Band4	10MHz	QPSK	20000	1RB#24	22.19	PASS
Band4	10MHz	16QAM	20000	1RB#24	21.40	PASS
Band4	10MHz	QPSK	20000	1RB#49	22.08	PASS
Band4	10MHz	16QAM	20000	1RB#49	21.23	PASS
Band4	10MHz	QPSK	20000	25RB#0	21.05	PASS
Band4	10MHz	16QAM	20000	25RB#0	20.06	PASS
Band4	10MHz	QPSK	20000	25RB#12	21.08	PASS
Band4	10MHz	16QAM	20000	25RB#12	20.13	PASS
Band4	10MHz	QPSK	20000	25RB#25	21.16	PASS
Band4	10MHz	16QAM	20000	25RB#25	20.18	PASS
Band4	10MHz	QPSK	20000	50RB#0	21.07	PASS
Band4	10MHz	16QAM	20000	50RB#0	20.12	PASS
Band4	10MHz	QPSK	20175	1RB#0	22.16	PASS
Band4	10MHz	16QAM	20175	1RB#0	21.37	PASS
Band4	10MHz	QPSK	20175	1RB#24	22.26	PASS
Band4	10MHz	16QAM	20175	1RB#24	21.42	PASS
Band4	10MHz	QPSK	20175	1RB#49	22.02	PASS
Band4	10MHz	16QAM	20175	1RB#49	21.14	PASS
Band4	10MHz	QPSK	20175	25RB#0	21.24	PASS
Band4	10MHz	16QAM	20175	25RB#0	20.30	PASS
Band4	10MHz	QPSK	20175	25RB#12	21.25	PASS
Band4	10MHz	16QAM	20175	25RB#12	20.34	PASS
Band4	10MHz	QPSK	20175	25RB#25	21.13	PASS
Band4	10MHz	16QAM	20175	25RB#25	20.22	PASS
Band4	10MHz	QPSK	20175	50RB#0	21.17	PASS
Band4	10MHz	16QAM	20175	50RB#0	20.25	PASS
Band4	10MHz	QPSK	20350	1RB#0	21.85	PASS
Band4	10MHz	16QAM	20350	1RB#0	20.97	PASS
Band4	10MHz	QPSK	20350	1RB#24	22.03	PASS
Band4	10MHz	16QAM	20350	1RB#24	21.12	PASS
Band4	10MHz	QPSK	20350	1RB#49	21.79	PASS
Band4	10MHz	16QAM	20350	1RB#49	20.90	PASS
Band4	10MHz	QPSK	20350	25RB#0	20.93	PASS
Band4	10MHz	16QAM	20350	25RB#0	19.91	PASS
Band4	10MHz	QPSK	20350	25RB#12	20.91	PASS
Band4	10MHz	16QAM	20350	25RB#12	19.94	PASS
Band4	10MHz	QPSK	20350	25RB#25	20.85	PASS
Band4	10MHz	16QAM	20350	25RB#25	19.85	PASS
Band4	10MHz	QPSK	20350	50RB#0	20.89	PASS
Band4	10MHz	16QAM	20350	50RB#0	19.87	PASS
Band4	15MHz	QPSK	20025	1RB#0	21.80	PASS
Band4	15MHz	16QAM	20025	1RB#0	20.98	PASS
Band4	15MHz	QPSK	20025	1RB#38	22.05	PASS
Band4	15MHz	16QAM	20025	1RB#38	21.22	PASS
Band4	15MHz	QPSK	20025	1RB#74	21.94	PASS
Band4	15MHz	16QAM	20025	1RB#74	21.14	PASS
Band4	15MHz	QPSK	20025	38RB#0	21.08	PASS
Band4	15MHz	16QAM	20025	38RB#0	21.08	PASS
Band4	15MHz	QPSK	20025	38RB#18	21.05	PASS
Band4	15MHz	16QAM	20025	38RB#18	21.10	PASS
Band4	15MHz	QPSK	20025	38RB#37	21.10	PASS
Band4	15MHz	16QAM	20025	38RB#37	21.09	PASS
Band4	15MHz	QPSK	20025	75RB#0	21.08	PASS
Band4	15MHz	16QAM	20025	75RB#0	19.99	PASS
Band4	15MHz	QPSK	20175	1RB#0	22.03	PASS
Band4	15MHz	16QAM	20175	1RB#0	21.23	PASS
Band4	15MHz	QPSK	20175	1RB#38	22.10	PASS
Band4	15MHz	16QAM	20175	1RB#38	21.40	PASS
Band4	15MHz	QPSK	20175	1RB#74	21.85	PASS
Band4	15MHz	16QAM	20175	1RB#74	21.04	PASS
Band4	15MHz	QPSK	20175	38RB#0	21.06	PASS
Band4	15MHz	16QAM	20175	38RB#0	21.12	PASS
Band4	15MHz	QPSK	20175	38RB#18	21.15	PASS
Band4	15MHz	16QAM	20175	38RB#18	21.13	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band4	15MHz	QPSK	20175	38RB#37	21.13	PASS
Band4	15MHz	16QAM	20175	38RB#37	21.14	PASS
Band4	15MHz	QPSK	20175	75RB#0	21.18	PASS
Band4	15MHz	16QAM	20175	75RB#0	20.15	PASS
Band4	15MHz	QPSK	20325	1RB#0	21.79	PASS
Band4	15MHz	16QAM	20325	1RB#0	20.96	PASS
Band4	15MHz	QPSK	20325	1RB#38	21.87	PASS
Band4	15MHz	16QAM	20325	1RB#38	20.97	PASS
Band4	15MHz	QPSK	20325	1RB#74	21.64	PASS
Band4	15MHz	16QAM	20325	1RB#74	20.76	PASS
Band4	15MHz	QPSK	20325	38RB#0	20.96	PASS
Band4	15MHz	16QAM	20325	38RB#0	20.94	PASS
Band4	15MHz	QPSK	20325	38RB#18	20.95	PASS
Band4	15MHz	16QAM	20325	38RB#18	20.97	PASS
Band4	15MHz	QPSK	20325	38RB#37	20.98	PASS
Band4	15MHz	16QAM	20325	38RB#37	20.97	PASS
Band4	15MHz	QPSK	20325	75RB#0	20.96	PASS
Band4	15MHz	16QAM	20325	75RB#0	19.89	PASS
Band4	20MHz	QPSK	20050	1RB#0	21.77	PASS
Band4	20MHz	16QAM	20050	1RB#0	20.74	PASS
Band4	20MHz	QPSK	20050	1RB#49	22.30	PASS
Band4	20MHz	16QAM	20050	1RB#49	21.32	PASS
Band4	20MHz	QPSK	20050	1RB#99	21.87	PASS
Band4	20MHz	16QAM	20050	1RB#99	20.87	PASS
Band4	20MHz	QPSK	20050	50RB#0	21.04	PASS
Band4	20MHz	16QAM	20050	50RB#0	20.04	PASS
Band4	20MHz	QPSK	20050	50RB#25	20.97	PASS
Band4	20MHz	16QAM	20050	50RB#25	19.99	PASS
Band4	20MHz	QPSK	20050	50RB#50	21.05	PASS
Band4	20MHz	16QAM	20050	50RB#50	20.06	PASS
Band4	20MHz	QPSK	20050	100RB#0	21.08	PASS
Band4	20MHz	16QAM	20050	100RB#0	20.12	PASS
Band4	20MHz	QPSK	20175	1RB#0	22.00	PASS
Band4	20MHz	16QAM	20175	1RB#0	21.13	PASS
Band4	20MHz	QPSK	20175	1RB#49	22.24	PASS
Band4	20MHz	16QAM	20175	1RB#49	21.41	PASS
Band4	20MHz	QPSK	20175	1RB#99	21.72	PASS
Band4	20MHz	16QAM	20175	1RB#99	20.75	PASS
Band4	20MHz	QPSK	20175	50RB#0	21.09	PASS
Band4	20MHz	16QAM	20175	50RB#0	20.17	PASS
Band4	20MHz	QPSK	20175	50RB#25	21.09	PASS
Band4	20MHz	16QAM	20175	50RB#25	20.18	PASS
Band4	20MHz	QPSK	20175	50RB#50	21.03	PASS
Band4	20MHz	16QAM	20175	50RB#50	20.06	PASS
Band4	20MHz	QPSK	20175	100RB#0	21.03	PASS
Band4	20MHz	16QAM	20175	100RB#0	20.08	PASS
Band4	20MHz	QPSK	20300	1RB#0	21.87	PASS
Band4	20MHz	16QAM	20300	1RB#0	20.84	PASS
Band4	20MHz	QPSK	20300	1RB#49	22.16	PASS
Band4	20MHz	16QAM	20300	1RB#49	21.03	PASS
Band4	20MHz	QPSK	20300	1RB#99	21.60	PASS
Band4	20MHz	16QAM	20300	1RB#99	20.57	PASS
Band4	20MHz	QPSK	20300	50RB#0	21.00	PASS
Band4	20MHz	16QAM	20300	50RB#0	20.04	PASS
Band4	20MHz	QPSK	20300	50RB#25	21.02	PASS
Band4	20MHz	16QAM	20300	50RB#25	19.95	PASS
Band4	20MHz	QPSK	20300	50RB#50	20.80	PASS
Band4	20MHz	16QAM	20300	50RB#50	19.84	PASS
Band4	20MHz	QPSK	20300	100RB#0	20.93	PASS
Band4	20MHz	16QAM	20300	100RB#0	19.92	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



LTE Band5

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band5	1.4MHz	QPSK	20407	1RB#0	22.66	PASS
Band5	1.4MHz	16QAM	20407	1RB#0	21.83	PASS
Band5	1.4MHz	QPSK	20407	1RB#2	22.73	PASS
Band5	1.4MHz	16QAM	20407	1RB#2	21.97	PASS
Band5	1.4MHz	QPSK	20407	1RB#5	22.57	PASS
Band5	1.4MHz	16QAM	20407	1RB#5	21.83	PASS
Band5	1.4MHz	QPSK	20407	3RB#0	22.72	PASS
Band5	1.4MHz	16QAM	20407	3RB#0	21.62	PASS
Band5	1.4MHz	QPSK	20407	3RB#1	22.75	PASS
Band5	1.4MHz	16QAM	20407	3RB#1	21.63	PASS
Band5	1.4MHz	QPSK	20407	3RB#3	22.72	PASS
Band5	1.4MHz	16QAM	20407	3RB#3	21.61	PASS
Band5	1.4MHz	QPSK	20407	6RB#0	21.68	PASS
Band5	1.4MHz	16QAM	20407	6RB#0	20.75	PASS
Band5	1.4MHz	QPSK	20525	1RB#0	22.52	PASS
Band5	1.4MHz	16QAM	20525	1RB#0	21.64	PASS
Band5	1.4MHz	QPSK	20525	1RB#2	22.59	PASS
Band5	1.4MHz	16QAM	20525	1RB#2	21.78	PASS
Band5	1.4MHz	QPSK	20525	1RB#5	22.52	PASS
Band5	1.4MHz	16QAM	20525	1RB#5	21.63	PASS
Band5	1.4MHz	QPSK	20525	3RB#0	22.59	PASS
Band5	1.4MHz	16QAM	20525	3RB#0	21.52	PASS
Band5	1.4MHz	QPSK	20525	3RB#1	22.60	PASS
Band5	1.4MHz	16QAM	20525	3RB#1	21.47	PASS
Band5	1.4MHz	QPSK	20525	3RB#3	22.62	PASS
Band5	1.4MHz	16QAM	20525	3RB#3	21.51	PASS
Band5	1.4MHz	QPSK	20525	6RB#0	21.65	PASS
Band5	1.4MHz	16QAM	20525	6RB#0	20.55	PASS
Band5	1.4MHz	QPSK	20643	1RB#0	22.37	PASS
Band5	1.4MHz	16QAM	20643	1RB#0	21.35	PASS
Band5	1.4MHz	QPSK	20643	1RB#2	22.52	PASS
Band5	1.4MHz	16QAM	20643	1RB#2	21.46	PASS
Band5	1.4MHz	QPSK	20643	1RB#5	22.40	PASS
Band5	1.4MHz	16QAM	20643	1RB#5	21.38	PASS
Band5	1.4MHz	QPSK	20643	3RB#0	22.43	PASS
Band5	1.4MHz	16QAM	20643	3RB#0	21.32	PASS
Band5	1.4MHz	QPSK	20643	3RB#1	22.46	PASS
Band5	1.4MHz	16QAM	20643	3RB#1	21.32	PASS
Band5	1.4MHz	QPSK	20643	3RB#3	22.50	PASS
Band5	1.4MHz	16QAM	20643	3RB#3	21.31	PASS
Band5	1.4MHz	QPSK	20643	6RB#0	21.49	PASS
Band5	1.4MHz	16QAM	20643	6RB#0	20.51	PASS
Band5	3MHz	QPSK	20415	1RB#0	22.76	PASS
Band5	3MHz	16QAM	20415	1RB#0	21.94	PASS
Band5	3MHz	QPSK	20415	1RB#8	22.70	PASS
Band5	3MHz	16QAM	20415	1RB#8	21.90	PASS
Band5	3MHz	QPSK	20415	1RB#14	22.70	PASS
Band5	3MHz	16QAM	20415	1RB#14	21.81	PASS
Band5	3MHz	QPSK	20415	8RB#0	21.80	PASS
Band5	3MHz	16QAM	20415	8RB#0	20.86	PASS
Band5	3MHz	QPSK	20415	8RB#4	21.82	PASS
Band5	3MHz	16QAM	20415	8RB#4	20.88	PASS
Band5	3MHz	QPSK	20415	8RB#7	21.79	PASS
Band5	3MHz	16QAM	20415	8RB#7	20.80	PASS
Band5	3MHz	QPSK	20415	15RB#0	21.75	PASS
Band5	3MHz	16QAM	20415	15RB#0	20.78	PASS
Band5	3MHz	QPSK	20525	1RB#0	22.60	PASS
Band5	3MHz	16QAM	20525	1RB#0	21.74	PASS
Band5	3MHz	QPSK	20525	1RB#8	22.63	PASS
Band5	3MHz	16QAM	20525	1RB#8	21.79	PASS
Band5	3MHz	QPSK	20525	1RB#14	22.59	PASS
Band5	3MHz	16QAM	20525	1RB#14	21.77	PASS
Band5	3MHz	QPSK	20525	8RB#0	21.69	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band5	3MHz	16QAM	20525	8RB#0	20.66	PASS
Band5	3MHz	QPSK	20525	8RB#4	21.68	PASS
Band5	3MHz	16QAM	20525	8RB#4	20.65	PASS
Band5	3MHz	QPSK	20525	8RB#7	21.68	PASS
Band5	3MHz	16QAM	20525	8RB#7	20.68	PASS
Band5	3MHz	QPSK	20525	15RB#0	21.65	PASS
Band5	3MHz	16QAM	20525	15RB#0	20.57	PASS
Band5	3MHz	QPSK	20635	1RB#0	22.57	PASS
Band5	3MHz	16QAM	20635	1RB#0	21.48	PASS
Band5	3MHz	QPSK	20635	1RB#8	22.54	PASS
Band5	3MHz	16QAM	20635	1RB#8	21.46	PASS
Band5	3MHz	QPSK	20635	1RB#14	22.48	PASS
Band5	3MHz	16QAM	20635	1RB#14	21.50	PASS
Band5	3MHz	QPSK	20635	8RB#0	21.67	PASS
Band5	3MHz	16QAM	20635	8RB#0	20.62	PASS
Band5	3MHz	QPSK	20635	8RB#4	21.66	PASS
Band5	3MHz	16QAM	20635	8RB#4	20.61	PASS
Band5	3MHz	QPSK	20635	8RB#7	21.63	PASS
Band5	3MHz	16QAM	20635	8RB#7	20.58	PASS
Band5	3MHz	QPSK	20635	15RB#0	21.57	PASS
Band5	3MHz	16QAM	20635	15RB#0	20.43	PASS
Band5	5MHz	QPSK	20425	1RB#0	22.67	PASS
Band5	5MHz	16QAM	20425	1RB#0	21.66	PASS
Band5	5MHz	QPSK	20425	1RB#12	22.70	PASS
Band5	5MHz	16QAM	20425	1RB#12	21.71	PASS
Band5	5MHz	QPSK	20425	1RB#24	22.54	PASS
Band5	5MHz	16QAM	20425	1RB#24	21.55	PASS
Band5	5MHz	QPSK	20425	12RB#0	21.75	PASS
Band5	5MHz	16QAM	20425	12RB#0	20.72	PASS
Band5	5MHz	QPSK	20425	12RB#6	21.78	PASS
Band5	5MHz	16QAM	20425	12RB#6	20.71	PASS
Band5	5MHz	QPSK	20425	12RB#13	21.63	PASS
Band5	5MHz	16QAM	20425	12RB#13	20.62	PASS
Band5	5MHz	QPSK	20425	25RB#0	21.71	PASS
Band5	5MHz	16QAM	20425	25RB#0	20.75	PASS
Band5	5MHz	QPSK	20525	1RB#0	22.51	PASS
Band5	5MHz	16QAM	20525	1RB#0	21.61	PASS
Band5	5MHz	QPSK	20525	1RB#12	22.64	PASS
Band5	5MHz	16QAM	20525	1RB#12	21.77	PASS
Band5	5MHz	QPSK	20525	1RB#24	22.52	PASS
Band5	5MHz	16QAM	20525	1RB#24	21.74	PASS
Band5	5MHz	QPSK	20525	12RB#0	21.55	PASS
Band5	5MHz	16QAM	20525	12RB#0	20.53	PASS
Band5	5MHz	QPSK	20525	12RB#6	21.55	PASS
Band5	5MHz	16QAM	20525	12RB#6	20.57	PASS
Band5	5MHz	QPSK	20525	12RB#13	21.56	PASS
Band5	5MHz	16QAM	20525	12RB#13	20.59	PASS
Band5	5MHz	QPSK	20525	25RB#0	21.59	PASS
Band5	5MHz	16QAM	20525	25RB#0	20.57	PASS
Band5	5MHz	QPSK	20625	1RB#0	22.51	PASS
Band5	5MHz	16QAM	20625	1RB#0	21.51	PASS
Band5	5MHz	QPSK	20625	1RB#12	22.61	PASS
Band5	5MHz	16QAM	20625	1RB#12	21.54	PASS
Band5	5MHz	QPSK	20625	1RB#24	22.40	PASS
Band5	5MHz	16QAM	20625	1RB#24	21.44	PASS
Band5	5MHz	QPSK	20625	12RB#0	21.57	PASS
Band5	5MHz	16QAM	20625	12RB#0	20.53	PASS
Band5	5MHz	QPSK	20625	12RB#6	21.49	PASS
Band5	5MHz	16QAM	20625	12RB#6	20.53	PASS
Band5	5MHz	QPSK	20625	12RB#13	21.42	PASS
Band5	5MHz	16QAM	20625	12RB#13	20.44	PASS
Band5	5MHz	QPSK	20625	25RB#0	21.49	PASS
Band5	5MHz	16QAM	20625	25RB#0	20.52	PASS
Band5	10MHz	QPSK	20450	1RB#0	22.67	PASS
Band5	10MHz	16QAM	20450	1RB#0	21.89	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band5	10MHz	QPSK	20450	1RB#24	22.77	PASS
Band5	10MHz	16QAM	20450	1RB#24	21.84	PASS
Band5	10MHz	QPSK	20450	1RB#49	22.46	PASS
Band5	10MHz	16QAM	20450	1RB#49	21.56	PASS
Band5	10MHz	QPSK	20450	25RB#0	21.78	PASS
Band5	10MHz	16QAM	20450	25RB#0	20.82	PASS
Band5	10MHz	QPSK	20450	25RB#12	21.79	PASS
Band5	10MHz	16QAM	20450	25RB#12	20.84	PASS
Band5	10MHz	QPSK	20450	25RB#25	21.62	PASS
Band5	10MHz	16QAM	20450	25RB#25	20.61	PASS
Band5	10MHz	QPSK	20450	50RB#0	21.68	PASS
Band5	10MHz	16QAM	20450	50RB#0	20.68	PASS
Band5	10MHz	QPSK	20525	1RB#0	22.53	PASS
Band5	10MHz	16QAM	20525	1RB#0	21.61	PASS
Band5	10MHz	QPSK	20525	1RB#24	22.73	PASS
Band5	10MHz	16QAM	20525	1RB#24	21.88	PASS
Band5	10MHz	QPSK	20525	1RB#49	22.53	PASS
Band5	10MHz	16QAM	20525	1RB#49	21.76	PASS
Band5	10MHz	QPSK	20525	25RB#0	21.57	PASS
Band5	10MHz	16QAM	20525	25RB#0	20.59	PASS
Band5	10MHz	QPSK	20525	25RB#12	21.54	PASS
Band5	10MHz	16QAM	20525	25RB#12	20.59	PASS
Band5	10MHz	QPSK	20525	25RB#25	21.60	PASS
Band5	10MHz	16QAM	20525	25RB#25	20.70	PASS
Band5	10MHz	QPSK	20525	50RB#0	21.59	PASS
Band5	10MHz	16QAM	20525	50RB#0	20.63	PASS
Band5	10MHz	QPSK	20600	1RB#0	22.57	PASS
Band5	10MHz	16QAM	20600	1RB#0	21.52	PASS
Band5	10MHz	QPSK	20600	1RB#24	22.50	PASS
Band5	10MHz	16QAM	20600	1RB#24	21.57	PASS
Band5	10MHz	QPSK	20600	1RB#49	22.36	PASS
Band5	10MHz	16QAM	20600	1RB#49	21.33	PASS
Band5	10MHz	QPSK	20600	25RB#0	21.68	PASS
Band5	10MHz	16QAM	20600	25RB#0	20.78	PASS
Band5	10MHz	QPSK	20600	25RB#12	21.69	PASS
Band5	10MHz	16QAM	20600	25RB#12	20.77	PASS
Band5	10MHz	QPSK	20600	25RB#25	21.44	PASS
Band5	10MHz	16QAM	20600	25RB#25	20.52	PASS
Band5	10MHz	QPSK	20600	50RB#0	21.59	PASS
Band5	10MHz	16QAM	20600	50RB#0	20.64	PASS





LTE Band 7

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band7	5MHz	QPSK	20775	1RB#0	20.25	PASS
Band7	5MHz	16QAM	20775	1RB#0	19.31	PASS
Band7	5MHz	QPSK	20775	1RB#12	20.31	PASS
Band7	5MHz	16QAM	20775	1RB#12	19.37	PASS
Band7	5MHz	QPSK	20775	1RB#24	20.13	PASS
Band7	5MHz	16QAM	20775	1RB#24	19.12	PASS
Band7	5MHz	QPSK	20775	12RB#0	19.26	PASS
Band7	5MHz	16QAM	20775	12RB#0	18.29	PASS
Band7	5MHz	QPSK	20775	12RB#6	19.27	PASS
Band7	5MHz	16QAM	20775	12RB#6	18.27	PASS
Band7	5MHz	QPSK	20775	12RB#13	19.17	PASS
Band7	5MHz	16QAM	20775	12RB#13	18.13	PASS
Band7	5MHz	QPSK	20775	25RB#0	19.28	PASS
Band7	5MHz	16QAM	20775	25RB#0	18.27	PASS
Band7	5MHz	QPSK	21100	1RB#0	20.48	PASS
Band7	5MHz	16QAM	21100	1RB#0	19.76	PASS
Band7	5MHz	QPSK	21100	1RB#12	20.53	PASS
Band7	5MHz	16QAM	21100	1RB#12	19.78	PASS
Band7	5MHz	QPSK	21100	1RB#24	20.39	PASS
Band7	5MHz	16QAM	21100	1RB#24	19.63	PASS
Band7	5MHz	QPSK	21100	12RB#0	19.54	PASS
Band7	5MHz	16QAM	21100	12RB#0	18.59	PASS
Band7	5MHz	QPSK	21100	12RB#6	19.56	PASS
Band7	5MHz	16QAM	21100	12RB#6	18.56	PASS
Band7	5MHz	QPSK	21100	12RB#13	19.39	PASS
Band7	5MHz	16QAM	21100	12RB#13	18.49	PASS
Band7	5MHz	QPSK	21100	25RB#0	19.56	PASS
Band7	5MHz	16QAM	21100	25RB#0	18.51	PASS
Band7	5MHz	QPSK	21425	1RB#0	20.13	PASS
Band7	5MHz	16QAM	21425	1RB#0	19.12	PASS
Band7	5MHz	QPSK	21425	1RB#12	20.23	PASS
Band7	5MHz	16QAM	21425	1RB#12	19.25	PASS
Band7	5MHz	QPSK	21425	1RB#24	20.18	PASS
Band7	5MHz	16QAM	21425	1RB#24	19.18	PASS
Band7	5MHz	QPSK	21425	12RB#0	19.26	PASS
Band7	5MHz	16QAM	21425	12RB#0	18.24	PASS
Band7	5MHz	QPSK	21425	12RB#6	19.25	PASS
Band7	5MHz	16QAM	21425	12RB#6	18.29	PASS
Band7	5MHz	QPSK	21425	12RB#13	19.15	PASS
Band7	5MHz	16QAM	21425	12RB#13	18.26	PASS
Band7	5MHz	QPSK	21425	25RB#0	19.25	PASS
Band7	5MHz	16QAM	21425	25RB#0	18.32	PASS
Band7	10MHz	QPSK	20800	1RB#0	20.29	PASS
Band7	10MHz	16QAM	20800	1RB#0	19.47	PASS
Band7	10MHz	QPSK	20800	1RB#24	20.20	PASS
Band7	10MHz	16QAM	20800	1RB#24	19.52	PASS
Band7	10MHz	QPSK	20800	1RB#49	20.01	PASS
Band7	10MHz	16QAM	20800	1RB#49	19.22	PASS
Band7	10MHz	QPSK	20800	25RB#0	19.38	PASS
Band7	10MHz	16QAM	20800	25RB#0	18.34	PASS
Band7	10MHz	QPSK	20800	25RB#12	19.36	PASS
Band7	10MHz	16QAM	20800	25RB#12	18.32	PASS
Band7	10MHz	QPSK	20800	25RB#25	19.29	PASS
Band7	10MHz	16QAM	20800	25RB#25	18.29	PASS
Band7	10MHz	QPSK	20800	50RB#0	19.32	PASS
Band7	10MHz	16QAM	20800	50RB#0	18.32	PASS
Band7	10MHz	QPSK	21100	1RB#0	20.54	PASS
Band7	10MHz	16QAM	21100	1RB#0	19.70	PASS
Band7	10MHz	QPSK	21100	1RB#24	20.60	PASS
Band7	10MHz	16QAM	21100	1RB#24	19.80	PASS
Band7	10MHz	QPSK	21100	1RB#49	20.28	PASS
Band7	10MHz	16QAM	21100	1RB#49	19.53	PASS
Band7	10MHz	QPSK	21100	25RB#0	19.69	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band7	10MHz	16QAM	21100	25RB#0	18.71	PASS
Band7	10MHz	QPSK	21100	25RB#12	19.64	PASS
Band7	10MHz	16QAM	21100	25RB#12	18.71	PASS
Band7	10MHz	QPSK	21100	25RB#25	19.48	PASS
Band7	10MHz	16QAM	21100	25RB#25	18.56	PASS
Band7	10MHz	QPSK	21100	50RB#0	19.59	PASS
Band7	10MHz	16QAM	21100	50RB#0	18.56	PASS
Band7	10MHz	QPSK	21400	1RB#0	20.11	PASS
Band7	10MHz	16QAM	21400	1RB#0	19.35	PASS
Band7	10MHz	QPSK	21400	1RB#24	20.28	PASS
Band7	10MHz	16QAM	21400	1RB#24	19.51	PASS
Band7	10MHz	QPSK	21400	1RB#49	20.12	PASS
Band7	10MHz	16QAM	21400	1RB#49	19.33	PASS
Band7	10MHz	QPSK	21400	25RB#0	19.30	PASS
Band7	10MHz	16QAM	21400	25RB#0	18.35	PASS
Band7	10MHz	QPSK	21400	25RB#12	19.27	PASS
Band7	10MHz	16QAM	21400	25RB#12	18.28	PASS
Band7	10MHz	QPSK	21400	25RB#25	19.25	PASS
Band7	10MHz	16QAM	21400	25RB#25	18.30	PASS
Band7	10MHz	QPSK	21400	50RB#0	19.28	PASS
Band7	10MHz	16QAM	21400	50RB#0	18.29	PASS
Band7	15MHz	QPSK	20825	1RB#0	20.16	PASS
Band7	15MHz	16QAM	20825	1RB#0	19.27	PASS
Band7	15MHz	QPSK	20825	1RB#38	20.11	PASS
Band7	15MHz	16QAM	20825	1RB#38	19.34	PASS
Band7	15MHz	QPSK	20825	1RB#74	19.89	PASS
Band7	15MHz	16QAM	20825	1RB#74	19.12	PASS
Band7	15MHz	QPSK	20825	38RB#0	19.22	PASS
Band7	15MHz	16QAM	20825	38RB#0	19.27	PASS
Band7	15MHz	QPSK	20825	38RB#18	19.23	PASS
Band7	15MHz	16QAM	20825	38RB#18	19.20	PASS
Band7	15MHz	QPSK	20825	38RB#37	19.25	PASS
Band7	15MHz	16QAM	20825	38RB#37	19.25	PASS
Band7	15MHz	QPSK	20825	75RB#0	19.27	PASS
Band7	15MHz	16QAM	20825	75RB#0	18.19	PASS
Band7	15MHz	QPSK	21100	1RB#0	20.28	PASS
Band7	15MHz	16QAM	21100	1RB#0	19.61	PASS
Band7	15MHz	QPSK	21100	1RB#38	20.45	PASS
Band7	15MHz	16QAM	21100	1RB#38	19.75	PASS
Band7	15MHz	QPSK	21100	1RB#74	20.07	PASS
Band7	15MHz	16QAM	21100	1RB#74	19.36	PASS
Band7	15MHz	QPSK	21100	38RB#0	19.52	PASS
Band7	15MHz	16QAM	21100	38RB#0	19.50	PASS
Band7	15MHz	QPSK	21100	38RB#18	19.51	PASS
Band7	15MHz	16QAM	21100	38RB#18	19.50	PASS
Band7	15MHz	QPSK	21100	38RB#37	19.50	PASS
Band7	15MHz	16QAM	21100	38RB#37	19.57	PASS
Band7	15MHz	QPSK	21100	75RB#0	19.52	PASS
Band7	15MHz	16QAM	21100	75RB#0	18.49	PASS
Band7	15MHz	QPSK	21375	1RB#0	19.99	PASS
Band7	15MHz	16QAM	21375	1RB#0	18.86	PASS
Band7	15MHz	QPSK	21375	1RB#38	20.08	PASS
Band7	15MHz	16QAM	21375	1RB#38	19.08	PASS
Band7	15MHz	QPSK	21375	1RB#74	20.04	PASS
Band7	15MHz	16QAM	21375	1RB#74	18.98	PASS
Band7	15MHz	QPSK	21375	38RB#0	19.19	PASS
Band7	15MHz	16QAM	21375	38RB#0	19.15	PASS
Band7	15MHz	QPSK	21375	38RB#18	19.20	PASS
Band7	15MHz	16QAM	21375	38RB#18	19.16	PASS
Band7	15MHz	QPSK	21375	38RB#37	19.14	PASS
Band7	15MHz	16QAM	21375	38RB#37	19.13	PASS
Band7	15MHz	QPSK	21375	75RB#0	19.12	PASS
Band7	15MHz	16QAM	21375	75RB#0	18.19	PASS
Band7	20MHz	QPSK	20850	1RB#0	20.10	PASS
Band7	20MHz	16QAM	20850	1RB#0	19.14	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band7	20MHz	QPSK	20850	1RB#49	20.25	PASS
Band7	20MHz	16QAM	20850	1RB#49	19.42	PASS
Band7	20MHz	QPSK	20850	1RB#99	20.00	PASS
Band7	20MHz	16QAM	20850	1RB#99	19.06	PASS
Band7	20MHz	QPSK	20850	50RB#0	19.26	PASS
Band7	20MHz	16QAM	20850	50RB#0	18.21	PASS
Band7	20MHz	QPSK	20850	50RB#25	19.49	PASS
Band7	20MHz	16QAM	20850	50RB#25	18.23	PASS
Band7	20MHz	QPSK	20850	50RB#50	19.27	PASS
Band7	20MHz	16QAM	20850	50RB#50	18.23	PASS
Band7	20MHz	QPSK	20850	100RB#0	19.27	PASS
Band7	20MHz	16QAM	20850	100RB#0	18.36	PASS
Band7	20MHz	QPSK	21100	1RB#0	20.63	PASS
Band7	20MHz	16QAM	21100	1RB#0	19.55	PASS
Band7	20MHz	QPSK	21100	1RB#49	20.65	PASS
Band7	20MHz	16QAM	21100	1RB#49	19.79	PASS
Band7	20MHz	QPSK	21100	1RB#99	19.95	PASS
Band7	20MHz	16QAM	21100	1RB#99	19.15	PASS
Band7	20MHz	QPSK	21100	50RB#0	19.61	PASS
Band7	20MHz	16QAM	21100	50RB#0	18.67	PASS
Band7	20MHz	QPSK	21100	50RB#25	19.68	PASS
Band7	20MHz	16QAM	21100	50RB#25	18.69	PASS
Band7	20MHz	QPSK	21100	50RB#50	19.32	PASS
Band7	20MHz	16QAM	21100	50RB#50	18.35	PASS
Band7	20MHz	QPSK	21100	100RB#0	19.51	PASS
Band7	20MHz	16QAM	21100	100RB#0	18.56	PASS
Band7	20MHz	QPSK	21350	1RB#0	19.73	PASS
Band7	20MHz	16QAM	21350	1RB#0	18.87	PASS
Band7	20MHz	QPSK	21350	1RB#49	20.08	PASS
Band7	20MHz	16QAM	21350	1RB#49	19.27	PASS
Band7	20MHz	QPSK	21350	1RB#99	19.80	PASS
Band7	20MHz	16QAM	21350	1RB#99	18.94	PASS
Band7	20MHz	QPSK	21350	50RB#0	19.16	PASS
Band7	20MHz	16QAM	21350	50RB#0	18.27	PASS
Band7	20MHz	QPSK	21350	50RB#25	19.11	PASS
Band7	20MHz	16QAM	21350	50RB#25	18.19	PASS
Band7	20MHz	QPSK	21350	50RB#50	19.16	PASS
Band7	20MHz	16QAM	21350	50RB#50	18.26	PASS
Band7	20MHz	QPSK	21350	100RB#0	19.13	PASS
Band7	20MHz	16QAM	21350	100RB#0	18.17	PASS





<WLAN 2.4GHz Conducted Power>

Mode	Channel	Frequency (MHz)	Average Output Power (dBm)
IEEE 802.11b	1	2412	15.46
	6	2437	15.31
	11	2462	14.83
IEEE 802.11g	1	2412	16.03
	6	2437	15.90
	11	2462	15.60
IEEE 802.11n HT20	1	2412	14.91
	6	2437	14.82
	11	2462	15.90
IEEE 802.11n HT40	3	2422	15.08
	6	2437	13.96
	9	2452	13.84

<WLAN 5.2G Conducted Power>

Mode	Channel	Frequency (MHz)	Conducted Output Power(dBm)	Worst Case Test Rate Data
IEEE 802.11a	36	5180	14.56	MCS0
	40	5200	13.21	MCS0
	48	5240	10.63	MCS0
IEEE 802.11n HT20	36	5180	12.47	MCS0
	40	5200	12.10	MCS0
	48	5240	10.49	MCS0
IEEE 802.11n HT40	38	5190	12.33	MCS0
	46	5230	10.80	MCS0
IEEE 802.11ac VHT20	36	5180	12.38	MCS0
	40	5200	12.27	MCS0
	48	5240	10.51	MCS0
IEEE 802.11ac VHT40	38	5190	12.26	MCS0
	46	5230	10.76	MCS0
IEEE 802.11ac VHT80	42	5210	11.32	MCS0

<WLAN 5.8GHz Conducted Power>

Mode	Channel	Frequency (MHz)	Conducted Output Power(dBm)
802.11a	149	5745	9.85
	157	5785	9.75
	165	5825	8.67
802.11n(20MHz)	149	5745	9.64
	157	5785	9.55
	165	5825	8.55
802.11n(40MHz)	151	5755	9.65
	159	5795	8.94
802.11ac(20MHz)	149	5745	9.64
	157	5785	9.47
	165	5825	8.53
802.11ac(40MHz)	151	5755	9.63
	159	5795	8.95
802.11ac(80MHz)	155	5775	9.22



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



<BT Conducted Power>

Mode	channel	Frequency (MHz)	Conducted AVG output power (dBm)
BLE	0	2402	-5.15
	19	2440	-6.35
	39	2480	-6.29
GFSK	0	2402	8.59
	39	2441	6.61
	78	2480	6.93
$\pi/4$ -DQPSK	0	2402	8.61
	39	2441	6.54
	78	2480	6.99
8DPSK	0	2402	8.64
	39	2441	6.53
	78	2480	7.00

Per KDB 447498 D01v06, the 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$$
 for 1-g SAR and ≤ 7.5 for 10-g extremity SAR

- $f(\text{GHz})$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation
- The result is rounded to one decimal place for comparison


Bluetooth Turn up Power (dBm)	Separation Distance (mm)	Frequency (GHz)	Exclusion Thresholds
9.0	5	2.45	2.5

Per KDB 447498 D01v06, when the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion. The test exclusion threshold is $2.5 < 3.0$, SAR testing is not required.





4.2. Transmit Antennas and SAR Measurement Position



Antenna information:

WLAN/BT Antenna	WLAN/BT TX/RX
WWAN Antenna	GSM/UMTS/LTE TX/RX

Note:

- 1). Per KDB648474 D04, because the overall diagonal distance of this devices is 283mm>160mm, it is considered as "Tablet PC" device.
- 2). Per KDB648474 D04, 10-g extremity SAR is not required when Body-Worn mode 1-g reported SAR < 1.2 W/Kg.
- 3). According to the KDB941225 D06 Hot Spot SAR v02, the edges with less than 25 mm distance to the antennas need to be tested for SAR.
- 4). Per KDB 616217 D04, The antennas in tablets are typically located near the back (bottom) surface and/or along the edges of the devices; therefore, SAR evaluation is required for these configurations. Exposures from antennas through the front (top) surface of the displaysection of a full-size tablet, away from the edges, are generally limited to the user's hands.

Distance of The Antenna to the EUT surface and edge (mm)					
Antennas	Back	Top Side	Bottom Side	Left Side	Right Side
WWAN	<5	232	<5	<5	<5
BT/WLAN	<5	163	84	<5	147

Positions for SAR tests; Hotspot mode					
Antennas	Back	Top Side	Bottom Side	Left Side	Right Side
WWAN	Yes	No	Yes	Yes	Yes
BT/WLAN	Yes	No	No	Yes	No

General Note: Referring to KDB 941225 D06 v02, When the overall device length and width are $\geq 9\text{cm} \times 5\text{cm}$, the test distance is 0mm, SAR must be measured for all sides and surfaces with a transmitting antenna located with 25mm from that surface or edge.





4.3. SAR Measurement Results

The calculated SAR is obtained by the following formula:

$$\text{Reported SAR} = \text{Measured SAR} * 10^{(P_{\text{target}} - P_{\text{measured}})/10}$$

$$\text{Scaling factor} = 10^{(P_{\text{target}} - P_{\text{measured}})/10}$$

$$\text{Reported SAR} = \text{Measured SAR} * \text{Scaling factor}$$

Where

P_{target} is the power of manufacturing upper limit;

P_{measured} is the measured power;

Measured SAR is measured SAR at measured power which including power drift)

Reported SAR which including Power Drift and Scaling factor

Duty Cycle

Test Mode	Duty Cycle
GSM	1:2.67
UMTS	1:1
LTE	1:1
WLAN2450	1:1
WLAN5200	1:1
WLAN5800	1:1

4.3.1 SAR Results

SAR Values [GSM 850]

Ch.	Freq. (MHz)	Time slots	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
190	836.6	3Txslots	Rear	29.49	29.50	1.00	1.002	0.592	0.593	Plot 1
190	836.6	3Txslots	Left	29.49	29.50	-4.21	1.002	0.575	0.576	
190	836.6	3Txslots	Right	29.49	29.50	0.02	1.002	0.562	0.563	
190	836.6	3Txslots	Bottom	29.49	29.50	3.96	1.002	0.543	0.544	

Remark:

1. The value with black color is the maximum SAR Value of each test band.

2. The frame average of GPRS (4Tx slots) higher than GSM and sample can support VoIP function, tested at GPRS (4Tx slots) mode for head.

3. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).

SAR Values [GSM 1900]

Ch.	Freq. (MHz)	time slots	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers – Body (hotspot open, distance 0mm)										
661	1880.0	4Txslots	Rear	25.03	25.50	2.41	1.114	0.546	0.608	Plot 2
661	1880.0	4Txslots	Left	25.03	25.50	-3.32	1.114	0.524	0.584	
661	1880.0	4Txslots	Right	25.03	25.50	0.05	1.114	0.516	0.575	
661	1880.0	4Txslots	Bottom	25.03	25.50	-4.75	1.114	0.503	0.560	

Remark:

1. The value with black color is the maximum SAR Value of each test band.

2. The frame average of GPRS (4Tx slots) higher than GSM and sample can support VoIP function, tested at GPRS (4Tx slots) mode for head.

3. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**SAR Values [WCDMA Band V]**

Ch.	Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers – Body (hotspot open, distance 0mm)										
4183	836.6	RMC*	Rear	23.51	24.00	-0.48	1.119	0.593	0.664	Plot 3
4183	836.6	RMC*	Left	23.51	24.00	-2.08	1.119	0.577	0.646	
4183	836.6	RMC*	Right	23.51	24.00	1.41	1.119	0.563	0.630	
4183	836.6	RMC*	Bottom	23.51	24.00	3.65	1.119	0.541	0.606	

Remark:

1. The value with black color is the maximum SAR Value of each test band.
2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).
3. RMC* - RMC 12.2kbps mode;

SAR Values [WCDMA Band II]

Ch.	Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reporte d	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
9400	1880.0	RMC*	Rear	23.65	24.00	1.28	1.084	0.727	0.788	Plot 4
9400	1880.0	RMC*	Left	23.65	24.00	-3.21	1.084	0.704	0.763	
9400	1880.0	RMC*	Right	23.65	24.00	0.52	1.084	0.688	0.746	
9400	1880.0	RMC*	Bottom	23.65	24.00	4.85	1.084	0.671	0.727	

Remark:

1. The value with black color is the maximum SAR Value of each test band.
2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).
3. RMC* - RMC 12.2kbps mode;

SAR Values [LTE Band 2]

Ch.	Freq. (MHz)	Channel Type (10M)	Test Position	Condu cted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR1-g results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
18900	1880.0	1RB	Rear	21.89	22.00	0.03	1.026	0.274	0.281	Plot 5
18900	1880.0	1RB	Left	21.89	22.00	-3.96	1.026	0.254	0.261	
18900	1880.0	1RB	Right	21.89	22.00	0.02	1.026	0.234	0.240	
18900	1880.0	1RB	Bottom	21.89	22.00	-4.71	1.026	0.221	0.227	
18900	1880.0	50%RB	Rear	20.79	21.00	2.58	1.050	0.137	0.144	
18900	1880.0	50%RB	Left	20.79	21.00	0.09	1.050	0.115	0.121	
18900	1880.0	50%RB	Right	20.79	21.00	-1.74	1.050	0.103	0.108	
18900	1880.0	50%RB	Bottom	20.79	21.00	-3.65	1.050	0.095	0.100	



**SAR Values [LTE Band 4]**

Ch.	Freq. (MHz)	Channel Type (10M)	Test Position	Conduc ted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR1-g results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
20175	1732.5	1RB	Rear	22.00	22.00	-1.13	1.000	0.662	0.662	Plot 6
20175	1732.5	1RB	Left	22.00	22.00	-4.74	1.000	0.653	0.653	
20175	1732.5	1RB	Right	22.00	22.00	3.65	1.000	0.638	0.638	
20175	1732.5	1RB	Bottom	22.00	22.00	0.02	1.000	0.614	0.614	
20175	1732.5	50%RB	Rear	21.09	21.50	4.52	1.099	0.332	0.365	
20175	1732.5	50%RB	Left	21.09	21.50	-1.98	1.099	0.316	0.347	
20175	1732.5	50%RB	Right	21.09	21.50	0.96	1.099	0.305	0.335	
20175	1732.5	50%RB	Bottom	21.09	21.50	0.02	1.099	0.288	0.317	

SAR Values [LTE Band 5]

Ch.	Freq. (MHz)	Channel Type (10M)	Test Position	Conduc ted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR1-g results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
20450	829.0	1RB	Rear	22.67	23.00	-2.67	1.079	0.718	0.775	Plot 7
20450	829.0	1RB	Left	22.67	23.00	-2.02	1.079	0.699	0.754	
20450	829.0	1RB	Right	22.67	23.00	3.36	1.079	0.682	0.736	
20450	829.0	1RB	Bottom	22.67	23.00	4.12	1.079	0.664	0.716	
20450	829.0	50%RB	Rear	21.68	22.00	-1.17	1.076	0.360	0.388	
20450	829.0	50%RB	Left	21.68	22.00	0.02	1.076	0.348	0.375	
20450	829.0	50%RB	Right	21.68	22.00	3.52	1.076	0.332	0.357	
20450	829.0	50%RB	Bottom	21.68	22.00	-0.09	1.076	0.314	0.338	

SAR Values [LTE Band 7]

Ch.	Freq. (MHz)	Channe l Type (20M)	Test Position	Condu cted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reporte d	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
21100	2535.0	1RB	Rear	20.63	21.00	-0.81	1.089	0.303	0.330	Plot 8
21100	2535.0	1RB	Left	20.63	21.00	-3.63	1.089	0.291	0.317	
21100	2535.0	1RB	Right	20.63	21.00	0.02	1.089	0.274	0.298	
21100	2535.0	1RB	Bottom	20.63	21.00	-1.74	1.089	0.263	0.286	
20850	1720.0	50%RB	Rear	19.26	19.50	2.98	1.057	0.150	0.159	
20850	1720.0	50%RB	Left	19.26	19.50	0.02	1.057	0.139	0.147	
20850	1720.0	50%RB	Right	19.26	19.50	-4.78	1.057	0.122	0.129	
20850	1720.0	50%RB	Bottom	19.26	19.50	3.63	1.057	0.115	0.122	

SAR Values [WIFI2.4G]

Ch.	Freq. (MHz)	Service	Test Position	Conduc ted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
1	2412	802.11b	Rear	15.46	15.50	3.66	1.009	0.040	0.040	
1	2412	802.11b	Left	15.46	15.50	-2.25	1.009	0.032	0.032	
1	2412	802.11g	Rear	16.03	16.50	1.49	1.114	0.045	0.050	Plot 9
1	2412	802.11g	Left	16.03	16.50	-2.22	1.114	0.038	0.042	



**SAR Values [WIFI5.2G]**

Ch.	Freq. (MHz)	Service	Test Position	Conduc ted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
36	5180	802.11a	Rear	14.56	15.00	-0.57	1.107	0.081	0.090	Plot 10
36	5180	802.11a	Left	14.56	15.00	1.42	1.107	0.065	0.072	

SAR Values [WIFI5.8G]

Ch.	Freq. (MHz)	Service	Test Position	Condu cted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
149	5745	802.11a	Rear	9.85	10.00	-1.60	1.035	0.021	0.022	Plot 11
149	5745	802.11a	Left	9.85	10.00	3.96	1.035	0.015	0.016	

Remark:

1. The value with black color is the maximum SAR Value of each test band.
2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).
3. When the same maximum output power is specified for both bands, begin SAR measurement in U-NII-2A band by applying the OFDM SAR requirements.19 If the highest reported SAR for a test configuration is ≤ 1.2 W/kg, SAR is not required for U-NII-1 band for that configuration (802.11 mode and exposure condition); otherwise, each band is tested independently for SAR.
4. When different maximum output power is specified for the bands, begin SAR measurement in the band with higher specified maximum output power. The highest reported SAR for the tested configuration is adjusted by the ratio of lower to higher specified maximum output power for the two bands. When the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for the band with lower maximum output power in that test configuration; otherwise, each band is tested independently for SAR.





4.3.2 Standalone SAR Test Exclusion Considerations and Estimated SAR

Per KDB447498 requires when the standalone SAR test exclusion of section 4.3.1 is applied to an antenna that transmits simultaneously with other antennas, the standalone SAR must be estimated according to the following to determine simultaneous transmission SAR test exclusion;

• $(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm}) \cdot [\sqrt{f(\text{GHz})} / x]$ W/kg for test separation distances ≤ 50 mm;

where $x = 7.5$ for 1-g SAR, and $x = 18.75$ for 10-g SAR.

• 0.4 W/kg for 1-g SAR and 1.0 W/kg for 10-g SAR, when the test separation distances is > 50 mm

Per FCC KD B447498 D01, simultaneous transmission SAR test exclusion may be applied when the sum of the 1-g SAR for all the transmitting antenna in a specific a physical test configuration is ≤ 1.6 W/Kg. When the sum is greater than the SAR limit, SAR test exclusion is determined by the SAR to peak location separation ratio.

$$\text{Ratio} = \frac{(\text{SAR}_1 + \text{SAR}_2)^{1.5}}{(\text{peak location separation, mm})} < 0.04$$

Estimated stand alone SAR					
Communication system	Frequency (MHz)	Configuration	Maximum Power (dBm)	Separation Distance (mm)	Estimated SAR _{1-g} (W/kg)
Bluetooth*	2450	Hotspot	9.0	5	0.333
Bluetooth*	2450	Body-worn	9.0	5	0.333

Remark:

1. Bluetooth*- Including Lower power Bluetooth
2. Maximum average power including tune-up tolerance;
3. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion
4. Body as body use distance is 0mm from manufacturer declaration of user manual

4.4. Simultaneous TX SAR Considerations

4.4.1 Introduction

Simultaneous transmission SAR test exclusion is determined for each operating configuration and exposure condition according to the reported standalone SAR of each applicable simultaneous transmitting antenna. The device has 4 antennas, WWAN main antenna, WWAN diversity antenna(RX only), and WiFi antenna supports 2.4Wi-Fi. The 2 TX antennas can always transmit simultaneously. The work mode combination is showed as below table.;

Application Simultaneous Transmission information:

Combination No.	Mode
1	WWAN+WIFI
2	WWAN+BT

4.4.2 Evaluation of Simultaneous SAR

Body Hotspot Exposure Conditions

Simultaneous transmission SAR for WiFi and GSM

Test Position	GSM850 Reported SAR _{1-g} (W/kg)	GSM1900 Reported SAR _{1-g} (W/kg)	WiFi2.4G Reported SAR _{1-g} (W/kg)	WiFi5.2G Reported SAR _{1-g} (W/kg)	WiFi5.8G Reported SAR _{1-g} (W/kg)	MAX. Σ SAR _{1-g} (W/kg)	SAR _{1-g} Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	/	/	/	/	/	/	1.6	no	no
Rear	0.593	0.608	0.050	0.090	0.022	0.698	1.6	no	no
Left	0.576	0.584	0.042	0.072	0.016	0.656	1.6	no	no
Right	0.563	0.575	/	/	/	0.575	1.6	no	no
Bottom	0.544	0.560	/	/	/	0.560	1.6	no	no
Top	/	/	/	/	/	/	1.6	no	no





Simultaneous transmission SAR for WiFi and UMTS

Test Position	UMTS Band V Reported SAR1-g (W/kg)	UMTS Band II Reported SAR1-g (W/kg)	WiFi2.4G Reported SAR1-g (W/kg)	WiFi5.2G Reported SAR1-g (W/kg)	WiFi5.8G Reported SAR1-g (W/kg)	MAX. Σ SAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	/	/	/	/	/	/	1.6	no	no
Rear	0.664	0.788	0.050	0.090	0.022	0.878	1.6	no	no
Left	0.646	0.763	0.042	0.072	0.016	0.835	1.6	no	no
Right	0.630	0.746	/	/	/	0.746	1.6	no	no
Bottom	0.606	0.727	/	/	/	0.727	1.6	no	no
Top	/	/	/	/	/	/	1.6	no	no

SAR for WiFi and LTE

Reported SAR1-g(W/kg)	Test Position					
	Front	Rear	Left	Right	Bottom	Top
LTE Band2	/	0.281	0.261	0.240	0.227	/
LTE Band4	/	0.662	0.653	0.638	0.614	/
LTE Band5	/	0.775	0.754	0.736	0.716	/
LTE Band7	/	0.330	0.317	0.298	0.286	/
WiFi2.4G	/	0.050	0.042	/	/	/
WiFi5.2G	/	0.090	0.072	/	/	/
WiFi5.8G	/	0.022	0.016	/	/	/
MAX. Σ SAR1-g (W/kg)	/	0.865	0.826	0.736	0.716	/
SAR1-g Limit (W/kg)	1.6	1.6	1.6	1.6	1.6	1.6
Peak location separation ratio	no	no	no	no	no	no
Simut Meas. Required	no	no	no	no	no	no

Simultaneous transmission SAR for BT and GSM

Test Position	GSM850 Reported SAR1-g (W/kg)	GSM1900 Reported SAR1-g (W/kg)	BT Estimated SAR1-g (W/kg)	MAX. Σ SAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	/	/	/	/	1.6	no	no
Rear	0.593	0.608	0.333	0.941	1.6	no	no
Left	0.576	0.584	0.333	0.917	1.6	no	no
Right	0.563	0.575	/	0.575	1.6	no	no
Bottom	0.544	0.560	/	0.560	1.6	no	no
Top	/	/	/	/	1.6	no	no

Simultaneous transmission SAR for BT and UMTS

Test Position	UMTS Band V Reported SAR1-g (W/kg)	UMTS Band II Reported SAR1-g (W/kg)	BT Estimated SAR1-g (W/kg)	MAX. Σ SAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	/	/	/	/	1.6	no	no
Rear	0.664	0.788	0.333	1.121	1.6	no	no
Left	0.646	0.763	0.333	1.096	1.6	no	no
Right	0.630	0.746	/	0.746	1.6	no	no
Bottom	0.606	0.727	/	0.727	1.6	no	no
Top	/	/	/	/	1.6	no	no

Simultaneous transmission SAR for BT and LTE

Reported SAR1-g(W/kg)	Test Position					
	Front	Rear	Left	Right	Bottom	Top
LTE Band2	/	0.281	0.261	0.240	0.227	/
LTE Band4	/	0.662	0.653	0.638	0.614	/
LTE Band5	/	0.775	0.754	0.736	0.716	/
LTE Band7	/	0.330	0.317	0.298	0.286	/
BT Estimated SAR1-g (W/kg)	/	0.333	0.333	/	/	/
MAX. Σ SAR1-g (W/kg)	/	1.108	1.087	0.736	0.716	/
SAR1-g Limit (W/kg)	1.6	1.6	1.6	1.6	1.6	1.6
Peak location separation ratio	no	no	no	no	no	no
Simut Meas. Required	no	no	no	no	no	no

Note:



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



1. The WiFi and BT share same antenna, so cannot transmit at same time.
2. The value with black color is the maximum values of standalone
3. The value with blue color is the maximum values of ΣSAR_{1-g}

4.5. SAR Measurement Variability

According to KDB865664, Repeated measurements are required only when the measured SAR is ≥ 0.80 W/kg. If the measured SAR value of the initial repeated measurement is < 1.45 W/kg with $\leq 20\%$ variation, only one repeated measurement is required to reaffirm that the results are not expected to have substantial variations, which may introduce significant compliance concerns. A second repeated measurement is required only if the measured result for the initial repeated measurement is within 10% of the SAR limit and vary by more than 20%, which are often related to device and measurement setup difficulties. The following procedures are applied to determine if repeated measurements are required. The same procedures should be adapted for measurements according to extremity and occupational exposure limits by applying a factor of 2.5 for extremity exposure and a factor of 5 for occupational exposure to the corresponding SAR thresholds.¹⁹ The repeated measurement results must be clearly identified in the SAR report. All measured SAR, including the repeated results, must be considered to determine compliance and for reporting according to KDB 690783. Repeated measurement is not required when the original highest measured SAR is < 0.80 W/kg; steps 2) through 4) do not apply.

- 3) When the original highest measured SAR is ≥ 0.80 W/kg, repeat that measurement once.
- 4) Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is > 1.20 or when the original or repeated measurement is ≥ 1.45 W/kg ($\sim 10\%$ from the 1-g SAR limit).
- 5) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .
- 6) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .

Frequency Band (MHz)	Air Interface	RF Exposure Configuration	Test Position	Repeated SAR (yes/no)	Highest Measured SAR _{1-g} (W/Kg)	First Repeated	
						Measured SAR _{1-g} (W/Kg)	Largest to Smallest SAR Ratio
850	GSM 850	Standalone	Body-Rear	no	0.592	n/a	n/a
	WCDMA Band V	Standalone	Body-Rear	no	0.593	n/a	n/a
	LTE Band 5	Standalone	Body-Rear	no	0.718	n/a	n/a
1800	LTE Band 4	Standalone	Body-Rear	no	0.662	n/a	n/a
1900	GSM 1900	Standalone	Body-Rear	no	0.546	n/a	n/a
	WCDMA Band II	Standalone	Body-Rear	no	0.727	n/a	n/a
	LTE Band 2	Standalone	Body-Rear	no	0.274	n/a	n/a
2450	2.4GWLAN	Standalone	Body-Rear	no	0.045	n/a	n/a
2600	LTE Band 7	Standalone	Body-Rear	no	0.303	n/a	n/a
5200	5.2GWLAN	Standalone	Body-Rear	no	0.081	n/a	n/a
5800	5.8 GWLAN	Standalone	Body-Rear	no	0.021	n/a	n/a

Remark:

1. Second Repeated Measurement is not required since the ratio of the largest to smallest SAR for the original and first repeated measurement is not > 1.20 or 3 (1-g or 10-g respectively)





4.6. General description of test procedures

1. Test positions as described in the tables above are in accordance with the specified test standard.
2. Tests in body position were performed in that configuration, which generates the highest time based averaged output power (see conducted power results).
3. According to IEEE 1528 the SAR test shall be performed at middle channel. Testing of top and bottom channel is optional.
4. According to KDB 447498 D01 testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz
 - ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz
 - ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
5. IEEE 1528-2003 require the middle channel to be tested first. This generally applies to wireless devices that are designed to operate in technologies with tight tolerances for maximum output power variations across channels in the band. When the maximum output power variation across the required test channels is $> \frac{1}{2}$ dB, instead of the middle channel, the highest output power channel must be used.
6. When the same maximum output power is specified for both bands, begin SAR measurement in U-NII-2A band by applying the OFDM SAR requirements.19 If the highest reported SAR for a test configuration is ≤ 1.2 W/kg, SAR is not required for U-NII-1 band for that configuration (802.11 mode and exposure condition); otherwise, each band is tested independently for SAR.
7. When different maximum output power is specified for the bands, begin SAR measurement in the band with higher specified maximum output power. The highest reported SAR for the tested configuration is adjusted by the ratio of lower to higher specified maximum output power for the two bands. When the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for the band with lower maximum output power in that test configuration; otherwise, each band is tested independently for SAR.

4.7. Measurement Uncertainty (450MHz-6GHz)

Not required as SAR measurement uncertainty analysis is required in SAR reports only when the highest measured SAR in a frequency band is ≥ 1.5 W/kg for 1-g SAR according to KDB865664D01.





4.8. System Check Results



Test mode:835MHz(Head)


Product Description:Validation

Model:Dipole SID835

E-Field Probe:SSE2(SN 25/22 EPGO376)

Test Date: July 14, 2023

Medium(liquid type)	HSL_835
Frequency (MHz)	835.0000
Relative permittivity (real part)	42.65
Conductivity (S/m)	0.87
Input power	100mW
Crest Factor	1.0
Conversion Factor	1.75
Variation (%)	-1.520000
SAR 10g (W/Kg)	0.638132
SAR 1g (W/Kg)	0.951488
SURFACE SAR	VOLUME SAR
	



Shenzhen LCS Compliance Testing Laboratory Ltd.



Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China


Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:1800MHz(Head)
Product Description:Validation
Model :Dipole SID1800
E-Field Probe:SSE2(SN 25/22 EPGO376)
Test Date: July 17, 2023




Medium(liquid type)	HSL_1800
Frequency (MHz)	1800.0000
Relative permittivity (real part)	39.11
Conductivity (S/m)	1.42
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.09
Variation (%)	0.970000
SAR 10g (W/Kg)	2.044283
SAR 1g (W/Kg)	3.831085
SURFACE SAR	VOLUME SAR
	





Test mode:1900MHz(Head)
Product Description:Validation
Model :Dipole SID1900
E-Field Probe:SSE2(SN 25/22 EPGO376)
Test Date: July 18, 2023

Medium(liquid type)	HSL_1900
Frequency (MHz)	1900.0000
Relative permittivity (real part)	38.71
Conductivity (S/m)	1.43
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.14
Variation (%)	-3.630000
SAR 10g (W/Kg)	2.087260
SAR 1g (W/Kg)	3.965162

SURFACE SAR**VOLUME SAR**





Test mode:2450MHz(Head)


Product Description:Validation

Model:Dipole SID2450

E-Field Probe:SSE2(SN 25/22 EPGO376)

Test Date: July 19, 2023

Medium(liquid type)	HSL_2450
Frequency (MHz)	2450.0000
Relative permittivity (real part)	40.24
Conductivity (S/m)	1.77
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.60
Variation (%)	1.780000
SAR 10g (W/Kg)	2.557463
SAR 1g (W/Kg)	5.435016
SURFACE SAR	VOLUME SAR
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





Test mode:2600MHz


Product Description:Validation

Model:Dipole SID2600

E-Field Probe: SSE2(SN 25/22 EPGO376)

Test Date: July 21, 2023

Medium(liquid type)	HSL_2600
Frequency (MHz)	2600.0000
Relative permittivity (real part)	37.85
Conductivity (S/m)	1.98
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.39
Variation (%)	0.520000
SAR 10g (W/Kg)	2.274235
SAR 1g (W/Kg)	5.733023
SURFACE SAR	VOLUME SAR
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China




Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:5200MHz(Head)
Product Description:Validation
Model:Dipole SID5000
E-Field Probe: SSE2(SN 25/22 EPGO376)
Test Date: July 24, 2023




Medium(liquid type)	HSL _5000
Frequency (MHz)	5200.0000
Relative permittivity (real part)	35.14
Conductivity (S/m)	4.69
Input power	100mW
Crest Factor	1.0
Conversion Factor	1.85
Variation (%)	-4.630000
SAR 10g (W/Kg)	5.900210
SAR 1g (W/Kg)	17.218034
SURFACE SAR	VOLUME SAR





Test mode:5800MHz(Head)
Product Description:Validation
Model:Dipole SID5000
E-Field Probe: SSE2(SN 25/22 EPG0376)
Test Date: July 26, 2023

Medium(liquid type)	HSL _5000
Frequency (MHz)	5800.0000
Relative permittivity (real part)	35.09
Conductivity (S/m)	5.29
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.01
Variation (%)	-1.890000
SAR 10g (W/Kg)	6.166085
SAR 1g (W/Kg)	18.297125
SURFACE SAR	VOLUME SAR





4.9. SAR Test Graph Results

SAR plots for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination





#1 Test Mode: GSM850MHz, Middle channel (Body Rear Side)

Product Description: Tablet

Model: 10LB2

Test Date: July 14, 2023

Medium(liquid type)	HSL_835
Frequency (MHz)	836.6000
Relative permittivity (real part)	43.27
Conductivity (S/m)	0.85
E-Field Probe	SN 25/22 EPG0376
Crest Factor	2.0
Conversion Factor	1.75
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7, dx=8mm dy=8mm dz=5mm
Variation (%)	1.000000
SAR 10g (W/Kg)	0.352567
SAR 1g (W/Kg)	0.592036
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity




#2

Test Mode: GPRS1900MHz,Middle channel(Body Rear Side)

Product Description:Tablet

Model:10LB2

Test Date: July 18, 2023



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







#3

Test Mode: WCDMA Band V, Middle channel(Body Rear Side)

Product Description: Tablet

Model:10LB2

Test Date: July 14, 2023

Medium(liquid type)	HSL_835
Frequency (MHz)	836.6000
Relative permittivity (real part)	43.27
Conductivity (S/m)	0.85
E-Field Probe	SN 25/22 EPG0376
Crest Factor	1.0
Conversion Factor	1.75
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.480000
SAR 10g (W/Kg)	0.363873
SAR 1g (W/Kg)	0.593258
SURFACE SAR	VOLUME SAR
	
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#4





Test Mode: WCDMA Band II, Middle channel(Body Rear Side)

Product Description: Tablet

Model:10LB2

Test Date: July 18, 2023

Medium(liquid type)	HSL_1900
Frequency (MHz)	1880.0000
Relative permittivity (real part)	39.04
Conductivity (S/m)	1.40
E-Field Probe	SN 25/22 EPG0376
Crest Factor	1.0
Conversion Factor	2.14
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	1.280000
SAR 10g (W/Kg)	0.441067
SAR 1g (W/Kg)	0.727209
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#5





Test Mode: LTE Band 2, 1RB,Middle channel(Body Rear Side)

Product Description:Tablet

Model:10LB2

Test Date: July 18, 2023

Medium(liquid type)	HSL_1900
Frequency (MHz)	1880.0000
Relative permittivity (real part)	39.04
Conductivity (S/m)	1.40
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.14
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	0.030000
SAR 10g (W/Kg)	0.147834
SAR 1g (W/Kg)	0.273632
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#6





Test Mode: LTE Band 4, 1RB,Middle channel(Body Rear Side)

Product Description:Tablet

Model:10LB2

Test Date: July 17, 2023

Medium(liquid type)	HSL_1800
Frequency (MHz)	1732.5000
Relative permittivity (real part)	38.46
Conductivity (S/m)	1.44
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.09
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-1.130000
SAR 10g (W/Kg)	0.347319
SAR 1g (W/Kg)	0.661983
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#7





Test Mode: LTE Band 5, 1RB, Low channel(Body Rear Side)

Product Description: Tablet

Model:10LB2

Test Date: July 14, 2023

Medium(liquid type)	HSL_835
Frequency (MHz)	829.0000
Relative permittivity (real part)	43.27
Conductivity (S/m)	0.85
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	1.75
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-2.670000
SAR 10g (W/Kg)	0.409710
SAR 1g (W/Kg)	0.718083
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







#8

Test Mode: LTE Band 7, 1RB, Middle channel (Body Rear Side)

Product Description: Tablet

Model: 10LB2

Test Date: July 21, 2023

Medium(liquid type)	HSL 2600
Frequency (MHz)	2535.0000
Relative permittivity (real part)	39.44
Conductivity (S/m)	1.96
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.39
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.810000
SAR 10g (W/Kg)	0.135628
SAR 1g (W/Kg)	0.302727
SURFACE SAR	VOLUME SAR
	
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#9





Test Mode: 802.11g (WiFi2.4G), Low channel(Body Rear Side)

Product Description: Tablet

Model:10LB2

Test Date: July 19, 2023

Medium(liquid type)	HSL_2450
Frequency (MHz)	2412.0000
Relative permittivity (real part)	41.46
Conductivity (S/m)	1.76
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.60
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	1.490000
SAR 10g (W/Kg)	0.018791
SAR 1g (W/Kg)	0.044959
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#10





Test Mode: 802.11a (WiFi5.2G), Low channel(Body Rear Side)

Product Description: Tablet

Model:10LB2

Test Date: July 24, 2023

Medium(liquid type)	HSL_5200
Frequency (MHz)	5180.0000
Relative permittivity (real part)	36.04
Conductivity (S/m)	4.67
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	1.85
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.570000
SAR 10g (W/Kg)	0.025834
SAR 1g (W/Kg)	0.081046
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#11





Test Mode: 802.11a (WiFi5.8G), Low channel(Body Rear Side)

Product Description: Tablet

Model:10LB2

Test Date: July 26, 2023

Medium(liquid type)	HSL_5800
Frequency (MHz)	5745.0000
Relative permittivity (real part)	36.45
Conductivity (S/m)	5.26
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.01
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-1.600000
SAR 10g (W/Kg)	0.007152
SAR 1g (W/Kg)	0.020637
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



5. CALIBRATION CERTIFICATES

5.1 Probe-EPGO376 Calibration Certificate



COMOSAR E-Field Probe Calibration Report

Ref : ACR.180.4.42.BES.A

SHENZHEN LCS COMPLIANCE TESTING LABORATORY LTD.

1F., XINGYUAN INDUSTRIAL PARK, TONGDA ROAD, BAO'AN
BLVD

BAO'AN DISTRICT, SHENZHEN, GUANGDONG, CHINA

MVG COMOSAR DOSIMETRIC E-FIELD PROBE

SERIAL NO.: SN 25/22 EPGO376

Calibrated at MVG

Z.I. de la pointe du diable

Technopôle Brest Iroise – 295 avenue Alexis de Rochon

29280 PLOUZANE - FRANCE

Calibration date: 06/22/2023



Accreditations #2-6792
Scope available on www.cofrac.fr

The use of the Cofrac brand and the accreditation references is prohibited from any reproduction.

Summary:

This document presents the method and results from an accredited COMOSAR Dosimetric E-Field Probe calibration performed at MVG, using the CALIPROBE test bench, for use with a MVG COMOSAR system only. The test results covered by accreditation are traceable to the International System of Units (SI).





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

	Name	Function	Date	Signature
Prepared by :	Jérôme Le Gall	Measurement Responsible	6/23/2023	
Checked & approved by:	Jérôme Luc	Technical Manager	6/23/2023	
Authorized by:	Yann Toutain	Laboratory Director	6/23/2023	

2023.06.23

13:37:50 +02'03'

	Customer Name
Distribution :	Shenzhen LCS Compliance Testing Laboratory Ltd.

Issue	Name	Date	Modifications
A	Jérôme Le Gall	6/23/2023	Initial release

Page: 2/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

TABLE OF CONTENTS

1	Device Under Test	4
2	Product Description	4
2.1	General Information	4
3	Measurement Method	4
3.1	Linearity	4
3.2	Sensitivity	4
3.3	Lower Detection Limit	5
3.4	Isotropy	5
3.1	Boundary Effect	5
4	Measurement Uncertainty	6
5	Calibration Measurement Results	6
5.1	Sensitivity in air	6
5.2	Linearity	7
5.3	Sensitivity in liquid	8
5.4	Isotropy	9
6	List of Equipment	10

Page: 3/11

*Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK**This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.*



COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

1 DEVICE UNDER TEST

Device Under Test	
Device Type	COMOSAR DOSIMETRIC E FIELD PROBE
Manufacturer	MVG
Model	SSE2
Serial Number	SN 25/22 EPG0376
Product Condition (new / used)	New
Frequency Range of Probe	0.15 GHz-6GHz
Resistance of Three Dipoles at Connector	Dipole 1: R1=0.193 MΩ Dipole 2: R2=0.188 MΩ Dipole 3: R3=0.198 MΩ

2 PRODUCT DESCRIPTION

2.1 GENERAL INFORMATION

MVG's COMOSAR E field Probes are built in accordance to the IEC/IEEE 62209-1528 and FCC KDB865664 D01 standards.



Figure 1 – MVG COMOSAR Dosimetric E field Probe

Probe Length	330 mm
Length of Individual Dipoles	2 mm
Maximum external diameter	8 mm
Probe Tip External Diameter	2.5 mm
Distance between dipoles / probe extremity	1 mm

3 MEASUREMENT METHOD

The IEC/IEEE 62209-1528 and FCC KDB865664 D01 standards provide recommended practices for the probe calibrations, including the performance characteristics of interest and methods by which to assess their affect. All calibrations / measurements performed meet the fore mentioned standards.

3.1 LINEARITY

The evaluation of the linearity was done in free space using the waveguide, performing a power sweep to cover the SAR range 0.01W/kg to 100W/kg.

3.2 SENSITIVITY

The sensitivity factors of the three dipoles were determined using a two step calibration method (air and tissue simulating liquid) using waveguides as outlined in the standards.

Page: 4/11

Template_ACR.DDD.N.YY.MVGE.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

3.3 LOWER DETECTION LIMIT

The lower detection limit was assessed using the same measurement set up as used for the linearity measurement. The required lower detection limit is 10 mW/kg.

3.4 ISOTROPY

The axial isotropy was evaluated by exposing the probe to a reference wave from a standard dipole with the dipole mounted under the flat phantom in the test configuration suggested for system validations and checks. The probe was rotated along its main axis from 0 to 360 degrees in 15-degree steps. The hemispherical isotropy is determined by inserting the probe in a thin plastic box filled with tissue-equivalent liquid, with the plastic box illuminated with the fields from a half wave dipole. The dipole is rotated about its axis (0°–180°) in 15° increments. At each step the probe is rotated about its axis (0°–360°).

3.1 BOUNDARY EFFECT

The boundary effect is defined as the deviation between the SAR measured data and the expected exponential decay in the liquid when the probe is oriented normal to the interface. To evaluate this effect, the liquid filled flat phantom is exposed to fields from either a reference dipole or waveguide. With the probe normal to the phantom surface, the peak spatial average SAR is measured and compared to the analytical value at the surface.

The boundary effect uncertainty can be estimated according to the following uncertainty approximation formula based on linear and exponential extrapolations between the surface and $d_{be} + d_{step}$ along lines that are approximately normal to the surface:

$$SAR_{uncertainty} [\%] = \Delta SAR_{be} \frac{(d_{be} + d_{step})^2}{2d_{step}} \frac{(e^{-d_{be}/\delta} - e^{-(d_{be} + d_{step})/\delta})}{\delta/2} \quad \text{for } (d_{be} + d_{step}) < 10 \text{ mm}$$

where

$SAR_{uncertainty}$ is the uncertainty in percent of the probe boundary effect

d_{be} is the distance between the surface and the closest *zoom-scan* measurement point, in millimetre

Δ_{step} is the separation distance between the first and second measurement points that are closest to the phantom surface, in millimetre, assuming the boundary effect at the second location is negligible

δ is the minimum penetration depth in millimetres of the head tissue-equivalent liquids defined in this standard, i.e., $\delta \approx 14$ mm at 3 GHz;

ΔSAR_{be} in percent of SAR is the deviation between the measured SAR value, at the distance d_{be} from the boundary, and the analytical SAR value.

The measured worst case boundary effect SAR uncertainty[%] for scanning distances larger than 4mm is 1.0% Limit ,2%).

Page: 5/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

4 MEASUREMENT UNCERTAINTY

The guidelines outlined in the IEC/IEEE 62209-1528 and FCC KDB865664 D01 standards were followed to generate the measurement uncertainty associated with an E-field probe calibration using the waveguide technique. All uncertainties listed below represent an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=2$, traceable to the Internationally Accepted Guides to Measurement Uncertainty.

Uncertainty analysis of the probe calibration in waveguide					
ERROR SOURCES	Uncertainty value (%)	Probability Distribution	Divisor	ci	Standard Uncertainty (%)
Expanded uncertainty 95 % confidence level $k = 2$					14 %

5 CALIBRATION MEASUREMENT RESULTS

Calibration Parameters	
Liquid Temperature	20 +/- 1 °C
Lab Temperature	20 +/- 1 °C
Lab Humidity	30-70 %

5.1 SENSITIVITY IN AIR

Normx dipole 1 ($\mu\text{V}/(\text{V}/\text{m})^2$)	Normy dipole 2 ($\mu\text{V}/(\text{V}/\text{m})^2$)	Normz dipole 3 ($\mu\text{V}/(\text{V}/\text{m})^2$)
0.76	0.78	0.76

DCP dipole 1 (mV)	DCP dipole 2 (mV)	DCP dipole 3 (mV)
106	107	108

Calibration curves $e_i=f(V)$ ($i=1,2,3$) allow to obtain E-field value using the formula:

$$E = \sqrt{E_1^2 + E_2^2 + E_3^2}$$

Page: 6/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.







COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

Calibration curves

5.2 LINEARITY

Linearity

Linearity: $\pm 1.81\%$ ($\pm 0.08\text{dB}$)

Page: 7/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

5.3 SENSITIVITY IN LIQUID

Liquid	Frequency (MHz +/- 100MHz)	ConvF
HL450*	450*	1.74*
BL450*	450*	1.67*
HL750	750	1.69
BL750	750	1.73
HL850	835	1.75
BL850	835	1.80
HL900	900	1.87
BL900	900	1.85
HL1800	1800	2.09
BL1800	1800	2.15
HL1900	1900	2.14
BL1900	1900	2.27
HL2000	2000	2.31
BL2000	2000	2.34
HL2300	2300	2.46
BL2300	2300	2.51
HL2450	2450	2.60
BL2450	2450	2.70
HL2600	2600	2.39
BL2600	2600	2.50
HL5200	5200	1.85
BL5200	5200	1.81
HL5400	5400	2.07
BL5400	5400	2.00
HL5600	5600	2.19
BL5600	5600	2.11
HL5800	5800	2.01
BL5800	5800	1.97

* Frequency not cover by COFRAC scope, calibration not accredited

LOWER DETECTION LIMIT: 7mW/kg

Page: 8/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK


This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

5.4 ISOTROPYHL1800 MHz

Page: 9/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

6 LIST OF EQUIPMENT

Equipment Summary Sheet				
Equipment Description	Manufacturer / Model	Identification No.	Current Calibration Date	Next Calibration Date
CALIPROBE Test Bench	Version 2	NA	Validated. No cal required.	Validated. No cal required.
Network Analyzer	Rohde & Schwarz ZVM	100203	08/2021	08/2024
Network Analyzer	Agilent 8753ES	MY40003210	10/2022	10/2025
Network Analyzer – Calibration kit	HP 85033D	3423A08186	06/2021	06/2027
Multimeter	Keithley 2000	1160271	02/2023	02/2026
Signal Generator	Rohde & Schwarz SMB	106589	03/2022	03/2025
Amplifier	MVG	MODU-023-C-0002	Characterized prior to test. No cal required.	Characterized prior to test. No cal required.
Power Meter	NI-USB 5680	170100013	06/2021	06/2024
Power Meter	Rohde & Schwarz NRVD	832839-056	11/2022	11/2025
Directional Coupler	Krytar 158020	131467	Characterized prior to test. No cal required.	Characterized prior to test. No cal required.
Waveguide	MVG	SN 32/16 WG4_1	Validated. No cal required.	Validated. No cal required.
Liquid transition	MVG	SN 32/16 WGLIQ_0G900_1	Validated. No cal required.	Validated. No cal required.
Waveguide	MVG	SN 32/16 WG6_1	Validated. No cal required.	Validated. No cal required.
Liquid transition	MVG	SN 32/16 WGLIQ_1G500_1	Validated. No cal required.	Validated. No cal required.
Waveguide	MVG	SN 32/16 WG8_1	Validated. No cal required.	Validated. No cal required.
Liquid transition	MVG	SN 32/16 WGLIQ_1G800B_1	Validated. No cal required.	Validated. No cal required.
Liquid transition	MVG	SN 32/16 WGLIQ_1G800H_1	Validated. No cal required.	Validated. No cal required.
Waveguide	MVG	SN 32/16 WG10_1	Validated. No cal required.	Validated. No cal required.
Liquid transition	MVG	SN 32/16 WGLIQ_3G500_1	Validated. No cal required.	Validated. No cal required.
Waveguide	MVG	SN 32/16 WG12_1	Validated. No cal required.	Validated. No cal required.

Page: 10/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

Liquid transition	MVG	SN 32/16 WGLIQ_5G000_1	Validated. No cal required.	Validated. No cal required.
Temperature / Humidity Sensor	Testo 184 H1	44225320	06/2021	06/2024

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.





5.2 SID835 Dipole Calibration Certificate



SAR Reference Dipole Calibration Report

Ref: ACR.287.4.14.SATU.A

SHENZHEN LCS COMPLIANCE TESTING LABORATORY LTD.

1F., XINGYUAN INDUSTRIAL PARK, TONGDA ROAD,
BAO'AN BLVD

BAO'AN DISTRICT, SHENZHEN, GUANGDONG, CHINA

SATIMO COMOSAR REFERENCE DIPOLE

FREQUENCY: 835 MHZ

SERIAL NO.: SN 07/14 DIP 0G835-303

Calibrated at SATIMO US

2105 Barrett Park Dr. - Kennesaw, GA 30144



09/29/2021

Summary:

This document presents the method and results from an accredited SAR reference dipole calibration performed in SATIMO USA using the COMOSAR test bench. All calibration results are traceable to national metrology institutions.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



SAR REFERENCE DIPOLE CALIBRATION REPORT

Ref: ACR.287.4.14.SATU.A

	Name	Function	Date	Signature
Prepared by :	Jérôme LUC	Product Manager	10/12/2021	
Checked by :	Jérôme LUC	Product Manager	10/12/2021	
Approved by :	Kim RUTKOWSKI	Quality Manager	10/12/2021	

	Customer Name
Distribution :	Shenzhen LCS Compliance Testing Laboratory Ltd.

Issue	Date	Modifications
A	10/12/2021	Initial release

Page: 2/11

This document shall not be reproduced, except in full or in part, without the written approval of SATIMO.
The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of SATIMO.





TABLE OF CONTENTS

1	Introduction.....	4
2	Device Under Test	4
3	Product Description	4
3.1	General Information	4
4	Measurement Method	5
4.1	Return Loss Requirements	5
4.2	Mechanical Requirements	5
5	Measurement Uncertainty	5
5.1	Return Loss	5
5.2	Dimension Measurement	5
5.3	Validation Measurement	5
6	Calibration Measurement Results	6
6.1	Return Loss and Impedance	6
6.2	Mechanical Dimensions	6
7	Validation measurement	7
7.1	Head Liquid Measurement	7
7.2	SAR Measurement Result With Head Liquid	7
7.3	Body Liquid Measurement	9
7.4	SAR Measurement Result With Body Liquid	9
8	List of Equipment	11





1 INTRODUCTION

This document contains a summary of the requirements set forth by the IEEE 1528, OET 65 Bulletin C and CEI/IEC 62209 standards for reference dipoles used for SAR measurement system validations and the measurements that were performed to verify that the product complies with the fore mentioned standards.

2 DEVICE UNDER TEST

Device Under Test	
Device Type	COMOSAR 835 MHz REFERENCE DIPOLE
Manufacturer	Satimo
Model	SID835
Serial Number	SN 07/14 DIP 0G835-303
Product Condition (new / used)	New

A yearly calibration interval is recommended.

3 PRODUCT DESCRIPTION

3.1 GENERAL INFORMATION

Satimo's COMOSAR Validation Dipoles are built in accordance to the IEEE 1528, OET 65 Bulletin C and CEI/IEC 62209 standards. The product is designed for use with the COMOSAR test bench only.



Figure 1 – Satimo COMOSAR Validation Dipole

Page: 4/11

*This document shall not be reproduced, except in full or in part, without the written approval of SATIMO.
The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of SATIMO.*

