

## **FCC ID: 2A83H-ECRF6F1**

### **RF EXPOSURE EVALUATION**

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm <sup>2</sup> )	Average Time
<b>(A) Limits for Occupational/Control Exposures</b>				
<b>300-1500</b>	--	--	<b>F/300</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>5</b>	<b>6</b>
<b>(B) Limits for General Population/Uncontrol Exposures</b>				
<b>300-1500</b>	--	--	<b>F/1500</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>1</b>	<b>30</b>

#### **11.1 Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$**

Where

$P_d$ = Power density in mW/cm<sup>2</sup>

$P_{out}$ =output power to antenna in mW

$G$ = Numeric gain of the antenna relative to isotropic antenna

$\pi$ =3.1416

$R$ = distance between observation point and center of the radiator in cm

$P_d$  the limit of MPE, 1mW/cm<sup>2</sup>, If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

RF Exposure Information: The radiated output power of this device meets the limits of FCC/IC radio frequency exposure limits. This device should be operated with a minimum separation distance of 20cm (8 inches) between the equipment and a person's body.

## 11.2 Measurement Result

RFID

Antenna gain: -28.44 dBi

Measured power (dBm)	Tune-up power (dBm)	Max tune-up power (dBm)	Antenna Gain Numeric	Evaluation result (mW/cm <sup>2</sup> )	Power density Limits (mW/cm <sup>2</sup> )
19.55	19 to 20	20	0.001	0.00003	1

Note: RFID radio frequency has only Single-input and Single-output, one dividing into four ports, The four interfaces cannot work at the same time do not support MIMO

\*\*\* End of Report \*\*\*