



BEC INCORPORATED

ANTENNA GAIN VALUE CALCULATION REPORT

**REFERENCE DOCUMENT:
KDB 789033 D02**

**Legrand Model WNA/WZ3A
adorne 4-Button Scene Controller**

FCC ID: 2AU5D-WACB4

REPORT# BEC-2194-05

**CUSTOMER:
Pass & Seymour/Legrand
50 Boyd Avenue
Syracuse, NY 13209**

PREPARED BY: 
Paul Banker, Test Engineer

REVIEWED and APPROVED BY: 
Steve Fanella, Quality Manager

The results described in this report relate only to the item(s) tested. This document shall not be reproduced except in full without prior written permission of BEC Incorporated







TABLE OF CONTENTS

Notice To Customer	3
Revision History	3
1.0 Administrative Information.....	4
1.1 General Information Table	4
1.2 Antenna Gain Value Calculation (EIRP Minus Maximum Conducted Output Power)...	5
1.3 EIRP (dBm).....	5
1.4 Maximum Conducted Output Power (dBm)	6



Notice To Customer

This report and any recommendations it contain represent the result of BEC’s testing and assessment on behalf of your company. Testing has been conducted according to accepted engineering standards and practices. This report reflects testing and assessment of product samples provided by your company and may not reflect the characteristics of other samples, especially those produced at different times. This report and its findings and recommendations, if implemented, should not be construed as an assurance or implied warranty for the continuing electromagnetic compatibility (EMC) of the product. **BEC shall not be liable for incidental or consequential damages, even if advised of the possibility thereof.**

BEC will not disseminate this report to other parties without your express permission. You may reproduce this report in its entirety including this notice and the entireties of any supplemental test reports on the same product (e.g. reports on additional testing following modification). However ‘you may not reproduce portions of the report (except for the entirety of the summary section) or quote from it for any purpose without specific prior written permission from BEC’.

Revision History

Revision #	Description of Changes	Date of Changes	Date Released
0	Test Report Initial Release	N/A	05/18/2022



1.0 Administrative Information

1.1 General Information Table

Project Number	BEC-2194
Manufacturer	Legrand
Model Number Tested	WNA/WZ3A
EUT Sample Type	FCC Test Code Radiated Sample
EUT Serial Number	None
EUT Sample Number	2194-01
EUT Firmware Version	TestRadio_WNRL63.bin
Frequency of Operation	2405 – 2480 MHz
Antenna Gain Calculated Value	+ 4.28 dBi
Antenna Type	Inverted F
Modulation	O-QPSK
FCC Classification	Digital Transmission System (DTS)
Date Samples Received	02/27/2022
Sample Type and Condition Received	Production Unit Suitable for Test
EUT Description	adorne Wireless 4-Button Scene Controller
FCC ID	2AU5D-WACB4
FCC KDB Guidance Document	KDB 789033 D02 General UNII Test Procedures New Rules v02r01 Section G 2(d)



1.2 Antenna Gain Value Calculation (EIRP Minus Maximum Conducted Output Power)

Antenna Gain Value is calculated as the difference between the Radiated EIRP measurement value of the Highest Peak Corrected Fundamental Tx Frequency Minus the Highest Peak Corrected Maximum Conducted Output Power.

EIRP (dBm): **9.60** dBm
 Maximum Conducted Output Power (dBm): - **5.32** dBm
Calculated Antenna Gain **4.28** dBi

1.3 EIRP (dBm)

“EIRP” is calculated using the following KDB Guidance found in KDB 789033 D02 General UNII Test Procedures New Rules v02r01 Section G 2(d). Highest Peak Corrected Fundamental Tx Frequency converted from dBuV/m to dBm by subtracting 95.2 to get EIRP in (dBm).

d) If radiated measurements are performed, field strength is then converted to EIRP as follows:

(i) $EIRP = ((E \times d)^2) / 30$

where:

- E is the field strength in V/m;
- d is the measurement distance in m;
- EIRP is the equivalent isotropically radiated power in W.

(ii) Working in dB units, the preceding equation is equivalent to:

$$EIRP[dBm] = E[dB\mu V/m] + 20 \log (d[m]) - 104.77$$

(iii) Or, if d is 3 m:

$$EIRP[dBm] = E[dB\mu V/m] - 95.2$$

The Settings on the Measurement Analyzer for measuring the Fundamental Tx Frequency were:

Zigbee Radio, O-QPSK modulation			
Spec Analyzer Settings			ANSI C63.10 requirement
Span	20	MHz	$\geq 3 \times RBW$
RBW	1	MHz	$RBW \geq DTS \text{ BW}$
VBW	3	MHz	$\geq 3 \times RBW$
Sweep	5	ms	Auto

Highest Peak Corrected Fundamental Tx Frequency=**104.8** dBuV/m

Fundamental Tx Frequency	Peak Level Uncorrected	Axis (EUT)	Ant Polarity	Turntable Angle	Antenna Height	Correction Factor	Peak Corrected Total
GHz	dBuV/m	X/Y/Z	H/V	degrees	cm	dB	dBuV/m
2.405	110.3	Y	V	069	102	-5.5	104.8

104.8 dBuV/m minus **95.2** = **9.60 dBm** (EIRP Final)



1.4 Maximum Conducted Output Power (dBm)

Maximum Conducted Output Power at the same Highest Tx Fundamental Frequency of 2.405 GHz during Bench testing of the EUT radio.

The Settings on the Measurement Analyzer for measuring the Fundamental Tx Frequency were:

Zigbee Radio, O-QPSK modulation			
Spec Analyzer Settings			ANSI C63.10 requirement
Span	10	MHz	$\geq 3 \times \text{RBW}$
RBW	3	MHz	$\text{RBW} \geq \text{DTS BW}$
VBW	10	MHz	$\geq 3 \times \text{RBW}$
Sweep	5	ms	Auto

Maximum Conducted Output Power at the same Highest Tx Fundamental Frequency of 2.405 GHz during Bench testing of the EUT radio= **5.32 dBm** (Maximum Conducted Output Power Final)

Channel	Modulation	Frequency (MHz)	Measured Level	Cable # 962 Loss	Total	
					dBm	Watts
11	O-QPSK	2405.0	4.85	0.47	5.32	0.0034
18		2440.0	4.85	0.47	5.32	0.0034
26		2480.0	4.98	0.47	5.45	0.0035