



Product External Specifications
For
802.11ac PCI Express Card

Model Number : MRLBB-1403

Revision: 1.0

Contents

1.0 SCOPE.....	3
1.1 DOCUMENT.....	3
1.2 PRODUCT FEATURES.....	3
2.0 REQUIREMENTS	4
2.1 RADIO CARD SPECIFICATIONS	4
2.2 GENERAL SECTION	4
2.3 SOFTWARE REQUIREMENTS	5
2.3.1 <i>Security</i>	5
2.4 MECHANICAL REQUIREMENTS	5

1.0 Scope

1.1 Document

This document is to specify the product requirements for **802.11ac PCI Express**. This PCI Express card is based on QCA (Qualcomm Atheros) chip that complied with IEEE 802.11ac from 5GHz, and it is also backward compatible to comply with IEEE 802.11a and IEEE 802.11n standard.

1.2 Product Features

- a) Dual band 802.11a / n/ ac radio
 - i) 3 streams 3x3 MIMO
 - ii) 5G operation
 - iii) 1.3Gbps data rate
- b) Miniature RF connectors
- c) PCI express mini card form factor
- d) 5 to 40 C operation
- e) ROHS complaint
- f) Low cost, highly integrated design

2.0 Requirements

The following sections identify the detailed requirements of the **802.11ac PCI Express**.

2.1 Radio Card Specifications

Specification	Description
Frequency Range	4900–5845 MHz Actual operating frequencies depend on regulatory approval for the country of use.
Wireless Medium	Orthogonal Frequency Division Multiplexing (OFDM), Spatial multiplexing (MIMO)
Network Standards	802.11a, 802.11n, 802.11ac
Channel Bandwidth Supported	20, 40, and 80 MHz
Spatial Streams	3 (3x3 configuration) Also support 1 and 2 streams modes
Data Rates Supported	802.11a: 6, 9, 12, 18, 24, 36, 48, and 54 Mbps 802.11n: MCS0 up to MCS23 (450 Mbps) 802.11ac: NSS1-MCS0 up to NSS3-MCS9 (1300 Mbps)
Maximum Available Conducted Transmit Power	5 GHz: 24.45 dBm Actual transmit power may be limited by the country of operation.
Transmit Power Control	1dB step
Operating Temperature	5°C to 40°C
Non-operating/Storage Temperature	-40°C to 70°C

2.2 General Section

#	Feature	Detailed Description
2.2.1	Antenna Connector	• Three UFL compatible antenna connectors
2.2.2	Operating Voltage	• 3.3VDC +/- 5%
2.2.3	Current Consumption	• 5.1W is use on continue TX
2.2.4	Form Factor and Interface	• Mini-card form factor with signal of PCI-e Gen1 X1 lane

2.3 Software Requirements

The Configuration Software supports Linux driver. This configuration software includes the following functions:

- **Information**
Information allows you to monitor network status.
- **Configuration**
Configuration allows you to configure parameters for wireless networking.
- **Security**
Supports enhanced security WEP, 802.1x, WPA and WPA2.

2.3.1 Security

#	Feature	Detailed Description
2.3.1.1	Encryption	• RC4 encryption algorithm • Support 64-bit and 128-bit WEP encryption • Support open system (OSA) and shared key authentication (SKA)
2.3.1.2	WEP Management	• Four WEP keys can be selected • STA with WEP off will never associate any AP with WEP enabled • WEP Key Format: Option for Hex format
2.3.1.3	802.1x	• Support EAP-TLS, EAP-TTLS, and EAP-PEAP
2.3.1.4	WPA/WPA2	• Support WPA/WPA2-PSK and WPA/WPA2-EAP • Support Cipher Mode AES and TKIP

2.4 Mechanical Requirements

The mechanical dimensions of the Mapletree radio card shall conform to the base PCI Express Mini Card Electromechanical Specification Revision 2.0 section 2.2.3 for Full Mini-card.

FCC Statement:

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This device and its antenna(s) must not be co-located with any other transmitters except in accordance with FCC multi-transmitter product procedures.

Referring to the multi-transmitter policy, multiple-transmitter(s) and module(s) can be operated simultaneously without C2P.

This device is restricted for indoor use.

IMPORTANT NOTE:

This module is intended for OEM integrator. The OEM integrator is responsible for the compliance to all the rules that apply to the product into which this certified RF module is integrated. Additional testing and certification may be necessary when multiple modules are used.

20cm minimum distance has to be able to be maintained between the antenna and the users for the host this module is integrated into. Under such configuration, the FCC radiation exposure limits set forth for an population/uncontrolled environment can be satisfied.

Any changes or modifications not expressly approved by the manufacturer could void the user's authority to operate this equipment.

USERS MANUAL OF THE END PRODUCT:

In the users manual of the end product, the end user has to be informed to keep at least 20cm separation with the antenna while this end product is installed and operated. The end user has to be informed that the FCC radio-frequency exposure guidelines for an uncontrolled environment can be satisfied. The end user has to also be informed that any changes or modifications not expressly approved by the manufacturer could void the user's authority to operate this equipment. If the size of the end product is smaller than 8x10cm, then additional FCC part 15.19 statement is required to be available in the users manual: This device complies with Part 15 of FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference and (2) this device must accept any interference received, including interference that may cause undesired operation.

LABEL OF THE END PRODUCT:

The final end product must be labeled in a visible area with the following " Contains TX FCC ID: B94MRLBB1403 ". If the size of the end product is larger than 8x10cm, then the following FCC part 15.19 statement has to also be available on the label: This device complies with Part 15 of FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference and (2) this device must accept any interference received, including interference that may cause undesired operation.

IC Statement

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

This device and its antenna(s) must not be co-located with any other transmitters except in accordance with IC multi-transmitter product procedures.

Referring to the multi-transmitter policy, multiple-transmitter(s) and module(s) can be operated simultaneously without reassessment permissive change.

Cet appareil et son antenne (s) ne doit pas être co-localisés ou fonctionner en association avec une autre antenne ou transmetteur.

Dynamic Frequency Selection (DFS) for devices operating in the bands 5250- 5350 MHz, 5470-5600 MHz and 5650-5725 MHz

Sélection dynamique de fréquences (DFS) pour les dispositifs fonctionnant dans les bandes 5250-5350 MHz, 5470-5600 MHz et 5650-5725 MHz

The device for the band 5150-5250 MHz is only for indoor usage to reduce potential for harmful interference to co-channel mobile satellite systems.

les dispositifs fonctionnant dans la bande 5150-5250 MHz sont réservés uniquement pour une utilisation à l'intérieur afin de réduire les risques de brouillage préjudiciable aux systèmes de satellites mobiles utilisant les mêmes canaux.

The maximum antenna gain permitted (for devices in the bands 5250-5350 MHz and 5470-5725 MHz) to comply with the e.i.r.p. limit.

le gain maximal d'antenne permis pour les dispositifs utilisant les bandes 5250-5350 MHz et 5470-5725 MHz doit se conformer à la limite de p.i.r.e.

Users should also be advised that high-power radars are allocated as primary users (i.e. priority users) of the bands 5250-5350 MHz and 5650-5850 MHz and that these radars could cause interference and/or damage to LE-LAN devices.

De plus, les utilisateurs devraient aussi être avisés que les utilisateurs de radars de haute puissance sont désignés utilisateurs principaux (c.-à-d., qu'ils ont la priorité) pour les bandes 5250-5350 MHz et 5650-5850 MHz et que ces radars pourraient causer du brouillage et/ou des dommages aux dispositifs LAN-EL.

The maximum antenna gain permitted for devices in the band 5725-5850 MHz shall be such that the equipment still complies with the e.i.r.p. limits specified for point-to-point and non-point-to-point operation as appropriate.

le gain maximal d'antenne permis (pour les dispositifs utilisant la bande 5725-5850 MHz) doit se conformer à la limite de p.i.r.e. spécifiée pour l'exploitation point à point et non point à point, selon le cas.

For indoor use only.

Pour une utilisation en intérieur uniquement.

IMPORTANT NOTE:**IC Radiation Exposure Statement:**

This equipment complies with IC RSS-102 radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

Cet équipement est conforme aux limites d'exposition aux rayonnements IC établies pour un environnement non contrôlé. Cet équipement doit être installé et utilisé avec un minimum de 20 cm de distance entre la source de rayonnement et votre corps.

IMPORTANT NOTE:

This module is intended for OEM integrator. The OEM integrator is still responsible for the IC compliance requirement of the end product, which integrates this module.

USERS MANUAL OF THE END PRODUCT:

In the users manual of the end product, the end user has to be informed to keep at least 20cm separation with the antenna while this end product is installed and operated. The end user has to be informed that the IC radio-frequency exposure guidelines for an uncontrolled environment can be satisfied. The end user has to also be informed that any changes or modifications not expressly approved by the manufacturer could void the user's authority to operate this equipment. IC statement is required to be available in the users manual: This Class B digital apparatus complies with Canadian ICES-003. Operation is subject to the following two conditions: (1) this device may not cause harmful interference and (2) this device must accept any interference received, including interference that may cause undesired operation.

LABEL OF THE END PRODUCT:

The final end product must be labeled in a visible area with the following " Contains TX IC : 466F-MRLBB1403 ".

This radio transmitter (466F-MRLBB1403) has been approved by Industry Canada to operate with the antenna types listed below with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Le présent émetteur radio (466F-MRLBB1403) a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés ci-dessous et ayant un gain admissible maximal et l'impédance requise pour chaque type d'antenne. Les types d'antenne non inclus dans cette liste, ou dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur.

Ant.	Brand	Part No.	Antenna Type	Connector	Gain (dBi)
1	M. gear	120300000095A	PCB Antenna	I-PEX	5.6
2	M. gear	120300000095A	PCB Antenna	I-PEX	5.5
3	M. gear	120300000095A	PCB Antenna	I-PEX	6.5

Note: The EUT has three Antennas.

Notice for Brazil, Aviso aos usuá rios no Brasil

Este equipamento opera em caráter secundário, isto é, não tem direito a proteção contra interferência prejudicial, mesmo de estações do mesmo tipo, e não pode causar interferência a sistemas operando em caráter primário.

Notice for Korea

기종별	사용자안내문
B급 기기 (가정용 방송통신기기)	이 기기는 가정용 (B급) 으로 전자파적합등록을 한 기기로서 주로 가정에서 사용하는 것을 목적으로 하되, 모든 지역에서 사용할 수 있습니다.
Class B (Broadcasting Communication Device for Home Use)	This device obtained EMC registration mainly for home use (Class B) and may be used in all areas.

당해 무선설비는 전원과 혼신 가능성이 있으므로 인명안전과 관련된 서비스는 할 수 없습니다.

Notice for Taiwan

低功率電波輻射性電機管理辦法

第十二條 經型式認證合格之低功率射頻電機，非經許可，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

第十四條 低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前項合法通信，指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

在 5.25-5.35 兆赫頻帶內操作之無線資訊傳輸設備，限於室內使用。