

1. RF Exposure Requirements

1.1 General Information

Client Information

Applicant:	AUTOEQUIPS TECH CO., LTD.
Address of applicant:	Room 04/11F, Block C, Wanhai Building No.1031 Nanhai Avenue, Shenzhen, Guangdong Province, China
Manufacturer:	HUIZHOU YUHONG TECH CO., LTD.
Address of manufacturer:	First Stage Plant, No.2 Xialuo Road, Zhongkai Hi-Tech Zone, Huizhou City, Guangdong Province, P.R. China

General Description of EUT:

Product Name:	AVTX24
Trade Name:	PSVT
Model No.:	AVTX24
Adding Model(s):	AE-CB213, TX-7056.2PCB
Rated Voltage:	DC12V
Battery Capacity	/
Power Adapter Model:	/
Software Version:	CB213_IL_DM_V0.07.bin
Hardware Version:	V1.0 20240219
FCC ID:	2AGPOAVTX24
Equipment Type:	Fixed device / Mobile device / Portable device

Technical Characteristics of EUT:

Frequency Range:	2406MHz-2469MHz
Max. Field Strength:	99.65dBuV/m
Modulation:	FHSS
Quantity of Channels:	15
Channel Separation:	4.5MHz
Antenna Type:	ANT 1: Dipolantenne / Dipole antenna ANT 2: Sperrtopfantenne / Sleeve antenna ANT 3: Monopolantenne / Monopole antenna ANT 4: Monopolantenne / Monopole antenna
Antenna Gain:	ANT 1:2.0dBi ANT 2:1.8dBi ANT 3:2.0dBi ANT 4:2.0dBi

1.2 RF Exposure Exemption

According to §1.1307(b)(3) and KDB 447498 D04 Interim General RF Exposure Guidance v01, system operating under the provisions of this section shall be operating in a manner that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure.

Option A: FCC Rule Part 1.1307 (b)(3)(i)(A): The available maximum time-averaged power is no more than 1mW, regardless of separation distance.

Option B: FCC Rule Part 1.1307 (b)(3)(i)(B): The available maximum time-averaged power or effective radiated power (ERP), whichever is greater, is less than or equal to the threshold P_{th} (mW) described in the following formula. P_{th} is given by:

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases}$$

Where

$$x = -\log_{10} \left(\frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right) \text{ and } f \text{ is in GHz;}$$

and

$$ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases}$$

d = the separation distance (cm);

Option C: FCC Rule Part 1.1307 (b)(3)(i)(C): The minimum separation distance (R in meters) from the body of a nearby person for the frequency (f in MHz) at which the source operates, the ERP (watts) is no more than the calculated value prescribed for that frequency. R must be at least $\lambda/2\pi$, where λ is the free-space operating wavelength in meters.

Single RF Sources Subject to Routine Environmental Evaluation	
RF Source frequency (MHz)	Threshold ERP (watts)
0.3-1.34	$1,920 R^2$
1.34-30	$3,450 R^2/f^2$
30-300	$3.83 R^2$
300-1,500	$0.0128 R^2 f$
1,500-100,000	$19.2 R^2$

For Multiple RF sources: FCC Rule Part 1.1307(b)(3)(ii):

- (A) The available maximum time-averaged power of each source is no more than 1 mW and there is a separation distance of two centimeters between any portion of a radiating structure operating and the nearest portion of any other radiating structure in the same device, except if the sum of multiple sources is less than 1 mW during the time-averaging period, in which case they may be treated as a single source (separation is not required).
- (B) In the case of fixed RF sources operating in the same time-averaging period, or of multiple mobile or portable RF sources within a device operating in the same time averaging period, if the sum of the fractional contributions to the applicable thresholds is less than or equal to 1 as indicated in the following equation.

$$\sum_{i=1}^a \frac{P_i}{P_{th,i}} + \sum_{j=1}^b \frac{ERP_j}{ERP_{th,j}} + \sum_{k=1}^c \frac{Evaluated_k}{Exposure Limit_k} \leq 1$$

1.3 Calculated Result

Radio Access Technology	Prediction Frequency (MHz)	Max. Field Strength (dBuV/m)	Antenna Gain (dBi)	Output Power (dBm)	Tune-Up Power (dBm)	ERP (dBm)
SRD_ANT1	2406	99.65	2.0	2.39	3.00	2.85
SRD_ANT2	2406	99.51	1.8	2.45	3.00	2.65
SRD_ANT3	2406	99.29	2.0	2.03	3.00	2.85
SRD_ANT4	2406	99.59	2.0	2.33	3.00	2.85

Frequency (MHz)	Option	Min. Distance (cm)	Max. Power (dBm)	Max. Power (mW)	Exposure Limit (mW)	Ratio	Result Pass/Fail
2406	B	0.5	3.00	2.00	2.784	0.72	Pass
2406	B	0.5	3.00	2.00	2.784	0.72	Pass
2406	B	0.5	3.00	2.00	2.784	0.72	Pass
2406	B	0.5	3.00	2.00	2.784	0.72	Pass

Note: 1. $EIRP = E - 104.8 + 20 \log D$; Output Power = EIRP - Antenna Gain;

$ERP = EIRP - 2.15 \text{ dB}$

2. Option A, B and C refers as clause 1.2.

3. For option B, Max (time-averaged power, effective radiated power (ERP)) converts to Max. Power. For option C, ERP converts to Max. Power;

4. For option B, P_{th} (mW) converts to Exposure Limit (mW); For option C, ERP (W) converts to Exposure Limit (mW).

5. Ratio = Tune-Up ERP (mW) / Exposure Limit (mW)

Mode for Simultaneous Multi-band Transmission:

Radio Access Technology	Ratio 1	Ratio 2	Ratio 3	Simultaneous Ratio	Limit	Result Pass/Fail
/	/	/	/	/	/	/

Note: ANT1, ANT2, ANT3 and ANT4 can't transmit at the same time.

Result: Pass