



CTC Laboratories, Inc.

2/F., Building 1 and 1-2/F., Building 2, Jiaquan Building, Guanlan High-Tech Park, Longhua District, Shenzhen, Guangdong, China

Tel: +86-755-27521059 Fax: +86-755-27521011 <http://www.sz-ctc.org.cn>

Maximum Permissible Exposure Evaluation

FCC ID: 2APN5SNZB06P

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b).

EUT Specification

Applicant	Shenzhen Sonoff Technologies Co.,Ltd.
Address	3F & 6F, Bldg A, No. 663, Bulong Rd, Shenzhen, Guangdong, China
Product Name:	Zigbee Human Presence Sensor
Trade Mark:	Sonoff
Model/Type Reference:	SNZB-06P
Listed Model(s):	/
Model Differences:	/
Frequency Band (Operating)	Zigbee: 2405~2480MHz FMCW: 5795MHz
Device Category	<input type="checkbox"/> Portable (<5mm separation) <input type="checkbox"/> Mobile (>20cm separation) <input checked="" type="checkbox"/> Fixed (>20cm separation) <input type="checkbox"/> Others ____
Exposure Classification	<input type="checkbox"/> Occupational/Controlled exposure (S=5mW/cm ²) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm ²)
Antenna Diversity	<input type="checkbox"/> Single antenna <input checked="" type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Antenna Gain (Max)	Zigbee: 2.07dBi FMCW: 2.0dBi
Evaluation Applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Averaging Time (minutes)
(A) Limits for Occupational/Controlled Exposure				
300-1500	--	--	F/300	<6
1500-100000	--	--	5	<6
(B) Limits for General Population/Uncontrolled Exposure				
300-1500	--	--	F/1500	<30
1500-100000	--	--	1	<30

CTC Laboratories, Inc.

1-2/F., Building 2, Jiaquan Building, Guanlan High-Tech Park, Shenzhen, Guangdong, China

Tel.: (86)755-27521059

Fax: (86)755-27521011

[Http://www.sz-ctc.org.cn](http://www.sz-ctc.org.cn)



For anti-fake verification, please visit the official website of Certification and Accreditation Administration of the People's Republic of China : yz.cnca.cn



Calculation Method

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where:

P_d = Power density in mW/cm^2

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

P_d limit of MPE is $1mW/cm^2$. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

$eirp = pt \times gt = (E \times d)^2 / 30$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, --- $10^{((dBuV/m)/20)} / 10^6$

d = measurement distance in meters (m), --- 3m

So $pt = (E \times d)^2 / (30 \times gt)$

FMCW 5795MHz Field strength = 91.86 dBuV/m @3m

Ant gain 2.0dBi, Ant numeric gain = 1.58

So $pt = \{ [10^{(91.86/20)} / 10^6 \times 3]^2 / (30 \times 1.58) \} \times 1000 \text{ mW} = 0.2914 \text{ mW}$

Measurement Result

Mode	Frequency (MHz)	Antenna Gain (dBi)	Maximum Power (dBm)	Tune Up Tolerance (dB)	Max. Tune Up Power (dBm)	Power Density at 20cm (mW/cm ²)	Limit (mW/cm ²)
Zigbee	2405	2.07	5.289	±1	6.00	0.00128	1
FMCW	5795	2.0	-5.355	±1	-4.50	0.00011	1

The Zigbee and FMCW can transmit simultaneously.

Mode	Frequency (MHz)	Antenna Gain (dBi)	Power Density at 20cm (mW/cm ²)	Total Power density at 20cm (mW/cm ²)	Limit (mW/cm ²)
Zigbee	2405	2.07	0.00128	0.00139	1
FMCW	5795	2.0	0.00011		

Note:

1. Calculate in the worst-case mode.
2. Max. Tune Up Power is declared by manufacturer, and used to calculate.
3. For a more detailed features description, please refer to the RF Test Report.

*****THE END*****