

User Manual

Please Read This User Manual Completely And Keep It Properly

Product Parameter

Brand: Baseus

Name: Power Bank

Model No: PPCXM10

Battery : Polymer Lithium battery

Power Capacity :10000mAh / 38.5Wh

Energy conversion rate: $\geq 75\%$

Type-C input: 5V/3A;9V/2A;

Type-C output:5V2.4A;9V2.22A;12V1.5A;

Wireless Output: 5W/7.5W/10W/15W

Total output:5V2.4A

Product size: 104.6x68.9x20 mm

Product weight: About 208g

Packing list:

- 1、 Power Bank *1
- 2、 User Manual * 1
- 3、 Warranty card *1
- 4、 Charging Cable *1

3、 Product Diagram

.....

Designed by Baseus \ Made in China

4、 Product description :

This product is a portable charging device that can provide wired or wireless charging for mobile phones, tablets, e-books, game machines and other digital products. The product has the characteristics of two in one of wired charging and wireless charging, ip20w pd fast charging, Type-C dual way fast charging, 15W wireless fast charging, etc. Product built-in FOD, overcharge, over discharge, temperature protection and other safety protection circuit.

5、 Use environment:

Working Temperature: Non-tropical area, 0°C to 40 °C

Storage ambient temperature: 0 °C to 40 °C

6、 Icon description:

The 5-year icon refers to the "effective life of environmental protection", not the product quality assurance period. Electronic products all contain toxic and harmful substances such as lead, mercury and cadmium. Once they are overused, toxic and harmful substances may leak or mutate, cause pollution to the environment, or cause serious damage to people and property. The term of "environmental protection use" means that all electronic products will be required to use within this effective period. We will no longer be responsible for the quality of the products due to the safety risks that arise after the safe use period.

7、 Operation description

For viewing electric quantity:

Press the button once to initiate the power output function, when you can view the remaining electric level of the power bank. After lit for 30sec, the LED indicator will extinguish automatically.

Operation for discharging by cable:

Connect the charging cable to the corresponding output port of the power supply, and the power supply will automatically turn on the output. Due to compatibility problems, some smart phones need to press the key to turn on the power output function, which is a normal phenomenon and need not be ignored. Press the key once to supply power to the external equipment. Press the key once to output power for about 30 seconds. If there is no external load in 30 seconds, the power output will be automatically turned off.

Operation for discharging by wireless:

The product has the function of Automatic wake-up wireless charging. When the mobile phone is put on, it will automatically start charging. Due to compatibility problems, individual mobile phones need to press the key to start the wireless charging function. Press the key once, and the power indicator will light up. At this time, the wireless output function is turned on, which can charge the mobile phone supporting wireless charging. If there is no wireless charging access within 30 seconds, the product will automatically turn off the wireless charging function.

8、 Wireless charging tips:

The wireless charging mobile phone should be placed in the wireless charging area of the product (the transmitting area of the wireless charging coil is illustrated in the figure) for wireless charging. The wireless charging distance is within 8 mm. If the distance exceeds 8 mm, the wireless charging can not be carried out. Please adjust the wireless charging distance within the wireless charging range.

9、 Safety warning instructions Tips

1. The charging contact surface on the back of the mobile phone should not be covered with metal materials, such as iron sheet, ring, metal protective case, etc.
2. When the mobile phone is charging, if intermittent charging or serious heating is found, it may be that the receiving coil of the mobile phone is not completely aligned with the wireless charging coil, or there is metal foreign matter in the protective sleeve of the mobile phone. Please try to cool the mobile phone, remove the protective sleeve, and then align it in the correct position.
3. Please do not disassemble the machine by yourself. Improper use or improper placement of the product by the user may reduce the service life or damage the product. Therefore, the responsibility does not belong to the warranty responsibility or the manufacturer's responsibility. Please understand.
4. Mobile power has conversion efficiency, so the battery capacity of mobile power is not equal to the rechargeable capacity.
5. Please charge your power regularly (at least every 5 months is recommended) to maintain its long service life.
6. In case of any personal and property damage caused by consumers' improper use or warning in violation of the product instructions, the company will bear all consequences, and the company will not bear any legal liability.
7. Avoid using electrical appliances or loads that exceed the output current of the product (the circuit will be protected, no output).
8. Avoid strong physical effects, including knocking, throwing, trampling, squeezing, etc.

10、Statement on Toxic and Hazardous Substances in Electronic Information

Products:

This form is compiled in accordance with SJ/T 11364.

O: It indicates that the content of the toxic and harmful substance in all homogeneous materials of the component is below the limit specified in GB/T 26572 standard.

X: The content of toxic and harmful substances in at least one homogeneous material of this part exceeds the limit stipulated in GB/T 26572 standard.

The product complies with EU ROHS 2.0 directive (2011 / 65 / EU)

11、Implementation criteria:

GB/T 35590-2017

12、Use icons:

13、Contact information

Brand: Baseus

Manufacturer: Shenzhen Baseus Technology Co., Ltd.

Add: 2th Floor, Building B, Baseus Intelligence Park, No.2008, Xuegang Rd,

Gangtou Community, Bantian Street, Longgang District, Shenzhen

TEL: +86 755-82433603 Hotline: 4000-712-711

FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.