

RF EXPOSURE EVALUATION METHOD

FCC ID: 2AVRVKRC101

Applicable standard :

In accordance with FCC 47 CFR part 2 (2.1093) this device has been defined as a portable device which is defined as a transmitting device designed to be used so that the radiating structure(s) of the device is/are within 20 centimeters of the body of the user.

Portable devices must be evaluated using the specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-1992. and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2003.

Per FCC KDB 447498 D01 v06, the 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances \leq 50 mm are determined by:

SAR Test Exclusion Thresholds for 100 MHz – 6 GHz and \leq 50 mm

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation

Distances are illustrated in the following Table.

MHz	5	10	15	20	25	mm
150	39	77	116	155	194	SAR Test Exclusion Threshold (mW)
300	27	55	82	110	137	
450	22	45	67	89	112	
835	16	33	49	66	82	
900	16	32	47	63	79	
1500	12	24	37	49	61	
1900	11	22	33	44	54	
2450	10	19	29	38	48	
3600	8	16	24	32	40	
5200	7	13	20	26	33	
5400	6	13	19	26	32	
5800	6	12	19	25	31	

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances \leq 50 mm are determined by:

$$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR and } \leq 7.5 \text{ for 10-g extremity SAR, where } f(\text{GHz}) \text{ is the RF channel transmit frequency in GHz}$$

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is \leq 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is $<$ 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

BT

Modulation	Test Channel	Output Power (dBm)	Limit (dBm)
GFSK	Low	-4.23	21
GFSK	Middle	-3.72	21
GFSK	High	-3.11	21
$\pi/4$ DQPSK	Low	-3.35	21
$\pi/4$ DQPSK	Middle	-2.84	21
$\pi/4$ DQPSK	High	-2.2	21
8DPSK	Low	-2.68	21
8DPSK	Middle	-2.22	21
8DPSK	High	-1.63	21

max possible output power (PK,conducted) : -1 ± 1 dBm

-0.58dBi logarithmic terms convert to numeric result is nearly 0.87

0dBm=1.00mW

2402MHz

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 1.00/5 \cdot \sqrt{2.402} = 0.31 \leq 3.0$

Threshold at which no SAR required is 10mw and ≤ 3.0 for 1-g SAR, Separation distance is 5mm.

2441MHz

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 1.00/5 \cdot \sqrt{2.441} = 0.312 \leq 3.0$

Threshold at which no SAR required is 10mw and ≤ 3.0 for 1-g SAR, Separation distance is 5mm.

2480MHz

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 1.00/5 \cdot \sqrt{2.48} = 0.315 \leq 3.0$

Threshold at which no SAR required is 10mw and ≤ 3.0 for 1-g SAR, Separation distance is 5mm.

Conclusion: No SAR is required.