



## Shenzhen Huaxia Testing Technology Co., Ltd.

1F., Block A of Tongsheng Technology Building, Huahui Road, Dalang Street, Longhua District, Shenzhen, China

Telephone: +86-755-26648640

Fax: +86-755-26648637

Website: [www.cqa-cert.com](http://www.cqa-cert.com)

Report Template Version: V05

Report Template Revision Date: 2021-11-03

# RF Exposure Evaluation Report

**Report No.:** CQASZ20241002142E-02  
**Applicant:** Zhejiang General Light Curtain Co.,LTD.  
**Address of Applicant:** Xin Tang Tou Village, Xin Jie Town, XiaoShan District, HangZhou City, China  
**Equipment Under Test (EUT):**  
**EUT Name:** Button Transmitter  
**Test Model No.:** PE5201  
**Model No.:** PE5201  
**Brand Name:** Poyal  
**FCC ID:** 2A839-PE5201  
**Standards:** 47 CFR Part 1.1307  
47 CFR Part 2.1093  
447498 D04 Interim General RF Exposure Guidance v01  
**Date of Receipt:** 2024-10-10  
**Date of Test:** 2024-10-10 to 2024-11-06  
**Date of Issue:** 2024-11-22  
**Test Result:** PASS\*

\*In the configuration tested, the EUT complied with the standards specified above

**Tested By:** Lewis Zhou  
( Lewis Zhou )

**Reviewed By:** Timo Lei  
( Timo Lei )

**Approved By:** Alex  
( Alex Wang )



## 1 Version

### Revision History Of Report

Report No.	Version	Description	Issue Date
CQASZ20241002142E-02	Rev.01	Initial report	2024-11-22

## 2 Contents

	Page
1 VERSION .....	2
2 CONTENTS .....	3
.....	3
3 GENERAL INFORMATION .....	4
3.1 CLIENT INFORMATION .....	4
3.2 GENERAL DESCRIPTION OF EUT .....	4
3.3 GENERAL DESCRIPTION OF 433.92MHZ .....	4
4 SAR EVALUATION .....	5
4.1 RF EXPOSURE COMPLIANCE REQUIREMENT .....	5
4.1.1 <i>Standard Requirement</i> .....	5
4.1.2 <i>Limits</i> .....	5
4.1.3 <i>EUT RF Exposure</i> .....	7

### 3 General Information

#### 3.1 Client Information

Applicant:	Zhejiang General Light Curtain Co.,LTD.
Address of Applicant:	Xin Tang Tou Village, Xin Jie Town, XiaoShan District, HangZhou City, China
Manufacturer:	Zhejiang General Light Curtain Co.,LTD.
Address of Manufacturer:	Xin Tang Tou Village, Xin Jie Town, XiaoShan District, HangZhou City, China
Factory:	Zhejiang General Light Curtain Co.,LTD.
Address of Factory:	Xin Tang Tou Village, Xin Jie Town, XiaoShan District, HangZhou City, China

#### 3.2 General Description of EUT

Product Name:	Button Transmitter
Model No.:	PE5201
Test Model No	PE5201
Trade Mark:	Poyal
EUT Supports Radios application:	433.92MHz
Software Version:	V1.0.0
Hardware Version:	V1.0.0
Sample Type:	<input type="checkbox"/> Mobile <input checked="" type="checkbox"/> Portable
EUT Power Supply:	Power supply DC 3V form Button cell

#### 3.3 General Description of 433.92MHz

Operation Frequency:	433.92MHz
Modulation Type:	FSK
Number of Channel:	1
Test Software of EUT:	EUT Key
Antenna Type:	PCB antenna
Antenna Gain:	-8.93dBi

## 4 SAR Evaluation

### 4.1 RF Exposure Compliance Requirement

#### 4.1.1 Standard Requirement

447498 D04 Interim General RF Exposure Guidance v01

##### 3.2. SAR Test Reduction Guidance

SAR test reduction procedures [Glossary] allow using a particular set of test data as representative of other, similar, test conditions. This may be applied for data within different test positions (e.g. body, head, extremity), wireless modes (e.g. Wi-Fi, cellular), and frequency bands. This test reduction process provides for the use of test data for one specific channel, while referencing to those data for demonstrating compliance in other required channels for each test position of an exposure condition, within the operating mode of a frequency band. This is limited specifically to when the reported 1-g or 10-g SAR for the mid-band or highest output power channel meets any of the following conditions.

#### 4.1.2 Limits

SAR-based thresholds are derived based on frequency, power, and separation distance of the RF source. The formula defines the thresholds in general for either available maximum time averaged power or maximum time-averaged ERP, whichever is greater.

If the ERP of a device is not easily determined, such as for a portable device with a small form factor, the applicant may use the available maximum time-averaged power exclusively if the device antenna or radiating structure does not exceed an electrical length of  $\lambda/4$ .

As for devices with antennas of length greater than  $\lambda/4$  where the gain is not well defined, but always less than that of a half-wave dipole (length  $\lambda/2$ ), the available maximum time-averaged power generated by the device may be used in place of the maximum time-averaged ERP, where that value is not known.

The separation distance is the smallest distance from any part of the antenna or radiating structure for all persons, during operation at the applicable ERP. In the case of mobile or portable devices, the separation distance is from the outer housing of the device where it is closest to the antenna.

The SAR-based exemption formula of § 1.1307(b)(3)(i)(B), repeated here as Formula (B.2), applies for single fixed, mobile, and portable RF sources with available maximum time-averaged power or effective radiated power (ERP), whichever is greater, of less than or equal to the threshold  $P_{th}$  (mW).

This method shall only be used at separation distances from 0.5 cm to 40 cm and at frequencies from 0.3 GHz to 6 GHz (inclusive).  $P_{th}$  is given by Formula (B.2).

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B. 2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20 \text{ cm}}$  is per Formula (B.1).  
The example values shown in Table B.2 are for illustration only.

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

#### 4.1.3 EUT RF Exposure

##### Measurement Data

$$EIRP = E_{Meas} + 20\log(d_{Meas}) - 104.7$$

where

EIRP is the equivalent isotropically radiated power, in dBm  
 $E_{Meas}$  is the field strength of the emission at the measurement distance, in dB $\mu$ V/m  
 $d_{Meas}$  is the measurement distance, in m

Channel	EIRP (dBm)	EIRP (mW)	Exclusion threshold (mW)
433.92MHz	-19.30	0.01	1

Remark: The Max Peak Output Power data refer to report Report No.: CQASZ20241002142E-01.

\*\*\* END OF REPORT \*\*\*