Go to www.vtechphones.com to register your product for enhanced warranty support and the latest VTech

Pan and Tilt Video Baby Monitor



vtech Quick start quide

01 00000000 01 000000 010 000 010 000

Baby unit power adapter: Output: 5V DC @ 1A Parent unit power adapter: Output: 5V DC @ 1A Parent unit: 3.6V, 2600mAh, 9.36Wh Li-ion battery Maximum power allowed by PCC and IC. Actual operating range may vary according to environmental conditions at the time of use.

абиез ализаца тецциом Crystal controlled PLL synthesizer

TECHNICAL SPECIFICATIONS

IMPORTANT SAFETY INSTRUCTIONS

VM924

VM924-2

Follow all warnings and instructions marked on the product.

Control 20 from Install the Day of Conduction of the behavior and the Conduction of the Conduction of the Proposition of the Conduction of the Conduction of the responsibility. This product could classe operating, and therefore you should not assume it will continue working, and therefore you should not assume it will continue working, and properly for any given period of time. Further, this is not a medical device and should not be used as such. This product is intended to assist you in supervising your baby.

Do not use this product near water. For example, do not use it next to a bath tub, wash bowl, kitchen sink, laundry tub or swimming pool, or in a wet basement

resident in an exposion of used battlery according to the model of used battlery according to the model of th

Zhuhai Great Power Energy Co., Ltd. Li-ion battery, 3.6V, 2600mAh, 9.36Wh; Model: ICR18650-2.6Ah-3.6V-1S1P

For pluggable equipment, the socket-outlet shall be installed near the equipment and shall be easily

for cleaning.

Do not cut off the power adapters to replace them with other plugs, as this causes a hazardous situation.

Do not allow anything to rest on the power cords.

Do not install this product where the cords may be walked

or place this product on an unstable table, shelf, for other unstable surfaces, product should not be placed in any area where or wentilation is not provided. Stots and opening proper ventilation is not provided. Slots and opening in the back or bottom of this product are provided for ventilation. To protect them from overheating, these openings must not be blocked by placing the produ-on a soft surface such as a bed, sofa or rug. This produ-

WHAT'S IN THE BOX wever push objects of any kind into this product through the slots because they may touch dangerous voltage points or create a short circuit. Never spill liquid

of any find on the product.

To reduce the risk of electric chock, do not disastemble this product, but take it to an authorize service facility, opening or removing parts of the product offer than specifical access doors might be producted to the thing part of the product offer the product of the production of the production of the product of the product is subsequently used. You should test the sound reception every time you turn on the units or move one of the components. Periodically eventure all components for damage, and

en should be supervised to ensure that they do
ny with the product nous play with the product.
The product is no finended for use by persons
(including children) with reduced physical, sensory
or mental capabilities, or lack of experience and
knowledge, unless they have been given supervision or
instruction concerning use of the appliance by a person
responsible for their action.

ole for their safety.


SAVE THESE INSTRUCTIONS

Use and store the product at a temperature between 32°F and 104°F

Do not expose the product to extreme cold, heat or direct sunlight. Do not put the product close to a heating source. Batteries should not be exposed to excessive heat such

maker. Id NOT place wireless devices directly over the maker, such as in a breast pocket, when it is turned

pacemakers from other persons using wireless device Electromagnetic fields (EMF) This VTech product complies with all standards regard electromagnetic fields (EMF). If handled properly and according to the instructions in this users' manual, the



CONNECT THE BABY MONITOR

MOTES

The rechargeable battery in the parent unit is built-in

Use only the power adapters supplied with this product Make sure the baby monitor is not connected to a switch-controlled electric outlet

Make suff me pary monitor is not connected to a symmetric properties. Connect the power adapters prongs are no designed to hold the weight of baby monitor, so do not connect them to any ceiling, under-the-ti-or cabinet outlets. Otherwise, the adapters may not properly connect to the outlets.



CONNECT THE BABY MONITOR (CONT'D)

Charge the parent unit battery When you have connected and turned on the parent unit, the battery will be charged automatically. **■Notes**

The battery icon indicates the battery status (see the following table). The screen displays The light flashes.


The light flashes.

The battery has very little power and can only be used for a short time.

Charge without interruption (about 30 minutes). The time light isomes. To a stront limbs.

The battery icon becomes The battery is fully charged. To keep the battery charged, connect the unit to AC power when not in use solid 🔚

Power on or off the baby monitor



POSITIONING THE BABY MONITOR



monitor while positioning:

Make sure your baby unit and parent unit are more than 3 feet (1 meter) apart, OR Turn down the volume of your parent unit **■NOTE** owaves, cell phones and computers

4 STATUS CHECK

Once you power on both unit, your parent unit displays image from the baby unit, and the LINK LED light turns on.

light turns on.



ON/OFF

Turn on/off temperature alert tone

the room temperature detected by the baby unit falls outside of the set

Set temperature display in Fahrenheit (°F) or Celsius (°C).

Baby unit speaker volume

Adjust the baby unit's speaker volume.

Set the minimum temperature.

· Set the maximum temperature.

temperature range.

Set the parent unit to beep whenever

BASIC OPERATION - PARENT UNIT

Press = to enter the menu, choose a menu item, or save a setting. You can use the parent unit for advanced settings or operations, such as to play or stop the baby unit lullaby, or to adjust the baby unit sound sensitivity.

While in the menu:

- Press

 or

 to scroll among the menu options. Press

 to select an item, or to save a setting.
- Press ∧ or ∨ to scroll among the sub-menus.
- or to adjust a setting.
- without changing the current setting.
- Press TALK to return to live video

Talk to your baby unit

Press and hold TALK and speak to your parent unit. Your voice is transmitted to the baby unit. Release TALK when finish talking and hear your baby again





Turn off the screen Press Do/POWER to put the monitor display

to sleep. The screen will be switched off, and you will still hear sounds from the baby unit

์ ≡



Press any key on the parent unit to turn the

Adjust parent unit volume

3 (III) Rattery I ED light

4 LINK LED light

Press VOL - / VOL + to adjust your paren



Press = to enter the menu Press **<** or **>** to select **Q**, then press **≡**


Press A or V to choose either @1X or ⊕2X, depending on how many times you want to zoom in, then press ≡ to

10 Power lack

11 RESET

12 Speaker

OVERVIEW - PARENT UNIT



6 ≡MENU/SELECT

TRETURN/TALK

8 Eg LCD off/POWER key

OVERVIEW - BABY UNIT



- Light sensor Camera
- Infrared LEDs
- Microphone
- POWER LED light 6 U ON/OFF switch
- Speaker Antenna Power lack 10 Slots for wall mounting
- 11 PAIR/RESET key

NEED HELP?

For operations and guides to help you use your video monito and for the latest information and support, check out our online help topics and online FAQs.





You can also call our Customer Support at 1 (800) 595-9511 (in US) or 1 (800) 267-7377 (in Canada) for help





VM924-2

PARENT UNIT ICONS

Main menu icons Main Sub-menu menu

Adjust the parent unit's LCD brightness.

Lullaby

Play/Stop Iuliaby

≋1 ≋2 ≋3 ≋4 Select one of the soothing sounds, or

> **11 11 12 11 3 11 4 11 5** Select one of the five melodies.

 \Box Play all melodies.

60min 45min 30min 15min

· Set timer to stop playing the selected melody or soothing sound. VOX (Voice Activated Alert) Settings

VOX sound sensitivity level You can adjust VOX sensitivity levels to activate the parent unit when the baby unit detects sounds that exceed a certain volume. See Sound sensitivity

VOX (Voice Activated Alert) Settings (continued)

Main Sub-menu

ON/OFF Turn on/off sound activation

Set sound activation on or off.


Set sound activation on or off.
 When it is on, and the baby unit does not detect sound, the parent unit screen stays off to save power. Once a sound is detected, the parent unit screen and speaker automatically turns on, and you will be able to see and hear your baby. The parent unit will turn off again after 50 seconds of no sound detection.


 When the parent unit screen is off and it receives alerts, for example, link lost between parent unit and baby unit, or battery is low, the parent unit screen and speaker will turn on for 10 seconds

Alert Tone Settings



 Set the parent unit to beep when the battery is low. Set the parent unit to been when the link







°F°C

<u>©</u>

Main Sub-meni

 Zoom in. Monitoring Mode (For pairing with VM924-2 only)




 Single CAM mode
 The screen displays images only from the selected baby unit in full screen.
 Split mode The screen displays images from all the paired baby units at the same time in split view.



 Patrol mode The screen displays a single cam view that transitions to a different baby unit every 10 seconds.



PARENT UNIT ICONS (CONT'D)



Sound sensitivity and sound activation


Adjust sound detection sensitivity

You can turn on **Sound activation** and adjust the **VOX sensitivity** to detect sounds and turn on the parent unit while its screen is switched off or dimmed.

When the haby unit detects sounds that exceed costain levels, the parent unit screen will with the baby unit detects sounds that exceed certain levels, the parent unit screen will unit on and the baby unit starts transmitting the sounds to the parent unit, and you can see and hear your baby.

If you turn off Sound activation, you will hear sounds from the baby unit all the time, even

If you have turned on sound alert, the parent unit beeps when the baby unit detect sounds while in Split mode ("For pairing with VM924-2 only).



When Sound activation is on, the paren the baby unit detects no sound. Once the haby unit detects sounds sensitivity level, the parent unit screen and speaker turn on automatically. The parent unit will then turn off again after 50 seconds of no sound detection.

Mote If you have muted the parent unit speaker, only the parent unit screen will turn on when a sound is detected.





DIM MODE

The parent unit display will dim to conserve energy after 10 minutes of inactivity, in



NIGHT VISION





The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the bal unit being viewed detects low light levels, the infrared LEDs are switched on automatically. The images from the baby unit are in black and white, and appears on the screen.

Notes

- It is normal to see a short white glare on It is normal to see a snort white glare on your parent unit screen as the baby unit is adapting to the dark environment. When the infrared LEDs are on, the images are in black and white. This is normal.

 Depending on the surroundings and other interfering factors, like lighting, objects, colors and backgrounds, the display resolution may vary. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display





Select Patrol as your monitoring mode to alternately view the image from baby units Q 1 and Q 2 every 10 seconds.






If you drill the holes into an object other than

2

a stud, insert the wall anchors into the holes, Tap gently on the ends with a hammer until the wall anchors are flush with the wall.



⊞Notes

- Check for reception strength and camera angle before drilling the holes
- The types of screws and anchors you the wall. You may need to purchase the screws and anchors separately to mount



angle before drilling the holes. Place the wall mount bracket on a wall and then use a pencil to mark two holes in parallel.



Drill two holes in the wall (7/23 inch drill bit If you drill the holes into a stud, go to step 3,



screws with the holes in the wall as shown. Tighten the screw in the middle position is fixed. You can tighten the other screw in the top hole



Place the camera unit on the wall mount bracket, and then slide it forward until it locks into place. Connect the power supply not controlled by a wall switch



Q₆ Frequently asked questions

Below are the questions most frequently asked about the baby monitor.

Try the following (in the order listed) for common cure:

1. Disconnect the power to the baby units and the perent unit.

2. Wat a few seconds before connecting power back to the baby units and the perent unit.

3. Turn on the baby units and the parent unit.

4. Wat for the perent unit to synchronize with the baby units. Allow up to one minute

baby at night?

Why does the parent unit beep?

and then? Why are there

Perhaps the parent unit is not connected to the power. Insert the appliance plug ink the parent unit and put the adapter in a wall socker. Then, <u>press and hold POWER</u> to switch on the parent unit and to establish connection with the baby unit. Perhaps the baby unit is not connected to the power. Insert the appliance plug into the baby unit and put the adapter in a wall socket. Then, slide the **ON/OFF** switch to **ON** to switch on the baby unit and to establish connection with the parent unit.

Why doesn't my parent Make sure the power is not controlled by a wall switch.

You may have used the battery for a long time. See Warranty for repair/replacement. connected to AC power?

to prevent glare and blurry display.

The screen is in black and white during night-time or in a dark room when the night vision feature is activated. This is normal. During night-time or in a dark room, the surroundings and other interfering factors, like lightings, objects, colors and backgrounds may affect the image quality on your parent unit screen. Adjust the baby unit's ande or place the baby unit at a higher level

Why does the baby The parent unit and baby units may be too close to each other. Move the parent unit away from the baby units until the noise stops; OR Turn down the volume of your parent unit.

The baby units may be out of range. Move the parent unit closer to the baby units (but The parent unit may not have enough charge for the parent unit to perform no Charge the battery in the parent unit until the battery icon becomes solid.

The temperature of your baby's room may be too high or too low.

Why does the parent unit react too quickly to sensitivity level to a lower level or lower the parent unit speaker volume.

Why don't I hear a The parent unit speaker volume may be too low. See Adjust parent unit speaker You may have set a low VOX sensitivity level. See **Adjust the sound sensitivity of the baby unit** to set to a higher level. volume to increase the volume.

If you power on only one baby unit, your parent unit may display $\overline{\|}_{\!\!\!B}$, and the LINK LED light will flash.

THE RBRC SEAL

The RRRC Seal and 1 (800) 8 RATTERY® are registered trademarks of California Inc.

FCC AND IC REGULATIONS

FCC Part 15

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This Class B digital apparatus complies with Canadian requirement CAN ICES-3 (B)/NMB-3(B)

Industry Canada

The term "IC" before the certification/registration number only signifies that the Industry Capacia technical specifications were and at most the applicable Innovation. Science and Economic Development Canada technical reactifications

The product conjugies with FCC RF radiation exposure limits set forth for an uncontrolled environment. The baby unit should be installed and operated with a minimum distance of 8 in /00 mill between the baby unit and all persons' body. Use of other secretaries with respect to Canada's Health Code 6 for Exposure of Humans to 8F fields.

855-102 with respect to Canada's Health Code 6 for Exposure of Humans to 8F fields.

CALIFORNIA ENERGY COMMISSION BATTERY CHARGING TESTING MODE

FOR CETL COMPLIANCE ONLY

Mesures de sécurité importantes La plaque signalétique appliquée est située au bas du socie de l'unité du bébé.

ceux qui suivent : Observez toutes les instructions et mises en garde inscrites rur l'avescrall

sur rappareii. L'installation par un adulte est requise. MISE FN GARDE: N'installer nas l'unité du héhé à une.

hauteur supérieure à 2 mètres.

Ce produit ne remplace par la surveillance aduite du nourisson est la responsabilité du perent ou de la personne qui Soccupe de l'enfent. Ce de la personne qui Soccupe de l'enfent. Ce vous ne devriez pas présumer qu'il continuer de forticionne correctement pendat rune période de temps donnée. De partie de la la continuer de l'enfent. Ce de l'enfent de l'en

MISE EN GARDE: Utilise uniquement les piles fournies. Il oxiste un risque d'explosion d'un autre type de batterje coriste un risque d'explosion d'un autre type de batterje chi requirement regolares, afest les piles sudes s'aboli est ci risquirement regolares, afest les piles sudes s'aboli en renseignements suivant le sceau du RBRC. N'utiliser que les d'abspletaurs intales avec co produit. N'utiliser que les d'abspletaurs intales avec co produit n'utiliser que les d'abspletaurs intales avec co produit n'utiliser que les voir securités en prés.

Adaptateur de l'unité du parent : Sorlie : SV DC 1A
VTech Telecommunications Ltd.
Modèle : VT0SEUS03100

Modèle : VTDSEUS05100 Adaptateur de l'unité du bébé : Sortie : SV DC 1A VTech Telecommunications Ltd. Modèle : VTDSEUS05100

Modelle: VTDSEUMUSEU

Linion battery, 3.0V, 2600mAh, 9.36Wh;
Model: ICR18650-2.6Ah-3.6V-151P

Model: ICR18650-2.6Ah-3.6V-151P Model: ICR18650-2,6Ah-3,6V-1SIP Lorsqu'ils sont branchés dans une prise de courant, los adaptateurs secteur ont été conçué pour être orientés correctement, soit à la verticale ou au plancher. Les tro-nom pas été conçues pour supporter le potic du bloc d'alimentation et le maintenir en place si coluci est bran chair une prise au plationd, sous une table ou dans un

pietiner.

Ne faltes fonctionner cet appareil qu'avec le type d'alimentation indiqué sur l'étiquerte. Si vous he con pas le type d'alimentation que vous possédez à votre domicile, consultez votre marchand ou votre compagilierale r'éléctririsé. Ne surchargez pas les prises de courant murales ni les rallonges électriques.

an manufaget plat see printer de courant murales ni les surprises par les parties que considerate de la courant murales ni les 15. Ne placer par cel appareil sur un charlot, mueble, répied, support die montage ni table chancelants. Les trous et ouverfunce du bolbier, attuels 13 famérier de parties de la courant de la companyation de la courant de Pour l'empécher de surchauffer, ne bloquez cous aucun présente ces ouverfunces et n'empécher par la charlot adéquate de l'appareil en le placer par un lig. Glean, de l'empécher de la courant de la courant de la courant de positionne par sa la proximité ni au-dessus d'une source de positionnes par sa proximité ni au-dessus d'une source de positionnes par sa proximité ni au-dessus d'une source de

des points de tension dangereux ou causer des courts-circuits qui peuvent dégénérer en incendies ou en risqu d'électrocution. Ne renversez lamais de liquide dans ce

. réduire les risques d'électrocution, ne démontez appareil, mais apportez-le dans un centre de servi pas cer appareir, mais apponers-re dans un centre de servir autorisé. L'ouverture du boîtier ou le retrait de toutes pièce que confient cet appareir, à l'exception de l'accès autorisé à certaines portes du ouvertures, risque de vous exposer à des points de tension dangereux ou d'autres dangers. Un remontage incorrect peut par la suite présenter dès risque-

d'électroculien. Vous devriez tester la réception chaque fois que vous mettre l'appareill en fonction. Examinez les composantes afin de vérifies si celles-ci ne sont pas endommagées. Il existe un très faible risque de perte de confidentialité avec cortains appareils électroniques (suntres écoute-béb hélophones sans fils etc.). Pour l'other, à sauverq que le

d'expérience et de connaissances, à moins qu'on leur ait donné suffisamment de supervision ou d'instructions relativement à l'utilisation de l'appareil par une personne

rable de leur sécurité. CONSERVEZ CES INSTRUCTIONS Mises en garde 1. Utilisez et entreposez le produit à une température entre 0. C (32° F) et 40° C (304° F). 2. Monages par est appareil à des froids ou des chalours.

N'exposez pas cet appareil à des froids ou des chaleurs extrêmes, ainsi qu'à la lumière directe du soleil. Ne l'installez pas près d'une source de chauffage.

Le bloc-piles ne doit pas être exposé à la chaleur excessive telle que la lumière du soleil ou au feu.

table que la lumière du soloi lou ba feu.

Aventiscement - Riscue de tranquation
- Las centants so sone ETRANCLES dans des
cordens. Cardes co corden hora de porties
corden diquette.

No la participa de la printe contra la corden de la printe
corden diquette.

No la participa de la printe corden diquette.

No la participa de la printe couyrir la moniteur o'ul
participa de la printe couyrir la moniteur d'inférieur du bercoas
un du participa de la printe couyrir la moniteur d'inférieur au che d'inférieur de un servicient de un un couvertifice de un contra l'acceptance de la printe de un servicient de un un couvertifice de un servicient de un un couvertifice de un contra l'acceptance de la printe de la printe de un servicient de un un couvertifice de un contra l'acceptance de la printe de la

couverfulre. D'autres équipements électroniques peuvent produire des interférences sur votre moniteur vicéo et audio. Tentez d'installer votre moniteur vicéo et audio a l'écar des appareils électroniques tels que des routeurs sans fil, radios

numenques sans til): L'organisme "Wireless Technology Research, LLC (WTR)", une firme de recherche indépendante, a mené une évaluation pluridisciplinaire des intérférences entre les téléphones sans poministratifs et les stimulateurs cardiaques implantés dans l'organisme. Appuyée par l'Administration des aliments et droques (FDA) des Etats-Unis, la firme WTR recommande au

medecins: Avis aux détenteurs de stimulateurs cardiaques • Vous devriez maintenir les dispositifs sans fil à au moins six vous devinez maintenir les dispositifs sans fil à au moins six pouces du simulateur cardiaque. Ils ne doivent PAS placer le téléphone sans fil directement sur le stimulateur cardiaque, tel que dans une poche de chemise, lorsque celui-c' est en marche. L'étude effectuée par l'organisme WRS n'a pas identifié de risque pour les détenteurs de simulateurs cardiaques causés les gens qui utilisent dispositifs sans fil à proximité de ceux-ci

LIMITED WARRANTY

What does this limited warranty cover?

The manufacture of this VIII che Product warrants to the holder of a valid proof of parchase ("Consumer" or "you") that the Product and all accessions provided in the sales package ("Product") are free from defects in material expensions are provided in the sales package ("Product") are free from defects in material conditions, when installed and used normally and in accordance with the Product operating instructions. This limited warranty sendence only in the Consumer for Product purchased and used in the United States of America and Clamida.

Crando.

What will Visch do if the Product is not free from defects in materials and workmanking during the limited warranty in the product is material and workmanking during the limited warranty broads. Visch's authorized service in presentative will repair or replace at Visch's option, and the product warranty product. Visch's and product service in presentative will repair or replace at Visch's option. The Product was made to produce the Product, we may replace and the Product, and the Product of the Product the Product o

How long is the limited warranty period?

How long is the immere warranty period or in the Product extends for ONE (I) YEAR from the date of purchase. If IY Rech repairs or replaces a Materially Defective Product under the terminal productive product under the terminal productive product under the terminal productive product under the relation of replaces and the product for appaired or replacement Product for an period of either (s). Yellow the productive productive

What is not covered by this limited warranty? This limited warranty does not cover:

 Product that has been subjected to misuse, accident shipping or other physical damage, improper installation, abnormal operation or handling, neglect, inundation, fire, water or other liquid intrusion; or Product that has been damaged due to repair, alteration or modification by anyone other than an authorized service representative of VTech; or

service representative of VTech; or
3. Product to the extent that the problem experienced is caused by signal conditions, network reliability, or cable or antenen systems of the signal conditions, network reliability, or cable or 4. Product to the extens that the postbern is caused by use 5. Product whose warrashify/capility stickers, product serial number plates or electronic serial numbers have been removed, aftered or rendered religible; or

Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or 7. Product returned without a valid proof of purchase (see item 2 below); or

Charges for installation or set up, adjustment of customer controls, and installation or repair of systems outside the

To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or call 1 (800) 267-7377.

NOTE: Before calling for service, please review the user's manual - a check of the Product's controls and features ma save you a service call.

trainport of the Productift to the service Scation. VT och will return repaired or replaced Product under the limited warranty. Transportation, delivery or handling charges are prepaid. VTeles seasons on role for demange or loss of the Product in harm. If the Product failure is not covered by the things of the product o

What must you return with the Product to get warranty

- Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or receipt; and

Other limitations
This warranty is the complete and exclusive agreement between you and Virech it superrades all other written or and communications related to this Product Virech provides of the product of the product of the product of the product. These are not one expensions regarding the product. These are no other express warrantes. No one is authorized to make modifications to this finited warranty and you may also have other right, which vary from state to state or provinces to province to province as provinces.

or province to province.

Limitation: Implied warranties, including those of filmest for a particular purpose and merchantability four unwritten warranty that the Product is fit for cridary use) are limited to one year from the date of purchase. Some stater/ provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you in no event all all Vitech be liable for any indirect, special, incidental, consequential, or winter damages (incidential, consequential, or winter damages (incidential, consequential, or winter damages) (incidential).

Please retain your original sales receipt as proof of purchase.

VTech Communications, Inc. and its suppliers assume no responsibility for any damage or loss resulting from the use of this user's manual. VTech Communications, Inc. and its suppliers assume no responsibility for any loss or claims by third parties that may arise through the use of this product.

DISCLAIMER AND LIMITATION OF LIABILITY