



FD7256U WIFI Module

Datasheet

V1.0

neardi

Shanghai Neardi Technology Co., Ltd.
www.neardi.com

Shanghai Neardi Technology Co., Ltd. (referred to as "Neardi Technology") always adheres to the customer-first service tenet and provides customers with fast and efficient support services. If you have any needs, please feel free to contact our company, the contact information is as follows:

Shanghai Neardi Technology Co., Ltd.

www.neardi.com

Tel: +86 21 20952021

Email: sales@neardi.com

Introduction

Neardi Technology provides this document for customers to use as a reference for product design and terminal applications. It is recommended that customers confirm the specifications and parameters provided in the document in detail, and confirm whether it can meet the design or application of the required products. At the same time, it is strongly recommended that customers do detailed tests in actual application scenarios based on the samples provided by our company to ensure that they meet the end use requirements. Neardi Technology is not responsible for any damages suffered due to the use of documents, materials and product functions.

The relevant parameters or design charts in this document are only examples, and customers should base their own independent analysis, evaluation and judgment when designing or using terminal products. Before customers use any design or service guided by this document, please read this statement carefully, understand and agree that although Neardi Technology has taken reasonable commercial efforts to provide the best possible experience, this document and its contents are PROVIDED TO YOU ON AN "AS AVAILABLE" BASIS. The information in this document is subject to change without notice.

Agreement

Unless specifically authorized by Neardi Technology, the recipient of the product documentation, hardware reference drawings, software descriptions and other materials provided by our company must keep the received content confidential and shall not use it for any other purpose other than the implementation and development of this project.

Copyright Statement

Documents and information provided by our company may not be obtained, used or disclosed to third parties, or such copyrighted materials may be copied, reproduced, plagiarized, published, displayed, translated, distributed or merged, modified or created derivative works unless obtain prior written consent. Neardi Technology has exclusive rights to copyrighted materials and does not grant or convey a license to any patent, copyright, trademark or service mark rights, and no purchase of any kind shall be deemed to be the grant of a license. Neardi Technology has the right to pursue legal responsibility for any illegal infringements that violate confidentiality, use without authorization or maliciously use the documents and information in other illegal forms.

© 2023 Shanghai Neardi Technology Co., Ltd. All Rights Reserved.

Version History

Version	Date	Illustrate
V1.0	2024/01/12	Initial Version

Contents

Contents.....	3
1 Product Overview.....	5
1.1 Product Introduction	5
1.2 Wi-Fi Characteristics	6
1.3 Bluetooth Characteristics	6
1.4 Block Diagram	7
1.5 Parameters.....	7
2 Pin Definition.....	8
2.1 Pin Number	8
2.2 Pin Description	8
3 Mechanical Specifications.....	10
3.1 Mechanical Dimensions	10
3.2 Recommended PCB Layout Footprint.....	11
4 Electrical Performance and Reliability	12
4.1 Absolute Maximum Voltage Range	12
4.2 Recommended Operation Conditions	12
4.3 Power On/Off Sequence	12
4.4 Reliability	13
5 RF Characteristics	14
5.1 2.4GHZ Wi-Fi Radio Frequency (RF) Characteristics	14
5.2 5GHZ Wi-Fi RF Characteristics	15
5.3 Bluetooth Radio Frequency (RF) Characteristics.....	17
6 Hardware Design Guide.....	18
6.1 Power Design Notice.....	18
6.1.1 Voltage Requirement.....	18
6.1.2 Current Requirement.....	18
6.1.3 Power Supply Reference.....	19
6.2 Interface Design Notice	19
6.2.1 HCI Commend Interface.....	19

7	Storage, Production and Packaging	20
7.1	Storage Conditions	20
7.2	Production Welding	20
7.3	Packing Specifications	21
7.3.1	Tape Dimensions	22
7.3.2	Plastic Reel Dimensions	22
7.3.3	Packaging Process	23
8	Antenna Design	23
8.1	Summarize	23
8.2	List of applicable FCC rules	24
8.3	Specific Operational Use Conditions - Antenna Placement Within the Host Platform	24
8.4	Limited Module Procedures	24
8.5	Trace Antenna Designs	24
8.6	RF Exposure Considerations	28
8.7	Antenna Type and Gain	26
8.8	End Product Labelling Compliance Information	27
8.9	Information on Test Modes and Additional Testing Requirements	27
8.10	Additional testing, Part 15 Subpart B Disclaimer	28
8.11	Manual Information to The End User	28
8.12	How to Make Changes - Important Note	28

1 Product Overview

1.1 Product Introduction

FD7256U is a highly integrated, low-cost combo module with high-performance and low-power. It supports Wi-Fi 6 and Bluetooth 5.0 protocol, supports Wi-Fi MAC of the final version of Wi-Fi 6 Wave2 protocol, Wi-Fi Baseband of 1T1R, and high-performance RF. It also supports USB2.0, HS-UART and PCM interfaces for connection with the main control. This module also supports BT and Wi-Fi to work in coexistence mode. It is suitable for consumer electronics such as CPE, IPC, tablet and IOT, and can also be used in fields with high reliability requirements such as industrial interconnection.




Figure 1-1

1.2 Wi-Fi Characteristics

- ✓ IEEE 802.11a/b/g/n/ac/ax (supports wave-2) wireless LAN communication protocol
- ✓ IEEE 802.11 d/e/h/i/k/mc/r/v/w
- ✓ Phy rate up to 600.8Mbps, Throughput rate up to 260Mbps
- ✓ Multiple modes such as Wi-Fi STA, AP, and P2P
- ✓ 80MHz bandwidth, 1T/1R
- ✓ Up to 1024QAM modulation, supports LDPC and STBC
- ✓ UL/DL OFDMA, DL MU-MIMO
- ✓ QoS, WFA WMM, WMM PS
- ✓ RSSI and CSI Reporting
- ✓ Beamformee and 4*1 Tx Beamforming
- ✓ WPA, WPA2, WPA3 encryption and decryption, WAPI and WPS2.0
- ✓ ER, DCM to improve transceiver gain
- ✓ 20in40/80/160, Partial band MU MIMO to improve air interface utilization;
- ✓ BSS Color, Spatial Reuse to improve air interface utilization
- ✓ TWT, Intra-PPDU PS, VHT TXOP PS to optimize dynamic power consumption in small bandwidth and multi-BSS environment

1.3 Bluetooth Characteristics

- ✓ Support Bluetooth (Classic BT+BLE) v2.1, v3.0, v4.2, v5.0 features
- ✓ USB2.0 interface for BT data transmission
- ✓ PCM/IIS interface for audio transmission
- ✓ BR/EDR/LE 1M/LE 2M/LE LR
- ✓ Support sco and esco link
- ✓ SSP/Secure Connection
- ✓ Low power mode (sniff, sniff sub-rating)
- ✓ Support BT/Wi-Fi coexistence

1.4 Block Diagram




Figure 1-4

1.5 Parameters

Table 1-5

Product Name	FD7256U
Product description	802.11ax/ac/a/b/g/n 1T1R dual band Wi-Fi and Bluetooth 5.0 comb module
Dimension	13(±0.1)mm*12.2(±0.1)mm*1.65(±0.2)mm
Power supply	VBAT: 3.0~3.6V
Host interface	USB2.0
Footprint	LCC 22pin
Operating temperature	-30°C to 70°C
Operating humidity	10% to 90% (Non-Condensing)
Storage temperature	-40°C to 85°C

2 Pin Definition

2.1 Pin Number



Figure 2-1

2.2 Pin Description

Table 2 -2

Pin Number	Pin Name	Pin Type	Pin Description
1	GND	G	Ground connections
2	WL_BT_ANT	RF	RF I/O port
3	NC	-	Floating (Don't connected to ground)
4	GND	G	Ground connections
5	NC	-	Floating (Don't connected to ground)
6	NC	-	Floating (Don't connected to ground)
7	NC	-	Floating (Don't connected to ground)
8	NC	-	Floating (Don't connected to ground)
9	NC	-	Floating (Don't connected to ground)
10	NC	-	Floating (Don't connected to ground)
11	VBAT	P	Main power voltage source input
12	USB_DM	I/O	USB Transmitter/Receiver Differential Pair
13	USB_DP	I/O	USB Transmitter/Receiver Differential Pair
14	GND	G	Ground connections

15	NC	-	Floating (Don't connected to ground)
16	NC	-	Floating (Don't connected to ground)
17	NC	-	Floating (Don't connected to ground)
18	CHIP_EN	I	Module enable signal
19	NC	-	Floating (Don't connected to ground)
20	NC	-	Floating (Don't connected to ground)
21	NC	-	Floating (Don't connected to ground)
22	NC	-	Floating (Don't connected to ground)

3 Mechanical Specifications

3.1 Mechanical Dimensions




Figure 3-1

3.2 Recommended PCB Layout Footprint




Figure 3-2

4 Electrical Performance and Reliability

4.1 Absolute Maximum Voltage Range

Table 4-1

Symbol	Description	Min	Max	Unit
VBAT	Power Supply Voltage	-0.5	5.25 ¹	V

4.2 Recommended Operation Conditions

Table 4-2

Symbol	Description	Min	Type	Max	Unit
Ta	Ambient Operating Temperature	-30	25	70	°C
Antenna	External Antenna VSWR	-	1.92:1	2:1	
VBAT	Power Supply Voltage	3.0	3.3	3.6	V

4.3 Power On/Off Sequence




Figure 4 -3

Table 4-3

Symbol	Description	Min	Type	Max	Unit
T1	VBAT Ramp up time	0.2	0.5	-	mS
T2	CHIP_EN should be powered on after VDDIO is powered on	0	-	-	mS
T3	CHIP_EN reset time	50	-	-	mS

¹ If the voltage exceeds this value, the chip will be irreversibly damaged.

4.4 Reliability

Table 4-4

Item	Test Model	Class	Level	Criteria
ESD	HBM	2	2000V	ANSI/ESDA/JEDEC JS-001-2017
	CDM	C2a	500V	ANSI/ESDA/JEDEC JS-002-2018
Latch-up	Current	II A	200mA	JEDEC STANDARD NO.78F JANUARY 2022
	Voltage	II A	1.5xVmax	JEDEC STANDARD NO.78F JANUARY 2022

5 RF Characteristics

5.1 2.4GHZ Wi-Fi Radio Frequency (RF) Characteristics

Table 5 -1

Conditions: VBAT=3.3V; VDDIO=1.8V; Ta:25°C					
Features	Description				
Wi-Fi Standard	IEEE 802.11b/g/n/ac/ax				
Frequency Range	2.4~2.4835GHz(2.4GHz ISM Band)				
Channels	Ch1~Ch13				
Modulation	802.11b (DSSS): CCK, DQPSK, DBPSK;				
	802.11g (OFDM): BPSK, QPSK, QAM16, QAM64;				
	802.11n (OFDM): BPSK, QPSK, QAM16, QAM64;				
	802.11ac (OFDM): BPSK, QPSK, QAM16, QAM64, QAM256;				
	802.11ax (OFDMA): BPSK, BPSK_DCM, QPSK, QPSK_DCM, QAM16, QAM16_DCM, QAM64, QAM256, QAM1024;				
Data Rate	802.11b: 1, 2, 5.5, 11Mbps;				
	802.11g: 6, 9, 12, 18, 24, 36, 48, 54Mbps;				
	802.11n (HT20): MCS0~MCS7 6.5~72.2Mbps;				
	802.11n (HT40): MCS0~MCS7 13.5~150Mbps;				
	802.11ac(VHT20): MCS0~MCS8 6.5~86.7Mbps;				
	802.11ac(VHT40): MCS0~MCS9 13.5~200Mbps;				
	802.11ax (HE20): MCS0~MCS11 8~143.4Mbps;				
802.11ax (HE40): MCS0~MCS11 16~286.8Mbps;					
Frequency Tolerance	±5ppm				
2.4G Transmitter Specifications					
Modulation	TX Rate		TX EVM (dB)	TX Mask	VBAT current (mA)
802.11b	1Mbps		≤35%	PASS	470
802.11b	11Mbps		≤35%	PASS	303
802.11g	6Mbps		≤-5	PASS	318
802.11g	54Mbps		≤-25	PASS	385
802.11n	HT20 MCS0		≤-5	PASS	305
802.11n	HT20 MCS7		≤-27	PASS	303
802.11n	HT40 MCS0		≤-5	PASS	302
802.11n	HT40 MCS7		≤-27	PASS	275
802.11ac	VHT20 MCS0		≤-5	PASS	305
802.11ac	VHT20 MCS8		≤-30	PASS	270
802.11ac	VHT40 MCS0		≤-5	PASS	296
802.11ac	VHT40 MCS9		≤-32	PASS	230
802.11ax	HE20 MCS0		≤-5	PASS	280

802.11ax	HE20 MCS11		≤-35	PASS	254
802.11ax	HE40 MCS0		≤-5	PASS	279
802.11ax	HE40 MCS11		≤-35	PASS	193
2.4G Receiver Specifications					
Modulation	RX Rate	Min Input Level (dBm)	Max Input Level (dBm)	PER	VBAT current (mA)
802.11b	1Mbps	≤-96	-5	8%	118
802.11b	11Mbps	≤-87	-5	8%	118
802.11g	6Mbps	≤-92	-5	10%	118
802.11g	54Mbps	≤-75	-5	10%	117
802.11n	HT20 MCS0	≤-92	-5	10%	122
802.11n	HT20 MCS7	≤-72	-5	10%	120
802.11n	HT40 MCS0	≤-89	-5	10%	126
802.11n	HT40 MCS7	≤-70	-5	10%	121
802.11ac	VHT20 MCS0	≤-91	-5	10%	122
802.11ac	VHT20 MCS8	≤-68	-5	10%	119
802.11ac	VHT40 MCS0	≤-89	-5	10%	126
802.11ac	VHT40 MCS9	≤-63	-5	10%	122
802.11ax	HE20 MCS0	≤-92	-5	10%	123
802.11ax	HE20 MCS11	≤-60	-5	10%	119
802.11ax	HE40 MCS0	≤-89	-5	10%	126
802.11ax	HE40 MCS11	≤-58	-5	10%	121

5.2 5GHZ Wi-Fi RF Characteristics

Table 5 -2

Conditions: VBAT=3.3V; VDDIO=1.8V; Ta:25°C	
Features	Description
Wi-Fi Standard	IEEE 802.11a/n/ac/ax
Frequency Range	5.15~5.25GHz; 5.25~5.35GHz; 5.47~5.73GHz; 5.735~5.835GHz (5GHz ISM Band)
Channels	Ch36,Ch40, Ch44, Ch48; Ch52~Ch64; Ch100~Ch140; Ch149~Ch165
Modulation	802.11a (OFDM): BPSK, QPSK, QAM16, QAM64; 802.11n (OFDM): BPSK, QPSK, QAM16, QAM64; 802.11ac (OFDM): BPSK, QPSK, QAM16, QAM64, QAM256; 802.11ax (OFDMA): BPSK, BPSK_DCM, QPSK, QPSK_DCM, QAM16, QAM16_DCM, QAM64, QAM256, QAM1024;
Date Rate	802.11a: 6, 9, 12, 18, 24, 36, 48, 54Mbps; 802.11n (HT20): MCS0~MCS7: 6.5~72.2Mbps; 802.11n (HT40): MCS0~MCS7: 13.5~150Mbps; 802.11ac (VHT20): MCS0~MCS8: 6.5~86.7Mbps; 802.11ac (VHT40): MCS0~MCS9: 13.5~200Mbps; 802.11ax (HE20): MCS0~MCS11: 8~143.4Mbps; 802.11ax (HE40): MCS0~MCS11: 16~286.8Mbps;

Frequency Tolerance	±5ppm				
5G Transmitter Specifications					
Modulation	TX Rate		TX EVM (dB)	TX Mask	VBAT current (mA)
802.11a	6Mbps		≤-5	PASS	276
802.11a	54Mbps		≤-25	PASS	342
802.11n	HT20 MCS0		≤-5	PASS	273
802.11n	HT20 MCS7		≤-27	PASS	276
802.11n	HT40 MCS0		≤-5	PASS	258
802.11n	HT40 MCS7		≤-27	PASS	232
802.11ac	VHT20 MCS0		≤-5	PASS	273
802.11ac	VHT20 MCS8		≤-30	PASS	242
802.11ac	VHT40 MCS0		≤-5	PASS	258
802.11ac	VHT40 MCS9		≤-32	PASS	186
802.11ac	VHT80 MCS0		≤-5	PASS	256
802.11ac	VHT80 MCS9		≤-32	PASS	285
802.11ax	HE20 MCS0		≤-5	PASS	247
802.11ax	HE20 MCS11		≤-35	PASS	221
802.11ax	HE40 MCS0		≤-5	PASS	243
802.11ax	HE40 MCS11		≤-35	PASS	149
802.11ax	HE80 MCS0		≤-5	PASS	246
802.11ax	HE80 MCS11		≤-35	PASS	267
5G Receiver Specifications					
Modulation	RX Rate	Min Input Level (dBm)	Max Input Level (dBm)	PER	VBAT current (mA)
802.11a	6Mbps	-91	-5	10%	87.5
802.11a	54Mbps	-74	-5	10%	88.1
802.11n	HT20 MCS0	-91	-5	10%	90.5
802.11n	HT20 MCS7	-71	-5	10%	92.7
802.11n	HT40 MCS0	-88	-5	10%	94.1
802.11n	HT40 MCS7	-69	-5	10%	98.2
802.11ac	VHT20 MCS0	-91	-5	10%	90.9
802.11ac	VHT20 MCS8	-67	-5	10%	92.4
802.11ac	VHT40 MCS0	-88	-5	10%	95.6
802.11ac	VHT40 MCS9	-63	-5	10%	98.7
802.11ac	VHT80 MCS0	-85	-5	10%	102.5
802.11ac	VHT80 MCS9	-59	-5	10%	109.2
802.11ax	HE20 MCS0	-91	-5	10%	92.1
802.11ax	HE20 MCS11	-60	-5	10%	92.5
802.11ax	HE40 MCS0	-89	-5	10%	96.7
802.11ax	HE40 MCS11	-58	-5	10%	96.6
802.11ax	HE80 MCS0	-86	-5	10%	105.3
802.11ax	HE80 MCS11	-53	-5	10%	106.5

5.3 Bluetooth Radio Frequency (RF) Characteristics

Table 5 -3

Conditions: VBAT=3.3V; VDDIO=1.8V; Ta:25°C					
Features	Description				
Bluetooth Standard	Bluetooth v2.1+EDR/3.0+HS/4.2/5. 0				
Frequency Range	2.4~2.4835GHz				
Channels	Bluetooth Classic: Ch0~Ch78 (For 1MHz Channels); Bluetooth Low Energy: Ch0~Ch39 (For 2MHz Channels);				
Power class	Bluetooth Classic: Class1; Bluetooth Low Energy: Class1.5;				
Modulation	BR_1Mbps: GFSK; EDR_2Mbps: π/4-DQPSK; EDR_3Mbps: 8DPSK; LE_125Kbps: GFSK (Coded_S=8); LE_500Kbps: GFSK (Coded_S=2); LE_1Mbps: GFSK (Uncoded); LE_2Mbps: GFSK (Uncoded);				
Bluetooth Receiver Specifications					
Item	Sensitivity (dBm)		Max Input Level (dBm)		VBAT current
	Input Level (Typ)	BER	Input Level (Typ)	BER	(mA)
BR_1M	TBD	TBD	TBD	TBD	TBD
EDR_2M /3M	TBD	TBD	TBD	TBD	TBD
LE_125/500K	TBD	TBD	TBD	TBD	TBD
LE_1M	TBD	TBD	TBD	TBD	TBD
LE_2M	TBD	TBD	TBD	TBD	TBD

6 Hardware Design Guide

6.1 Power Design Notice

6.1.1 Voltage Requirement

The main power supply (VBAT) input range of the module is 3.3V \pm 10%, and the interface VDDIO supports two level ranges, 1.8V \pm 10% or 3.3V \pm 10%. Due to the ripple of the main power can affect the RF performance of Wi-Fi and Bluetooth, therefore the power supply ripple VPP is required to be less than 50mV.

6.1.2 Current Requirement

Under different standards, when Wi-Fi transmits continuously, the peak value and amplitude of the operating current on the main power supply are as shown in the table below. The 3.3V power converter must be able to provide 650mA RMS current and fast transient response (when the transient current change rate is 80mA/us, the voltage drop is less than 100mV).

Table 6-1-2

Mode	Burst power (dBm)	Peak current (mA)	RMS current (mA)
11b 11M long 2.4G ch1	23.5	833	607
	21.8	753	573
	19.6	647	473
	17.4	593	440
	15.5	566	407
11ax MCS0 2.4G CH1	22	720	500
	20	640	427
	18	587	420
	16	553	393
11ax MCS0 5G CH36	22	827	560
	19.9	667	433
	18	620	380
	16	540	307

7 Storage, Production and Packaging

7.1 Storage Conditions

- ❖ FD7256U module is 3 (MSL3) and packed in a vacuum-sealed bag when shipped, the recommended storage temperature is $25\pm5^{\circ}\text{C}$, and the relative humidity is 35%~60%. Under this condition, the module can be stored for 12 months.
- ❖ The Module shall be stored without opening the packing. After the packing opened, the module shall be completed the patch soldering within 24 hours.
- ❖ FD7256U module can be stored for no more than 168 hours in a workshop environment with a temperature of $25\pm5^{\circ}\text{C}$, a relative humidity below 60% and in compliance with IPC/JEDEC J-STD-033. It is not recommended to expose the module unpacked to the air for a long time. If not immediately patch soldering, it is recommended to store the module in a moisture-proof cabinet with a relative humidity of less than 10% to keep the module dry.
- ❖ If the module is not stored according to the above recommended method, it needs to be baked at high temperature ($120\pm5^{\circ}\text{C}$) for 8 hours. The re-baked module shall be patched within 24 hours.
- ❖ Please pay attention to ESD protection when unpacking and handling modules.

7.2 Production Welding

During the production welding process, please do not use any organic solvents (such as alcohol, isopropanol, acetone, trichloroethylene, etc.) to wipe the shield of the FD7256U module, otherwise it may cause the shield to rust. Please do not ultrasonically clean the module, it may cause damage to the crystal inside the module. Please make sure that the spray material used will not chemically react with the module shield or PCB and will not flow into the module when spraying modules.

In order to ensure the welding quality and reliability of the FD7256U module, the thickness of the printed stencil is recommended to be 0.15~0.18mm; the recommended reflow curve is as follows:




Figure 7 -2 Recommended reflow curve

Table 7 -2

Item	Description	Value
Endothermic Zone Heating Rate	Interval A	$\leq 3^{\circ}\text{C/s}$
Soak time	From the end of interval A to the beginning of interval B	60~120s
Reflow Zone Heating Rate	Interval C	$\leq 3^{\circ}\text{C/s}$
Maximum Temperature	Highest point of the curve	$246^{\circ}\text{C} (+5/-0^{\circ}\text{C})$
Cooling Rate	Interval D	$< 6^{\circ}\text{C/s}$
Reflow Time	Interval E	60~150 seconds

7.3 Packing Specifications

The key parameters and packaging processes described in this chapter are for reference only. The appearance and structure of the specific packaging materials are subject to actual delivery.

7.3.1 Tape Dimensions




Figure 7-3-1 Tape dimensions

Table 7-3-1

W	P	T	A0	B0	K0	F	E	Unit
24	16	0.35	12.6	13.4	2.5	11.5	1.75	mm

7.3.2 Plastic Reel Dimensions




Figure 7-3-2 Tape dimension

Table 7-3-2

ØD1	ØD2	W	unit
330	100	24	mm

7.3.3 Packaging Process




Figure 7-3-3 Package specification

8 Antenna Design

8.1 Summarize

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
- This modular has been tested and found to comply with part 15 requirements for Modular Approval.
- FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
 - Integration instructions for host product manufacturers according to KDB 996369 D03 OEM Manual v01r01

8.2 List of applicable FCC rules

CFR 47 FCC Part 15 Subpart C and Subpart F has been investigated. It is applicable to the modular transmitter

8.3 Specific Operational Use Conditions - Antenna Placement Within the Host Platform

The module is tested for standalone mobile RF exposure use condition.

- The antenna must be installed such that 20cm is maintained between the antenna and users,
 - The transmitter module may not be co-located with any other transmitter or antenna.
- In the event that these conditions cannot be met (for example certain laptop configurations or co-location with another transmitter), then the FCC authorization is no longer considered valid and the FCC ID cannot be used on the final product. In these circumstances, the OEM integrator will be responsible for re-evaluating the end product (including the transmitter) and obtaining a separate FCC authorization.

8.4 Limited Module Procedures

Not applicable


8.5 Trace Antenna Designs

Users should connect antennas to half hole pad through copper tube structure or FP types of RF trace and the trace impedance must be controlled in 50Ω. recommends that the total insertion loss between the antenna pads and antennas should meet

the following requirements:

Frequency	Loss
2400MHz-2500MHz	<0.6dB
5150MHz-5850MHz	<1.2dB


To facilitate the antenna tuning and certification test, a RF connector and an antenna matching circuit should be added. The following figure is the recommended circuit.



The module needs to be attached to the PCB board and connected to the external antenna through the solder joint of the circuit on the PCB. The gain of the external antenna is 2dB (i Max.) ,the internal structure is copper tube structure or FPC. A resistance of 0R is added between the module and the antenna at C1003 to ensure that the impedance of the connection between the module and the antenna reaches 50R. The J0800 position on the PCB is where the external antenna is connected.

RF traces layout

- 1.Keep the RF trace from module ant pin to antenna as short as possible
- 2.RF trace should be 50 Ω either on the top layer or in the inner layer
- 3.RF trace should be avoided right angle and sharp angle.
- 4.Put enough GND vias around RF traces.
- 5.RF trace should be far away from other high speed signal lines.



External Antenna VSWR

Parameters	Min	Typ	Max
External Antenna VSWR		1.6	2.0

8.6 RF Exposure Considerations

This device complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

8.7 Antenna Type and Gain

The following antennas have been certified for use with this module.

Only antennas of the same type with equal or lower gain may also be used with this module. Other types of antennas and/or higher gain antennas may require the additional authorization for operation.

Antenna Specification list below:

Model	Type	Connector	Peak gain (dBi)				
			2400-2483.5 MHz	5150-5250 MHz	5250-5350 MHz	5470-5725 MHz	5725-5850 MHz
FD200U	External Antenna	/	2.00dBi	2.00dBi	2.00dBi	2.00dBi	2.00dBi

8.8 End Product Labelling Compliance Information

When the module is installed in the host device, the FCC ID label must be visible through a window on the final device or it must be visible when an access panel, door or cover is easily removed. If not, a second label must be placed on the outside of the final device that contains the following text: “Contains FCC ID: **2BFAK-FD200U**”. The FCC ID can be used only when all FCC compliance requirements are met.

8.9 Information on Test Modes and Additional Testing Requirements

This transmitter is tested in a standalone mobile RF exposure condition and any co-located or simultaneous transmission with other transmitter(s) class II permissive change re-evaluation or new FCC authorization.

Host manufacturer installed this modular with single modular approval should perform the test of radiated emission and spurious emission according to FCC part 15C, Part 15E, 15.209, 15.207 requirement, only if the test result comply with FCC part 15C, Part 15E, 15.209, 15.207 requirement, then the host can be sold legally.

8.10 Additional testing, Part 15 Subpart B Disclaimer

This transmitter modular is tested as a subsystem and its certification does not cover the FCC Part 15 Subpart B rules requirement applicable to the final host. The final host will still need to be reassessed for compliance to this portion of rules requirements if applicable.

As long as all conditions above are met, further transmitter test will not be required. However, the OEM integrator is still responsible for testing their end-product for any additional compliance requirements required with this modular installed.

8.11 Manual Information to The End User

The OEM integrator has to be aware not to provide information to the end user regarding how to install or remove this RF module in the user's manual of the end product which integrates this module.

The host integrator must follow the integration instructions provided in this document and ensure that the composite system end product complies with the requirements by a technical assessment or evaluation to the rules and to KDB Publication 996369.

The host integrator installing this module into their product must ensure that the final composite product complies with the requirements by a technical assessment or evaluation to the rules, including the transmitter operation and should refer to guidance in KDB Publication 996369.

OEM/Host Manufacturer Responsibilities

OEM/Host manufacturers are ultimately responsible for the compliance of the Host and Module. The final product must be reassessed against all the essential requirements of the FCC rule such as FCC Part 15 Subpart B before it can be placed on the US market. This includes reassessing the transmitter module for compliance with the Radio and RF Exposure essential requirements of the FCC rules.

8.12 How to Make Changes - Important Note

In the event that these conditions cannot be met (for example certain laptop configurations or co-location with another transmitter), then the FCC authorization is no longer considered valid and the FCC ID cannot be used on the final product. In these circumstances, the OEM integrator will be responsible for re-evaluating the end product (including the transmitter) and obtaining a separate FCC authorization.