

材质:双铜128g  
文字色号:PANTONE 431C

110.00 mm

85.00 mm

正

无线充音响带灯+  
时钟和手表耳机无线充

无线充

时钟闹钟

夜灯

蓝牙音箱

手机支架

产品使用说明

非常感谢您选择我司产品,在使用产品前请认真阅读好产品说明

产品特点

- 造型简易精致。
- 夜灯。
- 蓝牙音箱。
- 时钟闹钟。
- 无线快充。
- 充电距离≤6mm。

外观特征

①

②

③

④

⑤

⑥

⑦

⑧

⑨

① 灯罩

② 无线充电基准点

③ 手机支架

④ 硅胶按键

⑤ 时钟显示区域

⑥ 夜灯开关

⑦ 音箱腔体

⑧ Type-C输入接口

⑨ 硅胶脚垫

操作方法

1.将USB数据线的USB端口接入电源适配器,Type-C端口接入无线充电器时钟显示区域指示灯【】闪烁。

2.将需要的无线充电设备放在本产品充电指示区域,时钟显示区域充电指示灯【】常亮,进入充电状态充满后指示灯熄灭。

小夜灯功能

- 触摸开关第一档启动灯光,灯光亮度为30%。
- 触摸开关第二档,灯光亮度为70%。
- 触摸开关第三档,灯光亮度为100%。
- 触摸开关第四档关灯。
- 依次循环开启灯光。

按键功能

模式

切换

蓝牙

收音机

播放/暂停

向下/屏幕亮度

向上/闹钟开关

时钟如何设置

在正常时钟显示模式下:

- 短按【】时钟显示区域,时钟开始闪烁,进入时钟设置状态。
- 短按【】增加数字,短按【】减少数字
- 再次短按【】切换分钟,分钟开始闪烁,进入分钟设置状态,短按【】增加数字,短按【】减少数字。
- 短按【】增加数字,短按【】减少数字。
- 长按【】保存当前设置,并返回到时间显示。

闹钟如何设置

在正常时钟显示模式下:

- 1.短按【】4次,时钟显示区域,闹钟1【】图标和时钟同时闪烁,进入闹钟1时钟设置状态。
- 短按【】增加数字,短按【】减少数字。
- 2.再次短按【】切换分钟,分钟开始闪烁,进入分钟设置状态,短按【】增加数字,短按【】减少数字。
- 3.再次短按【】时钟显示区域,闹钟2【】图标和时钟同时闪烁,进入闹钟2时钟设置状态,闹钟2设置方法同闹钟1。
- 4.长按【】保存当前设置,并返回到时间显示。

打开/关闭 /

• 长按【】打开或关闭闹钟1/闹钟2。

贪睡

- 闹铃响时,短按【】贪睡,贪睡时长为5分钟,可贪睡4次。闹铃进入贪睡状态时,闹铃图标 / 在屏幕显示区域闪烁,贪睡未结束,长按 夜灯开关【】则可取消贪睡状态。

蓝牙音箱的使用方法

短按开关【】,有提示音,蓝牙功能打开,处于准备配对状态,此时打开手机蓝牙功能,在蓝牙设备中,搜索蓝牙音响出现"S09"字样,点击选中"S09"设备名称,自动进入配对,配对连接成功后,会有提示音,再次短按【】关闭蓝牙。

在音箱播放状态时:

1.短按【】→播放/暂停。

2.短按【】→减少音量;长按【】→切换上一曲。

3.短按【】→增加音量;长按【】→切换下一曲。

收音机的使用方法

短按开关【】,收音机功能打开;使用时,首先长按【】自动搜索周围频道,添加电台;再短按开关【】,收音机功能退出。

在收音机播放状态时:

1.短按【】播放/暂停,长按【】自动搜索电台

2.短按【】切换上一个频道;

长按【】减少音量。

3.短按【】切换下一个频道;

长按【】增加音量。

调整屏幕亮度

在正常时钟显示模式下:

- 短按【】调整时钟屏幕亮度,高亮—中亮—低亮—关闭依次循环调整屏幕亮度。

适用设备

本产品支持快速无线充电功能,符合Qi无线充电标准;通过磁感应方式实现短距离无线电能传输, 本设备支持所有符合Qi标准的无线充电设备,使用5V输出的适配器时,无线充电支持5W负载,使用符合QC2.0及以上标准的适配器时,无线充电支持10W负载;设有过充保护 (9V) 及过流保护 (2A)。

注意事项

- 请勿长时间在阳光直射或高温的地方使用、存放该产品。
- 请勿在离磁卡、磁记录媒体和精密的仪器太近的地方充电。
- 请勿用湿手接触交流适配器。
- 请将本产品远离水或其它液体。
- 如果您想清洁本产品, 请断开电源。
- 产品工作环境温度范围:-20—45℃。

无线充规格参数

产品材料:进口ABS+PC+五金  
电源输入:DC9V/2.1A  
充电效率:75%  
内置电池容量:1800mAh  
手机无线充电功率:5W/7.5W/10W/15W  
耳机输出功率:2.5W  
手表输出功率:2.5W  
产品尺寸:189x213x75mm  
电源充电口为国际通用Type-C端口

音箱规格参数

蓝牙版本:5.1  
蓝牙距离:10m  
喇叭功率:405W×2  
喇叭规格:50mm

RoHS

中国制造

WIRELESS CHARGER SPEAKER WITH LAMP  
CLOCK AND WATCH/EARPHONE WIRELESS CHARGER

WIRELESS CHARGER

ALARM CLOCK

NIGHTLIGHT

SPEAKER/BLUETOOTH

WIRELESS PHONE CHARGING

PRODUCT INSTRUCTIONS

Thank you so much for choosing our product, please read the manual carefully before using the product.

FEATURES

- Simple and exquisite.
- Night light.
- Wireless speaker
- Alarm clock.
- Wireless fast charger.
- Charging distance ≤6mm.

CHARACTERISTIC

①

②

③

④

⑤

⑥

⑦

⑧

⑨

① Lamp chimney

② Wireless charging area

③ Mobile phone holder

④ Silicone buttons

⑤ Clock display area

⑥ Night light switch

⑦ Speaker cavity

⑧ Type-C input port

⑨ Silicone foot pads

HOW TO OPERATE

1. Connect the USB port of the USB data cable to the power adapter and the Type-C portThe indicator light【】in the clock display area of the wireless charger flashes.

2. Place the required wireless charging device in the charging indication area of this product, and the clock will display The regional charging indicator【】is always on, and turns off when it is fully charged.

NIGHT LIGHT FUNCTION

- Touch the switch in the first gear to start the light, and the light brightness is 30%.
- Touch switch second gear, light brightness is 70%.
- Touch switch third gear, light brightness is 100%.
- Touch the switch in the fourth position to turn off the lights.
- Turn on the lights in sequence.

BUTTON FUNCTION

Mode

Switch

Bluetooth

Radio

Play/Stop

Down/Screen brightness

Up/Alarm switch

HOW TO SET THE CLOCK

In normal clock display mode:

- Short press【】in the clock display area, the clock starts to flash and enter the clock setting state.
- Short press【】to increase the number, Short press【】to decrease the number.
- Short press【】again to switch the minutes, the minutes start to flash, and enter the minute setting state, Short press【】to increase the number, Short press【】to decrease the number.
- Long press【】to save the current settings and return to the time display.

HOW TO SET THE ALARM

In normal clock display mode:

- 1. Short press【】4 times, in the clock display area, the alarm 1【】icon and the clock flash at the same time, entering the alarm 1 clock setting state. Short press【】to increase the number, short press【】to decrease the number.
- 2. Short press【】again to switch minutes, the minutes will start to flash and enter the minute setting state. Short press【】to increase the number, short press【】to decrease the number.
- 3. Short press【】again in the clock display area, the Alarm 2【】icon and the clock will flash at the same time, entering the Alarm 2 clock setting state. The setting method for Alarm 2 is the same as Alarm 1.
- 4. Long press【】to save the current settings and return to the time display.

Turn on/off the alarm /

Long press【】to turn on or off Alarm 1/Alarm 2

SNOOZE

- When the alarm rings, short press【】to snooze. The snooze duration is 5 minutes. You can snooze 4 times. When the alarm clock enters the snooze state, the alarm icon / is onThe screen display area flashes. The snooze is not over yet, press and hold the night light switch.【】will cancel the snooze state.

HOW TO USE WIRELESS SPEAKERS

Short press the switch【】, there will be a beep, the Bluetooth function is turned on, and it is ready for pairing. At this time, turn on the Bluetooth function of your mobile phone and search for the Bluetooth speaker in the Bluetooth device. The word "S09" appears, click to select the "S09" device name; automatically enter pairing, pairingAfter the connection is successful, there will be a prompt sound. Short press【】again to turn off Bluetooth.

When the speaker is playing:

1. Short press【】to play/pause, long press【】to switch to the previous song.

2. Short press【】to increase the volume, and long press【】to switch to the next song.

3. Short press【】to increase the volume, long press【】to switch to the next song.

HOW TO USE THE RADIO

Short press the switch【】, there will be a prompt sound, and the radio function is turned on; when using it, first long Press【】to automatically search surrounding channels and add stations; Then short press the switch【】, the radio function exits.

When the radio is playing:

1. Short press【】to play/pause, long press【】to automatically search for radio stations.

2. Short press【】to switch to the previous channel; Long press【】to reduce the volume.

3. Short press【】to switch to the next channel; Long press【】to increase the volume.

ADJUST SCREEN BRIGHTNESS

In normal clock display mode:

- Short press【】to adjust the clock screen brightness, High Brightness - Medium Brightness - Low Brightness - Off to adjust the screen brightness in turn.

APPLICABLE DEVICE

This product supports fast wireless charging, which complies with the Qi wireless charging standard; it realizes short-distance wireless power transmission through magnetic induction. This device supports all wireless charging devices that meet the Qi standard. When using a 5V output adapter, Wireless charging supports 5W load. When using an adapter that meets QC2.0 and above standards, the wireless charging supports 10W load; Support overcharge protection (9V) and overcurrent protection (2A).

ATTENTION POINTS

- Do not use or store the product in direct sunlight or high temperature places for a long time.
- Do not charge in places too close to magnetic cards, magnetic recording media, and precision instruments.
- Do not disassemble or modify this product.
- Do not touch the AC adapter with wet hands.
- Keep this product away from water or other liquids.
- If you want to clean the product, please disconnect the power.
- Product working environment temperature range: -20—45℃.

WIRELESS CHARGING SPECIFICATIONS

Material:Imported ABS+PP+Hardware  
Input:DC9V/2.1A  
Charging efficiency:75%  
Battery capacity:1800mAh  
Power:5W/7.5W/10W/15W  
Headphone output power: 2.5W  
Watch output power: 2.5W  
Product size:189x213x75mm  
Charging port:Universal Type-C

SPEAKER SPECIFICATIONS

Bluetooth version:5.1  
Bluetooth distance:10m  
Speaker power:405W×2  
Speaker specifications:50mm

RoHS

Made in China

FCC Warning

15.19 Labeling requirements.

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

15.21 Information to user.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

15.105 Information to the user.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.

-Increase the separation between the equipment and receiver.

-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-Consult the dealer or an experienced radio/TV technician for help.

FCC RF Radiation Exposure Statement:

1.This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

2.This equipment complies with RF radiation exposure limits set forth for an uncontrolled environment.

This equipment should be installed and operated with minimum distance 5mm between the radiator and your body.