Datasheet



TWX-100Bcc3B

WiFi 7/6E Whip Antenna

The Joymax TWX-100Bcc3B antenna is a blade-style, dipole antenna designed for use in 2.4 GHz, 5 GHz, 6 GHz bands supporting WiFi 7, WiFi 6E, and WiFi 6 applications.

The tilt/swivel design allows the antenna to be positioned for optimum performance and reduces the potential for damage from impact compared to a fixed whip design. The antenna is available with an RP-SMA Plug (female socket) or SMA plug (male pin) connector.



Features

- Broad bandwidth 2.4 GHz to 7.125 GHz
 - Performance at 2400 MHz to 2500 MHz VSWR: ≤ 1.6 Peak Gain: 2.6 dBi Efficiency: 71%
- Performance at 5150 MHz to 7125 MHz VSWR: ≤ 3.0 Peak Gain: 4.4 dBi Efficiency: 58%
- Hinged design with detents for straight, 45 degree and 90 degree positioning
- RP-SMA plug (female socket) or SMA plug (male pin) connector

Applications

- WiFi/WLAN applications:
 WiFi 7 (802.11be)
 WiFi 6E (802.11ax)
 WiFi 6 (802.11ax)
 WiFi 5 (802.11ac)
 - WiFi 4 (802.11n)
- 2.4 GHz ISM applications: Bluetooth[®] ZigBee[®] Thread[®] IEEE 802.15.4 IEEE 802.11b/g
- Internet of Things (IoT) devices
- Networking routers / gateways

Ordering Information

Part Number	Description
TWX-100BRS3B	WiFi 6E WiFi 7 Tilt/Swivel Whip Antenna with RP-SMA plug (female) connector
TWX-100BSA3B	WiFi 6E WiFi 7 Tilt/Swivel Whip Antenna with SMA plug (male) connector

Available from Joymax Electronics and select distributors and representatives.

Table 1: Electrical Specifications

TWX-100Bcc3B	WiFi / WLAN Band (MHz)		
Frequency Range	2400~2500	5150~5850	5925~7125
VSWR (Max)	1.6	1.5	3.0
Peak Gain (dBi)	2.6	4.3	4.4
Average Gain (dBi)	-1.5	-2.5	-2.5
Efficiency (%)	71	57	58
Polarization	Linear		
Radiation	Omni directional		
Max Power	1 W		
Wavelength	½-λ		
Electrical Type	Dipole		
Impedance	50 Ω		

Electrical specifications and plots measured with antenna in a straight orientation without ground plane.

Table 2: Mechanical Specifications

Parameter	Value
Connection	RP-SMA Plug (female socket) or SMA Plug (male pin)
Operating Temp.	-30°C to +70°C
Weight	15 g
Dimension	124 mm (Straight) x Ø13 mm
Antenna Color	Black
Ingress Protection	N/A

Packaging Information

The TWX-100Bcc3B antennas are individually sealed in a clear plastic bag. **Figure 1**. 500 pcs per carton, 320 mm x 250 mm x 230 mm (12.6 in x 9.8 in x 9.1 in), total weight 8.5 kgs (18.74 lb) Distribution channels may offer alternative packaging options.







1pcs antenna / 1 PE bag

50pcs antenna / 1 Bigger PE bag

500pcs antenna / 1 Carton

EnJOY MAX Wireless®

Figure 1. Antenna Packaging

Product Dimensions

Figure 2 provides dimensions of the TWX-100Bcc3B. The antenna blade can be tilted 90 degrees, and has a detent at 45 degrees enabling the antenna to be oriented in any direction. The rotating base allows for continuous positioning through 360 degrees even while installed.





Antenna Orientation

The TWX-100Bcc3B antenna is characterized in two antenna orientations as shown in **Figure 3**. The antenna straight orientation characterizes use of an antenna attached to an enclosure-mounted connector which is connected by cable to the VNA. Although the antenna is a dipole not requiring a ground plane for function, characterization with an adjacent ground plane (120 mm x 120 mm) provides insight into antenna performance when attached directly to a printed circuit board mounted connector. The two orientations represent the most common end-product use cases.





Straight, without ground plane

On edge of ground plane, bent 90 degrees

Figure 3. Antenna Test Orientation



STRAIGHT, NO GROUND PLANE

The charts on the following pages represent data taken with the antenna oriented straight, as shown in **Figure 4**.



Figure 4. Straight orientation, without ground plane

VSWR

Figure 5 provides the voltage standing wave ratio (VSWR) across the antenna bandwidth. VSWR is a function of the reflection coefficient, which describes the power reflected from the antenna back to the radio. A lower VSWR value indicates better antenna performance at a given frequency. Reflected power is also shown on the right-side vertical axis as a gauge of the percentage of transmitter power reflected back from the antenna.



Figure 5. Antenna VSWR, Straight without ground plane



Return Loss

Return loss (**Figure 6**), represents the loss in power at the antenna due to reflected signals. Like VSWR, a lower return loss value indicates better antenna performance at a given frequency.



Figure 6. Antenna Return Loss, Straight without ground plane

Peak Gain

The peak gain across the antenna bandwidth is shown in **Figure 7**. Peak gain represents the maximum antenna input power concentration across 3-dimensional space, and therefore peak performance at a given frequency, but does not consider any directionality in the gain pattern.



Figure 7. Antenna Peak Gain, Straight without ground plane



Average Gain

Average gain (**Figure 8**), is the average of all antenna gain in 3-dimensional space at each frequency, providing an indication of overall performance without expressing antenna directionality.



Figure 8. Antenna Average Gain, Straight without ground plane

Radiation Efficiency

Radiation efficiency (**Figure 9**), shows the ratio of power radiated by the antenna relative to the power supplied to the antenna, expressed as a percentage, where a higher percentage indicates better performance at a given frequency. An ideal antenna has 100% efficiency. But in really world, usually an external antenna radiates only 50~60% of power supplied to it.



Figure 9. Antenna Efficiency, Straight without ground plane



Radiation Patterns

Radiation patterns provide information about the directionality and 3-dimensional gain performance of the antenna by plotting gain at specific frequencies in three orthogonal planes. Antenna radiation patterns for a straight orientation are shown in **Figure 10** using polar plots covering 360 degrees. The antenna graphic at the top of the page provides reference to the plane of the column of plots below it.



Figure 10. Antenna Radiation Patterns, Straight without ground plane



5150 MHz to 5850 MHz (5550 MHz)









XY-Plane Gain

5925 MHz to 7125 MHz (6525 MHz)







YZ-Plane Gain





XZ-Plane Gain

YZ-Plane Gain

XY-Plane Gain

Figure 10-1. Antenna Radiation Patterns, Straight without ground plane

