



FCC RF Test Report

APPLICANT : Espressif Systems (Shanghai) Co.,Ltd.
EQUIPMENT : 2.4GHz Wi-Fi & BT IoT Module
BRAND NAME : ESPRESSIF
MODEL NAME : ESP32-C6-WROOM-1
FCC ID : 2AC7Z-ESPC6WROOM1
STANDARD : FCC Part 15 Subpart C §15.247
CLASSIFICATION : (DTS) Digital Transmission System
TEST DATE(S) : May 04, 2023 ~ Aug. 01, 2023

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.

Jason Jia

Approved by: Jason Jia



Sporton International Inc. (Kunshan)

**No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China**



TABLE OF CONTENTS

REVISION HISTORY.....	3
SUMMARY OF TEST RESULT	4
1 GENERAL DESCRIPTION	5
1.1 Applicant	5
1.2 Manufacturer	5
1.3 Product Feature of Equipment Under Test.....	5
1.4 Product Specification of Equipment Under Test.....	6
1.5 Modification of EUT	6
1.6 Testing Location	6
1.7 Test Software.....	7
1.8 Applicable Standards.....	7
2 TEST CONFIGURATION OF EQUIPMENT UNDER TEST	8
2.1 Carrier Frequency and Channel	8
2.2 Test Mode.....	8
2.3 Connection Diagram of Test System.....	9
2.4 Support Unit used in test configuration and system	10
2.5 EUT Operation Test Setup	10
2.6 Measurement Results Explanation Example.....	11
3 TEST RESULT	12
3.1 6dB and 99% Bandwidth Measurement	12
3.2 Output Power Measurement.....	14
3.3 Power Spectral Density Measurement	15
3.4 Conducted Band Edges and Spurious Emission Measurement	17
3.5 Radiated Band Edges and Spurious Emission Measurement	34
3.6 AC Conducted Emission Measurement.....	38
3.7 Antenna Requirements.....	40
4 LIST OF MEASURING EQUIPMENT	41
5 MEASUREMENT UNCERTAINTY	42
APPENDIX A. CONDUCTED TEST RESULTS	
APPENDIX B. AC CONDUCTED EMISSION TEST RESULT	
APPENDIX C. RADIATED SPURIOUS EMISSION	
APPENDIX D. DUTY CYCLE PLOTS	
APPENDIX E. SETUP PHOTOGRAPHS	



REVISION HISTORY

REPORT NO.	VERSION	DESCRIPTION	ISSUED DATE
FR330805B	Rev. 01	Initial issue of report	Sep. 01, 2023



SUMMARY OF TEST RESULT

Report Section	FCC Rule	Description	Limit	Result	Remark
3.1	15.247(a)(2)	6dB Bandwidth	$\geq 0.5\text{MHz}$	Pass	-
3.1	-	99% Bandwidth	-	Report Only	-
3.2	15.247(b)	Power Output Measurement	$\leq 30\text{dBm}$	Pass	-
3.3	15.247(e)	Power Spectral Density	$\leq 8\text{dBm}/3\text{kHz}$	Pass	-
3.4	15.247(d)	Conducted Band Edges	$\leq 20\text{dBc}$	Pass	-
		Conducted Spurious Emission		Pass	-
3.5	15.247(d)	Radiated Band Edges and Radiated Spurious Emission	15.209(a) & 15.247(d)	Pass	Under limit 1.04 dB at 2483.50 MHz
3.6	15.207	AC Conducted Emission	15.207(a)	Pass	Under limit 8.97 dB at 0.518 MHz
3.7	15.203 & 15.247(b)	Antenna Requirement	15.203 & 15.247(b)	Pass	-

Conformity Assessment Condition:

1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacture who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
2. The measurement uncertainty please refer to each test result in the section "Measurement Uncertainty"

Disclaimer:

The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.



1 General Description

1.1 Applicant

Espressif Systems (Shanghai) Co.,Ltd.

Suite 204, Block 2, 690 Bibo Road, Zhang Jiang Hi-Tech Park, Shanghai, China

1.2 Manufacturer

Espressif Systems (Shanghai) Co.,Ltd.

Suite 204, Block 2, 690 Bibo Road, Zhang Jiang Hi-Tech Park, Shanghai, China

1.3 Product Feature of Equipment Under Test

Product Feature	
Equipment	2.4GHz Wi-Fi & BT IoT Module
Brand Name	ESPRESSIF
Model Name	ESP32-C6-WROOM-1
FCC ID	2AC7Z-ESPC6WROOM1
SN	Conducted: 404CCA428314 Conduction: 404CCA42671C Radiation: 404CCA426768
HW Version	V1.2
SW Version	v1.1.3.4
EUT Stage	Identical Prototype

Remark: The above EUT's information was declared by manufacturer. Please refer to the specifications or user's manual for more detailed description.

1.4 Product Specification of Equipment Under Test

Standards-related Product Specification	
Tx/Rx Channel Frequency Range	2412 MHz ~ 2462 MHz
Maximum (Peak) Output Power to antenna	802.11b : 24.19 dBm (0.2624 W) 802.11g : 26.95 dBm (0.4955 W) 802.11n HT20 : 26.79 dBm (0.4775 W) 802.11n HT40 : 26.50 dBm (0.4467 W) 802.11ax HE20 : 26.81 dBm (0.4797 W)
99% Occupied Bandwidth	802.11b : 12.84MHz 802.11g : 16.98MHz 802.11n HT40 : 31.97MHz 802.11ax HE20 : 18.43MHz
Antenna Type / Gain	PCB Antenna type with gain 3.26 dBi
Type of Modulation	802.11b : DSSS (DBPSK / DQPSK / CCK) 802.11g/n : OFDM (BPSK / QPSK / 16QAM / 64QAM) 802.11ax : OFDM (BPSK / QPSK / 16QAM / 64QAM / 256QAM / 1024QAM)

Remark:

- For 802.11n HT20/ax HE20 mode, the whole testing has assessed only 802.11ax HE20 mode by referring to the higher output power.
- The device does not support partial RU tone for 802.11ax mode.

1.5 Modification of EUT

No modifications are made to the EUT during all test items.

1.6 Testing Location

Sporton International Inc. (Kunshan) is accredited to ISO/IEC 17025:2017 by American Association for Laboratory Accreditation with Certificate Number 5145.02.

Test Firm	Sporton International Inc. (Kunshan)		
Test Site Location	No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300 People's Republic of China TEL : +86-512-57900158		
Test Site No.	Sporton Site No.	FCC Designation No.	FCC Test Firm Registration No.
	CO01-KS 03CH05-KS TH01-KS	CN1257	314309



1.7 Test Software

Item	Site	Manufacturer	Name	Version
1.	TH01-KS	SPORTON	FCC 15C-15E Test Tools Ver10.0_210607	10.0
2.	03CH05-KS	AUDIX	E3	210616
3.	CO01-KS	AUDIX	E3	6.2009-8-24

1.8 Applicable Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ 47 CFR Part 15 Subpart C §15.247
- ♦ FCC KDB 558074 D01 15.247 Meas Guidance v05r02
- ♦ ANSI C63.10-2013

Remark: All test items were verified and recorded according to the standards and without any deviation during the test.

2 Test Configuration of Equipment Under Test

- a. The EUT has been associated with peripherals and configuration operated in a manner tended to maximize its emission characteristics in a typical application. Frequency range investigated: conduction emission (150 kHz to 30 MHz), radiation emission (9 kHz to the 10th harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower). For radiated measurement, pre-scanned in three orthogonal panels, X, Y, Z. The worst cases (X plane) were recorded in this report.
- b. AC power line Conducted Emission was tested under maximum output power.

2.1 Carrier Frequency and Channel

Frequency Band	Channel	Freq. (MHz)	Channel	Freq. (MHz)
2400-2483.5 MHz	1	2412	7	2442
	2	2417	8	2447
	3	2422	9	2452
	4	2427	10	2457
	5	2432	11	2462
	6	2437		

2.2 Test Mode


Final test modes are considering the modulation and worse data rates as below table.

Modulation	Data Rate
802.11b	1 Mbps
802.11g	6 Mbps
802.11ax HE20	MCS0
802.11n HT40	MCS0


Test Cases	
AC Conducted Emission	Mode 1 :Bluetooth LE TX + WLAN Link(2.4G) + Charging from Test Jig
	Mode 2 :Thread TX + WLAN Link(2.4G) + Charging from Test Jig
	Mode 3 :Zigbee TX + WLAN Link(2.4G) + Charging from Test Jig
Remark: The worst case of conducted emission is mode 3; only the test data of it was reported.	

2.3 Connection Diagram of Test System

Conducted Emission:



Radiated Emission:



2.4 Support Unit used in test configuration and system

Item	Equipment	Trade Name	Model Name	FCC ID	Data Cable	Power Cord
1.	Notebook	Lenovo	G480	QDS-BRCM1050I	N/A	AC I/P: Unshielded, 1.8 m DC O/P: Shielded, 1.8 m
2.	WLAN AP	D-link	DIR-655	KA21R655B1	N/A	Unshielded, 1.8m
3.	Hard Disk	WD	C6B	N/A	N/A	N/A
4.	Mobile Phone	Motorola	N/A	N/A	N/A	N/A
5.	Test Jig	N/A	N/A	N/A	N/A	N/A

2.5 EUT Operation Test Setup

For WLAN RF test items, an engineering test program was provided and enabled to make EUT continuous transmit.

For AC power line conducted emissions, the EUT was set to connect with the WLAN AP under large package sizes transmission.



2.6 Measurement Results Explanation Example

For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

Example:

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

Offset = RF cable loss + attenuator factor.

Following shows an offset computation example with cable loss 5.3 dB and 10dB attenuator.

$$\begin{aligned}\text{Offset(dB)} &= \text{RF cable loss(dB)} + \text{attenuator factor(dB)} \\ &= 5.3 + 10 = 15.3 \text{ (dB)}\end{aligned}$$

3 Test Result

3.1 6dB and 99% Bandwidth Measurement

3.1.1 Limit of 6dB and 99% Bandwidth

The minimum 6 dB bandwidth shall be at least 500 kHz.


3.1.2 Measuring Instruments

The measuring equipment is listed in the section 4 of this test report.

3.1.3 Test Procedures


1. The testing follows ANSI C63.10-2013 clause 11.8
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 100 kHz. Set the Video bandwidth (VBW) = 300 kHz. In order to make an accurate measurement. The 6 dB bandwidth must be greater than 500 kHz.
5. For 99% Bandwidth Measurement, the spectrum analyzer's resolution bandwidth (RBW) = 1%~5% of OBW and set the Video bandwidth (VBW) = 3MHz.
6. Measure and record the results in the test report.

3.1.4 Test Setup



3.1.5 Test Result of 6dB and 99% Occupied Bandwidth

Please refer to Appendix A.



Note : The occupied channel bandwidth is maintained within the band of operation for all of the modulations.

3.2 Output Power Measurement

3.2.1 Limit of Output Power

For systems using digital modulation in the 2400-2483.5MHz, the limit for peak output power is 30dBm. If transmitting antenna with directional gain greater than 6dBi is used, the peak output power from the intentional radiator shall be reduced below the above stated value by the amount in dB that the directional gain of the antenna exceeds 6 dBi. In case of point-to-point operation, the limit has to be reduced by 1dB for every 3dB that the directional gain of the antenna exceeds 6dBi.

3.2.2 Measuring Instruments

The measuring equipment is listed in the section 4 of this test report.

3.2.3 Test Procedures

1. The testing follows the Measurement Procedure of ANSI C63.10-2013 clause 11.9.1.3 PKPM1 Peak power meter or ANSI C63.10-2013 clause 11.9.2.3.1 Method AVGPM method.
2. The RF output of EUT was connected to the power meter by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Measure the conducted output power and record the results in the test report.

3.2.4 Test Setup



3.2.5 Test Result of Peak Output Power

Please refer to Appendix A.

3.2.6 Test Result of Average Output Power (Reporting Only)

Please refer to Appendix A.

3.3 Power Spectral Density Measurement

3.3.1 Limit of Power Spectral Density

The peak power spectral density shall not be greater than 8dBm in any 3kHz band at any time interval of continuous transmission.

3.3.2 Measuring Instruments

The measuring equipment is listed in the section 4 of this test report.

3.3.3 Test Procedures


1. The testing follows Measurement Procedure of ANSI C63.10-2013 clause 11.10.2 Method PKPSD.
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 3 kHz. Video bandwidth VBW = 10 kHz In order to make an accurate measurement, set the span to 1.5 times DTS Channel Bandwidth. (6dB BW)
5. Detector = peak, Sweep time = auto couple, Trace mode = max hold, Allow trace to fully stabilize. Use the peak marker function to determine the maximum power level.
6. Measure and record the results in the test report.

3.3.4 Test Setup



3.3.5 Test Result of Power Spectral Density

Please refer to Appendix A.



3.4 Conducted Band Edges and Spurious Emission Measurement

3.4.1 Limit of Conducted Band Edges and Spurious Emission Measurement

In any 100 kHz bandwidth outside of the authorized frequency band, the emissions which fall in the non-restricted bands shall be attenuated at least 20 dB / 30dB relative to the maximum PSD level in 100 kHz by RF conducted measurement.


3.4.2 Measuring Instruments

The measuring equipment is listed in the section 4 of this test report.

3.4.3 Test Procedures

1. The testing follows ANSI C63.10-2013 clause 11.11
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator. The path loss was compensated to the results for each measurement.
3. Set to the maximum power setting and enable the EUT transmit continuously.
4. Set RBW = 100 kHz, VBW=300 kHz, Peak Detector. Unwanted Emissions measured in any 100 kHz bandwidth outside of the authorized frequency band shall be attenuated by at least 20 dB relative to the maximum in-band peak PSD level in 100 kHz when maximum peak conducted output power procedure is used. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, the attenuation required under this paragraph shall be 30 dB instead of 20 dB per 15.247(d).
5. Measure and record the results in the test report.
6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.

3.4.4 Test Setup






3.4.5 Test Result of Conducted Band Edges and Spurious Emission

Test Engineer :	Jacob Zhang	Temperature :	21~25°C
		Relative Humidity :	51~54%


Test Mode :	802.11b	Test Channel :	01
-------------	---------	----------------	----






Test Mode :	802.11b	Test Channel :	06
-------------	---------	----------------	----


100kHz PSD reference Level



Spurious Emission 30MHz~3GHz




Spurious Emission 2GHz~25GHz






Test Mode :	802.11b	Test Channel :	11
-------------	---------	----------------	----






Test Mode :	802.11g	Test Channel :	01
-------------	---------	----------------	----


100kHz PSD reference Level




Channel Plot




Spurious Emission 30MHz~3GHz



Spurious Emission 2GHz~25GHz









Test Mode :	802.11g	Test Channel :	06
-------------	---------	----------------	----


100kHz PSD reference Level



Spurious Emission 30MHz~3GHz




Spurious Emission 2GHz~25GHz






Test Mode :	802.11g	Test Channel :	10
-------------	---------	----------------	----






Test Mode :	802.11g	Test Channel :	11
-------------	---------	----------------	----






Test Mode :	802.11ax HE20	Test Channel :	01
-------------	---------------	----------------	----






Test Mode :	802.11ax HE20	Test Channel :	02
-------------	---------------	----------------	----






Test Mode :	802.11ax HE20	Test Channel :	06
-------------	---------------	----------------	----


100kHz PSD reference Level



Spurious Emission 30MHz~3GHz




Spurious Emission 2GHz~25GHz






Test Mode :	802.11ax HE20	Test Channel :	10
-------------	---------------	----------------	----






Test Mode :	802.11ax HE20	Test Channel :	11
-------------	---------------	----------------	----






Test Mode :	802.11n HT40	Test Channel :	03
-------------	--------------	----------------	----






Test Mode :	802.11n HT40	Test Channel :	06
-------------	--------------	----------------	----


100kHz PSD reference Level



Spurious Emission 30MHz~3GHz



Spurious Emission 2GHz~25GHz







Test Mode : 802.11n HT40

Test Channel : 09


100kHz PSD reference Level




Channel Plot



Spurious Emission 30MHz~3GHz



Spurious Emission 2GHz~25GHz



3.5 Radiated Band Edges and Spurious Emission Measurement

3.5.1 Limit of Radiated band edge and Spurious Emission Measurement

In any 100 kHz bandwidth outside the intentional radiator frequency band, all harmonics/spurious must be at least 20 dB below the highest emission level within the authorized band. If the output power of this device was measured by spectrum analyzer, the attenuation under this paragraph shall be 30 dB instead of 20 dB. In addition, radiated emissions which fall in the restricted bands must also comply with the limits as below.

Frequency (MHz)	Field Strength (microvolts/meter)	Measurement Distance (meters)
0.009 – 0.490	2400/F(kHz)	300
0.490 – 1.705	24000/F(kHz)	30
1.705 – 30.0	30	30
30 – 88	100	3
88 – 216	150	3
216 - 960	200	3
Above 960	500	3

3.5.2 Measuring Instruments

The measuring equipment is listed in the section 4 of this test report.

3.5.3 Test Procedures


1. The testing follows ANSI C63.10-2013 clause 11.11 & 11.12
2. The EUT was arranged to its worst case and then tune the antenna tower (from 1 m to 4 m) and turntable (from 0 degree to 360 degrees) to find the maximum reading. A pre-amp and a high pass filter are used for the test in order to get better signal level.
3. The EUT was placed on a turntable with 0.8 meter for frequency below 1GHz and 1.5 meter for frequency above 1GHz respectively above ground.
4. The EUT was set 3 meters from the interference receiving antenna, which was mounted on the top of a variable height antenna tower.
5. Corrected Reading: Antenna Factor + Cable Loss + Read Level - Preamp Factor = Level
6. For testing below 1GHz, if the emission level of the EUT in peak mode was 3 dB lower than the limit specified, then peak values of EUT will be reported, otherwise, the emissions will be repeated one by one using the CISPR quasi-peak method and reported.
7. For testing above 1GHz, the emission level of the EUT in peak mode was 20dB lower than peak limit (that means the emission level in average mode also complies with the limit in average mode), then peak values of EUT will be reported, otherwise, the emissions will be measured in average mode again and reported.
8. Use the following spectrum analyzer settings:
 - (1) Span shall wide enough to fully capture the emission being measured;
 - (2) Set RBW=100 kHz for $f < 1$ GHz; VBW $\geq$ RBW; Sweep = auto; Detector function = peak; Trace = max hold;
 - (3) Set RBW = 1 MHz, VBW= 3MHz for $f \geq 1$ GHz for peak measurement.

For average measurement:


 - VBW = 10 Hz, when duty cycle is no less than 98 percent.
 - VBW $\geq 1/T$, when duty cycle is less than 98 percent where T is the minimum transmission duration over which the transmitter is on and is transmitting at its maximum power control level for the tested mode of operation.

3.5.4 Test Setup


For radiated emissions below 30MHz



For radiated emissions from 30MHz to 1GHz



For radiated emissions above 1GHz





3.5.5 Test Results of Radiated Spurious Emissions (9kHz ~ 30MHz)

The low frequency, which started from 9 kHz to 30MHz, was pre-scanned and the result which was 20dB lower than the limit line was not reported.

There is a comparison data of both open-field test site and semi-Anechoic chamber, and the result came out very similar.

3.5.6 Test Result of Radiated Spurious at Band Edges

Please refer to Appendix C.

3.5.7 Duty Cycle

Please refer to Appendix D.

3.5.8 Test Result of Radiated Spurious Emission (30MHz ~ 10th Harmonic or 40GHz, whichever is lower)

Please refer to Appendix C.

3.6 AC Conducted Emission Measurement

3.6.1 Limit of AC Conducted Emission

For equipment that is designed to be connected to the public utility (AC) power line, the radio frequency voltage that is conducted back onto the AC power line on any frequency or frequencies within the band 150 kHz to 30 MHz shall not exceed the limits in the following table.

Frequency of Emission (MHz)	Conducted Limit (dBμV)	
	Quasi-Peak	Average
0.15-0.5	66 to 56*	56 to 46*
0.5-5	56	46
5-30	60	50

*Decreases with the logarithm of the frequency.


3.6.2 Measuring Instruments

The measuring equipment is listed in the section 4 of this test report.

3.6.3 Test Procedures

1. The EUT was placed 0.4 meter from the conducting wall of the shielding room, and it was kept at least 80 centimeters from any other grounded conducting surface.
2. Connect EUT to the power mains through a line impedance stabilization network (LISN).
3. All the support units are connecting to the other LISN.
4. The LISN provides 50 ohm coupling impedance for the measuring instrument.
5. The FCC states that a 50 ohm, 50 microhenry LISN should be used.
6. Both sides of AC line were checked for maximum conducted interference.
7. The frequency range from 150 kHz to 30 MHz was searched.
8. Set the test-receiver system to Peak Detect Function and specified bandwidth (IF bandwidth = 9kHz) with Maximum Hold Mode.

3.6.4 Test Setup



3.6.5 Test Result of AC Conducted Emission

Please refer to Appendix B.



3.7 Antenna Requirements

3.7.1 Standard Applicable

If directional gain of transmitting Antennas is greater than 6dBi, the power shall be reduced by the same level in dB comparing to gain minus 6dBi. The use of a permanently attached Antenna or of an Antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the rule.

3.7.2 Antenna Anti-Replacement Construction

Non-standard antenna connector is used.

3.7.3 Antenna Gain

The antenna peak gain of EUT is less than 6 dBi. Therefore, it is not necessary to reduce maximum peak output power limit.



4 List of Measuring Equipment

Instrument	Manufacturer	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Spectrum Analyzer	R&S	FSV40	101040	10Hz~40GHz	Oct. 12, 2022	May 04, 2023~Jul. 31, 2023	Oct. 11, 2023	Conducted (TH01-KS)
Pulse Power Sensor	Anritsu	MA2411B	0917070	300MHz~40GHz	Jan. 05, 2023	May 04, 2023~Jul. 31, 2023	Jan. 04, 2024	Conducted (TH01-KS)
Power Meter	Anritsu	ML2495A	1005002	50MHz Bandwidth	Jan. 05, 2023	May 04, 2023~Jul. 31, 2023	Jan. 04, 2024	Conducted (TH01-KS)
EMI Test Receiver	Keysight	N9038A	MY56400004	3Hz~8.5GHz; Max 30dBm	Oct. 13, 2022	Aug. 01, 2023	Oct. 12, 2023	Radiation (03CH05-KS)
EXA Spectrum Analyzer	Keysight	N9010A	MY55150244	10Hz~44GHz, MAX 30dB	Mar. 24, 2023	Aug. 01, 2023	Mar. 23, 2024	Radiation (03CH05-KS)
Loop Antenna	R&S	HFH2-Z2	100321	9kHz~30MHz	Oct. 16, 2022	Aug. 01, 2023	Oct. 15, 2023	Radiation (03CH05-KS)
Bilog Antenna	TeseQ	CBL6111D	49922	30MHz~1GHz	Apr. 09, 2023	Aug. 01, 2023	Apr. 08, 2024	Radiation (03CH05-KS)
Double Ridge Horn Antenna	ETS-Lindgren	3117	00218642	1GHz~18GHz	Apr. 06, 2023	Aug. 01, 2023	Apr. 05, 2024	Radiation (03CH05-KS)
SHF-EHF Horn	Com-power	AH-840	101093	18GHz~40GHz	Jan. 08, 2023	Aug. 01, 2023	Jan. 07, 2024	Radiation (03CH05-KS)
Amplifier	SONOMA	310N	380826	9kHz~1GHz	Jul. 06, 2023	Aug. 01, 2023	Jul. 05, 2024	Radiation (03CH05-KS)
Amplifier	EM	EM18G40GA	060852	18~40GHz	Jan. 05, 2023	Aug. 01, 2023	Jan. 04, 2024	Radiation (03CH05-KS)
high gain Amplifier	EM	EM01G18GA	060839	1GHz~18GHz	Oct. 12, 2022	Aug. 01, 2023	Oct. 11, 2023	Radiation (03CH05-KS)
Amplifier	EM	EM01G18GA	060833	1GHz~18GHz	Jan. 05, 2023	Aug. 01, 2023	Jan. 04, 2024	Radiation (03CH05-KS)
AC Power Source	Chroma	61601	F104090004	N/A	NCR	Aug. 01, 2023	NCR	Radiation (03CH05-KS)
Turn Table	ChamPro	EM 1000-T	060762-T	0~360 degree	NCR	Aug. 01, 2023	NCR	Radiation (03CH05-KS)
Antenna Mast	ChamPro	EM 1000-A	060762-A	1 m~4 m	NCR	Aug. 01, 2023	NCR	Radiation (03CH05-KS)
EMI Receiver	R&S	ESCI7	100768	9kHz~7GHz;	May 16, 2023	Jul. 10, 2023	May 15, 2024	Conduction (CO01-KS)
AC LISN (for auxiliary equipment)	MessTec	AN3016	060103	9kHz~30MHz	Oct. 13, 2022	Jul. 10, 2023	Oct. 12, 2023	Conduction (CO01-KS)
AC LISN	MessTec	AN3016	060105	9kHz~30MHz	May 16, 2023	Jul. 10, 2023	May 15, 2024	Conduction (CO01-KS)
AC Power Source	Chroma	61602	ABP000000811	AC 0V~300V, 45Hz~1000Hz	Oct. 12, 2022	Jul. 10, 2023	Oct. 11, 2023	Conduction (CO01-KS)

NCR: No Calibration Required

5 Measurement Uncertainty

The measurement uncertainties shown below were calculated in accordance with the requirements of ANSI 63.10-2013. All the measurement uncertainty value were shown with a coverage K=2 to indicate 95% level of confidence. The measurement data show herein meets or exceeds the CISPR measurement uncertainty values specified in CISPR 16-4-2 and can be compared directly to specified limit to determine compliance.

Uncertainty of Conducted Measurement

Test Item	Uncertainty
Conducted Power	± 0.46 dB
Conducted Emissions	± 2.26 dB
Occupied Channel Bandwidth	± 0.1 %
Conducted Power Spectral Density	± 0.88 dB

Uncertainty of Conducted Emission Measurement (150 kHz ~ 30 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	2.94 dB
---	---------

Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	6.28 dB
---	---------

Uncertainty of Radiated Emission Measurement (1000 MHz ~ 18000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	4.88 dB
---	---------

Uncertainty of Radiated Emission Measurement (18000 MHz ~ 40000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	5.26 dB
---	---------

----- THE END -----



Appendix A. Conducted Test Results

Report Number : FR330805B

Test Engineer:	Jacob Zhang	Temperature:	21~25	°C
Test Date:	2023/5/4~2023/7/31	Relative Humidity:	51~54	%

TEST RESULTS DATA
6dB and 99% Occupied Bandwidth

2.4GHz Band Single Antenna								
Mod.	Data Rate	N _{TX}	CH.	Freq. (MHz)	99% Occupied BW (MHz)	6dB BW (MHz)	6dB BW Limit (MHz)	Pass/Fail
11b	1Mbps	1	1	2412	12.84	8.70	0.50	Pass
11b	1Mbps	1	6	2437	12.79	8.56	0.50	Pass
11b	1Mbps	1	11	2462	12.79	8.72	0.50	Pass
11g	6Mbps	1	1	2412	16.63	16.06	0.50	Pass
11g	6Mbps	1	2	2417	16.98	16.06	0.50	Pass
11g	6Mbps	1	6	2437	16.68	15.84	0.50	Pass
11g	6Mbps	1	10	2457	16.93	16.04	0.50	Pass
11g	6Mbps	1	11	2462	16.58	16.28	0.50	Pass
HT40	MCS0	1	3	2422	31.97	27.80	0.50	Pass
HT40	MCS0	1	6	2437	31.87	27.64	0.50	Pass
HT40	MCS0	1	9	2452	31.87	25.68	0.50	Pass

TEST RESULTS DATA
6dB and 99% Occupied Bandwidth

2.4GHz Band Single Antenna									
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	RU Config.	99% Occupied BW (MHz)	6dB BW (MHz)	6dB BW Limit (MHz)	Pass/Fail
HE20	MCS0	1	1	2412	Full	17.43	16.53	0.50	Pass
HE20	MCS0	1	2	2417	Full	18.38	17.18	0.50	Pass
HE20	MCS0	1	6	2437	Full	17.38	16.88	0.50	Pass
HE20	MCS0	1	10	2457	Full	18.43	17.18	0.50	Pass
HE20	MCS0	1	11	2462	Full	17.38	16.55	0.50	Pass

TEST RESULTS DATA
Peak Output Power

2.4GHz Band Single Antenna										
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	Peak Conducted Power (dBm)	Conducted Power Limit (dBm)	DG (dBi)	EIRP Power (dBm)	EIRP Power Limit (dBm)	Pass /Fail
11b	1Mbps	1	1	2412	23.77	30.00	3.26	27.03	36.00	Pass
11b	1Mbps	1	6	2437	24.19	30.00	3.26	27.45	36.00	Pass
11b	1Mbps	1	11	2462	22.64	30.00	3.26	25.90	36.00	Pass
11g	6Mbps	1	1	2412	25.27	30.00	3.26	28.53	36.00	Pass
11g	6Mbps	1	2	2417	26.47	30.00	3.26	29.73	36.00	Pass
11g	6Mbps	1	6	2437	26.95	30.00	3.26	30.21	36.00	Pass
11g	6Mbps	1	10	2457	26.36	30.00	3.26	29.62	36.00	Pass
11g	6Mbps	1	11	2462	24.43	30.00	3.26	27.69	36.00	Pass
HT20	MCS0	1	1	2412	24.51	30.00	3.26	27.77	36.00	Pass
HT20	MCS0	1	2	2417	26.32	30.00	3.26	29.58	36.00	Pass
HT20	MCS0	1	6	2437	26.79	30.00	3.26	30.05	36.00	Pass
HT20	MCS0	1	10	2457	26.36	30.00	3.26	29.62	36.00	Pass
HT20	MCS0	1	11	2462	24.16	30.00	3.26	27.42	36.00	Pass
HT40	MCS0	1	3	2422	25.38	30.00	3.26	28.64	36.00	Pass
HT40	MCS0	1	6	2437	26.50	30.00	3.26	29.76	36.00	Pass
HT40	MCS0	1	9	2452	24.47	30.00	3.26	27.73	36.00	Pass

TEST RESULTS DATA
Peak Output Power

2.4GHz Band Single Antenna											
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	RU Config.	Peak Conducted Power (dBm)	Conducted Power Limit (dBm)	DG (dBi)	EIRP Power (dBm)	EIRP Power Limit (dBm)	Pass /Fail
HE20	MCS0	1	1	2412	Full	24.78	30.00	3.26	28.04	36.00	Pass
HE20	MCS0	1	2	2417	Full	26.44	30.00	3.26	29.70	36.00	Pass
HE20	MCS0	1	6	2437	Full	26.81	30.00	3.26	30.07	36.00	Pass
HE20	MCS0	1	10	2457	Full	26.50	30.00	3.26	29.76	36.00	Pass
HE20	MCS0	1	11	2462	Full	24.55	30.00	3.26	27.81	36.00	Pass

TEST RESULTS DATA
Average Output Power

2.4GHz Band Single Antenna												Setting
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	Duty Factor (dB)	Average Conducted Power with duty factor	Conducted Power Limit (dBm)	DG (dBi)	EIRP Power (dBm)	EIRP Power Limit (dBm)	Pass /Fail	
11b	1Mbps	1	1	2412	0.00	20.73	30.00	3.26	23.99	36.00	Pass	0.00
11b	1Mbps	1	6	2437	0.00	21.19	30.00	3.26	24.45	36.00	Pass	0.00
11b	1Mbps	1	11	2462	0.00	19.65	30.00	3.26	22.91	36.00	Pass	2.00
11g	6Mbps	1	1	2412	0.00	15.54	30.00	3.26	18.80	36.00	Pass	10.00
11g	6Mbps	1	2	2417	0.00	18.74	30.00	3.26	22.00	36.00	Pass	2.00
11g	6Mbps	1	6	2437	0.00	19.31	30.00	3.26	22.57	36.00	Pass	0.00
11g	6Mbps	1	10	2457	0.00	17.94	30.00	3.26	21.20	36.00	Pass	4.00
11g	6Mbps	1	11	2462	0.00	15.03	30.00	3.26	18.29	36.00	Pass	14.00
HT20	MCS0	1	1	2412	0.00	14.43	30.00	3.26	17.69	36.00	Pass	9.00
HT20	MCS0	1	2	2417	0.00	17.88	30.00	3.26	21.14	36.00	Pass	0.00
HT20	MCS0	1	6	2437	0.00	18.09	30.00	3.26	21.35	36.00	Pass	0.00
HT20	MCS0	1	10	2457	0.00	17.86	30.00	3.26	21.12	36.00	Pass	0.00
HT20	MCS0	1	11	2462	0.00	14.32	30.00	3.26	17.58	36.00	Pass	10.00
HT40	MCS0	1	3	2422	0.05	15.73	30.00	3.26	18.99	36.00	Pass	3.00
HT40	MCS0	1	6	2437	0.05	17.49	30.00	3.26	20.75	36.00	Pass	0.00
HT40	MCS0	1	9	2452	0.05	14.92	30.00	3.26	18.18	36.00	Pass	6.00

TEST RESULTS DATA
Average Output Power

2.4GHz Band Single Antenna													Setting
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	RU Config.	Duty Factor (dB)	Average Conducted Power with duty factor (dBm)	Conducted Power Limit (dBm)	DG (dBi)	EIRP Power (dBm)	EIRP Power Limit (dBm)	Pass /Fail	
HE20	MCS0	1	1	2412	Full	0.00	14.59	30.00	3.26	17.85	36.00	Pass	9.00
HE20	MCS0	1	2	2417	Full	0.00	18.03	30.00	3.26	21.29	36.00	Pass	0.00
HE20	MCS0	1	6	2437	Full	0.00	18.28	30.00	3.26	21.54	36.00	Pass	0.00
HE20	MCS0	1	10	2457	Full	0.00	17.98	30.00	3.26	21.24	36.00	Pass	0.00
HE20	MCS0	1	11	2462	Full	0.00	14.36	30.00	3.26	17.62	36.00	Pass	10.00

Note: Measured power (dBm) has offset with cable loss.

TEST RESULTS DATA
Peak Power Spectral Density


2.4GHz Band Single Antenna									
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	Peak PSD (dBm/3kHz)		DG (dBi)	Peak PSD Limit (dBm/3kHz)	Pass/Fail
11b	1Mbps	1	1	2412	-2.85		3.26	8.00	Pass
11b	1Mbps	1	6	2437	-1.85		3.26	8.00	Pass
11b	1Mbps	1	11	2462	-3.05		3.26	8.00	Pass
11g	6Mbps	1	1	2412	-9.25		3.26	8.00	Pass
11g	6Mbps	1	2	2437	-6.89		3.26	8.00	Pass
11g	6Mbps	1	6	2437	-5.98		3.26	8.00	Pass
11g	6Mbps	1	10	2462	-7.54		3.26	8.00	Pass
11g	6Mbps	1	11	2462	-9.92		3.26	8.00	Pass
HT40	MCS0	1	3	2422	-12.49		3.26	8.00	Pass
HT40	MCS0	1	6	2437	-10.40		3.26	8.00	Pass
HT40	MCS0	1	9	2452	-13.25		3.26	8.00	Pass

TEST RESULTS DATA
Peak Power Spectral Density

2.4GHz Band Single Antenna										
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	RU Config.	Peak PSD (dBm/3kHz)		DG (dBi)	Peak PSD Limit (dBm/3kHz)	Pass/Fail
HE20	MCS0	1	1	2412	Full	-7.81		3.26	8.00	Pass
HE20	MCS0	1	2	2417	Full	-4.36		3.26	8.00	Pass
HE20	MCS0	1	6	2437	Full	-5.13		3.26	8.00	Pass
HE20	MCS0	1	10	2457	Full	-4.61		3.26	8.00	Pass
HE20	MCS0	1	11	2462	Full	-7.58		3.26	8.00	Pass




Appendix B. AC Conducted Emission Test Results





Test Engineer :	Amos Zhang	Temperature :	25.3~26.2°C
		Relative Humidity :	38~40%
Test Voltage :	120Vac / 60Hz	Phase :	Neutral
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO01-KS
Condition : 15C RSS247-QP LISN-060105-N 2023 NEUTRAL

	Freq	Level	Over	Limit	Read	LISN	Cable	
	MHz	dBuV	Limit	Line	Level	Factor	Loss	Remark
			dB	dBuV	dBuV	dB	dB	
1	0.161	49.87	-15.56	65.43	39.40	0.04	10.43	QP
2	0.161	36.97	-18.46	55.43	26.50	0.04	10.43	Average
3	0.184	50.57	-13.71	64.28	40.10	0.05	10.42	QP
4	0.184	42.07	-12.21	54.28	31.60	0.05	10.42	Average
5	0.244	42.19	-19.76	61.95	31.79	0.01	10.39	QP
6	0.244	35.99	-15.96	51.95	25.59	0.01	10.39	Average
7	0.310	37.20	-22.77	59.97	26.90	-0.04	10.34	QP
8	0.310	30.40	-19.57	49.97	20.10	-0.04	10.34	Average
9	0.518	43.93	-12.07	56.00	33.80	-0.07	10.20	QP
10 *	0.518	37.03	-8.97	46.00	26.90	-0.07	10.20	Average
11	2.779	35.73	-20.27	56.00	25.80	-0.13	10.06	QP
12	2.779	21.03	-24.97	46.00	11.10	-0.13	10.06	Average

Note:

- Level(dBμV) = Read Level(dBμV) + LISN Factor(dB) + Cable Loss(dB)
- Over Limit(dB) = Level(dBμV) – Limit Line(dBμV)



Appendix C. Radiated Spurious Emission

Test Engineer :	Carry Xu	Relative Humidity :	42~43%
		Temperature :	21~22℃

Radiated Spurious Emission Test Modes

Mode	Band (MHz)	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 17	2400-2483.5	802.11b	01	2412	1Mbps	-	-
Mode 18	2400-2483.5	802.11b	06	2437	1Mbps	-	-
Mode 19	2400-2483.5	802.11b	11	2462	1Mbps	-	-
Mode 20	2400-2483.5	802.11g	01	2412	6Mbps	-	-
Mode 21	2400-2483.5	802.11g	02	2417	6Mbps	-	-
Mode 22	2400-2483.5	802.11g	06	2437	6Mbps	-	-
Mode 23	2400-2483.5	802.11g	10	2457	6Mbps	-	-
Mode 24	2400-2483.5	802.11g	11	2462	6Mbps	-	-
Mode 25	2400-2483.5	802.11ax HE20	01	2412	MCS0	-	-
Mode 26	2400-2483.5	802.11ax HE20	02	2417	MCS0	-	-
Mode 27	2400-2483.5	802.11ax HE20	06	2437	MCS0	-	-
Mode 28	2400-2483.5	802.11ax HE20	10	2457	MCS0	-	-
Mode 29	2400-2483.5	802.11ax HE20	11	2462	MCS0	-	-
Mode 30	2400-2483.5	802.11n HT40	03	2422	MCS0	-	-
Mode 31	2400-2483.5	802.11n HT40	06	2437	MCS0	-	-
Mode 32	2400-2483.5	802.11n HT40	09	2452	MCS0	-	-
Mode 35	2400-2483.5	802.11ax HE20	11	2462	MCS0	-	LF







Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
17	802.11b	01	2386.05	50.69	54.00	-3.31	H	AVERAGE	Pass	Band Edge
17	802.11b	01	4824.00	44.80	74.00	-29.20	V	PEAK	Pass	Harmonic
18	802.11b	06	-	-	-	-	-	-	-	Band Edge
18	802.11b	06	4874.00	47.81	54.00	-6.19	H	AVERAGE	Pass	Harmonic
19	802.11b	11	2488.66	52.85	54.00	-1.15	H	AVERAGE	Pass	Band Edge
19	802.11b	11	4924.00	50.30	54.00	-3.70	H	AVERAGE	Pass	Harmonic
20	802.11g	01	2389.95	52.80	54.00	-1.20	H	AVERAGE	Pass	Band Edge
20	802.11g	01	4824.00	41.67	74.00	-32.33	V	PEAK	Pass	Harmonic
21	802.11g	02	2389.95	52.25	54.00	-1.75	H	AVERAGE	Pass	Band Edge
21	802.11g	02	7251.00	42.51	74.00	-31.49	V	PEAK	Pass	Harmonic
22	802.11g	06	-	-	-	-	-	-	-	Band Edge
	802.11g	06	7311.00	42.57	74.00	-31.43	H	PEAK	Pass	Harmonic
23	802.11g	10	2483.50	52.74	54.00	-1.26	H	AVERAGE	Pass	Band Edge
	802.11g	10	4914.00	44.96	74.00	-29.04	H	PEAK	Pass	Harmonic
24	802.11g	11	2483.50	52.75	54.00	-1.25	H	AVERAGE	Pass	Band Edge
	802.11g	11	4924.00	43.51	74.00	-30.49	V	PEAK	Pass	Harmonic
25	802.11ax HE20	01	2389.95	52.53	54.00	-1.47	H	AVERAGE	Pass	Band Edge
	802.11ax HE20	01	4824.00	40.11	74.00	-33.89	V	PEAK	Pass	Harmonic
26	802.11ax HE20	02	2389.95	51.10	54.00	-2.90	H	AVERAGE	Pass	Band Edge
	802.11ax HE20	02	7243.50	44.81	74.00	-29.19	H	PEAK	Pass	Harmonic
27	802.11ax HE20	06	-	-	-	-	-	-	-	Band Edge
	802.11ax HE20	06	7311.00	43.87	74.00	-30.13	H	PEAK	Pass	Harmonic
28	802.11ax HE20	10	2483.50	52.16	54.00	-1.84	H	AVERAGE	Pass	Band Edge
	802.11ax HE20	10	7371.00	43.59	74.00	-30.41	H	PEAK	Pass	Harmonic
29	802.11ax HE20	11	2483.50	52.96	54.00	-1.04	H	AVERAGE	Pass	Band Edge
	802.11ax HE20	11	7386.00	41.86	74.00	-32.14	H	PEAK	Pass	Harmonic







Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
30	802.11n HT40	03	2389.95	52.80	54.00	-1.20	H	AVERAGE	Pass	Band Edge
	802.11n HT40	03	7266.00	42.03	74.00	-31.97	V	PEAK	Pass	Harmonic
31	802.11n HT40	06	2389.95	50.76	54.00	-3.24	H	AVERAGE	Pass	Band Edge
	802.11n HT40	06	7311.00	42.66	74.00	-31.34	H	PEAK	Pass	Harmonic
32	802.11n HT40	09	2483.50	52.33	54.00	-1.67	H	AVERAGE	Pass	Band Edge
	802.11n HT40	09	4904.00	41.57	74.00	-32.43	V	PEAK	Pass	Harmonic
35	802.11ax HE20	11	95.99	36.50	43.50	-8.43	H	PEAK	Pass	LF





		17																																																																																																											
Mode		Band Edge																																																																																																											
		2400-2483.5_802.11b_CH01_2412MHz																																																																																																											
Pol.	Horizontal											Fundamental																																																																																																	
Peak																																																																																																													
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2386.31</td><td>61.37</td><td>74.00</td><td>-12.63</td><td>53.11</td><td>31.69</td><td>7.10</td><td>36.53</td><td>6.00</td><td>145</td><td>203</td><td>PEAK</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2386.31	61.37	74.00	-12.63	53.11	31.69	7.10	36.53	6.00	145	203	PEAK	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>117.07</td><td>-----</td><td>-----</td><td>100.75</td><td>31.80</td><td>7.14</td><td>36.62</td><td>6.00</td><td>145</td><td>203</td><td>PEAK</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	117.07	-----	-----	100.75	31.80	7.14	36.62	6.00	145	203
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	2386.31	61.37	74.00	-12.63	53.11	31.69	7.10	36.53	6.00	145	203	PEAK																																																																																																	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	2412.00	117.07	-----	-----	100.75	31.80	7.14	36.62	6.00	145	203	PEAK																																																																																																	
Avg																																																																																																													
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2386.05</td><td>50.69</td><td>54.00</td><td>-3.31</td><td>42.43</td><td>31.69</td><td>7.10</td><td>36.53</td><td>6.00</td><td>145</td><td>203</td><td>AVERAGE</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2386.05	50.69	54.00	-3.31	42.43	31.69	7.10	36.53	6.00	145	203	AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2412.00</td><td>109.23</td><td>-----</td><td>-----</td><td>100.91</td><td>31.80</td><td>7.14</td><td>36.62</td><td>6.00</td><td>145</td><td>203</td><td>AVERAGE</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	109.23	-----	-----	100.91	31.80	7.14	36.62	6.00	145	203
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	2386.05	50.69	54.00	-3.31	42.43	31.69	7.10	36.53	6.00	145	203	AVERAGE																																																																																																	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	2412.00	109.23	-----	-----	100.91	31.80	7.14	36.62	6.00	145	203	AVERAGE																																																																																																	





		17																																											
Mode		Band Edge																																											
		2400-2483.5_802.11b_CH01_2412MHz																																											
Pol.		Vertical																																											
Peak																																													
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor							MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2385.66	59.65	74.00	-14.35	51.39	31.69	7.10	36.53	6.00	367	214
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																				
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																			
1	2385.66	59.65	74.00	-14.35	51.39	31.69	7.10	36.53	6.00	367	214	PEAK																																	
Fundamental																																													
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor							MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	116.21	-----	-----	107.88	31.80	7.14	36.61	6.00	367	214
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																				
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																			
1	2412.00	116.21	-----	-----	107.88	31.80	7.14	36.61	6.00	367	214	PEAK																																	
Avg																																													
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor							MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2385.92	49.38	54.00	-4.62	41.12	31.69	7.10	36.53	6.00	367	214
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																				
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																			
1	2385.92	49.38	54.00	-4.62	41.12	31.69	7.10	36.53	6.00	367	214	AVERAGE																																	
Avg																																													
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor							MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	108.21	-----	-----	99.89	31.80	7.14	36.62	6.00	367	214
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																				
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																			
1	2412.00	108.21	-----	-----	99.89	31.80	7.14	36.62	6.00	367	214	AVERAGE																																	







Mode	17																																																																																																										
	Harmonic																																																																																																										
	2400-2483.5_802.11b_CH01_2412MHz																																																																																																										
Pol.	Horizontal						Vertical																																																																																																				
Peak Avg																																																																																																											
	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4824.00</td><td>41.33</td><td>74.00</td><td>-32.67</td><td>62.56</td><td>33.00</td><td>10.23</td><td>65.26</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></table>								Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4824.00	41.33	74.00	-32.67	62.56	33.00	10.23	65.26	0.00	---	---	PEAK	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4824.00</td><td>44.80</td><td>74.00</td><td>-29.20</td><td>66.03</td><td>33.00</td><td>10.23</td><td>65.26</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></table>								Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4824.00	44.80	74.00	-29.20	66.03	33.00	10.23	65.26	0.00	---	---
		Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																
1	4824.00	41.33	74.00	-32.67	62.56	33.00	10.23	65.26	0.00	---	---	PEAK																																																																																															
		Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																
1	4824.00	44.80	74.00	-29.20	66.03	33.00	10.23	65.26	0.00	---	---	PEAK																																																																																															



		18																																																																														
Mode		Harmonic																																																																														
		2400-2483.5_802.11b_CH06_2437MHz																																																																														
Pol.		Horizontal																																																																														
Peak Avg																																																																																
		Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	3249.00	44.82	80.00	-35.18	69.11	32.70	8.35	65.34	0.00	---	Peak	2	4874.00	52.72	74.00	-21.28	73.91	33.80	10.29	65.28	0.00	103	300 PEAK	3	4874.00	47.81	54.00	-6.19	69.00	33.80	10.29	65.28	0.00	103	300 AVERAGE	4	7312.50	48.21	74.00	-25.79	66.69	35.50	12.72	66.70	0.00	---
	Limit	Over	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																						
Freq	Level	Line	Limit	Level	Factor	Loss	Factor	Factor																																																																								
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																						
1	3249.00	44.82	80.00	-35.18	69.11	32.70	8.35	65.34	0.00	---	Peak																																																																					
2	4874.00	52.72	74.00	-21.28	73.91	33.80	10.29	65.28	0.00	103	300 PEAK																																																																					
3	4874.00	47.81	54.00	-6.19	69.00	33.80	10.29	65.28	0.00	103	300 AVERAGE																																																																					
4	7312.50	48.21	74.00	-25.79	66.69	35.50	12.72	66.70	0.00	---	Peak																																																																					
		Vertical																																																																														
																																																																																
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4874.00</td><td>46.65</td><td>74.00</td><td>-27.35</td><td>67.84</td><td>33.80</td><td>10.29</td><td>65.28</td><td>0.00</td><td>---</td><td>PEAK</td></tr><tr><td>2</td><td>7311.00</td><td>41.34</td><td>74.00</td><td>-32.66</td><td>59.81</td><td>35.50</td><td>12.72</td><td>66.69</td><td>0.00</td><td>---</td><td>PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4874.00	46.65	74.00	-27.35	67.84	33.80	10.29	65.28	0.00	---	PEAK	2	7311.00	41.34	74.00	-32.66	59.81	35.50	12.72	66.69	0.00	---	PEAK													
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																								
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																						
1	4874.00	46.65	74.00	-27.35	67.84	33.80	10.29	65.28	0.00	---	PEAK																																																																					
2	7311.00	41.34	74.00	-32.66	59.81	35.50	12.72	66.69	0.00	---	PEAK																																																																					

Note: The non-restricted frequency which limit is 100kHz-PSD down 20dB.





		19																																																																																																																
Mode		Band Edge																																																																																																																
		2400-2483.5_802.11b_CH11_2462MHz																																																																																																																
Pol.		Horizontal											Fundamental																																																																																																					
Peak																																																																																																																		
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th></th><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2486.26</td><td>63.27</td><td>74.00</td><td>-10.73</td><td>55.13</td><td>31.95</td><td>7.26</td><td>37.07</td><td>6.00</td><td>107</td><td>171</td><td>PEAK</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos			Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2486.26	63.27	74.00	-10.73	55.13	31.95	7.26	37.07	6.00	107	171	PEAK	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th></th><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>118.10</td><td>-----</td><td>-----</td><td>109.95</td><td>31.84</td><td>7.22</td><td>36.91</td><td>6.00</td><td>107</td><td>171</td><td>PEAK</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos			Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2462.00	118.10	-----	-----	109.95	31.84	7.22	36.91	6.00	107	171
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																										
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																							
1	2486.26	63.27	74.00	-10.73	55.13	31.95	7.26	37.07	6.00	107	171	PEAK																																																																																																						
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																										
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																							
1	2462.00	118.10	-----	-----	109.95	31.84	7.22	36.91	6.00	107	171	PEAK																																																																																																						
Avg																																																																																																																		
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th></th><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2488.66</td><td>52.85</td><td>54.00</td><td>-1.15</td><td>44.72</td><td>31.95</td><td>7.26</td><td>37.08</td><td>6.00</td><td>107</td><td>171</td><td>AVERAGE</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos			Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2488.66	52.85	54.00	-1.15	44.72	31.95	7.26	37.08	6.00	107	171	AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th></th><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>109.98</td><td>-----</td><td>-----</td><td>101.83</td><td>31.85</td><td>7.22</td><td>36.92</td><td>6.00</td><td>107</td><td>171</td><td>AVERAGE</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos			Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	2462.00	109.98	-----	-----	101.83	31.85	7.22	36.92	6.00	107	171
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																										
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																							
1	2488.66	52.85	54.00	-1.15	44.72	31.95	7.26	37.08	6.00	107	171	AVERAGE																																																																																																						
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																										
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																							
1	2462.00	109.98	-----	-----	101.83	31.85	7.22	36.92	6.00	107	171	AVERAGE																																																																																																						







		19																																																				
Mode		Band Edge																																																				
		2400-2483.5_802.11b_CH11_2462MHz																																																				
Pol.		Vertical						Fundamental																																														
Peak																																																						
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2487.88</td><td>61.42</td><td>74.00</td><td>-12.58</td><td>53.29</td><td>31.95</td><td>7.26</td><td>37.08</td><td>6.00</td><td>399</td><td>214</td><td>PEAK</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2487.88	61.42	74.00	-12.58	53.29	31.95	7.26	37.08	6.00	399
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																												
1	2487.88	61.42	74.00	-12.58	53.29	31.95	7.26	37.08	6.00	399	214	PEAK																																										
Fundamental																																																						
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>117.38</td><td>-----</td><td>-----</td><td>109.23</td><td>31.85</td><td>7.22</td><td>36.92</td><td>6.00</td><td>399</td><td>214</td><td>PEAK</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	117.38	-----	-----	109.23	31.85	7.22	36.92	6.00	399
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																												
1	2462.00	117.38	-----	-----	109.23	31.85	7.22	36.92	6.00	399	214	PEAK																																										
Avg																																																						
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2488.60</td><td>50.76</td><td>54.00</td><td>-3.24</td><td>42.63</td><td>31.95</td><td>7.26</td><td>37.08</td><td>6.00</td><td>399</td><td>214</td><td>AVERAGE</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2488.60	50.76	54.00	-3.24	42.63	31.95	7.26	37.08	6.00	399
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																												
1	2488.60	50.76	54.00	-3.24	42.63	31.95	7.26	37.08	6.00	399	214	AVERAGE																																										
Fundamental																																																						
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>2462.00</td><td>108.72</td><td>-----</td><td>-----</td><td>100.57</td><td>31.85</td><td>7.22</td><td>36.92</td><td>6.00</td><td>399</td><td>214</td><td>AVERAGE</td></tr></tbody></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	108.72	-----	-----	100.57	31.85	7.22	36.92	6.00	399
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																												
1	2462.00	108.72	-----	-----	100.57	31.85	7.22	36.92	6.00	399	214	AVERAGE																																										







Mode	19																																																																																																																																																																				
	Harmonic																																																																																																																																																																				
	2400-2483.5_802.11b_CH11_2462MHz																																																																																																																																																																				
Pol.	Horizontal						Vertical																																																																																																																																																														
Peak Avg																																																																																																																																																																					
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4924.00</td><td>54.63</td><td>74.00</td><td>-19.37</td><td>75.78</td><td>33.80</td><td>10.35</td><td>65.30</td><td>0.00</td><td>111</td><td>236</td><td>PEAK</td></tr><tr><td>2</td><td>4924.00</td><td>50.30</td><td>54.00</td><td>-3.70</td><td>71.45</td><td>33.80</td><td>10.35</td><td>65.30</td><td>0.00</td><td>111</td><td>236</td><td>AVERAGE</td></tr><tr><td>3</td><td>7386.00</td><td>50.47</td><td>74.00</td><td>-23.53</td><td>69.11</td><td>35.57</td><td>12.73</td><td>66.94</td><td>0.00</td><td>100</td><td>286</td><td>PEAK</td></tr><tr><td>4</td><td>7386.00</td><td>43.03</td><td>54.00</td><td>-10.97</td><td>61.67</td><td>35.57</td><td>12.73</td><td>66.94</td><td>0.00</td><td>100</td><td>286</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4924.00	54.63	74.00	-19.37	75.78	33.80	10.35	65.30	0.00	111	236	PEAK	2	4924.00	50.30	54.00	-3.70	71.45	33.80	10.35	65.30	0.00	111	236	AVERAGE	3	7386.00	50.47	74.00	-23.53	69.11	35.57	12.73	66.94	0.00	100	286	PEAK	4	7386.00	43.03	54.00	-10.97	61.67	35.57	12.73	66.94	0.00	100	286	AVERAGE	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4924.00</td><td>51.93</td><td>74.00</td><td>-22.07</td><td>73.08</td><td>33.80</td><td>10.35</td><td>65.30</td><td>0.00</td><td>100</td><td>315</td><td>PEAK</td></tr><tr><td>2</td><td>4924.00</td><td>47.06</td><td>54.00</td><td>-6.94</td><td>68.21</td><td>33.80</td><td>10.35</td><td>65.30</td><td>0.00</td><td>100</td><td>315</td><td>AVERAGE</td></tr><tr><td>3</td><td>7386.00</td><td>42.05</td><td>74.00</td><td>-31.95</td><td>60.69</td><td>35.57</td><td>12.73</td><td>66.94</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4924.00	51.93	74.00	-22.07	73.08	33.80	10.35	65.30	0.00	100	315	PEAK	2	4924.00	47.06	54.00	-6.94	68.21	33.80	10.35	65.30	0.00	100	315	AVERAGE	3	7386.00	42.05	74.00	-31.95	60.69	35.57	12.73	66.94	0.00	---	---
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																											
1	4924.00	54.63	74.00	-19.37	75.78	33.80	10.35	65.30	0.00	111	236	PEAK																																																																																																																																																									
2	4924.00	50.30	54.00	-3.70	71.45	33.80	10.35	65.30	0.00	111	236	AVERAGE																																																																																																																																																									
3	7386.00	50.47	74.00	-23.53	69.11	35.57	12.73	66.94	0.00	100	286	PEAK																																																																																																																																																									
4	7386.00	43.03	54.00	-10.97	61.67	35.57	12.73	66.94	0.00	100	286	AVERAGE																																																																																																																																																									
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																																																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																																																																										
1	4924.00	51.93	74.00	-22.07	73.08	33.80	10.35	65.30	0.00	100	315	PEAK																																																																																																																																																									
2	4924.00	47.06	54.00	-6.94	68.21	33.80	10.35	65.30	0.00	100	315	AVERAGE																																																																																																																																																									
3	7386.00	42.05	74.00	-31.95	60.69	35.57	12.73	66.94	0.00	---	---	PEAK																																																																																																																																																									





Mode	20																																																						
	Band Edge																																																						
	2400-2483.5_802.11g_CH01_2412MHz																																																						
Pol.	Horizontal						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2388.78</td><td>68.35</td><td>74.00</td><td>-5.65</td><td>60.06</td><td>31.71</td><td>7.10</td><td>36.52</td><td>6.00</td><td>100</td><td>172</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2388.78	68.35	74.00	-5.65	60.06	31.71	7.10	36.52	6.00	100	172
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2388.78	68.35	74.00	-5.65	60.06	31.71	7.10	36.52	6.00	100	172	PEAK																																											
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>111.79</td><td>-----</td><td>-----</td><td>103.48</td><td>31.80</td><td>7.15</td><td>36.64</td><td>6.00</td><td>100</td><td>172</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	111.79	-----	-----	103.48	31.80	7.15	36.64	6.00	100	172
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2412.00	111.79	-----	-----	103.48	31.80	7.15	36.64	6.00	100	172	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>52.80</td><td>54.00</td><td>-1.20</td><td>44.49</td><td>31.72</td><td>7.11</td><td>36.52</td><td>6.00</td><td>100</td><td>172</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.95	52.80	54.00	-1.20	44.49	31.72	7.11	36.52	6.00	100	172
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.95	52.80	54.00	-1.20	44.49	31.72	7.11	36.52	6.00	100	172	AVERAGE																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>101.31</td><td>-----</td><td>-----</td><td>93.02</td><td>31.80</td><td>7.15</td><td>36.66</td><td>6.00</td><td>100</td><td>172</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	101.31	-----	-----	93.02	31.80	7.15	36.66	6.00	100	172
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2412.00	101.31	-----	-----	93.02	31.80	7.15	36.66	6.00	100	172	AVERAGE																																											







Mode	20																																																						
	Band Edge																																																						
	2400-2483.5_802.11g_CH01_2412MHz																																																						
Pol.	Vertical						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.43</td><td>62.73</td><td>74.00</td><td>-11.27</td><td>54.43</td><td>31.72</td><td>7.10</td><td>36.52</td><td>6.00</td><td>367</td><td>209</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.43	62.73	74.00	-11.27	54.43	31.72	7.10	36.52	6.00	367	209
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.43	62.73	74.00	-11.27	54.43	31.72	7.10	36.52	6.00	367	209	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>47.86</td><td>54.00</td><td>-6.14</td><td>39.55</td><td>31.72</td><td>7.11</td><td>36.52</td><td>6.00</td><td>367</td><td>209</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.95	47.86	54.00	-6.14	39.55	31.72	7.11	36.52	6.00	367	209
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.95	47.86	54.00	-6.14	39.55	31.72	7.11	36.52	6.00	367	209	AVERAGE																																											
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>108.97</td><td>-----</td><td>-----</td><td>100.66</td><td>31.80</td><td>7.14</td><td>36.63</td><td>6.00</td><td>367</td><td>209</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	108.97	-----	-----	100.66	31.80	7.14	36.63	6.00	367	209
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2412.00	108.97	-----	-----	100.66	31.80	7.14	36.63	6.00	367	209	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>99.67</td><td>-----</td><td>-----</td><td>91.35</td><td>31.80</td><td>7.14</td><td>36.62</td><td>6.00</td><td>367</td><td>209</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	99.67	-----	-----	91.35	31.80	7.14	36.62	6.00	367	209
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2412.00	99.67	-----	-----	91.35	31.80	7.14	36.62	6.00	367	209	AVERAGE																																											



Mode	20																																																																																																										
	Harmonic																																																																																																										
	2400-2483.5_802.11g_CH01_2412MHz																																																																																																										
Pol.	Horizontal						Vertical																																																																																																				
Peak Avg																																																																																																											
	<table><thead><tr><th colspan="2"></th><th colspan="2">Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4824.00</td><td>40.41</td><td>74.00</td><td>-33.59</td><td>61.64</td><td>33.00</td><td>10.23</td><td>65.26</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></tbody></table>								Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4824.00	40.41	74.00	-33.59	61.64	33.00	10.23	65.26	0.00	---	---	PEAK	<table><thead><tr><th colspan="2"></th><th colspan="2">Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4824.00</td><td>41.67</td><td>74.00</td><td>-32.33</td><td>62.90</td><td>33.00</td><td>10.23</td><td>65.26</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></tbody></table>								Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1	4824.00	41.67	74.00	-32.33	62.90	33.00	10.23	65.26	0.00	---	---
		Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																
1	4824.00	40.41	74.00	-33.59	61.64	33.00	10.23	65.26	0.00	---	---	PEAK																																																																																															
		Limit		Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																																
1	4824.00	41.67	74.00	-32.33	62.90	33.00	10.23	65.26	0.00	---	---	PEAK																																																																																															




Mode	21																																																						
	Band Edge																																																						
	2400-2483.5_802.11g_CH02_2417MHz																																																						
Pol.	Horizontal						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2388.13</td><td>68.20</td><td>74.00</td><td>-5.80</td><td>60.31</td><td>31.71</td><td>7.10</td><td>36.92</td><td>6.00</td><td>100</td><td>180</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2388.13	68.20	74.00	-5.80	60.31	31.71	7.10	36.92	6.00	100	180
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2388.13	68.20	74.00	-5.80	60.31	31.71	7.10	36.92	6.00	100	180	PEAK																																											
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>111.34</td><td>-----</td><td>-----</td><td>103.32</td><td>31.80</td><td>7.15</td><td>36.93</td><td>6.00</td><td>100</td><td>180</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2417.00	111.34	-----	-----	103.32	31.80	7.15	36.93	6.00	100	180
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2417.00	111.34	-----	-----	103.32	31.80	7.15	36.93	6.00	100	180	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>52.25</td><td>54.00</td><td>-1.75</td><td>44.34</td><td>31.72</td><td>7.11</td><td>36.92</td><td>6.00</td><td>100</td><td>180</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.95	52.25	54.00	-1.75	44.34	31.72	7.11	36.92	6.00	100	180
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.95	52.25	54.00	-1.75	44.34	31.72	7.11	36.92	6.00	100	180	AVERAGE																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>102.29</td><td>-----</td><td>-----</td><td>94.27</td><td>31.80</td><td>7.15</td><td>36.93</td><td>6.00</td><td>100</td><td>180</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2417.00	102.29	-----	-----	94.27	31.80	7.15	36.93	6.00	100	180
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2417.00	102.29	-----	-----	94.27	31.80	7.15	36.93	6.00	100	180	AVERAGE																																											





Mode	21																																																						
	Band Edge																																																						
	2400-2483.5_802.11g_CH02_2417MHz																																																						
Pol.	Vertical						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.82</td><td>63.55</td><td>74.00</td><td>-10.45</td><td>55.64</td><td>31.72</td><td>7.11</td><td>36.92</td><td>6.00</td><td>369</td><td>216</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.82	63.55	74.00	-10.45	55.64	31.72	7.11	36.92	6.00	369	216
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.82	63.55	74.00	-10.45	55.64	31.72	7.11	36.92	6.00	369	216	PEAK																																											
Fundamental																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>109.27</td><td>-----</td><td>-----</td><td>101.25</td><td>31.80</td><td>7.15</td><td>36.93</td><td>6.00</td><td>369</td><td>216</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2417.00	109.27	-----	-----	101.25	31.80	7.15	36.93	6.00	369	216
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2417.00	109.27	-----	-----	101.25	31.80	7.15	36.93	6.00	369	216	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>47.81</td><td>54.00</td><td>-6.19</td><td>39.90</td><td>31.72</td><td>7.11</td><td>36.92</td><td>6.00</td><td>369</td><td>216</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.95	47.81	54.00	-6.19	39.90	31.72	7.11	36.92	6.00	369	216
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.95	47.81	54.00	-6.19	39.90	31.72	7.11	36.92	6.00	369	216	AVERAGE																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2417.00</td><td>99.72</td><td>-----</td><td>-----</td><td>91.70</td><td>31.80</td><td>7.15</td><td>36.93</td><td>6.00</td><td>369</td><td>216</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2417.00	99.72	-----	-----	91.70	31.80	7.15	36.93	6.00	369	216
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2417.00	99.72	-----	-----	91.70	31.80	7.15	36.93	6.00	369	216	AVERAGE																																											







Mode	21																																																																	
	Harmonic																																																																	
	2400-2483.5_802.11g_CH02_2417MHz																																																																	
Pol.	Horizontal																																																																	
Peak Avg																																																																		
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4834.00</td><td>41.90</td><td>74.00</td><td>-32.10</td><td>63.12</td><td>33.80</td><td>10.24</td><td>65.26</td><td>0.00</td><td>--- PEAK</td></tr><tr><td>2</td><td>7251.00</td><td>42.44</td><td>74.00</td><td>-31.56</td><td>60.50</td><td>35.50</td><td>12.72</td><td>66.28</td><td>0.00</td><td>--- PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4834.00	41.90	74.00	-32.10	63.12	33.80	10.24	65.26	0.00	--- PEAK	2	7251.00	42.44	74.00	-31.56	60.50	35.50	12.72	66.28	0.00	--- PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																								
1	4834.00	41.90	74.00	-32.10	63.12	33.80	10.24	65.26	0.00	--- PEAK																																																								
2	7251.00	42.44	74.00	-31.56	60.50	35.50	12.72	66.28	0.00	--- PEAK																																																								
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4834.00</td><td>41.88</td><td>74.00</td><td>-32.12</td><td>63.10</td><td>33.80</td><td>10.24</td><td>65.26</td><td>0.00</td><td>--- PEAK</td></tr><tr><td>2</td><td>7251.00</td><td>42.51</td><td>74.00</td><td>-31.49</td><td>60.57</td><td>35.50</td><td>12.72</td><td>66.28</td><td>0.00</td><td>--- PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4834.00	41.88	74.00	-32.12	63.10	33.80	10.24	65.26	0.00	--- PEAK	2	7251.00	42.51	74.00	-31.49	60.57	35.50	12.72	66.28	0.00	--- PEAK	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																								
1	4834.00	41.88	74.00	-32.12	63.10	33.80	10.24	65.26	0.00	--- PEAK																																																								
2	7251.00	42.51	74.00	-31.49	60.57	35.50	12.72	66.28	0.00	--- PEAK																																																								



Mode	22																																																																																																																													
	Harmonic																																																																																																																													
	2400-2483.5_802.11g_CH06_2437MHz																																																																																																																													
Pol.	Horizontal						Vertical																																																																																																																							
Peak Avg																																																																																																																														
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4874.00</td><td>41.02</td><td>74.00</td><td>-32.98</td><td>62.21</td><td>33.80</td><td>10.29</td><td>65.28</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr><tr><td>2</td><td>7311.00</td><td>42.57</td><td>74.00</td><td>-31.43</td><td>61.04</td><td>35.50</td><td>12.72</td><td>66.69</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4874.00	41.02	74.00	-32.98	62.21	33.80	10.29	65.28	0.00	---	---	PEAK	2	7311.00	42.57	74.00	-31.43	61.04	35.50	12.72	66.69	0.00	---	---	PEAK	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4874.00</td><td>42.33</td><td>74.00</td><td>-31.67</td><td>63.52</td><td>33.80</td><td>10.29</td><td>65.28</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr><tr><td>2</td><td>7311.00</td><td>40.64</td><td>74.00</td><td>-33.36</td><td>59.11</td><td>35.50</td><td>12.72</td><td>66.69</td><td>0.00</td><td>---</td><td>---</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4874.00	42.33	74.00	-31.67	63.52	33.80	10.29	65.28	0.00	---	---	PEAK	2	7311.00	40.64	74.00	-33.36	59.11	35.50	12.72	66.69	0.00	---	---	PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	4874.00	41.02	74.00	-32.98	62.21	33.80	10.29	65.28	0.00	---	---	PEAK																																																																																																																		
2	7311.00	42.57	74.00	-31.43	61.04	35.50	12.72	66.69	0.00	---	---	PEAK																																																																																																																		
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	4874.00	42.33	74.00	-31.67	63.52	33.80	10.29	65.28	0.00	---	---	PEAK																																																																																																																		
2	7311.00	40.64	74.00	-33.36	59.11	35.50	12.72	66.69	0.00	---	---	PEAK																																																																																																																		




Mode	23																																																						
	Band Edge																																																						
	2400-2483.5_802.11g_CH10_2457MHz																																																						
Pol.	Horizontal						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2485.90</td><td>70.30</td><td>74.00</td><td>-3.70</td><td>62.06</td><td>31.94</td><td>7.26</td><td>36.96</td><td>6.00</td><td>166</td><td>186</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2485.90	70.30	74.00	-3.70	62.06	31.94	7.26	36.96	6.00	166	186
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2485.90	70.30	74.00	-3.70	62.06	31.94	7.26	36.96	6.00	166	186	PEAK																																											
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2457.00</td><td>112.31</td><td>-----</td><td>-----</td><td>104.22</td><td>31.82</td><td>7.21</td><td>36.94</td><td>6.00</td><td>166</td><td>186</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2457.00	112.31	-----	-----	104.22	31.82	7.21	36.94	6.00	166	186
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2457.00	112.31	-----	-----	104.22	31.82	7.21	36.94	6.00	166	186	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>52.74</td><td>54.00</td><td>-1.26</td><td>44.51</td><td>31.93</td><td>7.26</td><td>36.96</td><td>6.00</td><td>166</td><td>186</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	52.74	54.00	-1.26	44.51	31.93	7.26	36.96	6.00	166	186
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2483.50	52.74	54.00	-1.26	44.51	31.93	7.26	36.96	6.00	166	186	AVERAGE																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2457.00</td><td>103.31</td><td>-----</td><td>-----</td><td>95.23</td><td>31.82</td><td>7.21</td><td>36.95</td><td>6.00</td><td>166</td><td>186</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2457.00	103.31	-----	-----	95.23	31.82	7.21	36.95	6.00	166	186
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2457.00	103.31	-----	-----	95.23	31.82	7.21	36.95	6.00	166	186	AVERAGE																																											







		23																																																		
Mode		Band Edge																																																		
		2400-2483.5_802.11g_CH10_2457MHz																																																		
Pol.		Vertical					Fundamental																																													
Peak																																																				
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 2485.78</td><td>67.51</td><td>74.00</td><td>-6.49</td><td>59.27</td><td>31.94</td><td>7.26</td><td>36.96</td><td>6.00</td><td>400</td><td>251 PEAK</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1 2485.78	67.51	74.00	-6.49	59.27	31.94	7.26	36.96	6.00	400
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																											
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																										
1 2485.78	67.51	74.00	-6.49	59.27	31.94	7.26	36.96	6.00	400	251 PEAK																																										
Fundamental																																																				
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 2457.00</td><td>111.45</td><td>-----</td><td>-----</td><td>103.36</td><td>31.83</td><td>7.21</td><td>36.95</td><td>6.00</td><td>400</td><td>251 PEAK</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1 2457.00	111.45	-----	-----	103.36	31.83	7.21	36.95	6.00	400
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																											
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																										
1 2457.00	111.45	-----	-----	103.36	31.83	7.21	36.95	6.00	400	251 PEAK																																										
Avg																																																				
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 2483.50</td><td>50.97</td><td>54.00</td><td>-3.03</td><td>42.74</td><td>31.93</td><td>7.26</td><td>36.96</td><td>6.00</td><td>400</td><td>251 AVERAGE</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1 2483.50	50.97	54.00	-3.03	42.74	31.93	7.26	36.96	6.00	400
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																											
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																										
1 2483.50	50.97	54.00	-3.03	42.74	31.93	7.26	36.96	6.00	400	251 AVERAGE																																										
Fundamental																																																				
		<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 2457.00</td><td>102.22</td><td>-----</td><td>-----</td><td>94.14</td><td>31.82</td><td>7.21</td><td>36.95</td><td>6.00</td><td>400</td><td>251 AVERAGE</td></tr></tbody></table>											Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg	1 2457.00	102.22	-----	-----	94.14	31.82	7.21	36.95	6.00	400
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																											
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor	Factor	Factor																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm	deg																																										
1 2457.00	102.22	-----	-----	94.14	31.82	7.21	36.95	6.00	400	251 AVERAGE																																										







Mode	23																																																																	
	Harmonic																																																																	
	2400-2483.5_802.11g_CH10_2457MHz																																																																	
Pol.	Horizontal																																																																	
Peak Avg																																																																		
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4914.00</td><td>44.96</td><td>74.00</td><td>-29.04</td><td>66.11</td><td>33.80</td><td>10.34</td><td>65.29</td><td>0.00</td><td>--- PEAK</td></tr><tr><td>2</td><td>7362.00</td><td>45.68</td><td>74.00</td><td>-28.32</td><td>64.02</td><td>35.52</td><td>12.73</td><td>66.59</td><td>0.00</td><td>--- PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4914.00	44.96	74.00	-29.04	66.11	33.80	10.34	65.29	0.00	--- PEAK	2	7362.00	45.68	74.00	-28.32	64.02	35.52	12.73	66.59	0.00	--- PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																								
1	4914.00	44.96	74.00	-29.04	66.11	33.80	10.34	65.29	0.00	--- PEAK																																																								
2	7362.00	45.68	74.00	-28.32	64.02	35.52	12.73	66.59	0.00	--- PEAK																																																								
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4914.00</td><td>44.33</td><td>74.00</td><td>-29.67</td><td>65.48</td><td>33.80</td><td>10.34</td><td>65.29</td><td>0.00</td><td>--- PEAK</td></tr><tr><td>2</td><td>7374.00</td><td>44.31</td><td>74.00</td><td>-29.69</td><td>62.65</td><td>35.55</td><td>12.73</td><td>66.62</td><td>0.00</td><td>--- PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4914.00	44.33	74.00	-29.67	65.48	33.80	10.34	65.29	0.00	--- PEAK	2	7374.00	44.31	74.00	-29.69	62.65	35.55	12.73	66.62	0.00	--- PEAK	
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																								
1	4914.00	44.33	74.00	-29.67	65.48	33.80	10.34	65.29	0.00	--- PEAK																																																								
2	7374.00	44.31	74.00	-29.69	62.65	35.55	12.73	66.62	0.00	--- PEAK																																																								





Mode	24																																																																																																														
	Band Edge																																																																																																														
	2400-2483.5_802.11g_CH11_2462MHz																																																																																																														
Pol.	Horizontal						Fundamental																																																																																																								
Peak																																																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.74</td><td>70.30</td><td>74.00</td><td>-3.70</td><td>62.16</td><td>31.93</td><td>7.26</td><td>37.05</td><td>6.00</td><td>167</td><td>172</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.74	70.30	74.00	-3.70	62.16	31.93	7.26	37.05	6.00	167	172	PEAK	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>111.87</td><td>-----</td><td>-----</td><td>103.73</td><td>31.83</td><td>7.21</td><td>36.90</td><td>6.00</td><td>167</td><td>172</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	111.87	-----	-----	103.73	31.83	7.21	36.90	6.00	167	172
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																							
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																					
1	2483.74	70.30	74.00	-3.70	62.16	31.93	7.26	37.05	6.00	167	172	PEAK																																																																																																			
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																							
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																					
1	2462.00	111.87	-----	-----	103.73	31.83	7.21	36.90	6.00	167	172	PEAK																																																																																																			
Avg																																																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>52.75</td><td>54.00</td><td>-1.25</td><td>44.61</td><td>31.93</td><td>7.26</td><td>37.05</td><td>6.00</td><td>167</td><td>172</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	52.75	54.00	-1.25	44.61	31.93	7.26	37.05	6.00	167	172	AVERAGE	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th>Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>102.10</td><td>-----</td><td>-----</td><td>93.95</td><td>31.85</td><td>7.22</td><td>36.92</td><td>6.00</td><td>167</td><td>172</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	102.10	-----	-----	93.95	31.85	7.22	36.92	6.00	167	172
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																							
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																					
1	2483.50	52.75	54.00	-1.25	44.61	31.93	7.26	37.05	6.00	167	172	AVERAGE																																																																																																			
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																																																																																							
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor	Factor			Remark																																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																					
1	2462.00	102.10	-----	-----	93.95	31.85	7.22	36.92	6.00	167	172	AVERAGE																																																																																																			

Note: The higher Signals which are no mark are within frequency band can be ignored.







Mode	24																																																						
	Band Edge																																																						
	2400-2483.5_802.11g_CH11_2462MHz																																																						
Pol.	Vertical						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>69.25</td><td>74.00</td><td>-4.75</td><td>61.11</td><td>31.93</td><td>7.26</td><td>37.05</td><td>6.00</td><td>399</td><td>213</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	69.25	74.00	-4.75	61.11	31.93	7.26	37.05	6.00	399	213
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2483.50	69.25	74.00	-4.75	61.11	31.93	7.26	37.05	6.00	399	213	PEAK																																											
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>109.70</td><td>-----</td><td>-----</td><td>101.55</td><td>31.84</td><td>7.22</td><td>36.91</td><td>6.00</td><td>399</td><td>213</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	109.70	-----	-----	101.55	31.84	7.22	36.91	6.00	399	213
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2462.00	109.70	-----	-----	101.55	31.84	7.22	36.91	6.00	399	213	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2483.50</td><td>50.54</td><td>54.00</td><td>-3.46</td><td>42.40</td><td>31.93</td><td>7.26</td><td>37.05</td><td>6.00</td><td>399</td><td>213</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.50	50.54	54.00	-3.46	42.40	31.93	7.26	37.05	6.00	399	213
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2483.50	50.54	54.00	-3.46	42.40	31.93	7.26	37.05	6.00	399	213	AVERAGE																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2462.00</td><td>100.62</td><td>-----</td><td>-----</td><td>92.47</td><td>31.85</td><td>7.22</td><td>36.92</td><td>6.00</td><td>399</td><td>213</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2462.00	100.62	-----	-----	92.47	31.85	7.22	36.92	6.00	399	213
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor	Remark																																														
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2462.00	100.62	-----	-----	92.47	31.85	7.22	36.92	6.00	399	213	AVERAGE																																											



Mode	24																																																																	
	Harmonic																																																																	
	2400-2483.5_802.11g_CH11_2462MHz																																																																	
Pol.	Horizontal																																																																	
Peak Avg																																																																		
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBUV/m</th><th>dBUV/m</th><th>dB</th><th>dBUV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4924.00</td><td>41.54</td><td>74.00</td><td>-32.46</td><td>62.69</td><td>33.80</td><td>10.35</td><td>65.30</td><td>0.00</td><td>--- PEAK</td></tr><tr><td>2</td><td>7386.00</td><td>42.11</td><td>74.00</td><td>-31.89</td><td>60.75</td><td>35.57</td><td>12.73</td><td>66.94</td><td>0.00</td><td>--- PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line Margin	Level	Factor	Loss Factor	Factor						MHz	dBUV/m	dBUV/m	dB	dBUV	dB/m	dB	dB	cm	deg	1	4924.00	41.54	74.00	-32.46	62.69	33.80	10.35	65.30	0.00	--- PEAK	2	7386.00	42.11	74.00	-31.89	60.75	35.57	12.73	66.94	0.00	--- PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																								
	Freq	Level	Line Margin	Level	Factor	Loss Factor	Factor																																																											
	MHz	dBUV/m	dBUV/m	dB	dBUV	dB/m	dB	dB	cm	deg																																																								
1	4924.00	41.54	74.00	-32.46	62.69	33.80	10.35	65.30	0.00	--- PEAK																																																								
2	7386.00	42.11	74.00	-31.89	60.75	35.57	12.73	66.94	0.00	--- PEAK																																																								
Vertical																																																																		
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBUV/m</th><th>dBUV/m</th><th>dB</th><th>dBUV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>4924.00</td><td>43.51</td><td>74.00</td><td>-30.49</td><td>64.66</td><td>33.80</td><td>10.35</td><td>65.30</td><td>0.00</td><td>--- PEAK</td></tr><tr><td>2</td><td>7386.00</td><td>40.83</td><td>74.00</td><td>-33.17</td><td>59.47</td><td>35.57</td><td>12.73</td><td>66.94</td><td>0.00</td><td>--- PEAK</td></tr></table>												Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Freq	Level	Line Margin	Level	Factor	Loss Factor	Factor						MHz	dBUV/m	dBUV/m	dB	dBUV	dB/m	dB	dB	cm	deg	1	4924.00	43.51	74.00	-30.49	64.66	33.80	10.35	65.30	0.00	--- PEAK	2	7386.00	40.83	74.00	-33.17	59.47	35.57	12.73	66.94	0.00	--- PEAK
		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																								
	Freq	Level	Line Margin	Level	Factor	Loss Factor	Factor																																																											
	MHz	dBUV/m	dBUV/m	dB	dBUV	dB/m	dB	dB	cm	deg																																																								
1	4924.00	43.51	74.00	-30.49	64.66	33.80	10.35	65.30	0.00	--- PEAK																																																								
2	7386.00	40.83	74.00	-33.17	59.47	35.57	12.73	66.94	0.00	--- PEAK																																																								



		25																																																					
Mode	Band Edge																																																						
	2400-2483.5_802.11ax HE20_CH01_2412MHz																																																						
Pol.	Horizontal						Fundamental																																																
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2388.78</td><td>68.00</td><td>74.00</td><td>-6.00</td><td>59.71</td><td>31.71</td><td>7.10</td><td>36.52</td><td>6.00</td><td>100</td><td>169</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2388.78	68.00	74.00	-6.00	59.71	31.71	7.10	36.52	6.00	100	169
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2388.78	68.00	74.00	-6.00	59.71	31.71	7.10	36.52	6.00	100	169	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2389.95</td><td>52.53</td><td>54.00</td><td>-1.47</td><td>44.22</td><td>31.72</td><td>7.11</td><td>36.52</td><td>6.00</td><td>100</td><td>169</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.95	52.53	54.00	-1.47	44.22	31.72	7.11	36.52	6.00	100	169
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2389.95	52.53	54.00	-1.47	44.22	31.72	7.11	36.52	6.00	100	169	AVERAGE																																											
Peak																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>110.29</td><td>-----</td><td>-----</td><td>102.00</td><td>31.80</td><td>7.15</td><td>36.66</td><td>6.00</td><td>100</td><td>169</td><td>PEAK</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	110.29	-----	-----	102.00	31.80	7.15	36.66	6.00	100	169
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2412.00	110.29	-----	-----	102.00	31.80	7.15	36.66	6.00	100	169	PEAK																																											
Avg																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>2412.00</td><td>101.01</td><td>-----</td><td>-----</td><td>92.70</td><td>31.80</td><td>7.15</td><td>36.64</td><td>6.00</td><td>100</td><td>169</td><td>AVERAGE</td></tr></table>													Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2412.00	101.01	-----	-----	92.70	31.80	7.15	36.64	6.00	100	169
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																														
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Factor																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																													
1	2412.00	101.01	-----	-----	92.70	31.80	7.15	36.64	6.00	100	169	AVERAGE																																											