

PARENT UNIT ICONS (CONT'D)

Status icons

Connection status

- Strong signal strength.
- Moderate signal strength.
- Low signal strength.
- Weak signal strength.

Split mode ("For VM5255-2 only")

Patrol mode ("For VM5255-2 only")

Current view status

- The baby unit number that is being viewed when in:
 - Single CAM mode.
 - Patrol mode ("For VM5255-2 only").
 - Split mode ("For VM5255-2 only").

Night vision - On

Zoom - On

Lullaby - On

Night light - Auto-on

- Color icon indicates the night light is set to auto-on, and is currently turned on by sound activation.
- Gray icon indicates the night light is currently off but is set to auto-on. Night light will turn on when sound is detected by the baby unit.

Status icons

°F or °C

- Real-time temperature detected by the baby unit in Fahrenheit (°F) or Celsius (°C) (e.g. 57°F or 14°C).

Temperature alert tone - On

9-level sound indicator

- Indicates low sound level detected by the baby unit.
- Indicates moderate sound level detected by the baby unit.
- Indicates high sound level detected by the baby unit.

Mute alert

- Displays when the parent unit speaker volume is set to off.
- Displays when the parent unit is talking to the baby unit.

Battery status

- animates when the battery is charging.
- battery is fully charged.
- battery is low and needs charging.

Alert icons

- Displays when parent unit's battery is low and needs charging.
- Displays when connection between parent unit and baby unit is lost.
- Displays when sound is detected at a baby unit when in **Split view** (For VM5255-2 only).
- Baby unit temperature reaches or exceeds the set maximum.
- Baby unit detects temperature is at or lower than the set minimum.

SOUND SENSITIVITY AND SOUND ACTIVATION

Adjust sound detection sensitivity

You can turn on **Sound activation** and adjust the **VOX sensitivity** to detect sounds and turn on the parent unit while its screen is switched off or dimmed.

When the baby unit detects sounds that exceed certain levels, the parent unit screen turns on, the baby unit starts transmitting sounds to the parent unit, and you can see and hear your baby. If you have turned on the **Night light Auto-on** feature, it will turn on automatically to soothe your baby.

If you turn off **Sound activation**, you will hear sounds from the baby unit all the time, even when the parent unit screen is switched off.

If you have turned on sound alert, the parent unit beeps when the baby unit detect sounds while in **Split mode** ("For VM5255-2 only").

VOX sensitivity level	Level 5 (Highest)	Level 4 (High)	Level 3 (Medium)	Level 2 (Low)	Level 1 (Lowest)
Description	(Default setting) The parent unit screen and speaker turn on for very soft babbling and sounds from your baby's room.	The parent unit screen and speaker turn on for soft babbling and louder sounds from your baby. The parent unit remains quiet when your baby sleeps soundly.	The parent unit screen and speaker turn on for loud babbling and louder sounds from your baby. The parent unit remains quiet when your baby makes soft sounds.	The parent unit screen and speaker turn on for loud crying or screaming or loud sounds from your baby. The parent unit remains quiet when your baby makes soft sounds.	The parent unit screen and speaker turn on for loud crying or screaming or loud sounds from your baby. The parent unit remains quiet when your baby makes soft sounds.

Sound activated screen and audio

When **Sound activation** is on, the parent unit screen stays off to save power when the baby unit detects no sound.

Once the baby unit detects sounds that are louder than the chosen sound sensitivity level, the parent unit screen and speaker turn on automatically. The parent unit will then turn off again after 50 seconds of no sound detection.

NOTE

- If you have muted the parent unit speaker, only the parent unit screen will turn on when a sound is detected.

NIGHT VISION

The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the baby unit is viewing detected lights (low light levels), the infrared LEDs are switched on automatically. The images from the baby unit are in black and white, and appears on the screen.

NOTES

- It is normal to see a short white glare on your parent unit screen as the baby unit is adjusting to the dark environment.
- When the infrared LEDs are on, the images are in black and white. This is normal.

Tip

- Depending on the surroundings and other interfering factors, like lighting, objects, colors and backgrounds, the video quality may vary. Adjust the baby unit's angle or place the baby unit at a higher elevation to prevent glare and blurry displays.

MOUNT THE BABY UNIT ON DRY WALL (OPTIONAL)

NOTES

- Check for reception strength and camera angle before drilling the holes.
- The types of screws and anchors you need depend on the composition of the wall. You may need to purchase the screws and anchors separately to mount your camera units.

1. Place the wall mount bracket on a wall and then use a pencil to mark two holes in parallel. Remove the wall mount bracket and drill two holes in the wall (7/32 inch drill bit).

2. If you drill the holes into a stud, go to step 3.

- If you drill the holes into an object other than a stud, insert the wall anchors into the holes. Tap gently on the ends with a hammer until the wall anchors are flush with the wall.

3. Align the wall mount bracket and screws with the holes in the wall as shown. Tighten the screw in the middle hole first, so that the wall mount bracket position is fixed. You can tighten the other screw in the top hole.

4. Place the camera unit on the wall mount bracket, and then slide it forward until it locks into place. Connect the power adapter to the camera unit and a power supply not controlled by a wall switch.

5. You can maximize your camera unit's viewing angles by tilting the wall mount bracket.

Hold the camera unit up, and then rotate the knob in an anti-clockwise direction. This will loosen the joint of the wall mount bracket.

Tilt your camera unit up or down to adjust to your preferred angle. Then, rotate the knob in a clockwise direction to tighten the joint and secure the angle.

THE RBRC SEAL

The RBRC seal on the Li-ion battery indicates that Vtech Communications, Inc. is voluntarily participating in an industry program to collect and recycle these batteries at the end of their useful lives, when taken out of service within the United States and Canada.

This program provides a convenient alternative to placing used Li-ion batteries into the trash or municipal waste, which may be illegal in your area.

Vtech's participation makes it easy for you to drop off the spent battery at local retailers participating in the program or at authorized Vtech product service centers. Please call 1-800-8-BATTERY for information on Li-ion battery recycling and disposal laws/restrictions in your area. Vtech's involvement in this program is part of its commitment to protecting our environment and conserving natural resources.

The RBRC seal and 1-800-8-BATTERY® are registered trademarks of CalRecycle, Inc.

FCC AND IC REGULATIONS

FCC Part 15

This equipment has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

To ensure safety of use, the FCC/ISED has established criteria for the amount of radio frequency energy that can be safely absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC/ISED criteria. The baby unit shall be installed and used such that parts of all persons' body are maintained at a distance of approximately 18 in (20 cm) or more. The transmitter and antenna of the parent unit shall be held at least 18 in (2.5 cm) from your face.

This Class B digital apparatus complies with Canadian requirement: CAN ICES-3 (B)/NMB-3 (B).

Battery Cautions

This device contains lithium-ion (except transmitter/receiver) that comply with Innovation, Science and Economic Development Canada's license-exempt RSSB. Operation is subject to the following two conditions: (1) This device may not cause interference. (2) This device must accept any interference, including interference that may cause undesired operation of the device. "IC" before the registration number only signifies that the Industry Canada technical specifications were met.

This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.

CALIFORNIA ENERGY COMMISSION BATTERY CHARGING TESTING MODE

This baby monitor meets the California Energy Commission (CEC) regulations for energy consumption. Your baby monitor is set up to comply with the energy conservation standards right out of the box. Follow the instructions to install and charge the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to baby units, the CEC battery charging testing mode is activated while it is powered off and charging.

FOR CETL COMPLIANCE ONLY

Measures de sécurité importantes

La plaque signalétique appliquée est située au bas du socle de la batterie. Elle indique que Vtech Communications, Inc. participe volontairement à un programme industriel pour recueillir et recycler ces batteries à la fin de leur durée utile, lorsqu'elles sont retirées du service au sein des États-Unis et du Canada.

Cette mesure de précaution vise à empêcher les batteries de finir dans les poubelles ou les déchets municipaux, ce qui peut être illégal dans votre région.

Vtech participe à ce programme pour vous permettre de déposer vos batteries usagées chez des détaillants participants ou dans des centres agréés Vtech. Veuillez appeler 1-800-8-BATTERY pour obtenir des renseignements sur les lois et restrictions relatives au recyclage et à l'élimination des batteries dans votre région. L'engagement de Vtech dans ce programme fait partie de son engagement à protéger notre environnement et à préserver les ressources naturelles.

Le sceau RBRC et 1-800-8-BATTERY® sont des marques déposées de CalRecycle, Inc.

FCC Part 15

Cet équipement a été testé et trouvé conforme aux exigences pour un appareil numérique de classe B de la partie 15 des règles de la Commission fédérale des communications (FCC). Ces exigences sont destinées à fournir une protection raisonnable contre les interférences nuisibles dans une installation résidentielle. Cet équipement génère, utilise et peut émettre de l'énergie radiofréquence et, s'il n'est pas installé et utilisé conformément aux instructions, peut causer des interférences nuisibles aux communications radio. Toutefois, nous ne pouvons pas garantir qu'il n'y aura pas d'interférence dans une installation particulière. Si l'équipement provoque des interférences nuisibles à la réception radio ou télévision, ce qui peut être déterminé en éteignant et rallumant l'équipement, l'utilisateur est encouragé à tenter de corriger l'interférence en utilisant l'une ou plusieurs des mesures suivantes :

- Repositionner ou réorienter l'antenne.
- Augmenter l'écart entre l'équipement et le récepteur.
- Brancher l'équipement sur une prise d'alimentation électrique différente de celle à laquelle le récepteur est branché.
- Consulter le revendeur ou un technicien expérimenté en radio/télévision pour obtenir de l'aide.

AVERTISSEMENT : Toute modification ou altération de cet équipement non approuvée par la partie responsable de la conformité peut entraîner l'annulation de l'autorisation d'utiliser l'équipement.

Cet appareil est conforme à la partie 15 des règles de la FCC. Son utilisation est soumise aux deux conditions suivantes : (1) cet appareil ne doit pas causer d'interférence nuisible, et (2) cet appareil doit accepter toute interférence reçue, y compris l'interférence qui peut entraîner un fonctionnement indésirable de l'appareil.

Pour garantir la sécurité d'usage, la FCC/ISED a établi des critères quant à la quantité d'énergie radiofréquence que peut absorber un utilisateur ou un tiers de manière sûre. Ce produit a été testé et trouvé conforme aux critères de la FCC/ISED. L'unité bébé doit être installée et utilisée de manière à ce que toutes les parties du corps des personnes soient maintenues à une distance d'environ 18 po (20 cm) ou plus. L'émission et l'antenne de l'unité parent doivent être maintenues à au moins 18 po (2,5 cm) de votre visage.

Cet appareil numérique de classe B est conforme aux exigences canadiennes : CAN ICES-3 (B)/NMB-3 (B).

Précautions relatives aux batteries

Cet appareil contient des batteries au lithium-ion (à l'exception du transmetteur/récepteur) qui sont conformes aux normes de l'Innovation, de la Science et du Développement économique du Canada. Son utilisation est soumise aux deux conditions suivantes : (1) cet appareil ne doit pas causer d'interférence nuisible, et (2) cet appareil doit accepter toute interférence reçue, y compris l'interférence qui peut entraîner un fonctionnement indésirable de l'appareil. "IC" avant le numéro d'enregistrement indique uniquement que les spécifications techniques de l'Industrie Canada ont été respectées.

Cet produit respecte les normes de l'Innovation, de la Science et du Développement économique du Canada relatives aux appareils radio sans licence (RSSB). Son utilisation est soumise aux deux conditions suivantes : (1) cet appareil ne doit pas causer d'interférence nuisible, et (2) cet appareil doit accepter toute interférence reçue, y compris l'interférence qui peut entraîner un fonctionnement indésirable de l'appareil. "IC" avant le numéro d'enregistrement indique uniquement que les spécifications techniques de l'Industrie Canada ont été respectées.

Mode de test de charge de la batterie de l'Energy Commission de la Californie

Cet appareil respecte les normes de l'Energy Commission de la Californie (CEC) relatives à la consommation d'énergie. Votre appareil est configuré pour respecter les normes de conservation de l'énergie dès sa sortie de la boîte. Suivez les instructions pour installer et charger la batterie. Le mode de test de charge de la batterie de l'Energy Commission de la Californie est activé pendant la charge. Même si l'unité parent est jumelée à des unités bébé, le mode de test de charge de la batterie de l'Energy Commission de la Californie est activé pendant la charge.

FOR VM5255-2 ONLY

Status check - Two baby units

If you are viewing baby unit 1, the **POWER LED** light of baby unit 1 turns on. As baby unit 2 is not being viewed, its **POWER LED** light flashes.

NOTE

- If you power on only one baby unit, you may see the parent unit displaying 1 and then the UNLK LED light flashing.
- Press **VIEW** in **Single CAM** or **Patrol** mode to switch to the baby unit you have powered on.

Change different views - Single CAM

In **Single CAM** or **Patrol** mode, press **VIEW** to switch between the image of baby units 1 and 2.

Change different views - Patrol

Select **Patrol** as your monitoring mode to alternately view from baby units 1 and 2 every 10 seconds.

Change different views - Split

Select **Split** as your monitoring mode to view the images from both baby units at once.

LIMITED WARRANTY

What does this limited warranty cover?

The manufacturer of this Vtech Product warrants to the holder of a valid proof of purchase ("Consumer" or "you") that the Product and all accessories provided in the sales package ("Product") are free from defects in material and workmanship, pursuant to the following terms and conditions, when installed and used in conformity and in accordance with the Product operating instructions. This limited warranty extends only to the Consumer for Products purchased and used in the United States of America and Canada.

What will Vtech do if the Product is not free from defects in materials and workmanship during the limited warranty period ("Materially Defective Product")?

During the limited warranty period, Vtech's authorized service representative will repair or replace at Vtech's option, without charge, a Materially Defective Product. If we repair the Product, we may use new or refurbished replacement parts. If we choose to replace the Product, we may replace it with a new or refurbished Product of the same or similar design. We will return defective parts, modules, or equipment. Repair or replacement of the Product, at Vtech's option, is your exclusive remedy. Vtech will return the repaired or replacement products to you in working condition. You should report the repair or replacement to the representative approximately 30 days.

How long is the limited warranty period?

The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase. If Vtech repairs or replaces a Materially Defective Product under the terms of this limited warranty, this limited warranty also applies to the repaired or replacement Product for a period of either (a) 90 days from the date the repair or replacement Product is shipped to you or (b) the time remaining on the original one-year warranty, whichever is longer.

What is not covered by this limited warranty?

This limited warranty does not cover:

- Product that has been subjected to misuse, accident, shipping or other physical damage, improper installation, unauthorized or false modifications to the limited warranty, fire, water or other liquid intrusion or;
- Product that has been damaged due to repair, alteration or modification by anyone other than an authorized service representative of Vtech; or;
- Product to the extent that the problem experienced is caused by physical conditions, network reliability, or cable or other external factors.

Product to the extent that the problem is caused by use of non-Vtech accessories; or

Product whose warranty quality criteria, product serial number plates or electronic serial numbers have been removed, altered or rendered illegible; or

Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or

Product returned without a valid proof of purchase (see item 2 below); or

Changes for installation or set up, adjustment of customer controls, and installation or repair of systems outside the unit.

Other limitations

This warranty is a complete and exclusive agreement between you and Vtech. It supersedes all other written or oral communications related to this Product. Vtech provides no other warranties for this Product. The warranty exclusively describes all of Vtech's responsibilities regarding the Product. There are no other express warranties. No one is authorized to make modifications to the limited warranty, and you should not rely on any such modification. State/Provincial Laws: This warranty grants you specific legal rights, and you may also have other rights, which vary from state to state or province to province.

Limitations: Implied warranties, including those of fitness for a particular purpose and merchantability (an unwritten warranty that the Product is fit for ordinary use) are limited to one year from the date of purchase. Some states/provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you. In addition, Vtech does not warrant the quality, condition, or performance of the Product or its accessories (including, but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of substitute equipment, and claims by third parties) resulting from the use of this Product. Some states/provinces do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you.

Please retain your original sales receipt as proof of purchase.