

November 11, 2005

RadioShack Corporation  
100 Throckmorton St., Suite 1300,  
Fort Worth, TX 76102-2802.

Dear Dwayne Campbell:

Enclosed you will find your file copy of a Part 15 report (FCC ID: AAO3301197R).

For your reference, TCB will normally take another 15-20 days for reviewing the report.  
Approval will then be granted when no query is sorted.

Please contact me if you have any questions regarding the enclosed material.

Sincerely,

A handwritten signature in blue ink, appearing to read "Billy Chow".

Billy Chow  
Assistant Manager

Enclosure

# **RadioShack Corporation**

Application  
For  
Certification  
**(FCC ID: AAO3301197R)**  
Superheterodyne Receiver

0519741  
TC/el  
November 11, 2005

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

## **Intertek Testing Services Hong Kong Ltd.**

2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.  
Tel: (852) 2173 8888 Fax: (852) 2785 5487 Website: [www.hk.intertek-etlsemko.com](http://www.hk.intertek-etlsemko.com)

# INTERTEK TESTING SERVICES

---

## LIST OF EXHIBITS

### *INTRODUCTION*

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information

# INTERTEK TESTING SERVICES

## MEASUREMENT / TECHNICAL REPORT

RadioShack Corporation – MODEL: 33-1197

FCC ID: AAO3301197R

November 11, 2005

This report concerns (check one:)      Original Grant ☒      Class II Change ☐

Equipment Type: Superheterodyne Receiver (example: computer, printer, modem, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes ☐      No ☒

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37?      Yes ☐      No ☒

If no, assumed Part 15, Subpart B for unintentional radiator – the new 47 CFR [10-01-04 Edition] provision.

Report prepared by:

Billy Chow  
Intertek Testing Services  
2/F., Garment Center,  
576 Castle Peak Road,  
Kowloon, Hong Kong.  
Phone: 852-2173-8491  
Fax: 852-2371-0914

---

# INTERTEK TESTING SERVICES

---

## Table of Contents

<b>1.0</b>	<b><u>General Description</u></b>	<b>2</b>
1.1	Product Description	2
1.2	Related Submittal(s) Grants	2
1.3	Test Methodology	3
1.4	Test Facility	3
<b>2.0</b>	<b><u>System Test Configuration</u></b>	<b>5</b>
2.1	Justification	5
2.2	EUT Exercising Software	5
2.3	Special Accessories	5
2.4	Equipment Modification	6
2.5	Measurement Uncertainty	6
2.6	Support Equipment List and Description	6
<b>3.0</b>	<b><u>Emission Results</u></b>	<b>8</b>
3.1	Field Strength Calculation	9
3.2	Radiated Emission Configuration Photograph	11
3.3	Radiated Emission Data	12
3.4	Conducted Emission Configuration Photograph	15
3.5	Conducted Emission Data	16
<b>4.0</b>	<b><u>Equipment Photographs</u></b>	<b>18</b>
<b>5.0</b>	<b><u>Product Labelling</u></b>	<b>20</b>
<b>6.0</b>	<b><u>Technical Specifications</u></b>	<b>22</b>
<b>7.0</b>	<b><u>Instruction Manual</u></b>	<b>24</b>
<b>8.0</b>	<b><u>Miscellaneous Information</u></b>	<b>26</b>
8.1	Discussion of Pulse Desensitization	27
8.2	Calculation of Average Factor	28
8.3	Emissions Test Procedures	29

## INTERTEK TESTING SERVICES

---

### List of attached file

Exhibit Type	File Description	Filename
Test Report	Test Report	report.pdf
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Setup Photo	Conducted Emission	conducted photos.pdf
Test Report	Conducted Emission Test Result	conducted.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	internal photos.pdf
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label / Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf

# **INTERTEK TESTING SERVICES**

---

## **EXHIBIT 1**

### **GENERAL DESCRIPTION**

## INTERTEK TESTING SERVICES

---

### 1.0 **General Description**

#### 1.1 Product Description

This Equipment Under Test (EUT) is an audio wireless headphone receiver for its corresponding transmitter. The main function of the EUT is used to receive the modulated signal that can be transmitted by its corresponding transmitter. It is powered by three new "AAA" size rechargeable batteries. The red LED on the side of the EUT's body will be lit while the power switch is on. And, there is a tuning knob for volume control. In addition, it can recharge the batteries via the metal contact at the bottom of the EUT by the corresponding transmitter.

For electronic filing, the brief circuit description is saved with filename: descri.pdf

#### 1.2 Related Submittal(s) Grants

The Certification procedure of transmitter for this receiver (with FCC ID: AAO3301197T) is being processed at the same time of this application.



## INTERTEK TESTING SERVICES

---

### 1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (2003). Radiated Emission measurement was performed in Open Area Test Sites and Conducted Emission was performed in Shield Room. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 2**

### **SYSTEM TEST CONFIGURATION**

## INTERTEK TESTING SERVICES

---

### 2.0 **System Test Configuration**

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2003).

The EUT was powered by three new "AAA" size rechargeable batteries.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. The step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The unit was operated standalone and placed in the center of the turntable.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on turntable, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

For simplicity of testing, the unit was operated to receive continuously.

#### 2.2 EUT Exercising Software

There was no special software to exercise the device. Once the unit is powered up, it receives the RF signal continuously.

#### 2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by RadioShack Corporation will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services.

### 2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

### 2.6 Support Equipment List and Description

Transmitter with FCC ID: AAO3301197T.

All the items listed under section 2.0 of this report are

*Confirmed by:*

*Billy Chow  
Assistant Manager  
Intertek Testing Services Hong Kong Ltd.  
Agent for RadioShack Corporation*



\_\_\_\_\_  
*Signature*

\_\_\_\_\_  
November 11, 2005

\_\_\_\_\_  
*Date*

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 3**

### **EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

### 3.0 **Emission Results**

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in dB $\mu$ V/m

RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation (cont'd)

#### Example

Assume a receiver reading of 62.0dB $\mu$ V is obtained. The antenna factor of 7.4dB and cable factor of 1.6dB is added. The amplifier gain of 29dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0dB, and the resultant average factor was -10dB. The net field strength for comparison to the appropriate emission limit is 32dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

$$RA = 62.0\text{dB}\mu\text{V}$$

$$AF = 7.4\text{dB}$$

$$CF = 1.6\text{dB}$$

$$AG = 29.0\text{dB}$$

$$PD = 0\text{dB}$$

$$AV = -10\text{dB}$$

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32\text{dB}\mu\text{V/m}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm } [(32\text{dB}\mu\text{V/m})/20] = 39.8\mu\text{V/m}$$



## **INTERTEK TESTING SERVICES**

---

### 3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission  
at  
904.897MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos.pdf.

## INTERTEK TESTING SERVICES

---

### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 3.4dB margin

### **TEST PERSONNEL:**



---

*Signature*

Terry C. H. Chan, Compliance Engineer  
*Typed / Printed Name*

November 11, 2005  
*Date*

## INTERTEK TESTING SERVICES

Company: RadioShack Corporation  
Model: 33-1197  
Worst Case Operating Mode: Receiving

Date of Test: September 16, 2005

**Table 1**

### **Radiated Emissions**

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp (dB)	Antenna factor (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
V	904.897	26.6	16	32.0	42.6	46.0	-3.4
V	1809.794	50.6	34	27.2	43.8	54.0	-10.2
V	2714.691	46.2	34	30.4	42.6	54.0	-11.4
V	3619.588	42.7	34	33.3	42.0	54.0	-12.0
V	4524.485	41.0	34	34.9	41.9	54.0	-12.1

NOTES: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

‘\*’ Emission within the restricted band fulfil the requirement of Section 15.205.

Test Engineer: Terry C. H. Chan

## INTERTEK TESTING SERVICES

Company: RadioShack Corporation  
Model: 33-1197  
Worst Case Operating Mode: Charging

Date of Test: September 16, 2005

**Table 2**

### **Radiated Emissions**

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp (dB)	Antenna factor (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
V	38.486	35.6	16	10.0	29.6	40.0	-10.4
V	45.384	35.4	16	10.0	29.4	40.0	-10.6
V	55.724	35.6	16	11.0	30.6	40.0	-9.4
V	59.672	36.8	16	10.0	30.8	40.0	-9.2
V	63.841	36.2	16	9.0	29.2	40.0	-10.8
V	69.506	37.4	16	7.0	28.4	40.0	-11.6

NOTES: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

‘\*’ Emission within the restricted band fulfil the requirement of Section 15.205.

Test Engineer: Terry C. H. Chan

## **INTERTEK TESTING SERVICES**

---

### 3.4 Conducted Emission Configuration Photograph

Worst Case Line-Conducted Emission  
at  
0.305MHz

For electronic filing, the worst case line-conducted configuration photographs are saved with filename: conducted photos.pdf.

## INTERTEK TESTING SERVICES

---

### 3.5 Conducted Emission Data

For electronic filing, the graph and data table of conducted emission are saved with filename: conducted.pdf. The data table lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 28.6dB margin

### **TEST PERSONNEL:**



---

*Signature*

Terry C. H. Chan, Compliance Engineer  
*Typed / Printed Name*

November 11, 2005  
*Date*

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 4**

### **EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 **Equipment Photographs**

For electronic filing, photographs of the tested EUT are saved with filename: external photos.pdf and internal photos.pdf.



**EXHIBIT 5**  
**PRODUCT LABELLING**

## INTERTEK TESTING SERVICES

---

### 5.0 **Product Labelling**

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 6**

### **TECHNICAL SPECIFICATIONS**

## INTERTEK TESTING SERVICES

---

### 6.0 **Technical Specifications**

For electronic filing, the block diagram and schematic of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

**EXHIBIT 7**  
**INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

### 7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold / leased in the United States.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 8**

### **MISCELLANEOUS INFORMATION**

## INTERTEK TESTING SERVICES

---

### 8.0 **Miscellaneous Information**

The miscellaneous information includes details of the test procedure.



## **INTERTEK TESTING SERVICES**

---

### **8.1 Discussion of Pulse Desensitization**

This device is a superheterodyne receiver. No desensitization of the measurement equipment is required as the received signals are continuously.

## **INTERTEK TESTING SERVICES**

---

### **8.2 Calculation of Average Factor**

This device is a superheterodyne receiver. It is not necessary to apply average factor to the measurement result.

## INTERTEK TESTING SERVICES

---

### 8.3 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of superheterodyne receivers operating under Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 – 2003.

The equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axes to obtain maximum emission levels. The antenna height and polarization are varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings. A detailed description for the calculation of the average factor can be found in Exhibit 8.2.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9kHz to the tenth harmonic of the highest fundamental frequency or 40GHz, whichever is lower. For line-conducted emissions, the range scanned is 150kHz to 30MHz.

## INTERTEK TESTING SERVICES

---

### 8.3 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements are made as described in ANSI C63.4 – 2003.

The IF bandwidth used for measurement of radiated signal strength was 100kHz or greater when frequency is below 1000MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.1). Above 1000MHz, a resolution bandwidth of 1MHz is used.

Measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the forbidden bands and above 1GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.