

TEST REPORT

Report No.: BCTC2312178980-1E

Applicant: SHENZHEN SNAPPER TECHNOLOGY CO., LTD

Product Name: Universal Power Charger

Test Model: PS-B006WA

Tested Date: 2023-12-13 to 2024-01-31

Issued Date: 2024-01-31

Shenzhen BCTC Testing Co., Ltd.



FCC ID: 2BC8J-PS-B006WA

Product Name: Universal Power Charger

Trademark: N/A

Model/Type Reference: PS-B006WA
PS-B006, PS-B006W, PS-B006WS

Prepared For: SHENZHEN SNAPPER TECHNOLOGY CO., LTD

Address: F4, BldgE, Fenghuang third Industrial area, Tengfeng Road, Fuyong, Baoan, Shenzhen China 518000

Manufacturer: SHENZHEN SNAPPER TECHNOLOGY CO., LTD

Address: F4, BldgE, Fenghuang third Industrial area, Tengfeng Road, Fuyong, Baoan, Shenzhen China 518000

Prepared By: Shenzhen BCTC Testing Co., Ltd.

Address: 1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China.

Sample Received Date: 2023-12-05

Sample Tested Date: 2023-12-13 to 2024-01-31

Issue Date: 2024-01-31

Report No.: BCTC2312178980-1E

Test Standards: FCC Part15.209
ANSI C63.10-2013

Test Results: PASS

Tested by:



Eric Yang/Project Handler

Approved by:



Zero Zhou/Reviewer

The test report is effective only with both signature and specialized stamp. This result(s) shown in this report refer only to the sample(s) tested. Without written approval of Shenzhen BCTC Testing Co., Ltd, this report can't be reproduced except in full. The tested sample(s) and the sample information are provided by the client.

Table Of Content


Test Report Declaration	Page
1. Version	4
2. Test Summary	5
3. Measurement Uncertainty	6
4. Product Information And Test Setup	7
4.1 Product Information	7
4.2 Support Equipment	7
4.3 Test Setup Configuration	8
4.4 Test Mode	9
5. Test Facility And Test Instrument Used	10
5.1 Test Facility	10
5.2 Test Instrument Used	10
6. Conducted Emissions	12
6.1 Block Diagram Of Test Setup	12
6.2 Limit	12
6.3 Test procedure	12
6.4 EUT operating Conditions	12
6.5 Test Result	13
7. Radiated Emissions	15
7.1 Block Diagram Of Test Setup	15
7.2 Limit	16
7.3 Test procedure	16
7.4 Test Result	17
8. Bandwidth Test	22
8.1 Test Procedure	22
8.2 Test Setup	22
8.3 Test Result	22
9. Antenna Requirements	23
9.1 Limit	23
9.2 Test Result	23
10. EUT Photographs	24
11. EUT Test Setup Photographs	25

(Note: N/A Means Not Applicable)

1. Version

Report No.	Issue Date	Description	Approved
BCTC2312178980-1E	2024-01-26	Original	Valid

TEST
TC
OVER
t See



2. Test Summary

The Product has been tested according to the following specifications:

No.	Test Parameter	Clause No.	Results
1	Conducted Emission	15.207	PASS
2	Radiated Emission	15.209	PASS
3	20dB Bandwidth	15.215	PASS
4	Antenna Requirement	15.203	PASS



3. Measurement Uncertainty

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the Product as specified in CISPR 16-4-2. This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=2$.

No.	Item	Uncertainty
1	3m chamber Radiated spurious emission(30MHz-1GHz)	U=4.3dB
2	Conducted Emission (150kHz-30MHz)	U=3.2dB
3	humidity uncertainty	U=5.3%
4	Temperature uncertainty	U=0.59°C

CO., LTD.

4. Product Information And Test Setup

4.1 Product Information

Model/Type Reference:	PS-B006WA PS-B006, PS-B006W, PS-B006WS
Model Differences:	All the model are the same circuit and RF module, except model names and appearance of the color.
Modulation:	MSK
Operation Frequency:	115-205kHz
Antenna installation:	Coil antenna
Ratings:	Battery: 5000mAh, 54Wh, @10.8V AC Input: 100-240V-50/60Hz 0.5A Type-C Input: DC5V/3A, 9V/2A, 12V/1.5A, 15V/3A, 20V/2.25A PD45W Max Type-C Output: DC5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A PD65W Max Type-C Cable Output: DC5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A PD65W Max USB-A Output: DC5V/3A, 9V/2A, 12V/1.5A 18W Max Wireless Output: 5W/7.5W/10W/15WMax Sharing Output: DC5V/3A Max

4.2 Support Equipment

No.	Device Type	Brand	Model	Series No.	Note
E-2	ADAPTER	Hoco.	N18	N/A	Auxiliary
E-3	Dummy load	N/A	DL01	N/A	Auxiliary


Notes:

1. All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.
2. Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.



4.3 Test Setup Configuration

See test photographs attached in *EUT TEST SETUP PHOTOGRAPHS* for the actual connections between Product and support equipment.

Conducted Emission:



Radiated Spurious Emission:



4.4 Test Mode

To investigate the maximum EMI emission characteristics generates from EUT, the test system was pre-scanning tested base on the consideration of following EUT operation mode or test configuration mode which possible have effect on EMI emission level. Each of these EUT operation mode(s) or test configuration mode(s) mentioned above was evaluated respectively.

Conducted Emission:

AC Mode	Test Mode 1	AC Plug in
	Test Mode 2	Type-C 5V in 5V 3A*
	Test Mode 3	Type-C 9V in 9V 3A
	Test Mode 4	Type-C 9V in 12V 1.5A
	Test Mode 5	Type-C 15V in 15V 3A
	Test Mode 6	Type-C 20V in 20V 2.25A

Radiated Spurious Emission:

AC Mode	Test Mode 1	AC Plug in
	Test Mode 2	Type-C 5V in 5V 3A
	Test Mode 3	Type-C 9V in 9V 3A*
	Test Mode 4	Type-C 9V in 12V 1.5A
	Test Mode 5	Type-C 15V in 15V 3A
	Test Mode 6	Type-C 20V in 20V 2.25A
DC Mode	Test Mode 7	Wireless 5W
	Test Mode 8	Wireless 7.5W
	Test Mode 9	Wireless 10W *
	Test Mode 10	Wireless 15W

Note:

- (1) EUT does not support wireless charging when charging.
- (2) All test mode were tested and passed, shows (*) is the worst case mode which were recorded in this report.

5. Test Facility And Test Instrument Used

5.1 Test Facility

All measurement facilities used to collect the measurement data are located at Shenzhen BCTC Testing Co., Ltd. Address:1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China. The site and apparatus are constructed in conformance with the requirements of ANSI C63.4 and CISPR 16-1-1 other equivalent standards.

FCC Test Firm Registration Number: 712850

A2LA certificate registration number is: CN1212

ISED Registered No.: 23583


ISED CAB identifier: CN0017

5.2 Test Instrument Used

Conducted Emissions Test					
Equipment	Manufacturer	Model#	Serial#	Last Cal.	Next Cal.
Receiver	R&S	ESR3	102075	May 15, 2023	May 14, 2024
LISN	R&S	ENV216	101375	May 15, 2023	May 14, 2024
Software	Frad	EZ-EMC	EMC-CON 3A1	\	\
Pulse limiter	Schwarzbeck	VTSD9561-F	01323	Sept. 22, 2023	Sept. 21, 2024

RF Conducted Test					
Equipment	Manufacturer	Model#	Serial#	Last Cal.	Next Cal.
Power Meter	Keysight	E4419	\	May 15, 2023	May 14, 2024
Power Sensor (AV)	Keysight	E9300A	\	May 15, 2023	May 14, 2024
Signal Analyzer 20kHz-26.5G Hz	Keysight	N9020A	MY49100060	May 15, 2023	May 14, 2024
Spectrum Analyzer 9kHz-40GHz	R&S	FSP 40	\	May 15, 2023	May 14, 2024

Radiated Emissions Test (966 Chamber01)					
Equipment	Manufacturer	Model#	Serial#	Last Cal.	Next Cal.
966 chamber	ChengYu	966 Room	966	May 15, 2023	May 14, 2026
Receiver	R&S	ESR3	102075	May 15, 2023	May 14, 2024
Receiver	R&S	ESRP	101154	May 15, 2023	May 14, 2024
Amplifier	Schwarzbeck	BBV9744	9744-0037	May 15, 2023	May 14, 2024
TRILOG Broadband Antenna	Schwarzbeck	VULB9163	942	May 29, 2023	May 28, 2024
Loop Antenna(9KHz -30MHz)	Schwarzbeck	FMZB1519B	00014	May 31, 2023	May 30, 2024
Amplifier	SKET	LAPA_01G18 G-45dB	SK2021040901	May 15, 2023	May 14, 2024
Horn Antenna	Schwarzbeck	BBHA9120D	1541	May 31, 2023	May 30, 2024
Amplifier(18G Hz-40GHz)	MITEQ	TTA1840-35-HG	2034381	May 15, 2023	May 14, 2024
Horn Antenna(18G Hz-40GHz)	Schwarzbeck	BBHA9170	00822	May 31, 2023	May 30, 2024
Spectrum Analyzer9kHz-40GHz	R&S	FSP40	100363	May 15, 2023	May 14, 2024
Software	Frad	EZ-EMC	FA-03A2 RE	\	\



6. Conducted Emissions

6.1 Block Diagram Of Test Setup



6.2 Limit

Frequency (MHz)	Limit (dBuV)	
	Quas-peak	Average
0.15 -0.5	66 - 56 *	56 - 46 *
0.50 -5.0	56.00	46.00
5.0 -30.0	60.00	50.00

Notes:
1. *Decreasing linearly with logarithm of frequency.
2. The lower limit shall apply at the transition frequencies.

6.3 Test procedure

Receiver Parameters	Setting
Attenuation	10 dB
Start Frequency	0.15 MHz
Stop Frequency	30 MHz
IF Bandwidth	9 kHz


- The Product was placed on a nonconductive table 0.8 m above the horizontal ground reference plane, and 0.4 m from the vertical ground reference plane, and connected to the main through Line Impedance Stability Network (L.I.S.N).
- The RBW of the receiver was set at 9 kHz in 150 kHz ~ 30MHz with Peak and AVG detector in Max Hold mode. Run the receiver's pre-scan to record the maximum disturbance generated from Product in all power lines in the full band.
- For each frequency whose maximum record was higher or close to limit, measure its QP and AVG values and record.

6.4 EUT operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.

6.5 Test Result

Temperature:	26 °C	Relative Humidity:	54%
Pressure:	101KPa	Phase :	L
Test Mode:	Mode 2	Test Voltage:	AC 120V/60Hz




Remark:

1. All readings are Quasi-Peak and Average values.
2. Factor = Insertion Loss + Cable Loss.
3. Measurement = Reading Level + Correct Factor
4. Over = Measurement - Limit

No.	Mk.	Freq. MHz	Reading Level dB	Correct Factor dB	Measure- ment dBuV	Limit dBuV	Over dB	Detector
1		0.2535	24.33	19.83	44.16	61.64	-17.48	QP
2	*	0.2535	19.46	19.83	39.29	51.64	-12.35	AVG
3		0.3731	18.85	19.84	38.69	58.43	-19.74	QP
4		0.3731	13.74	19.84	33.58	48.43	-14.85	AVG
5		0.7470	12.37	19.86	32.23	56.00	-23.77	QP
6		0.7470	10.30	19.86	30.16	46.00	-15.84	AVG
7		1.2422	9.85	19.95	29.80	56.00	-26.20	QP
8		1.2422	6.75	19.95	26.70	46.00	-19.30	AVG
9		2.2367	10.94	20.03	30.97	56.00	-25.03	QP
10		2.2367	6.17	20.03	26.20	46.00	-19.80	AVG
11		4.7213	14.24	20.49	34.73	56.00	-21.27	QP
12		4.7213	12.69	20.49	33.18	46.00	-12.82	AVG

Temperature:	26 °C	Relative Humidity:	54%
Pressure:	101KPa	Phase :	N
Test Mode:	Mode 2	Test Voltage:	AC 120V/60Hz


Remark:


1. All readings are Quasi-Peak and Average values.
2. Factor = Insertion Loss + Cable Loss.
3. Measurement = Reading Level + Correct Factor
4. Over = Measurement - Limit

No.	Mk.	Freq. MHz	Reading Level dB	Correct Factor dB	Measure- ment dBuV	Limit dBuV	Over dB	Detector
1		0.2481	25.58	19.83	45.41	61.82	-16.41	QP
2		0.2481	19.32	19.83	39.15	51.82	-12.67	AVG
3		0.3791	16.58	19.84	36.42	58.30	-21.88	QP
4		0.3791	13.36	19.84	33.20	48.30	-15.10	AVG
5		0.7470	11.07	19.86	30.93	56.00	-25.07	QP
6		0.7470	9.22	19.86	29.08	46.00	-16.92	AVG
7		0.8710	9.51	19.90	29.41	56.00	-26.59	QP
8		0.8710	6.21	19.90	26.11	46.00	-19.89	AVG
9		2.3090	9.25	20.06	29.31	56.00	-26.69	QP
10		2.3090	3.39	20.06	23.45	46.00	-22.55	AVG
11		4.7464	16.40	20.49	36.89	56.00	-19.11	QP
12	*	4.7464	15.41	20.49	35.90	46.00	-10.10	AVG


7. Radiated Emissions

7.1 Block Diagram Of Test Setup

(A) Radiated Emission Test-Up Frequency Below 30MHz



(B) Radiated Emission Test-Up Frequency 30MHz~1GHz



7.2 Limit

FCC §15.209; §15.205.

Test Standard	FCC Part15 C Section 15.209 and 15.205				
Test Limit	Frequency (MHz)	Field strength (microvolt/meter)	Limit (dBuV/m)	Remark	Measurement distance (m)
	0.009MHz~0.490MHz	2400/F(kHz)	-	-	300
	0.490MHz~1.705MHz	24000/F(kHz)	-	-	30
	1.705MHz~30MHz	30	-	-	30
	30MHz~88MHz	100	40.0	Quasi-peak	3
	88MHz~216MHz	150	43.5	Quasi-peak	3
	216MHz~960MHz	200	46.0	Quasi-peak	3
	960MHz~1000MHz	500	54.0	Quasi-peak	3
	Above 1000MHz	500	54.0	Average	3
		-	74.0	Peak	3

7.3 Test procedure

Receiver Parameter	Setting
Attenuation	Auto
9kHz~150kHz	RBW 200Hz for QP
150kHz~30MHz	RBW 9kHz for QP
30MHz~1000MHz	RBW 120kHz for QP

Below 1GHz test procedure as below:

- The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.
- The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
- The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.
- If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

Above 1GHz test procedure as below:


- Different between above is the test site, change from Semi- Anechoic Chamber to fully Anechoic Chamber and change form table 0.8 metre to 1.5 metre(Above 18GHz the distance is 1 meter and table is 1.5 metre).
- Test the EUT in the lowest channel ,the middle channel ,the Highest channel.

Note: Both horizontal and vertical antenna polarities were tested and performed pretest to three orthogonal axis. The worst case emissions were reported.

7.4 Test Result

9kHz-30MHz


Temperature:	26°C	Relative Humidity:	54%
Pressure:	101 kPa	Test Voltage:	AC 120V/60Hz
Test Mode:	Mode 9	Polarization:	Coaxial(Worst)



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1	*	0.1178	94.60	-7.52	87.08	106.1	-19.10	peak
2		0.2366	64.18	-7.75	56.43	100.1	-43.69	peak
3		0.3549	69.70	-7.67	62.03	96.60	-34.57	peak
4		0.4714	52.04	-7.59	44.45	94.14	-49.69	peak
5		0.5916	58.20	-7.47	50.73	72.17	-21.44	peak
6		0.8251	49.19	-7.36	41.83	69.29	-27.46	peak

Between 30MHz – 1GHz

Temperature:	26 °C	Relative Humidity:	54%
Pressure:	101KPa	Phase:	Horizontal
Test Mode:	Mode 3	Test Voltage:	AC 120V/60Hz




Remark:

1. Factor = Antenna Factor + Cable Loss – Pre-amplifier.
2. Measurement = Reading Level + Correct Factor
3. Over = Measurement - Limit

No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over	
		MHz	dBuV	dB	dBuV/m	dB/m	dB	Detector
1	*	69.1141	45.53	-17.76	27.77	40.00	-12.23	QP
2		142.8243	44.17	-18.93	25.24	43.50	-18.26	QP
3		170.7926	47.73	-17.89	29.84	43.50	-13.66	QP
4		236.6447	41.24	-14.67	26.57	46.00	-19.43	QP
5		478.8456	41.66	-9.14	32.52	46.00	-13.48	QP
6		672.8444	32.52	-5.95	26.57	46.00	-19.43	QP

Temperature:	26 °C	Relative Humidity:	54%
Pressure:	101KPa	Phase :	Vertical
Test Mode:	Mode 3	Test Voltage:	AC 120V/60Hz




Remark:

1. Factor = Antenna Factor + Cable Loss – Pre-amplifier.
2. Measurement = Reading Level + Correct Factor
3. Over = Measurement - Limit

No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1	*	63.7588	54.48	-16.28	38.20	40.00	-1.80	QP
2		142.8243	52.39	-18.93	33.46	43.50	-10.04	QP
3		170.7926	51.87	-17.89	33.98	43.50	-9.52	QP
4		343.1800	38.17	-11.72	26.45	46.00	-19.55	QP
5		487.3151	40.89	-8.93	31.96	46.00	-14.04	QP
6		670.4893	33.79	-5.98	27.81	46.00	-18.19	QP

Temperature:	26 °C	Relative Humidity:	54%
Pressure:	101KPa	Phase :	Horizontal
Test Mode:	Mode 9	Test Voltage:	DC 10.8V




Remark:

- Factor = Antenna Factor + Cable Loss – Pre-amplifier.
- Measurement = Reading Level + Correct Factor
- Over = Measurement - Limit

No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over	Detector
		MHz	dBuV	dB	dBuV/m	dB/m	dB	
1		74.6569	31.93	-18.81	13.12	40.00	-26.88	QP
2	*	162.6106	49.52	-18.49	31.03	43.50	-12.47	QP
3		250.3012	40.55	-14.28	26.27	46.00	-19.73	QP
4		323.3204	42.38	-12.42	29.96	46.00	-16.04	QP
5		501.1790	31.86	-8.65	23.21	46.00	-22.79	QP
6		869.1302	27.05	-3.65	23.40	46.00	-22.60	QP

Temperature:	26 °C	Relative Humidity:	54%
Pressure:	101KPa	Phase :	Vertical
Test Mode:	Mode 9	Test Voltage:	DC 10.8V



Remark:

- Factor = Antenna Factor + Cable Loss – Pre-amplifier.
- Measurement = Reading Level + Correct Factor
- Over = Measurement - Limit

No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over	Detector
		MHz	dBuV	dB	dBuV/m	dB/m	dB	
1	*	73.6170	47.09	-18.63	28.46	40.00	-11.54	QP
2		162.0414	45.38	-18.54	26.84	43.50	-16.66	QP
3		337.2155	38.60	-11.93	26.67	46.00	-19.33	QP
4		501.1789	33.13	-8.65	24.48	46.00	-21.52	QP
5		625.0779	29.43	-6.59	22.84	46.00	-23.16	QP
6		948.7609	28.27	-2.94	25.33	46.00	-20.67	QP

8. Bandwidth Test

8.1 Test Procedure


1. Set RBW = 1%~5% OBW.
2. Set the video bandwidth (VBW) $\geq 3 \times$ RBW.
3. Detector = Peak.
4. Trace mode = max hold.
5. Sweep = auto couple.
6. Allow the trace to stabilize.
7. Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 20 dB relative to the maximum level measured in the fundamental emission.

8.2 Test Setup



8.3 Test Result

Frequency (kHz)	20dB bandwidth (Hz)	Result
122	81	Pass



9. Antenna Requirements

9.1 Limit

For intentional device, according to FCC 47 CFR Section 15.203, An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the provisions of this section. The manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

9.2 Test Result

The antenna used for this product is Inductive coil antenna.

10. EUT Photographs


EUT Photo 1





NOTE: Appendix-Photographs Of EUT Constructional Details

11. EUT Test Setup Photographs

Conducted emissions



Radiated Measurement Photos



STATEMENT

1. The equipment lists are traceable to the national reference standards.
2. The test report can not be partially copied unless prior written approval is issued from our lab.
3. The test report is invalid without the "special seal for inspection and testing".
4. The test report is invalid without the signature of the approver.
5. The test process and test result is only related to the Unit Under Test.
6. Sample information is provided by the client and the laboratory is not responsible for its authenticity.
7. The quality system of our laboratory is in accordance with ISO/IEC17025.
8. If there is any objection to this test report, the client should inform issuing laboratory within 15 days from the date of receiving test report.

Address:

1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China

TEL: 400-788-9558

P.C.: 518103

FAX: 0755-33229357

Website: <http://www.chnbctc.com>

E-Mail: bctc@bctc-lab.com.cn

***** END *****