

120.00 mm

540.00 mm

HelloBaby®

Ver: 1.0

User Manual

2.4GHz Digital Wireless Video Baby Monitor
2.4GHz Digital Wireless Video Baby Camera



Model: HB6256

The pictures are for reference only, please subject to practicality.

www.hellobaby.net.cn
service@hellobaby.net.cn

Thank you for purchasing the HB6256 Baby Monitor. With our baby monitor, you could see and hear your baby sleeping or playing in their room anytime.

Please return your original dated sales receipt for your records. For warranty service of your product, you will need to provide a copy of your dated sales receipt to confirm warranty status. Registration is not required for warranty coverage.

Please make sure the following included in your package

Parent unit x1	Camera unit x1	Power Adapter x2
User manual x1	Wall-mounting kit x1	

1. SAFETY INSTRUCTIONS
CAUTION: Keep the device away from children.
Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3ft (0.9m) away). Never use extension cords with AC Adapters. Only use the AC Adapters provided.
Choking hazard: This product contains small parts, please be careful when unpack and assemble the product.
Read and keep to instructions: All the safety and operating in instructions should be read before the video baby monitor is used. This product cannot replace responsible adult supervision.

Water and moisture: This product is designed for indoor use only. The unit should not be exposed to rain, moisture, dripping or splashing. No objects filled with liquid should be placed on top of, or beside the product, such as a glass or vase. This item should not be used near water.

DO NOT: Use the appliance if the cord or plug is damaged. If your baby monitor is not operating properly or has suffered any damage, contact "service@hellobaby.net.cn" service center to request inspection and repair of the appliance in order to avoid any possible risk.
DO NOT: be not attempt to repair or adjust any of the electrical or mechanical functions of the unit. Otherwise, the guarantee will be void.

Ventilation: This baby monitor should not be used on a bed, sofa, rug or similar surface that may block the ventilation openings, or be placed in an enclosed area such as a bookcase or drawer that may impede air flow.
Keep away from sources of heat: This unit should not be exposed to direct heat sources such as a candle, radiator, heater register, stove or other appliance that emits heat. The unit should not be left in direct sunlight.

Power source: This unit should only be used with the AC power adapter included in this package (rated 5V DC 3A).
Damage requiring service: This unit should be serviced by qualified personnel only when: Objects have fallen or liquid has been spilled into the product;
The units have been exposed to rain;

The units do not appear to operate normally or exhibits a distinct change in performance;
The units have been dropped or the enclosure damaged;

2. WARRANTY TERMS
We offer one-year warranty from the original purchase date against defects in workmanship and materials. If you have warranty or support issues, please contact our after-sales service via email.

3. INSTALLATION GUIDELINES
* To use your parent unit and camera unit together, you have to establish a radio link between them, and the range will be affected by environmental conditions.
* Any large metal object, like a refrigerator, a mirror, a filing cabinet, metallic doors or reinforced concrete between the baby and parent unit may block the radio signal.
* The signal strength may also be reduced by other solid structures, like walls, or by radio or electrical equipment, such as TV, computers, cordless or mobile phones, fluorescent lights or dimmer switches.
* Use of other 2.4GHz product, such as wireless networks (Wi-Fi routers), Bluetooth systems, or microwave ovens, may cause interference with this product, so keep the baby monitor away at least 3ft (1.5m) from such products, or turn them off if they cause interference.

4. PLACEMENT OF THE BABY MONITOR
The camera can be placed on the desktop or mounted on the wall. Don't place baby monitor on soft quilts or blankets in the corners of cupboards, shelves, etc. Keep the baby monitor away from heat sources such as radiators, chimneys, cookers and direct sunlight. Keep the baby unit away from TV sets, microwave oven and radios. If interference occurs, move the camera to elsewhere.
* Place the camera within 6 feet (2 meters) of the area being monitored for optimum performance.



5. GETTING STARTED
5.1 TURN ON THE BABY UNIT:
1. Insert the DC plug of the power adapter into the DC jack in the rear of the Baby Unit;
2. Insert the other end of the power adapter into a suitable electrical outlet;
3. Once the adapter is connected, the power LED will light up.

5.2 TURN ON THE PARENT UNIT:
1. Insert the DC plug of the power adapter into the DC Jack in the side of the parent unit;
2. Insert the other end of the power adapter into a suitable electrical outlet;
3. Press and hold the power key 3 seconds on the side of the parent unit;
4. Once parent unit is on, the power LED will light up and the image will display on the LCD

5.3 INFRARED NIGHT VISION (AUTOMATIC)
The infrared night vision function allows the camera to pick up images in dark or low light conditions. In this mode, only black and white images will be displayed on the monitor. The optimum image lies in where baby unit is 6ft (2m) away from object. The camera is in night vision mode, the icon will be displayed on the top of screen.

6. PRODUCT OVERVIEW
6.1 ICONS OVERVIEW:

Signal Strength	Volume	Zoom
Alarm	Brightness	Two-Way Talk
Lullaby	Night vision	Battery Level
Camera	Energy Saving	Temperature



7. KEY OPERATION
7.1 TURN ON/OFF
Press and hold the power key for 3 seconds to turn on / off the parents unit.
7.2 UP & KEY
Press once to tilt the camera up by one step. Press and hold to tilt continuously.
7.3 DOWN & KEY
Press once to tilt the camera down by one step. Press and hold to tilt continuously.
7.4 LEFT & KEY
Press once to pan the camera left by one step. Press and hold to pan continuously.
7.5 RIGHT & KEY
Press once to pan the camera right by one step. Press and hold to pan continuously.


7.6 CAMERA VIEW/SCAN
Press scan key to view/scan camera. During scan mode, the scan icon will be displayed on the top of screen. Each camera's view will be displayed on the LCD around 10 seconds then change to next camera.

7.7 DIGITAL ZOOM
Press zoom in key to zoom in. Press zoom out key to zoom out. Press zoom in/out key around 2 seconds to operate zoom in/out.
7.8 Two Way Talk
Press and hold key to enter two way talk mode. A microphone icon will be displayed in the corner of the LCD screen. Release the key to stop.
Note: When you are in the two-way talk mode, the parent unit speaker is muted.

8. MENU OPERATION
8.1 PAIRING THE CAMERA AND PARENT UNITS
The baby unit is pre-registered to your parent unit. You do not need to register it again unless the baby unit loses its link with the parent unit. To re-register your baby unit, or register a

WARNING
Strangulation Hazard: Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3 ft (0.9 m) away). Do not remove this tag.

AVERTISSEMENT
DANGER D'ÉTRANGLEMENT: Des enfants se sont ÉTRANGLÉS avec des cordons électriques. Gardez le cordon/électrique hors de la portée des enfants (à plus de 0.9m/3 pi du lit d'enfant). Ne pas enlever cette étiquette.



new baby unit, follow the procedure below:
Note: Camera icon with "✓" means it is well registered. You should select and pair with the camera icon without "✓" sign.
8.1.1 ADD CAMERA
1. Press the MENU key then the menu will pop up;
2. Press the key until the camera icon is selected by red box;
3. Press the key to enter into sub-menu, then press the key to select your desired camera;
4. Press the key to enter into sub-menu; Press the key to select the camera; then press the key;
5. When the icon is displayed on the LCD screen, press the PAIR button on the back of camera;
6. Once paired, Successful pairing icon shows on the LCD screen;
7. If fails, repeat the above steps.

8.1.2 DELETE CAMERA
1. Press the MENU key and the menu will pop up;
2. Press the key until the camera icon is selected by red box;
3. Press the key to enter into sub-menu, then press the key to select the camera you want to delete;
4. Press the key to enter into sub-menu; Press the key to select the camera; then press the key;
5. Press the key to select the icon to delete the camera;
6. Press the key to confirm the option.

8.2 VOLUME
1. Press the key then the menu will pop up;
2. Press the key until the volume icon is selected by red box;
3. Press the key to enter into sub-menu, then press the key to select the volume level you want to set;
4. Press the key to confirm the option.

8.3 DISPLAY BRIGHTNESS
1. Press the MENU key then the menu will pop up;
2. Press the key until the brightness icon is selected by red box;
3. Press the key to enter into sub-menu; Press the key to select the brightness level you want to set;
4. Press the key to confirm the option.

8.4 TEMPERATURE UNIT SETTING
1. Press the MENU key then the menu will pop up;
2. Press the key until the temperature icon is selected by red box;
3. Press the key to enter into sub-menu;
4. Press the key to select the °F or °C for setting temperature unit;
5. Press the key to confirm the option.

Note: The detected temperature range is 0°-40 °C.

8.4.1 TEMPERATURE ALARM SETTING
1. Press the key until the alarm icon is selected by red box;
2. Press the key to confirm the option;
3. Press the key to confirm the option;
4. Press the key to confirm the option;
5. Press the key to confirm the option;
6. Press the key to confirm the option;
7. Press the key to confirm the option;
8. Press the key to confirm the option;
9. Press the key to confirm the option;
10. Press the key to confirm the option;
11. Press the key to confirm the option;
12. Press the key to confirm the option;
13. Press the key to confirm the option;
14. Press the key to confirm the option;
15. Press the key to confirm the option;
16. Press the key to confirm the option;
17. Press the key to confirm the option;
18. Press the key to confirm the option;
19. Press the key to confirm the option;
20. Press the key to confirm the option;
21. Press the key to confirm the option;
22. Press the key to confirm the option;
23. Press the key to confirm the option;
24. Press the key to confirm the option;
25. Press the key to confirm the option;
26. Press the key to confirm the option;
27. Press the key to confirm the option;
28. Press the key to confirm the option;
29. Press the key to confirm the option;
30. Press the key to confirm the option;
31. Press the key to confirm the option;
32. Press the key to confirm the option;
33. Press the key to confirm the option;
34. Press the key to confirm the option;
35. Press the key to confirm the option;
36. Press the key to confirm the option;
37. Press the key to confirm the option;
38. Press the key to confirm the option;
39. Press the key to confirm the option;
40. Press the key to confirm the option;
41. Press the key to confirm the option;
42. Press the key to confirm the option;
43. Press the key to confirm the option;
44. Press the key to confirm the option;
45. Press the key to confirm the option;
46. Press the key to confirm the option;
47. Press the key to confirm the option;
48. Press the key to confirm the option;
49. Press the key to confirm the option;
50. Press the key to confirm the option;
51. Press the key to confirm the option;
52. Press the key to confirm the option;
53. Press the key to confirm the option;
54. Press the key to confirm the option;
55. Press the key to confirm the option;
56. Press the key to confirm the option;
57. Press the key to confirm the option;
58. Press the key to confirm the option;
59. Press the key to confirm the option;
60. Press the key to confirm the option;
61. Press the key to confirm the option;
62. Press the key to confirm the option;
63. Press the key to confirm the option;
64. Press the key to confirm the option;
65. Press the key to confirm the option;
66. Press the key to confirm the option;
67. Press the key to confirm the option;
68. Press the key to confirm the option;
69. Press the key to confirm the option;
70. Press the key to confirm the option;
71. Press the key to confirm the option;
72. Press the key to confirm the option;
73. Press the key to confirm the option;
74. Press the key to confirm the option;
75. Press the key to confirm the option;
76. Press the key to confirm the option;
77. Press the key to confirm the option;
78. Press the key to confirm the option;
79. Press the key to confirm the option;
80. Press the key to confirm the option;
81. Press the key to confirm the option;
82. Press the key to confirm the option;
83. Press the key to confirm the option;
84. Press the key to confirm the option;
85. Press the key to confirm the option;
86. Press the key to confirm the option;
87. Press the key to confirm the option;
88. Press the key to confirm the option;
89. Press the key to confirm the option;
90. Press the key to confirm the option;
91. Press the key to confirm the option;
92. Press the key to confirm the option;
93. Press the key to confirm the option;
94. Press the key to confirm the option;
95. Press the key to confirm the option;
96. Press the key to confirm the option;
97. Press the key to confirm the option;
98. Press the key to confirm the option;
99. Press the key to confirm the option;
100. Press the key to confirm the option;

8.4.2 SET TEMPERATURE/H2O ALERT LIMITS
1. Press the key to select the limit;
2. Press the key to select the limit;
3. Press the key to select the limit;
4. Press the key to select the limit;
5. Press the key to select the limit;
6. Press the key to select the limit;
7. Press the key to select the limit;
8. Press the key to select the limit;
9. Press the key to select the limit;
10. Press the key to select the limit;
11. Press the key to select the limit;
12. Press the key to select the limit;
13. Press the key to select the limit;
14. Press the key to select the limit;
15. Press the key to select the limit;
16. Press the key to select the limit;
17. Press the key to select the limit;
18. Press the key to select the limit;
19. Press the key to select the limit;
20. Press the key to select the limit;
21. Press the key to select the limit;
22. Press the key to select the limit;
23. Press the key to select the limit;
24. Press the key to select the limit;
25. Press the key to select the limit;
26. Press the key to select the limit;
27. Press the key to select the limit;
28. Press the key to select the limit;
29. Press the key to select the limit;
30. Press the key to select the limit;
31. Press the key to select the limit;
32. Press the key to select the limit;
33. Press the key to select the limit;
34. Press the key to select the limit;
35. Press the key to select the limit;
36. Press the key to select the limit;
37. Press the key to select the limit;
38. Press the key to select the limit;
39. Press the key to select the limit;
40. Press the key to select the limit;
41. Press the key to select the limit;
42. Press the key to select the limit;
43. Press the key to select the limit;
44. Press the key to select the limit;
45. Press the key to select the limit;
46. Press the key to select the limit;
47. Press the key to select the limit;
48. Press the key to select the limit;
49. Press the key to select the limit;
50. Press the key to select the limit;
51. Press the key to select the limit;
52. Press the key to select the limit;
53. Press the key to select the limit;
54. Press the key to select the limit;
55. Press the key to select the limit;
56. Press the key to select the limit;
57. Press the key to select the limit;
58. Press the key to select the limit;
59. Press the key to select the limit;
60. Press the key to select the limit;
61. Press the key to select the limit;
62. Press the key to select the limit;
63. Press the key to select the limit;
64. Press the key to select the limit;
65. Press the key to select the limit;
66. Press the key to select the limit;
67. Press the key to select the limit;
68. Press the key to select the limit;
69. Press the key to select the limit;
70. Press the key to select the limit;
71. Press the key to select the limit;
72. Press the key to select the limit;
73. Press the key to select the limit;
74. Press the key to select the limit;
75. Press the key to select the limit;
76. Press the key to select the limit;
77. Press the key to select the limit;
78. Press the key to select the limit;
79. Press the key to select the limit;
80. Press the key to select the limit;
81. Press the key to select the limit;
82. Press the key to select the limit;
83. Press the key to select the limit;
84. Press the key to select the limit;
85. Press the key to select the limit;
86. Press the key to select the limit;
87. Press the key to select the limit;
88. Press the key to select the limit;
89. Press the key to select the limit;
90. Press the key to select the limit;
91. Press the key to select the limit;
92. Press the key to select the limit;
93. Press the key to select the limit;
94. Press the key to select the limit;
95. Press the key to select the limit;
96. Press the key to select the limit;
97. Press the key to select the limit;
98. Press the key to select the limit;
99. Press the key to select the limit;
100. Press the key to select the limit;

8.5 LULLABY SETTING
You can soothe the baby to sleep by playing a gentle lullaby from the Camera unit.
1. Press the MENU key and the menu will pop up;
2. Press the key until the lullaby icon is selected by red box;
3. Press the key to enter into sub-menu;
4. Press the key to select the lullaby you want to play;
5. Press the key to confirm the option;

8.6 ALARM SETTING
1. Press the MENU key and the menu will pop up;
2. Press the key until the alarm icon is selected by red box;
3. Press the key to enter into sub-menu; Press the key to select the alarm time you need;
4. Press the key to confirm the option;

Note: The minimum unit is 0.5 hour. The maximum setting is 5 hours (7 levels).
Note: Once the alarm is turned on, alarm icon will display on the screen.
Note: The alarm default setting is OFF.
Note: When the alarm is sounding, press any key on the parent unit to turn the alarm off.
Note: 5. If you don't turn off the alarm, the alarm will ring for 1 minute. After three minutes the alarm will ring again for 1 minute. The alarm will ring for three times in total, after this the alarm goes off.

8.7 ENERGY SAVING
The device allows you to control the sound activation of your baby unit. If there is no sound around the baby unit within 30 seconds, it will stop audio transmission and turn off the

screen of the parent unit. When the baby unit detects any sounds louder than the sensitivity level, it will start transmitting the signal to the parent unit again and turn on the screen of the parent unit. To change the ECO level, please follow the below instructions.
1. Press the MENU key and the menu will pop up;
2. Press the key until the ECO icon is selected by red box;
3. Press the key to enter into sub-menu, then press the key to select desired level;
4. Press the key to confirm the option;
5. Press the key to confirm the option;
6. Press the key to confirm the option;
7. Press the key to confirm the option;
8. Press the key to confirm the option;
9. Press the key to confirm the option;
10. Press the key to confirm the option;
11. Press the key to confirm the option;
12. Press the key to confirm the option;
13. Press the key to confirm the option;
14. Press the key to confirm the option;
15. Press the key to confirm the option;
16. Press the key to confirm the option;
17. Press the key to confirm the option;
18. Press the key to confirm the option;
19. Press the key to confirm the option;
20. Press the key to confirm the option;
21. Press the key to confirm the option;
22. Press the key to confirm the option;
23. Press the key to confirm the option;
24. Press the key to confirm the option;
25. Press the key to confirm the option;
26. Press the key to confirm the option;
27. Press the key to confirm the option;
28. Press the key to confirm the option;
29. Press the key to confirm the option;
30. Press the key to confirm the option;
31. Press the key to confirm the option;
32. Press the key to confirm the option;
33. Press the key to confirm the option;
34. Press the key to confirm the option;
35. Press the key to confirm the option;
36. Press the key to confirm the option;
37. Press the key to confirm the option;
38. Press the key to confirm the option;
39. Press the key to confirm the option;
40. Press the key to confirm the option;
41. Press the key to confirm the option;
42. Press the key to confirm the option;
43. Press the key to confirm the option;
44. Press the key to confirm the option;
45. Press the key to confirm the option;
46. Press the key to confirm the option;
47. Press the key to confirm the option;
48. Press the key to confirm the option;
49. Press the key to confirm the option;
50. Press the key to confirm the option;
51. Press the key to confirm the option;
52. Press the key to confirm the option;
53. Press the key to confirm the option;
54. Press the key to confirm the option;
55. Press the key to confirm the option;
56. Press the key to confirm the option;
57. Press the key to confirm the option;
58. Press the key to confirm the option;
59. Press the key to confirm the option;
60. Press the key to confirm the option;
61. Press the key to confirm the option;
62. Press the key to confirm the option;
63. Press the key to confirm the option;
64. Press the key to confirm the option;
65. Press the key to confirm the option;
66. Press the key to confirm the option;
67. Press the key to confirm the option;
68. Press the key to confirm the option;
69. Press the key to confirm the option;
70. Press the key to confirm the option;
71. Press the key to confirm the option;
72. Press the key to confirm the option;
73. Press the key to confirm the option;
74. Press the key to confirm the option;
75. Press the key to confirm the option;
76. Press the key to confirm the option;
77. Press the key to confirm the option;
78. Press the key to confirm the option;
79. Press the key to confirm the option;
80. Press the key to confirm the option;
81. Press the key to confirm the option;
82. Press the key to confirm the option;
83. Press the key to confirm the option;
84. Press the key to confirm the option;
85. Press the key to confirm the option;
86. Press the key to confirm the option;
87. Press the key to confirm the option;
88. Press the key to confirm the option;
89. Press the key to confirm the option;
90. Press the key to confirm the option;
91. Press the key to confirm the option;
92. Press the key to confirm the option;
93. Press the key to confirm the option;
94. Press the key to confirm the option;
95. Press the key to confirm the option;
96. Press the key to confirm the option;
97. Press the key to confirm the option;
98. Press the key to confirm the option;
99. Press the key to confirm the option;
100. Press the key to confirm the option;

8.8 LANGUAGE SETTING
1. Press the MENU key and the menu will pop up;
2. Press the key until the language icon is selected by red box;
3. Press the key to enter into sub-menu; Press the key to select the language you need;
4. Press the key to confirm the option;

Frequency	2412MHz/2469MHz
Power Adapter	Parent Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A Camera Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A
Operating Range	Up to 1000ft (300m) outdoor (line of sight) Up to 165ft (50m) indoor
Display	5.0" Diagonal TFT LCD Resolution: 800x480 (14.8WV)
Battery (Parent Unit)	Up to 22 hours
Main power power	<1500mW
Operation environment	Operation Temperature: +32°F/+04F (0°C~+0°C) Battery Charging Temperature: +50°F/+104F (10°C~+40°C) Relative Humidity: 15%-85%

10. TROUBLE SHOOTING
No reception on the monitor
* The power adapters may not be properly connected;
* Confirmed the camera and monitor are ON;
* Camera may be far away from the monitor;
* Camera and monitor may not be properly paired; follow PAIRING instructions;
* Increase the separation between the equipment and receiver.
Interference or poor reception
* The camera or monitor may be placed too close to many metal objects;
* Other electronic devices may be interfering with the signal;
* The battery power may be too low;
* The camera and monitor may be placed too close;
* The volume on the monitor may be set too high;
* Repower the baby unit plug out the adapter, then plug it into the socket again;
* Press the RESET key at the back of parent unit
Audio feedback (high pitched noise)
* The camera and monitor may be placed too close;
* The volume on the monitor may be set too high;
* Repower the baby unit plug out the adapter, then plug it into the socket again;
* Press the RESET key at the back of parent unit
Frozen Picture on Screen
* The camera and monitor may be placed too close;
* The volume on the monitor may be set too high;
* Repower the baby unit plug out the adapter, then plug it into the socket again;
* Press the RESET key at the back of parent unit

11. MAINTENANCE
1. Clean your baby monitor with a slightly damp or anti-static cloth.
2. Never use cleaning agents or solvents.
3. Remember to dispose of the product in an environmentally responsible way.
4. For proper collection and processing of these products, take them to the collection points designated by local authorities. You can also contact the store where you purchased the product.
5. Improper or incorrect use of batteries may cause corrosion or battery leakage, which could cause personal injury or damage to property. Use only the types of the batteries that are indicated in the instructions.
6. CAUTION: Risk of Fire and Burns. Do Not Open, Crush, Heat Above 45 degree C or Incinerate. Follow Manufacturer's Instructions.
7. Dispose of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that will result in an explosion.
8. Leaving a battery in an extremely high temperature surrounding environment that can result in an explosion or the leakage of flammable liquid or gas.
9. A battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas.
10. The battery shall not be exposed to excessive heat such as sunshine, fire or the like;

FCC/ISED Statement
This device complies with Part 15 of the FCC Rules and with Industry Canada licence-exempt RSS (standards). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Cet appareil est conforme à la partie 15 des règles de la FCC et aux normes RSS exemptées de licence d'Industrie Canada. Le fonctionnement est soumis aux deux conditions suivantes: (1) l'appareil ne doit pas causer d'interférences nuisibles, et (2) l'appareil doit accepter toute interférence reçue, y compris les interférences pouvant entraîner un fonctionnement indésirable.
Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102 RF exposure, users can obtain Canadian information on RF exposure and compliance.
Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cr. 102 et conforme avec les RSS 102 de l'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité.
Cet équipement est exempté de l'évaluation des limites de l'exposition aux champs RF pour un environnement non contrôlé.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non contrôlé.
Radiation Exposure Statement for camera
This camera has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102 RF exposure, users can obtain Canadian information on RF exposure and compliance.
Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cr. 102 et conforme avec les RSS 102 de l'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité.
Cet équipement est exempté de l'évaluation des limites de l'exposition aux champs RF pour un environnement non contrôlé.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non contrôlé.
Radiation Exposure Statement for camera
This camera has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102 RF exposure, users can obtain Canadian information on RF exposure and compliance.
Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cr. 102 et conforme avec les RSS 102 de l'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité.
Cet équipement est exempté de l'évaluation des limites de l'exposition aux champs RF pour un environnement non contrôlé.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non contrôlé.
Radiation Exposure Statement for camera
This camera has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102 RF exposure, users can obtain Canadian information on RF exposure and compliance.
Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cr. 102 et conforme avec les RSS 102 de l'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité.
Cet équipement est exempté de l'évaluation des limites de l'exposition aux champs RF pour un environnement non contrôlé.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non contrôlé.
Radiation Exposure Statement for camera
This camera has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102 RF exposure, users can obtain Canadian information on RF exposure and compliance.
Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cr. 102 et conforme avec les RSS 102 de l'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité.
Cet équipement est exempté de l'évaluation des limites de l'exposition aux champs RF pour un environnement non contrôlé.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non contrôlé.
Radiation Exposure Statement for camera
This camera has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
This device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS 102 RF exposure, users can obtain Canadian information on RF exposure and compliance.
Cet appareil est conforme à l'exemption des limites d'évaluation courantes dans la section 2.5 du cr. 102 et conforme avec les RSS 102 de l'exposition aux RF, les utilisateurs peuvent obtenir des données canadiennes sur l'exposition aux champs RF à la conformité.
Cet équipement est exempté de l'évaluation des limites de l'exposition aux champs RF pour un environnement non contrôlé.
Cet équipement est conforme aux limites d'exposition aux rayonnements du Canada établies pour un environnement non contrôlé.
Radiation Exposure Statement for camera
This