

RF Exposure Report

Report No.: SA150423E12

FCC ID: UZ7RFD8500

Test Model: RFD8500

Received Date: Apr. 23, 2015

Test Date: June 17, 2015

Issued Date: July 20, 2015

Applicant: Zebra Technologies Corporation

Address: 1 Zebra Plaza, Holtsville, NY 11742

Manufacturer: Zebra Technologies Corporation

Address: 1 Zebra Plaza, Holtsville, NY 11742

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch
Hsin Chu Laboratory

Lab Address: No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.

Test Location (1): No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.

Test Location (2): No. 49, Ln. 206, Wende Rd., Shangshan Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by any government agencies.



Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
3 Antenna Gain	5
4 Calculation Result Of Maximum Conducted Power	6



A D T

Release Control Record

Issue No.	Description	Date Issued
SA150423E12	Original release.	July 20, 2015

1 Certificate of Conformity

Product: RFD8500 UHF RFID READER

Brand: ZEBRA

Test Model: RFD8500

Sample Status: ENGINEERING SAMPLE

Applicant: Zebra Technologies Corporation

Test Date: June 17, 2015


Standards: FCC Part 2 (Section 2.1091)

KDB 447498 D03

IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by :  , **Date:** July 20, 2015
Claire Kuan / Specialist

Approved by :  , **Date:** July 20, 2015
May Chen / Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm ²)	AVERAGE TIME (minutes)
LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE				
1.34-30	824/f	2.19/f	*(180/f ²)	30
30-300	27.5	0.073	0.2	30
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

*Plane-wave equivalent power density

2.2 MPE Calculation Formula

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 23cm away from the body of the user.

3 Antenna Gain

The antenna provided to the EUT, please refer to the following table:

The antenna provided to the ESI, please refer to the following table.

Bluetooth							
No.	Brand	Antenna Type	Gain (dBi) < excluded cable loss>	Connector Type	Frequency range (MHz)	Cable Loss (dB)	
1	Auden	PIFA and PCB chip	2.6	NA	2400~2483.5	1	
RFID Antenna Spec.							
No.	Brand	Antenna Type	Gain (dBi) < included cable loss>	Connector Type	Frequency range (MHz)	Cable Loss (dB)	Cable Length (mm)
1	Auden	Patch	4.63	U.fl	902~928	0.4	130

4 Calculation Result Of Maximum Conducted Power

For BT-EDR:

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2402-2480	3.428	1.6	23	0.00075	1

For BT-LE:

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2402-2480	2.188	1.6	23	0.00028	1

For RFID:

RFID Power	
Max Avg. Power (mW)	*Max Time Avg. Power (mW)
679.204	428.549

*Time Avg. power was measured from power meter in frequency hopping mode

Frequency Band (MHz)	Max Time Avg. Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
902.75-927.25	428.549	4.63	23	0.18721	0.61816

Conclusion:

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

Bluetooth + RFID = $(0.00075 / 1) + (0.18721 / 0.61816) = 0.304$

Therefore the maximum calculations of above situations are less than the "1" limit.

--- END ---