









Mode	18																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-2C_5.47-5.725_802.11n HT20_CH140_5700MHz																																																																																																																			
ANT	SISO																																																																																																																			
Pol.	Horizontal								Vertical																																																																																																											
Peak Avg																																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11400.00</td><td>49.05</td><td>74.00</td><td>-24.95</td><td>46.87</td><td>38.12</td><td>14.78</td><td>50.72</td><td>--- --- Peak</td></tr><tr><td>2</td><td>17100.00</td><td>49.62</td><td>68.30</td><td>-18.68</td><td>41.89</td><td>42.00</td><td>17.53</td><td>51.80</td><td>--- --- Peak</td></tr></table>									Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	11400.00	49.05	74.00	-24.95	46.87	38.12	14.78	50.72	--- --- Peak	2	17100.00	49.62	68.30	-18.68	41.89	42.00	17.53	51.80	--- --- Peak	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11400.00</td><td>48.88</td><td>74.00</td><td>-25.12</td><td>46.70</td><td>38.12</td><td>14.78</td><td>50.72</td><td>--- --- Peak</td></tr><tr><td>2</td><td>17100.00</td><td>49.86</td><td>68.30</td><td>-18.44</td><td>42.13</td><td>42.00</td><td>17.53</td><td>51.80</td><td>--- --- Peak</td></tr></table>									Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	11400.00	48.88	74.00	-25.12	46.70	38.12	14.78	50.72	--- --- Peak	2	17100.00	49.86	68.30	-18.44	42.13	42.00	17.53	51.80	--- --- Peak
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																											
	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																											
1	11400.00	49.05	74.00	-24.95	46.87	38.12	14.78	50.72	--- --- Peak																																																																																																											
2	17100.00	49.62	68.30	-18.68	41.89	42.00	17.53	51.80	--- --- Peak																																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																											
1	11400.00	48.88	74.00	-25.12	46.70	38.12	14.78	50.72	--- --- Peak																																																																																																											
2	17100.00	49.86	68.30	-18.44	42.13	42.00	17.53	51.80	--- --- Peak																																																																																																											







		19																																																																																															
Mode		Band Edge - L																																																																																															
		U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																																																																															
ANT		SISO																																																																																															
Pol.		Horizontal					Fundamental																																																																																										
Peak																																																																																																	
	<table><tr><th colspan="2"></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5149.06</td><td>58.01</td><td>74.00</td><td>-15.99</td><td>43.83</td><td>34.87</td><td>11.09</td><td>31.78</td><td>354</td><td>266</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5149.06	58.01	74.00	-15.99	43.83	34.87	11.09	31.78	354	266	PEAK	<table><tr><th colspan="2"></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5190.00</td><td>96.83</td><td>-----</td><td>-----</td><td>82.74</td><td>34.86</td><td>11.06</td><td>31.83</td><td>354</td><td>266</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5190.00	96.83	-----	-----	82.74	34.86	11.06	31.83	354	266
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	5149.06	58.01	74.00	-15.99	43.83	34.87	11.09	31.78	354	266	PEAK																																																																																						
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	5190.00	96.83	-----	-----	82.74	34.86	11.06	31.83	354	266	PEAK																																																																																						
Avg																																																																																																	
	<table><tr><th colspan="2"></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5149.83</td><td>48.15</td><td>54.00</td><td>-5.85</td><td>33.97</td><td>34.87</td><td>11.09</td><td>31.78</td><td>354</td><td>266</td><td>AVERAGE</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5149.83	48.15	54.00	-5.85	33.97	34.87	11.09	31.78	354	266	AVERAGE	<table><tr><th colspan="2"></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5190.00</td><td>91.05</td><td>-----</td><td>-----</td><td>76.96</td><td>34.86</td><td>11.06</td><td>31.83</td><td>354</td><td>266</td><td>AVERAGE</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5190.00	91.05	-----	-----	76.96	34.86	11.06	31.83	354	266
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	5149.83	48.15	54.00	-5.85	33.97	34.87	11.09	31.78	354	266	AVERAGE																																																																																						
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																								
1	5190.00	91.05	-----	-----	76.96	34.86	11.06	31.83	354	266	AVERAGE																																																																																						







Mode	19																																									
	Band Edge - R																																									
	U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																									
ANT	SISO																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2023-08-31 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5383.19</td><td>52.64</td><td>74.00</td><td>-21.36</td><td>38.97</td><td>34.82</td><td>10.92</td><td>32.07</td><td>354 266 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5383.19	52.64	74.00	-21.36	38.97	34.82	10.92	32.07	354 266 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5383.19	52.64	74.00	-21.36	38.97	34.82	10.92	32.07	354 266 PEAK																																	
Avg	Date: 2023-08-31 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5373.76</td><td>43.28</td><td>54.00</td><td>-10.72</td><td>29.58</td><td>34.83</td><td>10.93</td><td>32.06</td><td>354 266 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5373.76	43.28	54.00	-10.72	29.58	34.83	10.93	32.06	354 266 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5373.76	43.28	54.00	-10.72	29.58	34.83	10.93	32.06	354 266 AVERAGE																																	



Mode	19																																																																																	
	Band Edge - L																																																																																	
	U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																																																																	
ANT	SISO																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2023-08-30  5000 5038 5076 5114 5152 5190 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5146.79</td><td>62.47</td><td>74.00</td><td>-11.53</td><td>48.29</td><td>34.87</td><td>11.09</td><td>31.78</td><td>200 164 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5146.79	62.47	74.00	-11.53	48.29	34.87	11.09	31.78	200 164 PEAK	Level (dBuV/m) Date: 2023-08-30  1000 2200 3400 4600 5800 7000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5190.00</td><td>99.26</td><td>-----</td><td>85.15</td><td>34.86</td><td>11.07</td><td>31.82</td><td>200</td><td>164 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	99.26	-----	85.15	34.86	11.07	31.82	200	164 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5146.79	62.47	74.00	-11.53	48.29	34.87	11.09	31.78	200 164 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5190.00	99.26	-----	85.15	34.86	11.07	31.82	200	164 PEAK																																																																									
Avg	Level (dBuV/m) Date: 2023-08-30  5000 5038 5076 5114 5152 5190 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5149.82</td><td>49.92</td><td>54.00</td><td>-4.08</td><td>35.74</td><td>34.87</td><td>11.09</td><td>31.78</td><td>200 164 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5149.82	49.92	54.00	-4.08	35.74	34.87	11.09	31.78	200 164 AVERAGE	Level (dBuV/m) Date: 2023-08-30  1000 2200 3400 4600 5800 7000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5190.00</td><td>92.94</td><td>-----</td><td>78.83</td><td>34.86</td><td>11.07</td><td>31.82</td><td>200</td><td>164 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	92.94	-----	78.83	34.86	11.07	31.82	200	164 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5149.82	49.92	54.00	-4.08	35.74	34.87	11.09	31.78	200 164 AVERAGE																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5190.00	92.94	-----	78.83	34.86	11.07	31.82	200	164 AVERAGE																																																																									



		20																																																																																							
Mode		Band Edge - L																																																																																							
		U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz																																																																																							
ANT		SISO																																																																																							
Pol.		Horizontal					Fundamental																																																																																		
Peak																																																																																									
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5031.63</td><td>53.03</td><td>74.00</td><td>-20.97</td><td>38.62</td><td>34.89</td><td>11.15</td><td>31.63</td><td>304</td><td>179 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5031.63	53.03	74.00	-20.97	38.62	34.89	11.15	31.63	304	179 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5230.00</td><td>99.33</td><td>-----</td><td>-----</td><td>85.32</td><td>34.85</td><td>11.04</td><td>31.88</td><td>304</td><td>179 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5230.00	99.33	-----	-----	85.32	34.85	11.04	31.88	304
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5031.63	53.03	74.00	-20.97	38.62	34.89	11.15	31.63	304	179 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5230.00	99.33	-----	-----	85.32	34.85	11.04	31.88	304	179 PEAK																																																																																
Avg																																																																																									
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5103.85</td><td>43.76</td><td>54.00</td><td>-10.24</td><td>29.49</td><td>34.88</td><td>11.11</td><td>31.72</td><td>304</td><td>179 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5103.85	43.76	54.00	-10.24	29.49	34.88	11.11	31.72	304	179 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5230.00</td><td>93.22</td><td>-----</td><td>-----</td><td>79.21</td><td>34.85</td><td>11.04</td><td>31.88</td><td>304</td><td>179 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5230.00	93.22	-----	-----	79.21	34.85	11.04	31.88	304
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5103.85	43.76	54.00	-10.24	29.49	34.88	11.11	31.72	304	179 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5230.00	93.22	-----	-----	79.21	34.85	11.04	31.88	304	179 AVERAGE																																																																																





Mode	20																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz																																										
ANT	SISO																																										
Pol.	Horizontal	Fundamental																																									
Peak	Date: 2023-08-31 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5394.59</td><td>52.87</td><td>74.00</td><td>-21.13</td><td>39.22</td><td>34.82</td><td>10.91</td><td>32.08</td><td>304</td><td>179 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5394.59	52.87	74.00	-21.13	39.22	34.82	10.91	32.08	304	179 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5394.59	52.87	74.00	-21.13	39.22	34.82	10.91	32.08	304	179 PEAK																																	
Avg	Date: 2023-08-31 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5359.15</td><td>43.86</td><td>54.00</td><td>-10.14</td><td>30.13</td><td>34.83</td><td>10.94</td><td>32.04</td><td>304</td><td>179 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5359.15	43.86	54.00	-10.14	30.13	34.83	10.94	32.04	304	179 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5359.15	43.86	54.00	-10.14	30.13	34.83	10.94	32.04	304	179 AVERAGE																																	



Mode	20	
	Band Edge - L	
	U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz	
ANT	SISO	
Pol.	Vertical	Fundamental
Peak	<	



Mode	20																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz																																										
ANT	SISO																																										
Pol.	Vertical	Fundamental																																									
Peak	Level (dBuV/m)Date: 2023-08-31  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5374.35</td><td>53.30</td><td>74.00</td><td>-20.70</td><td>39.60</td><td>34.83</td><td>10.93</td><td>32.06</td><td>100</td><td>218 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5374.35	53.30	74.00	-20.70	39.60	34.83	10.93	32.06	100	218 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5374.35	53.30	74.00	-20.70	39.60	34.83	10.93	32.06	100	218 PEAK																																	
Avg	Level (dBuV/m)Date: 2023-08-31  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5351.81</td><td>44.27</td><td>54.00</td><td>-9.73</td><td>30.53</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>218 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5351.81	44.27	54.00	-9.73	30.53	34.83	10.94	32.03	100	218 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5351.81	44.27	54.00	-9.73	30.53	34.83	10.94	32.03	100	218 AVERAGE																																	



Mode	21																																																																											
	Band Edge - L																																																																											
	U-NII-2A_5.25-5.35_802.11n HT40_CH54_5270MHz																																																																											
ANT	SISO																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5129.76</td><td>53.65</td><td>74.00</td><td>-20.35</td><td>39.44</td><td>34.87</td><td>11.10</td><td>31.76</td><td>306 179 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5129.76	53.65	74.00	-20.35	39.44	34.87	11.10	31.76	306 179 PEAK	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5270.00</td><td>100.43</td><td>-----</td><td>-----</td><td>86.49</td><td>34.85</td><td>11.01</td><td>31.92</td><td>306 179 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5270.00	100.43	-----	-----	86.49	34.85	11.01	31.92	306 179 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5129.76	53.65	74.00	-20.35	39.44	34.87	11.10	31.76	306 179 PEAK																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5270.00	100.43	-----	-----	86.49	34.85	11.01	31.92	306 179 PEAK																																																																			
Avg	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5046.79</td><td>44.02</td><td>54.00</td><td>-9.98</td><td>29.64</td><td>34.89</td><td>11.14</td><td>31.65</td><td>306 179 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5046.79	44.02	54.00	-9.98	29.64	34.89	11.14	31.65	306 179 AVERAGE	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5270.00</td><td>94.64</td><td>-----</td><td>-----</td><td>80.70</td><td>34.85</td><td>11.01</td><td>31.92</td><td>306 179 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5270.00	94.64	-----	-----	80.70	34.85	11.01	31.92	306 179 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5046.79	44.02	54.00	-9.98	29.64	34.89	11.14	31.65	306 179 AVERAGE																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5270.00	94.64	-----	-----	80.70	34.85	11.01	31.92	306 179 AVERAGE																																																																			







Mode	21																																																																																	
	Band Edge - L																																																																																	
	U-NII-2A_5.25-5.35_802.11n HT40_CH54_5270MHz																																																																																	
ANT	SISO																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5146.48</td><td>53.89</td><td>74.00</td><td>-20.11</td><td>39.71</td><td>34.87</td><td>11.09</td><td>31.78</td><td>100</td><td>218</td><td>PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5146.48	53.89	74.00	-20.11	39.71	34.87	11.09	31.78	100	218	PEAK	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5270.00</td><td>100.30</td><td>-----</td><td>-----</td><td>86.36</td><td>34.85</td><td>11.01</td><td>31.92</td><td>100</td><td>218</td><td>PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5270.00	100.30	-----	-----	86.36	34.85	11.01	31.92	100	218	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5146.48	53.89	74.00	-20.11	39.71	34.87	11.09	31.78	100	218	PEAK																																																																							
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5270.00	100.30	-----	-----	86.36	34.85	11.01	31.92	100	218	PEAK																																																																							
Avg	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5134.60</td><td>44.35</td><td>54.00</td><td>-9.65</td><td>30.15</td><td>34.87</td><td>11.09</td><td>31.76</td><td>100</td><td>218</td><td>AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5134.60	44.35	54.00	-9.65	30.15	34.87	11.09	31.76	100	218	AVERAGE	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5270.00</td><td>93.58</td><td>-----</td><td>-----</td><td>79.64</td><td>34.85</td><td>11.01</td><td>31.92</td><td>100</td><td>218</td><td>AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5270.00	93.58	-----	-----	79.64	34.85	11.01	31.92	100	218	AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5134.60	44.35	54.00	-9.65	30.15	34.87	11.09	31.76	100	218	AVERAGE																																																																							
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5270.00	93.58	-----	-----	79.64	34.85	11.01	31.92	100	218	AVERAGE																																																																							



Mode	21																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11n HT40_CH54_5270MHz																																										
ANT	SISO																																										
Pol.	Vertical	Fundamental																																									
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5353.33</td><td>59.84</td><td>74.00</td><td>-14.16</td><td>46.10</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>218 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5353.33	59.84	74.00	-14.16	46.10	34.83	10.94	32.03	100	218 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5353.33	59.84	74.00	-14.16	46.10	34.83	10.94	32.03	100	218 PEAK																																	
Avg	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5351.80</td><td>47.54</td><td>54.00</td><td>-6.46</td><td>33.80</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>218 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5351.80	47.54	54.00	-6.46	33.80	34.83	10.94	32.03	100	218 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5351.80	47.54	54.00	-6.46	33.80	34.83	10.94	32.03	100	218 AVERAGE																																	



		22																																																																						
Mode		Band Edge - L																																																																						
		U-NII-2A_5.25-5.35_802.11n HT40_CH62_5310MHz																																																																						
ANT		SISO																																																																						
Pol.		Horizontal					Fundamental																																																																	
Peak	 Level (dBuV/m) Date: 2023-09-04 5000 5062 5124 5186 5248 5310 Frequency (MHz) 15.407					 Level (dBuV/m) Date: 2023-09-04 1000 2200 3400 4600 5800 7000 Frequency (MHz) 15.407																																																																		
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5040.49	52.48	74.00	-21.52	38.09	34.89	11.15	31.65	204 144 PEAK	<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5310.00</td><td>96.41</td><td>-----</td><td>-----</td><td>82.56</td><td>34.84</td><td>10.98</td><td>31.97</td><td>204 144 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5310.00	96.41	-----	-----	82.56	34.84	10.98	31.97
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																
1 5040.49	52.48	74.00	-21.52	38.09	34.89	11.15	31.65	204 144 PEAK																																																																
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																
1 5310.00	96.41	-----	-----	82.56	34.84	10.98	31.97	204 144 PEAK																																																																
Avg	 Level (dBuV/m) Date: 2023-09-04 5000 5062 5124 5186 5248 5310 Frequency (MHz) 15.407 AVG					 Level (dBuV/m) Date: 2023-09-04 1000 2200 3400 4600 5800 7000 Frequency (MHz) 15.407 AVG																																																																		
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5041.73	43.46	54.00	-10.54	29.07	34.89	11.15	31.65	204 144 AVERAGE	<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5310.00</td><td>89.35</td><td>-----</td><td>-----</td><td>75.50</td><td>34.84</td><td>10.98</td><td>31.97</td><td>204 144 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5310.00	89.35	-----	-----	75.50	34.84	10.98	31.97
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																
1 5041.73	43.46	54.00	-10.54	29.07	34.89	11.15	31.65	204 144 AVERAGE																																																																
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																
1 5310.00	89.35	-----	-----	75.50	34.84	10.98	31.97	204 144 AVERAGE																																																																



Mode	22																																																		
	Band Edge - R																																																		
	U-NII-2A_5.25-5.35_802.11n HT40_CH62_5310MHz																																																		
ANT	SISO																																																		
Pol.	Horizontal					Fundamental																																													
Peak	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.89</td><td>61.80</td><td>74.00</td><td>-12.20</td><td>48.06</td><td>34.83</td><td>10.94</td><td>32.03</td><td>204</td><td>144 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.89	61.80	74.00	-12.20	48.06	34.83	10.94	32.03	204	144 PEAK	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																										
1	5350.89	61.80	74.00	-12.20	48.06	34.83	10.94	32.03	204	144 PEAK																																									
Avg	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.29</td><td>48.39</td><td>54.00</td><td>-5.61</td><td>34.65</td><td>34.83</td><td>10.94</td><td>32.03</td><td>204</td><td>144 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.29	48.39	54.00	-5.61	34.65	34.83	10.94	32.03	204	144 AVERAGE	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																										
1	5350.29	48.39	54.00	-5.61	34.65	34.83	10.94	32.03	204	144 AVERAGE																																									



		22																																																		
Mode	Band Edge - L																																																			
	U-NII-2A_5.25-5.35_802.11n HT40_CH62_5310MHz																																																			
ANT	SISO																																																			
Pol.	Vertical																																																			
Peak	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5137.18</td><td>52.43</td><td>74.00</td><td>-21.57</td><td>38.24</td><td>34.87</td><td>11.09</td><td>31.77</td><td>100</td><td>217 PEAK</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5137.18	52.43	74.00	-21.57	38.24	34.87	11.09	31.77	100	217 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5137.18	52.43	74.00	-21.57	38.24	34.87	11.09	31.77	100	217 PEAK																																										
Fundamental	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5310.00</td><td>95.69</td><td>-----</td><td>-----</td><td>81.86</td><td>34.84</td><td>10.97</td><td>31.98</td><td>100</td><td>217 PEAK</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5310.00	95.69	-----	-----	81.86	34.84	10.97	31.98	100	217 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5310.00	95.69	-----	-----	81.86	34.84	10.97	31.98	100	217 PEAK																																										
Avg	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5043.28</td><td>43.42</td><td>54.00</td><td>-10.58</td><td>29.03</td><td>34.89</td><td>11.15</td><td>31.65</td><td>100</td><td>217 AVERAGE</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5043.28	43.42	54.00	-10.58	29.03	34.89	11.15	31.65	100	217 AVERAGE
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5043.28	43.42	54.00	-10.58	29.03	34.89	11.15	31.65	100	217 AVERAGE																																										
AVERAGE	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5310.00</td><td>90.21</td><td>-----</td><td>-----</td><td>76.36</td><td>34.84</td><td>10.98</td><td>31.97</td><td>100</td><td>217 AVERAGE</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5310.00	90.21	-----	-----	76.36	34.84	10.98	31.97	100	217 AVERAGE
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																														
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5310.00	90.21	-----	-----	76.36	34.84	10.98	31.97	100	217 AVERAGE																																										



Mode	22																																											
	Band Edge - R																																											
	U-NII-2A_5.25-5.35_802.11n HT40_CH62_5310MHz																																											
ANT	SISO																																											
Pol.	Vertical	Fundamental																																										
Peak	Date: 2023-09-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5352.09</td><td>63.89</td><td>74.00</td><td>-10.11</td><td>50.15</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>217 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5352.09	63.89	74.00	-10.11	50.15	34.83	10.94	32.03	100	217 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																			
	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																		
1	5352.09	63.89	74.00	-10.11	50.15	34.83	10.94	32.03	100	217 PEAK																																		
Avg	Date: 2023-09-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.01</td><td>48.42</td><td>54.00</td><td>-5.58</td><td>34.68</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>217 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5350.01	48.42	54.00	-5.58	34.68	34.83	10.94	32.03	100	217 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																			
	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																		
1	5350.01	48.42	54.00	-5.58	34.68	34.83	10.94	32.03	100	217 AVERAGE																																		



Mode	23																																																																																														
	Band Edge - L																																																																																														
	U-NII-2C_5.47-5.725_802.11n HT40_CH102_5510MHz																																																																																														
ANT	SISO																																																																																														
Pol.	Horizontal	Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.56</td><td>54.01</td><td>74.00</td><td>-19.99</td><td>40.25</td><td>34.81</td><td>11.11</td><td>32.16</td><td>100</td><td>151 PEAK</td></tr><tr><td>2</td><td>5465.76</td><td>57.11</td><td>68.30</td><td>-11.19</td><td>43.33</td><td>34.81</td><td>11.14</td><td>32.17</td><td>100</td><td>151 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5458.56	54.01	74.00	-19.99	40.25	34.81	11.11	32.16	100	151 PEAK	2	5465.76	57.11	68.30	-11.19	43.33	34.81	11.14	32.17	100	151 PEAK	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>98.38</td><td>-----</td><td>-----</td><td>84.47</td><td>34.81</td><td>11.32</td><td>32.22</td><td>100</td><td>151 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5510.00	98.38	-----	-----	84.47	34.81	11.32	32.22	100	151 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																					
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5458.56	54.01	74.00	-19.99	40.25	34.81	11.11	32.16	100	151 PEAK																																																																																					
2	5465.76	57.11	68.30	-11.19	43.33	34.81	11.14	32.17	100	151 PEAK																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5510.00	98.38	-----	-----	84.47	34.81	11.32	32.22	100	151 PEAK																																																																																					
Avg	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5460.00</td><td>44.66</td><td>54.00</td><td>-9.34</td><td>30.90</td><td>34.81</td><td>11.12</td><td>32.17</td><td>100</td><td>151 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5460.00	44.66	54.00	-9.34	30.90	34.81	11.12	32.17	100	151 AVERAGE	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>92.05</td><td>-----</td><td>-----</td><td>78.14</td><td>34.81</td><td>11.32</td><td>32.22</td><td>100</td><td>151 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5510.00	92.05	-----	-----	78.14	34.81	11.32	32.22	100	151 AVERAGE											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5460.00	44.66	54.00	-9.34	30.90	34.81	11.12	32.17	100	151 AVERAGE																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5510.00	92.05	-----	-----	78.14	34.81	11.32	32.22	100	151 AVERAGE																																																																																					



Mode	23																																																																																											
	Band Edge - L																																																																																											
	U-NII-2C_5.47-5.725_802.11n HT40_CH102_5510MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Vertical	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5453.92</td><td>54.75</td><td>74.00</td><td>-19.25</td><td>41.01</td><td>34.81</td><td>11.09</td><td>32.16</td><td>100 77 PEAK</td></tr><tr><td>2</td><td>5469.92</td><td>58.69</td><td>68.30</td><td>-9.61</td><td>44.90</td><td>34.81</td><td>11.16</td><td>32.18</td><td>100 77 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5453.92	54.75	74.00	-19.25	41.01	34.81	11.09	32.16	100 77 PEAK	2	5469.92	58.69	68.30	-9.61	44.90	34.81	11.16	32.18	100 77 PEAK	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>98.28</td><td>-----</td><td>-----</td><td>84.37</td><td>34.81</td><td>11.32</td><td>32.22</td><td>100 77 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5510.00	98.28	-----	-----	84.37	34.81	11.32	32.22	100 77 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5453.92	54.75	74.00	-19.25	41.01	34.81	11.09	32.16	100 77 PEAK																																																																																			
2	5469.92	58.69	68.30	-9.61	44.90	34.81	11.16	32.18	100 77 PEAK																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5510.00	98.28	-----	-----	84.37	34.81	11.32	32.22	100 77 PEAK																																																																																			
Avg	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5452.34</td><td>46.47</td><td>54.00</td><td>-7.53</td><td>32.73</td><td>34.81</td><td>11.09</td><td>32.16</td><td>100 77 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5452.34	46.47	54.00	-7.53	32.73	34.81	11.09	32.16	100 77 AVERAGE	Level (dBuV/m) Date: 2023-09-01 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>92.24</td><td>-----</td><td>-----</td><td>78.33</td><td>34.81</td><td>11.32</td><td>32.22</td><td>100 77 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5510.00	92.24	-----	-----	78.33	34.81	11.32	32.22	100 77 AVERAGE										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5452.34	46.47	54.00	-7.53	32.73	34.81	11.09	32.16	100 77 AVERAGE																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5510.00	92.24	-----	-----	78.33	34.81	11.32	32.22	100 77 AVERAGE																																																																																			



Mode	24																																																																																														
	Band Edge - L																																																																																														
	U-NII-2C_5.47-5.725_802.11n HT40_CH134_5670MHz																																																																																														
ANT	SISO																																																																																														
Pol.	Horizontal	Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5394.64</td><td>51.69</td><td>74.00</td><td>-22.31</td><td>38.04</td><td>34.82</td><td>10.91</td><td>32.08</td><td>100</td><td>157 PEAK</td></tr><tr><td>2</td><td>5466.96</td><td>51.98</td><td>68.30</td><td>-16.32</td><td>38.19</td><td>34.81</td><td>11.15</td><td>32.17</td><td>100</td><td>157 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5394.64	51.69	74.00	-22.31	38.04	34.82	10.91	32.08	100	157 PEAK	2	5466.96	51.98	68.30	-16.32	38.19	34.81	11.15	32.17	100	157 PEAK	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>102.79</td><td>-----</td><td>-----</td><td>88.42</td><td>35.03</td><td>11.68</td><td>32.34</td><td>100</td><td>157 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	102.79	-----	-----	88.42	35.03	11.68	32.34	100	157 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																					
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5394.64	51.69	74.00	-22.31	38.04	34.82	10.91	32.08	100	157 PEAK																																																																																					
2	5466.96	51.98	68.30	-16.32	38.19	34.81	11.15	32.17	100	157 PEAK																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5670.00	102.79	-----	-----	88.42	35.03	11.68	32.34	100	157 PEAK																																																																																					
Avg	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5451.31</td><td>43.01</td><td>54.00</td><td>-10.99</td><td>29.27</td><td>34.81</td><td>11.08</td><td>32.15</td><td>100</td><td>157 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5451.31	43.01	54.00	-10.99	29.27	34.81	11.08	32.15	100	157 AVERAGE	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>95.95</td><td>-----</td><td>-----</td><td>81.58</td><td>35.03</td><td>11.68</td><td>32.34</td><td>100</td><td>157 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	95.95	-----	-----	81.58	35.03	11.68	32.34	100	157 AVERAGE											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5451.31	43.01	54.00	-10.99	29.27	34.81	11.08	32.15	100	157 AVERAGE																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5670.00	95.95	-----	-----	81.58	35.03	11.68	32.34	100	157 AVERAGE																																																																																					



Mode	24																																																																																														
	Band Edge - L																																																																																														
	U-NII-2C_5.47-5.725_802.11n HT40_CH134_5670MHz																																																																																														
ANT	SISO																																																																																														
Pol.	Vertical	Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2023-09-01 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5414.19</td><td>51.69</td><td>74.00</td><td>-22.31</td><td>38.05</td><td>34.82</td><td>10.93</td><td>32.11</td><td>301</td><td>194 PEAK</td></tr><tr><td>2</td><td>5460.56</td><td>51.40</td><td>68.30</td><td>-16.90</td><td>37.64</td><td>34.81</td><td>11.12</td><td>32.17</td><td>301</td><td>194 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5414.19	51.69	74.00	-22.31	38.05	34.82	10.93	32.11	301	194 PEAK	2	5460.56	51.40	68.30	-16.90	37.64	34.81	11.12	32.17	301	194 PEAK	Level (dBuV/m) Date: 2023-09-01 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>99.68</td><td>-----</td><td>-----</td><td>85.30</td><td>35.04</td><td>11.68</td><td>32.34</td><td>301</td><td>194 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	99.68	-----	-----	85.30	35.04	11.68	32.34	301	194 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																						
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5414.19	51.69	74.00	-22.31	38.05	34.82	10.93	32.11	301	194 PEAK																																																																																					
2	5460.56	51.40	68.30	-16.90	37.64	34.81	11.12	32.17	301	194 PEAK																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5670.00	99.68	-----	-----	85.30	35.04	11.68	32.34	301	194 PEAK																																																																																					
Avg	Level (dBuV/m) Date: 2023-09-01 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5459.92</td><td>42.46</td><td>54.00</td><td>-11.54</td><td>28.70</td><td>34.81</td><td>11.12</td><td>32.17</td><td>301</td><td>194 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5459.92	42.46	54.00	-11.54	28.70	34.81	11.12	32.17	301	194 AVERAGE	Level (dBuV/m) Date: 2023-09-01 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>93.15</td><td>-----</td><td>-----</td><td>78.78</td><td>35.03</td><td>11.68</td><td>32.34</td><td>301</td><td>194 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	93.15	-----	-----	78.78	35.03	11.68	32.34	301	194 AVERAGE											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5459.92	42.46	54.00	-11.54	28.70	34.81	11.12	32.17	301	194 AVERAGE																																																																																					
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5670.00	93.15	-----	-----	78.78	35.03	11.68	32.34	301	194 AVERAGE																																																																																					



Mode	24																															
	Band Edge - R																															
	U-NII-2C_5.47-5.725_802.11n HT40_CH134_5670MHz																															
ANT	SISO																															
Pol.	Vertical						Fundamental																									
Peak	Date: 2023-09-01 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark <table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5727.06</td><td>56.44</td><td>68.30</td><td>-11.86</td><td>42.06</td><td>35.12</td><td>11.65</td><td>32.39</td><td>301</td><td>194</td><td>PEAK</td></tr></table>						MHz	dBuV/m	dBuV/m	dB	dB/m	dB	dB	cm	deg	1	5727.06	56.44	68.30	-11.86	42.06	35.12	11.65	32.39	301	194	PEAK	Blank				
MHz	dBuV/m	dBuV/m	dB	dB/m	dB	dB	cm	deg																								
1	5727.06	56.44	68.30	-11.86	42.06	35.12	11.65	32.39	301	194	PEAK																					



		25									
Mode		Band Edge - L									
		U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz									
ANT		SISO									
Pol.		Horizontal					Fundamental				
Peak	Level (dBuV/m) Date: 2023-09-04 <										



Mode	25									
	Band Edge - R									
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz									
ANT	SISO									
Pol.	Horizontal					Fundamental				
Peak	</									



		25																																																																																									
Mode	Band Edge - L																																																																																										
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																																																																										
ANT	SISO																																																																																										
Pol.	Vertical										Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5148.39</td><td>56.61</td><td>74.00</td><td>-17.39</td><td>42.43</td><td>34.87</td><td>11.09</td><td>31.78</td><td>100</td><td>215 PEAK</td></tr></tbody></table>											Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg	1 5148.39	56.61	74.00	-17.39	42.43	34.87	11.09	31.78	100	215 PEAK	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5210.00</td><td>95.38</td><td>-----</td><td>-----</td><td>81.32</td><td>34.86</td><td>11.05</td><td>31.85</td><td>100</td><td>215 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg	1 5210.00	95.38	-----	-----	81.32	34.86	11.05	31.85	100	215 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																		
1 5148.39	56.61	74.00	-17.39	42.43	34.87	11.09	31.78	100	215 PEAK																																																																																		
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																		
1 5210.00	95.38	-----	-----	81.32	34.86	11.05	31.85	100	215 PEAK																																																																																		
Avg	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5149.44</td><td>48.98</td><td>54.00</td><td>-5.02</td><td>34.80</td><td>34.87</td><td>11.09</td><td>31.78</td><td>100</td><td>215 AVERAGE</td></tr></tbody></table>											Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg	1 5149.44	48.98	54.00	-5.02	34.80	34.87	11.09	31.78	100	215 AVERAGE	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5210.00</td><td>88.45</td><td>-----</td><td>-----</td><td>74.39</td><td>34.86</td><td>11.05</td><td>31.85</td><td>100</td><td>215 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg	1 5210.00	88.45	-----	-----	74.39	34.86	11.05	31.85	100	215 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																		
1 5149.44	48.98	54.00	-5.02	34.80	34.87	11.09	31.78	100	215 AVERAGE																																																																																		
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	dB	cm	deg																																																																																		
1 5210.00	88.45	-----	-----	74.39	34.86	11.05	31.85	100	215 AVERAGE																																																																																		



Mode	25																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																										
ANT	SISO																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2023-09-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5386.65</td><td>53.64</td><td>74.00</td><td>-20.36</td><td>39.97</td><td>34.82</td><td>10.92</td><td>32.07</td><td>100</td><td>215 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5386.65	53.64	74.00	-20.36	39.97	34.82	10.92	32.07	100	215 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5386.65	53.64	74.00	-20.36	39.97	34.82	10.92	32.07	100	215 PEAK																																	
Avg	Date: 2023-09-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5371.38</td><td>46.48</td><td>54.00</td><td>-7.52</td><td>32.78</td><td>34.83</td><td>10.93</td><td>32.06</td><td>100</td><td>215 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5371.38	46.48	54.00	-7.52	32.78	34.83	10.93	32.06	100	215 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5371.38	46.48	54.00	-7.52	32.78	34.83	10.93	32.06	100	215 AVERAGE																																	







Mode	26																																																																																	
	Band Edge - L																																																																																	
	U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																																																																	
ANT	SISO																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5092.39</td><td>53.25</td><td>74.00</td><td>-20.75</td><td>38.96</td><td>34.88</td><td>11.12</td><td>31.71</td><td>100</td><td>213 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5092.39	53.25	74.00	-20.75	38.96	34.88	11.12	31.71	100	213 PEAK	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5290.00</td><td>93.03</td><td>-----</td><td>-----</td><td>79.18</td><td>34.84</td><td>10.98</td><td>31.97</td><td>100</td><td>213 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5290.00	93.03	-----	-----	79.18	34.84	10.98	31.97	100	213 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5092.39	53.25	74.00	-20.75	38.96	34.88	11.12	31.71	100	213 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5290.00	93.03	-----	-----	79.18	34.84	10.98	31.97	100	213 PEAK																																																																									
Avg	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5065.40</td><td>45.68</td><td>54.00</td><td>-8.32</td><td>31.34</td><td>34.89</td><td>11.13</td><td>31.68</td><td>100</td><td>213 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5065.40	45.68	54.00	-8.32	31.34	34.89	11.13	31.68	100	213 AVERAGE	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5290.00</td><td>85.80</td><td>-----</td><td>-----</td><td>71.92</td><td>34.84</td><td>10.99</td><td>31.95</td><td>100</td><td>213 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5290.00	85.80	-----	-----	71.92	34.84	10.99	31.95	100	213 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5065.40	45.68	54.00	-8.32	31.34	34.89	11.13	31.68	100	213 AVERAGE																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5290.00	85.80	-----	-----	71.92	34.84	10.99	31.95	100	213 AVERAGE																																																																									



Mode	26																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																										
ANT	SISO																																										
Pol.	Horizontal	Fundamental																																									
Peak	Date: 2023-09-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5351.80</td><td>56.51</td><td>74.00</td><td>-17.49</td><td>42.77</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>213 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5351.80	56.51	74.00	-17.49	42.77	34.83	10.94	32.03	100	213 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5351.80	56.51	74.00	-17.49	42.77	34.83	10.94	32.03	100	213 PEAK																																	
Avg	Date: 2023-09-04 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5351.97</td><td>48.54</td><td>54.00</td><td>-5.46</td><td>34.80</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>213 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5351.97	48.54	54.00	-5.46	34.80	34.83	10.94	32.03	100	213 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5351.97	48.54	54.00	-5.46	34.80	34.83	10.94	32.03	100	213 AVERAGE																																	







		26																																																																																							
Mode		Band Edge - L																																																																																							
		U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																																																																							
ANT		SISO																																																																																							
Pol.		Vertical					Fundamental																																																																																		
Peak																																																																																									
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5073.17</td><td>52.96</td><td>74.00</td><td>-21.04</td><td>38.63</td><td>34.89</td><td>11.13</td><td>31.69</td><td>100</td><td>214 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5073.17	52.96	74.00	-21.04	38.63	34.89	11.13	31.69	100	214 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5290.00</td><td>94.68</td><td>-----</td><td>-----</td><td>80.80</td><td>34.84</td><td>10.99</td><td>31.95</td><td>100</td><td>214 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5290.00	94.68	-----	-----	80.80	34.84	10.99	31.95	100
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5073.17	52.96	74.00	-21.04	38.63	34.89	11.13	31.69	100	214 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5290.00	94.68	-----	-----	80.80	34.84	10.99	31.95	100	214 PEAK																																																																																
Avg																																																																																									
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5117.89</td><td>45.42</td><td>54.00</td><td>-8.58</td><td>31.18</td><td>34.88</td><td>11.10</td><td>31.74</td><td>100</td><td>214 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5117.89	45.42	54.00	-8.58	31.18	34.88	11.10	31.74	100	214 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5290.00</td><td>87.83</td><td>-----</td><td>-----</td><td>73.96</td><td>34.84</td><td>10.99</td><td>31.96</td><td>100</td><td>214 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5290.00	87.83	-----	-----	73.96	34.84	10.99	31.96	100
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5117.89	45.42	54.00	-8.58	31.18	34.88	11.10	31.74	100	214 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1 5290.00	87.83	-----	-----	73.96	34.84	10.99	31.96	100	214 AVERAGE																																																																																



Mode	26																																																			
	Band Edge - R																																																			
	U-NII-2A_5.25-5.35_802.11ac VHT80_CH58_5290MHz																																																			
ANT	SISO																																																			
Pol.	Vertical					Fundamental																																														
Peak	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5351.64</td><td>58.00</td><td>74.00</td><td>-16.00</td><td>44.26</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>214</td><td>PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5351.64	58.00	74.00	-16.00	44.26	34.83	10.94	32.03	100	214	PEAK	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																											
1	5351.64	58.00	74.00	-16.00	44.26	34.83	10.94	32.03	100	214	PEAK																																									
Avg	Level (dBuV/m) Date: 2023-09-04 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5351.47</td><td>49.65</td><td>54.00</td><td>-4.35</td><td>35.91</td><td>34.83</td><td>10.94</td><td>32.03</td><td>100</td><td>214</td><td>AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5351.47	49.65	54.00	-4.35	35.91	34.83	10.94	32.03	100	214	AVERAGE	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																											
1	5351.47	49.65	54.00	-4.35	35.91	34.83	10.94	32.03	100	214	AVERAGE																																									



		27																																																																																																											
Mode		Band Edge - L																																																																																																											
		U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																																																																																											
ANT		SISO																																																																																																											
Pol.		Horizontal					Fundamental																																																																																																						
Peak	 Level (dBuV/m) Date: 2023-09-04 5350 5386 5422 5458 5494 5530 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5457.93</td><td>53.98</td><td>74.00</td><td>-20.02</td><td>40.22</td><td>34.81</td><td>11.11</td><td>32.16</td><td>100</td><td>154 PEAK</td></tr><tr><td>2</td><td>5461.51</td><td>55.22</td><td>68.30</td><td>-13.08</td><td>41.45</td><td>34.81</td><td>11.13</td><td>32.17</td><td>100</td><td>154 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5457.93	53.98	74.00	-20.02	40.22	34.81	11.11	32.16	100	154 PEAK	2	5461.51	55.22	68.30	-13.08	41.45	34.81	11.13	32.17	100	154 PEAK	 Level (dBuV/m) Date: 2023-09-04 1000 2200 3400 4600 5800 7000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>94.91</td><td>-----</td><td>-----</td><td>80.90</td><td>34.84</td><td>11.40</td><td>32.23</td><td>100</td><td>154 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5530.00	94.91	-----	-----	80.90	34.84	11.40	32.23	100	154 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																																				
	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	5457.93	53.98	74.00	-20.02	40.22	34.81	11.11	32.16	100	154 PEAK																																																																																																			
2	5461.51	55.22	68.30	-13.08	41.45	34.81	11.13	32.17	100	154 PEAK																																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																					
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																																				
	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	5530.00	94.91	-----	-----	80.90	34.84	11.40	32.23	100	154 PEAK																																																																																																			
Avg	 Level (dBuV/m) Date: 2023-09-04 5350 5386 5422 5458 5494 5530 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.47</td><td>46.37</td><td>54.00</td><td>-7.63</td><td>32.61</td><td>34.81</td><td>11.11</td><td>32.16</td><td>100</td><td>154 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5458.47	46.37	54.00	-7.63	32.61	34.81	11.11	32.16	100	154 AVERAGE	 Level (dBuV/m) Date: 2023-09-04 1000 2200 3400 4600 5800 7000 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>88.18</td><td>-----</td><td>-----</td><td>74.17</td><td>34.84</td><td>11.40</td><td>32.23</td><td>100</td><td>154 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5530.00	88.18	-----	-----	74.17	34.84	11.40	32.23	100	154 AVERAGE											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																					
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																																				
	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	5458.47	46.37	54.00	-7.63	32.61	34.81	11.11	32.16	100	154 AVERAGE																																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																					
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																																				
	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1	5530.00	88.18	-----	-----	74.17	34.84	11.40	32.23	100	154 AVERAGE																																																																																																			



Mode	27																																																			
	Band Edge - R																																																			
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																																			
ANT	SISO																																																			
Pol.	Horizontal	Fundamental																																																		
Peak	Date: 2023-09-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5761.83</td><td>52.62</td><td>68.30</td><td>-15.68</td><td>38.22</td><td>35.17</td><td>11.64</td><td>32.41</td><td>100</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>154 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5761.83	52.62	68.30	-15.68	38.22	35.17	11.64	32.41	100										154 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5761.83	52.62	68.30	-15.68	38.22	35.17	11.64	32.41	100																																											
									154 PEAK																																											



		27									
Mode	Band Edge - L										
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz										
ANT	SISO										
Pol.	Fundamental										
Peak	Vertical										
	Fundamental										
Avg	Vertical										
	Fundamental										

Date: 2023-09-04																																																																	
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="2">Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5441.55</td><td>57.00</td><td>74.00</td><td>-17.00</td><td>43.29</td><td>34.81</td><td>11.04</td><td>32.14</td><td>100</td><td>219 PEAK</td></tr><tr><td>2</td><td>5464.75</td><td>57.45</td><td>68.30</td><td>-10.85</td><td>43.67</td><td>34.81</td><td>11.14</td><td>32.17</td><td>100</td><td>219 PEAK</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5441.55	57.00	74.00	-17.00	43.29	34.81	11.04	32.14	100	219 PEAK	2	5464.75	57.45	68.30	-10.85	43.67	34.81	11.14	32.17	100	219 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																								
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																								
1	5441.55	57.00	74.00	-17.00	43.29	34.81	11.04	32.14	100	219 PEAK																																																							
2	5464.75	57.45	68.30	-10.85	43.67	34.81	11.14	32.17	100	219 PEAK																																																							

Date: 2023-09-04																																																						
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="2">Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5530.00</td><td>93.76</td><td>-----</td><td>-----</td><td>79.75</td><td>34.84</td><td>11.40</td><td>32.23</td><td>100</td><td>219 PEAK</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5530.00	93.76	-----	-----	79.75	34.84	11.40	32.23	100	219 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																													
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																													
1	5530.00	93.76	-----	-----	79.75	34.84	11.40	32.23	100	219 PEAK																																												

Date: 2023-09-04																																																						
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="2">Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5454.85</td><td>49.18</td><td>54.00</td><td>-4.82</td><td>35.43</td><td>34.81</td><td>11.10</td><td>32.16</td><td>100</td><td>219 AVERAGE</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5454.85	49.18	54.00	-4.82	35.43	34.81	11.10	32.16	100	219 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																													
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																													
1	5454.85	49.18	54.00	-4.82	35.43	34.81	11.10	32.16	100	219 AVERAGE																																												

Date: 2023-09-04																																																						
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2"></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="2">Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5530.00</td><td>87.44</td><td>-----</td><td>-----</td><td>73.41</td><td>34.85</td><td>11.42</td><td>32.24</td><td>100</td><td>219 AVERAGE</td></tr></table>												Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5530.00	87.44	-----	-----	73.41	34.85	11.42	32.24	100	219 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																													
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																													
1	5530.00	87.44	-----	-----	73.41	34.85	11.42	32.24	100	219 AVERAGE																																												



Mode	27																																																			
	Band Edge - R																																																			
	U-NII-2C_5.47-5.725_802.11ac VHT80_CH106_5530MHz																																																			
ANT	SISO																																																			
Pol.	Vertical	Fundamental																																																		
Peak	Date: 2023-09-04 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5743.03</td><td>53.02</td><td>68.30</td><td>-15.28</td><td>38.64</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>219 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5743.03	53.02	68.30	-15.28	38.64	35.14	11.64	32.40	100										219 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5743.03	53.02	68.30	-15.28	38.64	35.14	11.64	32.40	100																																											
									219 PEAK																																											



Mode	28																																																																																																																																		
	Band Edge																																																																																																																																		
	U-NII-3_5.725-5.85_802.11a_CH149_5745MHz																																																																																																																																		
ANT	SISO																																																																																																																																		
Pol.	Horizontal										Fundamental																																																																																																																								
Peak	Level (dBuV/m) Date: 2023-09-11 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 5600 5629 5658 5687 5716 5745 PEAK_BE(B4)_10-24 1 2 3 4 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5647.20</td><td>53.70</td><td>68.30</td><td>-14.60</td><td>39.32</td><td>35.01</td><td>11.69</td><td>32.32</td><td>100</td><td>216</td><td>PEAK</td></tr><tr><td>2</td><td>5650.69</td><td>52.79</td><td>68.81</td><td>-16.02</td><td>38.42</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>216</td><td>PEAK</td></tr><tr><td>3</td><td>5717.67</td><td>74.45</td><td>110.15</td><td>-35.70</td><td>60.07</td><td>35.10</td><td>11.66</td><td>32.38</td><td>100</td><td>216</td><td>PEAK</td></tr><tr><td>4</td><td>5720.00</td><td>73.77</td><td>110.80</td><td>-37.03</td><td>59.38</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>216</td><td>PEAK</td></tr></table>											Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5647.20	53.70	68.30	-14.60	39.32	35.01	11.69	32.32	100	216	PEAK	2	5650.69	52.79	68.81	-16.02	38.42	35.01	11.69	32.33	100	216	PEAK	3	5717.67	74.45	110.15	-35.70	60.07	35.10	11.66	32.38	100	216	PEAK	4	5720.00	73.77	110.80	-37.03	59.38	35.11	11.66	32.38	100	216	PEAK	Level (dBuV/m) Date: 2023-09-11 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 1000 2200 3400 4600 5800 7000 PART 15.407 1 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5745.00</td><td>105.42</td><td>-----</td><td>-----</td><td>91.04</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td><td>216</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	105.42	-----	-----	91.04	35.14	11.64	32.40	100	216	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5647.20	53.70	68.30	-14.60	39.32	35.01	11.69	32.32	100	216	PEAK																																																																																																																								
2	5650.69	52.79	68.81	-16.02	38.42	35.01	11.69	32.33	100	216	PEAK																																																																																																																								
3	5717.67	74.45	110.15	-35.70	60.07	35.10	11.66	32.38	100	216	PEAK																																																																																																																								
4	5720.00	73.77	110.80	-37.03	59.38	35.11	11.66	32.38	100	216	PEAK																																																																																																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5745.00	105.42	-----	-----	91.04	35.14	11.64	32.40	100	216	PEAK																																																																																																																								
Avg	Blank										Level (dBuV/m) Date: 2023-09-11 140 122.5 105.0 87.5 70.0 52.5 35.0 17.5 0 1000 2200 3400 4600 5800 7000 PART 15.407 AVG 1 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5745.00</td><td>99.50</td><td>-----</td><td>-----</td><td>85.12</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td><td>216</td><td>AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	99.50	-----	-----	85.12	35.14	11.64	32.40	100	216	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5745.00	99.50	-----	-----	85.12	35.14	11.64	32.40	100	216	AVERAGE																																																																																																																								





Mode	28																																																																																																																									
	Band Edge																																																																																																																									
	U-NII-3_5.725-5.85_802.11a_CH149_5745MHz																																																																																																																									
ANT	SISO																																																																																																																									
Pol.	Vertical	Fundamental																																																																																																																								
Peak	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5623.27</td><td>53.35</td><td>68.30</td><td>-14.95</td><td>38.99</td><td>34.97</td><td>11.70</td><td>32.31</td><td>100</td><td>222</td><td>PEAK</td></tr><tr><td>2</td><td>5650.53</td><td>51.58</td><td>68.70</td><td>-17.12</td><td>37.21</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>222</td><td>PEAK</td></tr><tr><td>3</td><td>5717.52</td><td>72.49</td><td>110.11</td><td>-37.62</td><td>58.11</td><td>35.10</td><td>11.66</td><td>32.38</td><td>100</td><td>222</td><td>PEAK</td></tr><tr><td>4</td><td>5720.00</td><td>71.91</td><td>110.80</td><td>-38.89</td><td>57.52</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>222</td><td>PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5623.27	53.35	68.30	-14.95	38.99	34.97	11.70	32.31	100	222	PEAK	2	5650.53	51.58	68.70	-17.12	37.21	35.01	11.69	32.33	100	222	PEAK	3	5717.52	72.49	110.11	-37.62	58.11	35.10	11.66	32.38	100	222	PEAK	4	5720.00	71.91	110.80	-38.89	57.52	35.11	11.66	32.38	100	222	PEAK	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5745.00</td><td>103.81</td><td>-----</td><td>-----</td><td>89.43</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td><td>222</td><td>PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	103.81	-----	-----	89.43	35.14	11.64	32.40	100	222	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5623.27	53.35	68.30	-14.95	38.99	34.97	11.70	32.31	100	222	PEAK																																																																																																															
2	5650.53	51.58	68.70	-17.12	37.21	35.01	11.69	32.33	100	222	PEAK																																																																																																															
3	5717.52	72.49	110.11	-37.62	58.11	35.10	11.66	32.38	100	222	PEAK																																																																																																															
4	5720.00	71.91	110.80	-38.89	57.52	35.11	11.66	32.38	100	222	PEAK																																																																																																															
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5745.00	103.81	-----	-----	89.43	35.14	11.64	32.40	100	222	PEAK																																																																																																															
Blank	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5745.00</td><td>97.96</td><td>-----</td><td>-----</td><td>83.58</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td><td>222</td><td>AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	97.96	-----	-----	83.58	35.14	11.64	32.40	100	222	AVERAGE																																																																															
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5745.00	97.96	-----	-----	83.58	35.14	11.64	32.40	100	222	AVERAGE																																																																																																															



Mode	28																																																																																																																		
	Harmonic																																																																																																																		
	U-NII-3_5.725-5.85_802.11a_CH149_5745MHz																																																																																																																		
ANT	SISO																																																																																																																		
Pol.	Horizontal						Vertical																																																																																																												
Peak Avg	Date: 2023-09-05						Date: 2023-09-05																																																																																																												
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11490.00</td><td>49.96</td><td>74.00</td><td>-24.04</td><td>47.64</td><td>38.19</td><td>14.83</td><td>50.70</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>17235.00</td><td>50.03</td><td>68.30</td><td>-18.27</td><td>42.53</td><td>41.86</td><td>17.57</td><td>51.93</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11490.00	49.96	74.00	-24.04	47.64	38.19	14.83	50.70	---	---	Peak	2	17235.00	50.03	68.30	-18.27	42.53	41.86	17.57	51.93	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11490.00</td><td>50.20</td><td>74.00</td><td>-23.80</td><td>47.88</td><td>38.19</td><td>14.83</td><td>50.70</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>17235.00</td><td>49.11</td><td>68.30</td><td>-19.19</td><td>41.61</td><td>41.86</td><td>17.57</td><td>51.93</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11490.00	50.20	74.00	-23.80	47.88	38.19	14.83	50.70	---	---	Peak	2	17235.00	49.11	68.30	-19.19	41.61	41.86	17.57	51.93	---	---	Peak
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																										
1	11490.00	49.96	74.00	-24.04	47.64	38.19	14.83	50.70	---	---	Peak																																																																																																								
2	17235.00	50.03	68.30	-18.27	42.53	41.86	17.57	51.93	---	---	Peak																																																																																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																										
1	11490.00	50.20	74.00	-23.80	47.88	38.19	14.83	50.70	---	---	Peak																																																																																																								
2	17235.00	49.11	68.30	-19.19	41.61	41.86	17.57	51.93	---	---	Peak																																																																																																								



Mode	29																																																																																											
	Harmonic																																																																																											
	U-NII-3_5.725-5.85_802.11a_CH157_5785MHz																																																																																											
ANT	SISO																																																																																											
Pol.	Horizontal						Vertical																																																																																					
Peak Avg																																																																																												
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>11570.00</td><td>50.19</td><td>74.00</td><td>-23.81</td><td>47.71</td><td>38.26</td><td>14.88</td><td>50.66</td><td>--- --- Peak</td></tr><tr><td>2</td><td>17355.00</td><td>50.28</td><td>68.30</td><td>-18.02</td><td>42.99</td><td>41.74</td><td>17.60</td><td>52.05</td><td>--- --- Peak</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	1	11570.00	50.19	74.00	-23.81	47.71	38.26	14.88	50.66	--- --- Peak	2	17355.00	50.28	68.30	-18.02	42.99	41.74	17.60	52.05	--- --- Peak	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>11570.00</td><td>49.91</td><td>74.00</td><td>-24.09</td><td>47.43</td><td>38.26</td><td>14.88</td><td>50.66</td><td>--- --- Peak</td></tr><tr><td>2</td><td>17355.00</td><td>50.22</td><td>68.30</td><td>-18.08</td><td>42.93</td><td>41.74</td><td>17.60</td><td>52.05</td><td>--- --- Peak</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	1	11570.00	49.91	74.00	-24.09	47.43	38.26	14.88	50.66	--- --- Peak	2	17355.00	50.22	68.30	-18.08	42.93	41.74	17.60	52.05	--- --- Peak
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																			
1	11570.00	50.19	74.00	-23.81	47.71	38.26	14.88	50.66	--- --- Peak																																																																																			
2	17355.00	50.28	68.30	-18.02	42.99	41.74	17.60	52.05	--- --- Peak																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																			
1	11570.00	49.91	74.00	-24.09	47.43	38.26	14.88	50.66	--- --- Peak																																																																																			
2	17355.00	50.22	68.30	-18.08	42.93	41.74	17.60	52.05	--- --- Peak																																																																																			





Mode	30																																																																																																																																			
	Band Edge																																																																																																																																			
	U-NII-3_5.725-5.85_802.11a_CH165_5825MHz																																																																																																																																			
ANT	SISO																																																																																																																																			
Pol.	Horizontal						Fundamental																																																																																																																													
Peak	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5854.83</td><td>69.12</td><td>111.20</td><td>-42.08</td><td>54.79</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>216</td><td>PEAK</td></tr><tr><td>2</td><td>5866.44</td><td>67.24</td><td>107.60</td><td>-40.36</td><td>52.93</td><td>35.31</td><td>11.50</td><td>32.50</td><td>100</td><td>216</td><td>PEAK</td></tr><tr><td>3</td><td>5924.83</td><td>52.99</td><td>68.33</td><td>-15.34</td><td>38.74</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>216</td><td>PEAK</td></tr><tr><td>4</td><td>5944.08</td><td>53.37</td><td>68.30</td><td>-14.93</td><td>39.14</td><td>35.42</td><td>11.37</td><td>32.56</td><td>100</td><td>216</td><td>PEAK</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.83	69.12	111.20	-42.08	54.79	35.30	11.52	32.49	100	216	PEAK	2	5866.44	67.24	107.60	-40.36	52.93	35.31	11.50	32.50	100	216	PEAK	3	5924.83	52.99	68.33	-15.34	38.74	35.39	11.40	32.54	100	216	PEAK	4	5944.08	53.37	68.30	-14.93	39.14	35.42	11.37	32.56	100	216	PEAK	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5825.00</td><td>105.64</td><td>-----</td><td>-----</td><td>91.27</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>216</td><td>PEAK</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	105.64	-----	-----	91.27	35.25	11.58	32.46	100	216	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	5854.83	69.12	111.20	-42.08	54.79	35.30	11.52	32.49	100	216	PEAK																																																																																																																									
2	5866.44	67.24	107.60	-40.36	52.93	35.31	11.50	32.50	100	216	PEAK																																																																																																																									
3	5924.83	52.99	68.33	-15.34	38.74	35.39	11.40	32.54	100	216	PEAK																																																																																																																									
4	5944.08	53.37	68.30	-14.93	39.14	35.42	11.37	32.56	100	216	PEAK																																																																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	5825.00	105.64	-----	-----	91.27	35.25	11.58	32.46	100	216	PEAK																																																																																																																									
Avg	Blank						Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5825.00</td><td>99.40</td><td>-----</td><td>-----</td><td>85.03</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>216</td><td>AVERAGE</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	99.40	-----	-----	85.03	35.25	11.58	32.46	100	216	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	5825.00	99.40	-----	-----	85.03	35.25	11.58	32.46	100	216	AVERAGE																																																																																																																									






Mode	30																																																																																																																																	
	Band Edge																																																																																																																																	
	U-NII-3_5.725-5.85_802.11a_CH165_5825MHz																																																																																																																																	
ANT	SISO																																																																																																																																	
Pol.	Vertical					Fundamental																																																																																																																												
Peak	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5854.83</td><td>65.71</td><td>111.20</td><td>-45.49</td><td>51.38</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>227</td><td>PEAK</td></tr><tr><td>2</td><td>5857.44</td><td>66.51</td><td>110.12</td><td>-43.61</td><td>52.18</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>227</td><td>PEAK</td></tr><tr><td>3</td><td>5924.33</td><td>52.27</td><td>68.70</td><td>-16.43</td><td>38.02</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>227</td><td>PEAK</td></tr><tr><td>4</td><td>5944.58</td><td>52.85</td><td>68.30</td><td>-15.45</td><td>38.62</td><td>35.42</td><td>11.37</td><td>32.56</td><td>100</td><td>227</td><td>PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.83	65.71	111.20	-45.49	51.38	35.30	11.52	32.49	100	227	PEAK	2	5857.44	66.51	110.12	-43.61	52.18	35.30	11.52	32.49	100	227	PEAK	3	5924.33	52.27	68.70	-16.43	38.02	35.39	11.40	32.54	100	227	PEAK	4	5944.58	52.85	68.30	-15.45	38.62	35.42	11.37	32.56	100	227	PEAK	Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5825.00</td><td>103.67</td><td>-----</td><td>-----</td><td>89.30</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>227</td><td>PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	103.67	-----	-----	89.30	35.25	11.58	32.46	100	227	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	5854.83	65.71	111.20	-45.49	51.38	35.30	11.52	32.49	100	227	PEAK																																																																																																																							
2	5857.44	66.51	110.12	-43.61	52.18	35.30	11.52	32.49	100	227	PEAK																																																																																																																							
3	5924.33	52.27	68.70	-16.43	38.02	35.39	11.40	32.54	100	227	PEAK																																																																																																																							
4	5944.58	52.85	68.30	-15.45	38.62	35.42	11.37	32.56	100	227	PEAK																																																																																																																							
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	5825.00	103.67	-----	-----	89.30	35.25	11.58	32.46	100	227	PEAK																																																																																																																							
Avg	Blank					Level (dBuV/m) Date: 2023-09-11 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5825.00</td><td>97.40</td><td>-----</td><td>-----</td><td>83.03</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>227</td><td>AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	97.40	-----	-----	83.03	35.25	11.58	32.46	100	227	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	5825.00	97.40	-----	-----	83.03	35.25	11.58	32.46	100	227	AVERAGE																																																																																																																							



Mode	30																																																																																																					
	Harmonic																																																																																																					
	U-NII-3_5.725-5.85_802.11a_CH165_5825MHz																																																																																																					
ANT	SISO																																																																																																					
Pol.	Horizontal	Vertical																																																																																																				
Peak Avg	Date: 2023-09-05 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 11650.00</td><td>50.47</td><td>74.00</td><td>-23.53</td><td>47.83</td><td>38.32</td><td>14.93</td><td>50.61</td><td>---</td><td>--- Peak</td></tr><tr><td>2 17475.00</td><td>50.82</td><td>68.30</td><td>-17.48</td><td>43.74</td><td>41.62</td><td>17.63</td><td>52.17</td><td>---</td><td>--- Peak</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 11650.00	50.47	74.00	-23.53	47.83	38.32	14.93	50.61	---	--- Peak	2 17475.00	50.82	68.30	-17.48	43.74	41.62	17.63	52.17	---	--- Peak	Date: 2023-09-05 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 11650.00</td><td>49.43</td><td>74.00</td><td>-24.57</td><td>46.79</td><td>38.32</td><td>14.93</td><td>50.61</td><td>---</td><td>--- Peak</td></tr><tr><td>2 17475.00</td><td>50.88</td><td>68.30</td><td>-17.42</td><td>43.80</td><td>41.62</td><td>17.63</td><td>52.17</td><td>---</td><td>--- Peak</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 11650.00	49.43	74.00	-24.57	46.79	38.32	14.93	50.61	---	--- Peak	2 17475.00	50.88	68.30	-17.42	43.80	41.62	17.63	52.17	---	--- Peak
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																													
	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 11650.00	50.47	74.00	-23.53	47.83	38.32	14.93	50.61	---	--- Peak																																																																																													
2 17475.00	50.82	68.30	-17.48	43.74	41.62	17.63	52.17	---	--- Peak																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 11650.00	49.43	74.00	-24.57	46.79	38.32	14.93	50.61	---	--- Peak																																																																																													
2 17475.00	50.88	68.30	-17.42	43.80	41.62	17.63	52.17	---	--- Peak																																																																																													



Mode	31																																																																																																																												
	Band Edge																																																																																																																												
	U-NII-3_5.725-5.85_802.11n HT20_CH149_5745MHz																																																																																																																												
ANT	SISO																																																																																																																												
Pol.	Horizontal					Fundamental																																																																																																																							
Peak																																																																																																																													
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5603.12</td><td>53.03</td><td>68.30</td><td>-15.27</td><td>38.67</td><td>34.94</td><td>11.71</td><td>32.29</td><td>100</td><td>222 PEAK</td></tr><tr><td>2</td><td>5650.53</td><td>52.26</td><td>68.70</td><td>-16.44</td><td>37.89</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>222 PEAK</td></tr><tr><td>3</td><td>5719.12</td><td>64.22</td><td>110.55</td><td>-46.33</td><td>49.83</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>222 PEAK</td></tr><tr><td>4</td><td>5720.15</td><td>64.92</td><td>111.14</td><td>-46.22</td><td>50.53</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>222 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5603.12	53.03	68.30	-15.27	38.67	34.94	11.71	32.29	100	222 PEAK	2	5650.53	52.26	68.70	-16.44	37.89	35.01	11.69	32.33	100	222 PEAK	3	5719.12	64.22	110.55	-46.33	49.83	35.11	11.66	32.38	100	222 PEAK	4	5720.15	64.92	111.14	-46.22	50.53	35.11	11.66	32.38	100	222 PEAK	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5745.00</td><td>103.95</td><td>-----</td><td>-----</td><td>89.57</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td><td>222 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	103.95	-----	-----	89.57	35.14	11.64	32.40	100	222 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																							
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	5603.12	53.03	68.30	-15.27	38.67	34.94	11.71	32.29	100	222 PEAK																																																																																																																			
2	5650.53	52.26	68.70	-16.44	37.89	35.01	11.69	32.33	100	222 PEAK																																																																																																																			
3	5719.12	64.22	110.55	-46.33	49.83	35.11	11.66	32.38	100	222 PEAK																																																																																																																			
4	5720.15	64.92	111.14	-46.22	50.53	35.11	11.66	32.38	100	222 PEAK																																																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																							
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	5745.00	103.95	-----	-----	89.57	35.14	11.64	32.40	100	222 PEAK																																																																																																																			
Avg	Blank																																																																																																																												
						<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5745.00</td><td>97.04</td><td>-----</td><td>-----</td><td>82.66</td><td>35.14</td><td>11.64</td><td>32.40</td><td>100</td><td>222 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	97.04	-----	-----	82.66	35.14	11.64	32.40	100	222 AVERAGE																																																																										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																							
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	5745.00	97.04	-----	-----	82.66	35.14	11.64	32.40	100	222 AVERAGE																																																																																																																			





Mode	31																																																																																																																				
	Band Edge																																																																																																																				
	U-NII-3_5.725-5.85_802.11n HT20_CH149_5745MHz																																																																																																																				
ANT	SISO																																																																																																																				
Pol.	Vertical	Fundamental																																																																																																																			
Peak	Level (dBuV/m) Date: 2023-08-29 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5610.82</td><td>53.97</td><td>68.30</td><td>-14.33</td><td>39.60</td><td>34.96</td><td>11.71</td><td>32.30</td><td>187</td><td>156 PEAK</td></tr><tr><td>2</td><td>5650.11</td><td>52.10</td><td>68.38</td><td>-16.28</td><td>37.73</td><td>35.01</td><td>11.69</td><td>32.33</td><td>187</td><td>156 PEAK</td></tr><tr><td>3</td><td>5708.24</td><td>64.62</td><td>107.51</td><td>-42.89</td><td>50.24</td><td>35.09</td><td>11.66</td><td>32.37</td><td>187</td><td>156 PEAK</td></tr><tr><td>4</td><td>5720.44</td><td>66.45</td><td>111.80</td><td>-45.35</td><td>52.06</td><td>35.11</td><td>11.66</td><td>32.38</td><td>187</td><td>156 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5610.82	53.97	68.30	-14.33	39.60	34.96	11.71	32.30	187	156 PEAK	2	5650.11	52.10	68.38	-16.28	37.73	35.01	11.69	32.33	187	156 PEAK	3	5708.24	64.62	107.51	-42.89	50.24	35.09	11.66	32.37	187	156 PEAK	4	5720.44	66.45	111.80	-45.35	52.06	35.11	11.66	32.38	187	156 PEAK	Level (dBuV/m) Date: 2023-08-29 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5745.00</td><td>104.87</td><td>-----</td><td>-----</td><td>90.49</td><td>35.14</td><td>11.64</td><td>32.40</td><td>187</td><td>156 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	104.87	-----	-----	90.49	35.14	11.64	32.40	187	156 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5610.82	53.97	68.30	-14.33	39.60	34.96	11.71	32.30	187	156 PEAK																																																																																																											
2	5650.11	52.10	68.38	-16.28	37.73	35.01	11.69	32.33	187	156 PEAK																																																																																																											
3	5708.24	64.62	107.51	-42.89	50.24	35.09	11.66	32.37	187	156 PEAK																																																																																																											
4	5720.44	66.45	111.80	-45.35	52.06	35.11	11.66	32.38	187	156 PEAK																																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5745.00	104.87	-----	-----	90.49	35.14	11.64	32.40	187	156 PEAK																																																																																																											
Avg	Blank	Level (dBuV/m) Date: 2023-08-29 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5745.00</td><td>98.04</td><td>-----</td><td>-----</td><td>83.66</td><td>35.14</td><td>11.64</td><td>32.40</td><td>187</td><td>156 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5745.00	98.04	-----	-----	83.66	35.14	11.64	32.40	187	156 AVERAGE																																																																										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5745.00	98.04	-----	-----	83.66	35.14	11.64	32.40	187	156 AVERAGE																																																																																																											



Mode	31																																																																																															
	Harmonic																																																																																															
	U-NII-3_5.725-5.85_802.11n HT20_CH149_5745MHz																																																																																															
ANT	SISO																																																																																															
Pol.	Horizontal								Vertical																																																																																							
Peak Avg	Level (dBuV/m) Date: 2023-09-05 Frequency (MHz)								Level (dBuV/m) Date: 2023-09-05 Frequency (MHz)																																																																																							
	<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td></tr><tr><td>1</td><td>11490.00</td><td>49.76</td><td>74.00</td><td>-24.24</td><td>47.44</td><td>38.19</td><td>14.83</td></tr><tr><td>2</td><td>17235.00</td><td>50.04</td><td>68.30</td><td>-18.26</td><td>42.54</td><td>41.86</td><td>17.57</td></tr></table>								Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	11490.00	49.76	74.00	-24.24	47.44	38.19	14.83	2	17235.00	50.04	68.30	-18.26	42.54	41.86	17.57	<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td></tr><tr><td>1</td><td>11490.00</td><td>50.85</td><td>74.00</td><td>-23.15</td><td>48.53</td><td>38.19</td><td>14.83</td></tr><tr><td>2</td><td>17235.00</td><td>49.58</td><td>68.30</td><td>-18.72</td><td>42.08</td><td>41.86</td><td>17.57</td></tr></table>								Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	11490.00	50.85	74.00	-23.15	48.53	38.19	14.83	2	17235.00	49.58	68.30	-18.72	42.08	41.86	17.57
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																								
	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																								
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																																																									
1	11490.00	49.76	74.00	-24.24	47.44	38.19	14.83																																																																																									
2	17235.00	50.04	68.30	-18.26	42.54	41.86	17.57																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																									
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																																																									
1	11490.00	50.85	74.00	-23.15	48.53	38.19	14.83																																																																																									
2	17235.00	49.58	68.30	-18.72	42.08	41.86	17.57																																																																																									
<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td></tr><tr><td>1</td><td>11490.00</td><td>49.76</td><td>74.00</td><td>-24.24</td><td>47.44</td><td>38.19</td><td>14.83</td></tr><tr><td>2</td><td>17235.00</td><td>50.04</td><td>68.30</td><td>-18.26</td><td>42.54</td><td>41.86</td><td>17.57</td></tr></table>								Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	11490.00	49.76	74.00	-24.24	47.44	38.19	14.83	2	17235.00	50.04	68.30	-18.26	42.54	41.86	17.57	<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td></tr><tr><td>1</td><td>11490.00</td><td>50.85</td><td>74.00</td><td>-23.15</td><td>48.53</td><td>38.19</td><td>14.83</td></tr><tr><td>2</td><td>17235.00</td><td>49.58</td><td>68.30</td><td>-18.72</td><td>42.08</td><td>41.86</td><td>17.57</td></tr></table>								Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	11490.00	50.85	74.00	-23.15	48.53	38.19	14.83	2	17235.00	49.58	68.30	-18.72	42.08	41.86	17.57	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																									
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																																																									
1	11490.00	49.76	74.00	-24.24	47.44	38.19	14.83																																																																																									
2	17235.00	50.04	68.30	-18.26	42.54	41.86	17.57																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																									
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																																																									
1	11490.00	50.85	74.00	-23.15	48.53	38.19	14.83																																																																																									
2	17235.00	49.58	68.30	-18.72	42.08	41.86	17.57																																																																																									
<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td></tr><tr><td>1</td><td>11490.00</td><td>49.76</td><td>74.00</td><td>-24.24</td><td>47.44</td><td>38.19</td><td>14.83</td></tr><tr><td>2</td><td>17235.00</td><td>50.04</td><td>68.30</td><td>-18.26</td><td>42.54</td><td>41.86</td><td>17.57</td></tr></table>								Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	11490.00	49.76	74.00	-24.24	47.44	38.19	14.83	2	17235.00	50.04	68.30	-18.26	42.54	41.86	17.57	<table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>dB</td><td>cm</td></tr><tr><td>1</td><td>11490.00</td><td>50.85</td><td>74.00</td><td>-23.15</td><td>48.53</td><td>38.19</td><td>14.83</td></tr><tr><td>2</td><td>17235.00</td><td>49.58</td><td>68.30</td><td>-18.72</td><td>42.08</td><td>41.86</td><td>17.57</td></tr></table>								Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	11490.00	50.85	74.00	-23.15	48.53	38.19	14.83	2	17235.00	49.58	68.30	-18.72	42.08	41.86	17.57	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																									
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																																																									
1	11490.00	49.76	74.00	-24.24	47.44	38.19	14.83																																																																																									
2	17235.00	50.04	68.30	-18.26	42.54	41.86	17.57																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																									
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																																																									
1	11490.00	50.85	74.00	-23.15	48.53	38.19	14.83																																																																																									
2	17235.00	49.58	68.30	-18.72	42.08	41.86	17.57																																																																																									



Mode	32																																																																										
	Harmonic																																																																										
	U-NII-3_5.725-5.85_802.11n HT20_CH157_5785MHz																																																																										
ANT	SISO																																																																										
Pol.	Horizontal								Vertical																																																																		
Peak Avg																																																																											
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr></table>									Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss Factor		Remark	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr></table>									Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss Factor		Remark																							
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor		Remark																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor		Remark																																																																			
<table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11570.00</td><td>49.07</td><td>74.00</td><td>-24.93</td><td>46.59</td><td>38.26</td><td>14.88</td><td>50.66</td><td>---</td><td>--- Peak</td></tr><tr><td>2 17355.00</td><td>50.59</td><td>68.30</td><td>-17.71</td><td>43.30</td><td>41.74</td><td>17.60</td><td>52.05</td><td>---</td><td>--- Peak</td></tr></table>								MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 11570.00	49.07	74.00	-24.93	46.59	38.26	14.88	50.66	---	--- Peak	2 17355.00	50.59	68.30	-17.71	43.30	41.74	17.60	52.05	---	--- Peak	<table><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11570.00</td><td>49.30</td><td>74.00</td><td>-24.70</td><td>46.82</td><td>38.26</td><td>14.88</td><td>50.66</td><td>---</td><td>--- Peak</td></tr><tr><td>2 17355.00</td><td>49.76</td><td>68.30</td><td>-18.54</td><td>42.47</td><td>41.74</td><td>17.60</td><td>52.05</td><td>---</td><td>--- Peak</td></tr></table>								MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 11570.00	49.30	74.00	-24.70	46.82	38.26	14.88	50.66	---	--- Peak	2 17355.00	49.76	68.30	-18.54	42.47	41.74	17.60	52.05	---	--- Peak
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																		
1 11570.00	49.07	74.00	-24.93	46.59	38.26	14.88	50.66	---	--- Peak																																																																		
2 17355.00	50.59	68.30	-17.71	43.30	41.74	17.60	52.05	---	--- Peak																																																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																		
1 11570.00	49.30	74.00	-24.70	46.82	38.26	14.88	50.66	---	--- Peak																																																																		
2 17355.00	49.76	68.30	-18.54	42.47	41.74	17.60	52.05	---	--- Peak																																																																		





Mode	33																																																																																																																									
	Band Edge																																																																																																																									
	U-NII-3_5.725-5.85_802.11n HT20_CH165_5825MHz																																																																																																																									
ANT	SISO																																																																																																																									
Pol.	Horizontal	Fundamental																																																																																																																								
Peak	Level (dBuV/m) Date: 2023-08-30 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5854.69</td><td>63.62</td><td>111.51</td><td>-47.89</td><td>49.29</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>218</td><td>PEAK</td></tr><tr><td>2</td><td>5856.69</td><td>66.18</td><td>110.33</td><td>-44.15</td><td>51.85</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>218</td><td>PEAK</td></tr><tr><td>3</td><td>5924.94</td><td>52.05</td><td>68.25</td><td>-16.20</td><td>37.80</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>218</td><td>PEAK</td></tr><tr><td>4</td><td>5936.19</td><td>53.63</td><td>68.30</td><td>-14.67</td><td>39.39</td><td>35.41</td><td>11.38</td><td>32.55</td><td>100</td><td>218</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.69	63.62	111.51	-47.89	49.29	35.30	11.52	32.49	100	218	PEAK	2	5856.69	66.18	110.33	-44.15	51.85	35.30	11.52	32.49	100	218	PEAK	3	5924.94	52.05	68.25	-16.20	37.80	35.39	11.40	32.54	100	218	PEAK	4	5936.19	53.63	68.30	-14.67	39.39	35.41	11.38	32.55	100	218	PEAK	Level (dBuV/m) Date: 2023-08-30 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5825.00</td><td>105.03</td><td>-----</td><td>-----</td><td>90.66</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>218</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	105.03	-----	-----	90.66	35.25	11.58	32.46	100	218	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5854.69	63.62	111.51	-47.89	49.29	35.30	11.52	32.49	100	218	PEAK																																																																																																															
2	5856.69	66.18	110.33	-44.15	51.85	35.30	11.52	32.49	100	218	PEAK																																																																																																															
3	5924.94	52.05	68.25	-16.20	37.80	35.39	11.40	32.54	100	218	PEAK																																																																																																															
4	5936.19	53.63	68.30	-14.67	39.39	35.41	11.38	32.55	100	218	PEAK																																																																																																															
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5825.00	105.03	-----	-----	90.66	35.25	11.58	32.46	100	218	PEAK																																																																																																															
Avg	Blank	Level (dBuV/m) Date: 2023-08-30 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5825.00</td><td>98.75</td><td>-----</td><td>-----</td><td>84.38</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>218</td><td>AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	98.75	-----	-----	84.38	35.25	11.58	32.46	100	218	AVERAGE																																																																														
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5825.00	98.75	-----	-----	84.38	35.25	11.58	32.46	100	218	AVERAGE																																																																																																															



Mode	33																																																																																																																																			
	Band Edge																																																																																																																																			
	U-NII-3_5.725-5.85_802.11n HT20_CH165_5825MHz																																																																																																																																			
ANT	SISO																																																																																																																																			
Pol.	Vertical						Fundamental																																																																																																																													
Peak	Level (dBuV/m) Date: 2023-08-30 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5854.44</td><td>66.40</td><td>112.08</td><td>-45.68</td><td>52.07</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>225</td><td>PEAK</td></tr><tr><td>2</td><td>5857.94</td><td>63.41</td><td>109.98</td><td>-46.57</td><td>49.08</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>225</td><td>PEAK</td></tr><tr><td>3</td><td>5924.58</td><td>51.34</td><td>68.51</td><td>-17.17</td><td>37.09</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>225</td><td>PEAK</td></tr><tr><td>4</td><td>5949.33</td><td>52.56</td><td>68.30</td><td>-15.74</td><td>38.33</td><td>35.43</td><td>11.36</td><td>32.56</td><td>100</td><td>225</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.44	66.40	112.08	-45.68	52.07	35.30	11.52	32.49	100	225	PEAK	2	5857.94	63.41	109.98	-46.57	49.08	35.30	11.52	32.49	100	225	PEAK	3	5924.58	51.34	68.51	-17.17	37.09	35.39	11.40	32.54	100	225	PEAK	4	5949.33	52.56	68.30	-15.74	38.33	35.43	11.36	32.56	100	225	PEAK	Level (dBuV/m) Date: 2023-08-30 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5825.00</td><td>102.90</td><td>-----</td><td>-----</td><td>88.53</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>225</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	102.90	-----	-----	88.53	35.25	11.58	32.46	100	225	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	5854.44	66.40	112.08	-45.68	52.07	35.30	11.52	32.49	100	225	PEAK																																																																																																																									
2	5857.94	63.41	109.98	-46.57	49.08	35.30	11.52	32.49	100	225	PEAK																																																																																																																									
3	5924.58	51.34	68.51	-17.17	37.09	35.39	11.40	32.54	100	225	PEAK																																																																																																																									
4	5949.33	52.56	68.30	-15.74	38.33	35.43	11.36	32.56	100	225	PEAK																																																																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	5825.00	102.90	-----	-----	88.53	35.25	11.58	32.46	100	225	PEAK																																																																																																																									
Avg	Blank						Level (dBuV/m) Date: 2023-08-30 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5825.00</td><td>96.71</td><td>-----</td><td>-----</td><td>82.34</td><td>35.25</td><td>11.58</td><td>32.46</td><td>100</td><td>225</td><td>AVERAGE</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5825.00	96.71	-----	-----	82.34	35.25	11.58	32.46	100	225	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																											
1	5825.00	96.71	-----	-----	82.34	35.25	11.58	32.46	100	225	AVERAGE																																																																																																																									



Mode	33																																																																																																					
	Harmonic																																																																																																					
	U-NII-3_5.725-5.85_802.11n HT20_CH165_5825MHz																																																																																																					
ANT	SISO																																																																																																					
Pol.	Horizontal	Vertical																																																																																																				
Peak Avg	Level (dBuV/m) Date: 2023-09-05  PART 15.407 PART 15.407.AVG <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11650.00</td><td>49.34</td><td>74.00</td><td>-24.66</td><td>46.70</td><td>38.32</td><td>14.93</td><td>50.61</td><td>---</td><td>--- Peak</td></tr><tr><td>2 17475.00</td><td>49.80</td><td>68.30</td><td>-18.50</td><td>42.72</td><td>41.62</td><td>17.63</td><td>52.17</td><td>---</td><td>--- Peak</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 11650.00	49.34	74.00	-24.66	46.70	38.32	14.93	50.61	---	--- Peak	2 17475.00	49.80	68.30	-18.50	42.72	41.62	17.63	52.17	---	--- Peak	Level (dBuV/m) Date: 2023-09-05  PART 15.407 PART 15.407.AVG <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11650.00</td><td>50.29</td><td>74.00</td><td>-23.71</td><td>47.65</td><td>38.32</td><td>14.93</td><td>50.61</td><td>---</td><td>--- Peak</td></tr><tr><td>2 17475.00</td><td>50.33</td><td>68.30</td><td>-17.97</td><td>43.25</td><td>41.62</td><td>17.63</td><td>52.17</td><td>---</td><td>--- Peak</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 11650.00	50.29	74.00	-23.71	47.65	38.32	14.93	50.61	---	--- Peak	2 17475.00	50.33	68.30	-17.97	43.25	41.62	17.63	52.17	---	--- Peak
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 11650.00	49.34	74.00	-24.66	46.70	38.32	14.93	50.61	---	--- Peak																																																																																													
2 17475.00	49.80	68.30	-18.50	42.72	41.62	17.63	52.17	---	--- Peak																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1 11650.00	50.29	74.00	-23.71	47.65	38.32	14.93	50.61	---	--- Peak																																																																																													
2 17475.00	50.33	68.30	-17.97	43.25	41.62	17.63	52.17	---	--- Peak																																																																																													



Mode	34																																																																																																																																		
	Band Edge - L																																																																																																																																		
	U-NII-3_5.725-5.85_802.11n HT40_CH151_5755MHz																																																																																																																																		
ANT	SISO																																																																																																																																		
Pol.	Horizontal										Fundamental																																																																																																																								
Peak	Level (dBuV/m) Date: 2023-08-30 140 122.5 105.0 70.0 52.5 35.0 17.5 0 5600 5631 5662 5693 5724 5755 PEAK_BE[B4]_10-24 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5645.03</td><td>54.18</td><td>68.30</td><td>-14.12</td><td>39.81</td><td>35.00</td><td>11.69</td><td>32.32</td><td>100</td><td>220</td><td>PEAK</td></tr><tr><td>2</td><td>5651.24</td><td>53.68</td><td>69.22</td><td>-15.54</td><td>39.31</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>220</td><td>PEAK</td></tr><tr><td>3</td><td>5719.99</td><td>65.31</td><td>110.80</td><td>-45.49</td><td>50.92</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>220</td><td>PEAK</td></tr><tr><td>4</td><td>5720.06</td><td>68.70</td><td>110.94</td><td>-42.24</td><td>54.31</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>220</td><td>PEAK</td></tr></table>											Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5645.03	54.18	68.30	-14.12	39.81	35.00	11.69	32.32	100	220	PEAK	2	5651.24	53.68	69.22	-15.54	39.31	35.01	11.69	32.33	100	220	PEAK	3	5719.99	65.31	110.80	-45.49	50.92	35.11	11.66	32.38	100	220	PEAK	4	5720.06	68.70	110.94	-42.24	54.31	35.11	11.66	32.38	100	220	PEAK	Level (dBuV/m) Date: 2023-08-30 140 122.5 105.0 70.0 52.5 35.0 17.5 0 1000 2200 3400 4600 5800 7000 PART 15.407 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5755.00</td><td>102.27</td><td>-----</td><td>-----</td><td>87.88</td><td>35.16</td><td>11.64</td><td>32.41</td><td>100</td><td>220</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5755.00	102.27	-----	-----	87.88	35.16	11.64	32.41	100	220	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5645.03	54.18	68.30	-14.12	39.81	35.00	11.69	32.32	100	220	PEAK																																																																																																																								
2	5651.24	53.68	69.22	-15.54	39.31	35.01	11.69	32.33	100	220	PEAK																																																																																																																								
3	5719.99	65.31	110.80	-45.49	50.92	35.11	11.66	32.38	100	220	PEAK																																																																																																																								
4	5720.06	68.70	110.94	-42.24	54.31	35.11	11.66	32.38	100	220	PEAK																																																																																																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5755.00	102.27	-----	-----	87.88	35.16	11.64	32.41	100	220	PEAK																																																																																																																								
Avg	Blank										Level (dBuV/m) Date: 2023-08-30 140 122.5 105.0 70.0 52.5 35.0 17.5 0 1000 2200 3400 4600 5800 7000 PART 15.407 AVG <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5755.00</td><td>95.39</td><td>-----</td><td>-----</td><td>81.00</td><td>35.16</td><td>11.64</td><td>32.41</td><td>100</td><td>220</td><td>AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5755.00	95.39	-----	-----	81.00	35.16	11.64	32.41	100	220	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5755.00	95.39	-----	-----	81.00	35.16	11.64	32.41	100	220	AVERAGE																																																																																																																								



Mode	34																																																																																																																																		
	Band Edge - L																																																																																																																																		
	U-NII-3_5.725-5.85_802.11n HT40_CH151_5755MHz																																																																																																																																		
ANT	SISO																																																																																																																																		
Pol.	Vertical						Fundamental																																																																																																																												
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5609.53</td><td>54.27</td><td>68.30</td><td>-14.03</td><td>39.91</td><td>34.95</td><td>11.71</td><td>32.30</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>2</td><td>5650.31</td><td>52.67</td><td>68.53</td><td>-15.86</td><td>38.30</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>3</td><td>5712.16</td><td>63.45</td><td>108.61</td><td>-45.16</td><td>49.07</td><td>35.10</td><td>11.66</td><td>32.38</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>4</td><td>5720.68</td><td>65.09</td><td>112.36</td><td>-47.27</td><td>50.70</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>226</td><td>PEAK</td></tr></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5609.53	54.27	68.30	-14.03	39.91	34.95	11.71	32.30	100	226	PEAK	2	5650.31	52.67	68.53	-15.86	38.30	35.01	11.69	32.33	100	226	PEAK	3	5712.16	63.45	108.61	-45.16	49.07	35.10	11.66	32.38	100	226	PEAK	4	5720.68	65.09	112.36	-47.27	50.70	35.11	11.66	32.38	100	226	PEAK	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5755.00</td><td>101.47</td><td>-----</td><td>-----</td><td>87.08</td><td>35.16</td><td>11.64</td><td>32.41</td><td>100</td><td>226</td><td>PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5755.00	101.47	-----	-----	87.08	35.16	11.64	32.41	100	226	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5609.53	54.27	68.30	-14.03	39.91	34.95	11.71	32.30	100	226	PEAK																																																																																																																								
2	5650.31	52.67	68.53	-15.86	38.30	35.01	11.69	32.33	100	226	PEAK																																																																																																																								
3	5712.16	63.45	108.61	-45.16	49.07	35.10	11.66	32.38	100	226	PEAK																																																																																																																								
4	5720.68	65.09	112.36	-47.27	50.70	35.11	11.66	32.38	100	226	PEAK																																																																																																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5755.00	101.47	-----	-----	87.08	35.16	11.64	32.41	100	226	PEAK																																																																																																																								
Avg	Blank						Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5755.00</td><td>95.25</td><td>-----</td><td>-----</td><td>80.86</td><td>35.16</td><td>11.64</td><td>32.41</td><td>100</td><td>226</td><td>AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5755.00	95.25	-----	-----	80.86	35.16	11.64	32.41	100	226	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																													
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	5755.00	95.25	-----	-----	80.86	35.16	11.64	32.41	100	226	AVERAGE																																																																																																																								




Mode	34																																																								
	Band Edge - R																																																								
	U-NII-3_5.725-5.85_802.11n HT40_CH151_5755MHz																																																								
ANT	SISO																																																								
Pol.	Vertical	Fundamental																																																							
Peak	Date: 2023-08-31 Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor cm deg Remark <table><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th>Remark</th></tr><tr><td>1</td><td>5854.96</td><td>53.83</td><td>110.90</td><td>-57.07</td><td>39.50</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>226 PEAK</td></tr><tr><td>2</td><td>5873.07</td><td>52.19</td><td>105.74</td><td>-53.55</td><td>37.88</td><td>35.32</td><td>11.49</td><td>32.50</td><td>100</td><td>226 PEAK</td></tr><tr><td>3</td><td>5924.75</td><td>51.42</td><td>68.39</td><td>-16.97</td><td>37.17</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>226 PEAK</td></tr><tr><td>4</td><td>5937.25</td><td>53.00</td><td>68.30</td><td>-15.30</td><td>38.76</td><td>35.41</td><td>11.38</td><td>32.55</td><td>100</td><td>226 PEAK</td></tr></table>		MHz	dBuV/m	dBuV/m	dB	dB/m	dB	dB	cm	deg	Remark	1	5854.96	53.83	110.90	-57.07	39.50	35.30	11.52	32.49	100	226 PEAK	2	5873.07	52.19	105.74	-53.55	37.88	35.32	11.49	32.50	100	226 PEAK	3	5924.75	51.42	68.39	-16.97	37.17	35.39	11.40	32.54	100	226 PEAK	4	5937.25	53.00	68.30	-15.30	38.76	35.41	11.38	32.55	100	226 PEAK	Blank
	MHz	dBuV/m	dBuV/m	dB	dB/m	dB	dB	cm	deg	Remark																																															
1	5854.96	53.83	110.90	-57.07	39.50	35.30	11.52	32.49	100	226 PEAK																																															
2	5873.07	52.19	105.74	-53.55	37.88	35.32	11.49	32.50	100	226 PEAK																																															
3	5924.75	51.42	68.39	-16.97	37.17	35.39	11.40	32.54	100	226 PEAK																																															
4	5937.25	53.00	68.30	-15.30	38.76	35.41	11.38	32.55	100	226 PEAK																																															



Mode	35																																																																																																																				
	Band Edge - L																																																																																																																				
	U-NII-3_5.725-5.85_802.11n HT40_CH159_5795MHz																																																																																																																				
ANT	SISO																																																																																																																				
Pol.	Horizontal	Fundamental																																																																																																																			
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5608.48</td><td>53.82</td><td>68.30</td><td>-14.48</td><td>39.45</td><td>34.95</td><td>11.71</td><td>32.29</td><td>100</td><td>219 PEAK</td></tr><tr><td>2</td><td>5652.16</td><td>52.96</td><td>69.90</td><td>-16.94</td><td>38.59</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>219 PEAK</td></tr><tr><td>3</td><td>5700.74</td><td>52.66</td><td>105.41</td><td>-52.75</td><td>38.29</td><td>35.08</td><td>11.66</td><td>32.37</td><td>100</td><td>219 PEAK</td></tr><tr><td>4</td><td>5720.02</td><td>55.37</td><td>110.85</td><td>-55.48</td><td>40.98</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>219 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5608.48	53.82	68.30	-14.48	39.45	34.95	11.71	32.29	100	219 PEAK	2	5652.16	52.96	69.90	-16.94	38.59	35.01	11.69	32.33	100	219 PEAK	3	5700.74	52.66	105.41	-52.75	38.29	35.08	11.66	32.37	100	219 PEAK	4	5720.02	55.37	110.85	-55.48	40.98	35.11	11.66	32.38	100	219 PEAK	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5795.00</td><td>102.09</td><td>-----</td><td>-----</td><td>87.69</td><td>35.22</td><td>11.62</td><td>32.44</td><td>100</td><td>219 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5795.00	102.09	-----	-----	87.69	35.22	11.62	32.44	100	219 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5608.48	53.82	68.30	-14.48	39.45	34.95	11.71	32.29	100	219 PEAK																																																																																																											
2	5652.16	52.96	69.90	-16.94	38.59	35.01	11.69	32.33	100	219 PEAK																																																																																																											
3	5700.74	52.66	105.41	-52.75	38.29	35.08	11.66	32.37	100	219 PEAK																																																																																																											
4	5720.02	55.37	110.85	-55.48	40.98	35.11	11.66	32.38	100	219 PEAK																																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5795.00	102.09	-----	-----	87.69	35.22	11.62	32.44	100	219 PEAK																																																																																																											
Avg	Blank	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5795.00</td><td>95.50</td><td>-----</td><td>-----</td><td>81.11</td><td>35.21</td><td>11.62</td><td>32.44</td><td>100</td><td>219 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5795.00	95.50	-----	-----	81.11	35.21	11.62	32.44	100	219 AVERAGE																																																																										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5795.00	95.50	-----	-----	81.11	35.21	11.62	32.44	100	219 AVERAGE																																																																																																											



Mode	35																																																																											
	Band Edge - R																																																																											
	U-NII-3_5.725-5.85_802.11n HT40_CH159_5795MHz																																																																											
ANT	SISO																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Date: 2023-08-31 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5854.99</td><td>56.51</td><td>110.83</td><td>-54.32</td><td>42.18</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>219 PEAK</td></tr><tr><td>2</td><td>5869.65</td><td>57.61</td><td>106.70</td><td>-49.09</td><td>43.29</td><td>35.32</td><td>11.50</td><td>32.50</td><td>100</td><td>219 PEAK</td></tr><tr><td>3</td><td>5924.52</td><td>52.11</td><td>68.56</td><td>-16.45</td><td>37.86</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>219 PEAK</td></tr><tr><td>4</td><td>5932.41</td><td>53.37</td><td>68.30</td><td>-14.93</td><td>39.12</td><td>35.41</td><td>11.39</td><td>32.55</td><td>100</td><td>219 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.99	56.51	110.83	-54.32	42.18	35.30	11.52	32.49	100	219 PEAK	2	5869.65	57.61	106.70	-49.09	43.29	35.32	11.50	32.50	100	219 PEAK	3	5924.52	52.11	68.56	-16.45	37.86	35.39	11.40	32.54	100	219 PEAK	4	5932.41	53.37	68.30	-14.93	39.12	35.41	11.39	32.55	100	219 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																			
1	5854.99	56.51	110.83	-54.32	42.18	35.30	11.52	32.49	100	219 PEAK																																																																		
2	5869.65	57.61	106.70	-49.09	43.29	35.32	11.50	32.50	100	219 PEAK																																																																		
3	5924.52	52.11	68.56	-16.45	37.86	35.39	11.40	32.54	100	219 PEAK																																																																		
4	5932.41	53.37	68.30	-14.93	39.12	35.41	11.39	32.55	100	219 PEAK																																																																		



Mode	35																																																																																																																									
	Band Edge - L																																																																																																																									
	U-NII-3_5.725-5.85_802.11n HT40_CH159_5795MHz																																																																																																																									
ANT	SISO																																																																																																																									
Pol.	Vertical	Fundamental																																																																																																																								
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5618.45</td><td>53.29</td><td>68.30</td><td>-15.01</td><td>38.92</td><td>34.97</td><td>11.70</td><td>32.30</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>2</td><td>5650.04</td><td>51.99</td><td>68.33</td><td>-16.34</td><td>37.62</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>3</td><td>5700.74</td><td>53.59</td><td>105.41</td><td>-51.82</td><td>39.22</td><td>35.08</td><td>11.66</td><td>32.37</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>4</td><td>5720.00</td><td>52.95</td><td>110.81</td><td>-57.86</td><td>38.56</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>226</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5618.45	53.29	68.30	-15.01	38.92	34.97	11.70	32.30	100	226	PEAK	2	5650.04	51.99	68.33	-16.34	37.62	35.01	11.69	32.33	100	226	PEAK	3	5700.74	53.59	105.41	-51.82	39.22	35.08	11.66	32.37	100	226	PEAK	4	5720.00	52.95	110.81	-57.86	38.56	35.11	11.66	32.38	100	226	PEAK	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5795.00</td><td>101.52</td><td>-----</td><td>-----</td><td>87.13</td><td>35.21</td><td>11.62</td><td>32.44</td><td>100</td><td>226</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5795.00	101.52	-----	-----	87.13	35.21	11.62	32.44	100	226	PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5618.45	53.29	68.30	-15.01	38.92	34.97	11.70	32.30	100	226	PEAK																																																																																																															
2	5650.04	51.99	68.33	-16.34	37.62	35.01	11.69	32.33	100	226	PEAK																																																																																																															
3	5700.74	53.59	105.41	-51.82	39.22	35.08	11.66	32.37	100	226	PEAK																																																																																																															
4	5720.00	52.95	110.81	-57.86	38.56	35.11	11.66	32.38	100	226	PEAK																																																																																																															
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5795.00	101.52	-----	-----	87.13	35.21	11.62	32.44	100	226	PEAK																																																																																																															
Avg	Blank	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5795.00</td><td>95.10</td><td>-----</td><td>-----</td><td>80.71</td><td>35.21</td><td>11.62</td><td>32.44</td><td>100</td><td>226</td><td>AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5795.00	95.10	-----	-----	80.71	35.21	11.62	32.44	100	226	AVERAGE																																																																														
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																	
1	5795.00	95.10	-----	-----	80.71	35.21	11.62	32.44	100	226	AVERAGE																																																																																																															



Mode	35																																																																															
	Band Edge - R																																																																															
	U-NII-3_5.725-5.85_802.11n HT40_CH159_5795MHz																																																																															
ANT	SISO																																																																															
Pol.	Vertical	Fundamental																																																																														
Peak	Date: 2023-08-31 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5854.77</td><td>58.50</td><td>111.33</td><td>-52.83</td><td>44.17</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>2</td><td>5862.52</td><td>57.86</td><td>108.69</td><td>-50.83</td><td>43.53</td><td>35.31</td><td>11.51</td><td>32.49</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>3</td><td>5924.36</td><td>52.03</td><td>68.67</td><td>-16.64</td><td>37.78</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>226</td><td>PEAK</td></tr><tr><td>4</td><td>5949.15</td><td>53.09</td><td>68.30</td><td>-15.21</td><td>38.86</td><td>35.43</td><td>11.36</td><td>32.56</td><td>100</td><td>226</td><td>PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.77	58.50	111.33	-52.83	44.17	35.30	11.52	32.49	100	226	PEAK	2	5862.52	57.86	108.69	-50.83	43.53	35.31	11.51	32.49	100	226	PEAK	3	5924.36	52.03	68.67	-16.64	37.78	35.39	11.40	32.54	100	226	PEAK	4	5949.15	53.09	68.30	-15.21	38.86	35.43	11.36	32.56	100	226	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																							
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1	5854.77	58.50	111.33	-52.83	44.17	35.30	11.52	32.49	100	226	PEAK																																																																					
2	5862.52	57.86	108.69	-50.83	43.53	35.31	11.51	32.49	100	226	PEAK																																																																					
3	5924.36	52.03	68.67	-16.64	37.78	35.39	11.40	32.54	100	226	PEAK																																																																					
4	5949.15	53.09	68.30	-15.21	38.86	35.43	11.36	32.56	100	226	PEAK																																																																					



Mode	36																																																																																																																				
	Band Edge - L																																																																																																																				
	U-NII-3_5.725-5.85_802.11ac VHT80_CH155_5775MHz																																																																																																																				
ANT	SISO																																																																																																																				
Pol.	Horizontal	Fundamental																																																																																																																			
Peak	Date: 2023-08-31 Level (dBuV/m) Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5612.71</td><td>53.75</td><td>68.30</td><td>-14.55</td><td>39.38</td><td>34.96</td><td>11.71</td><td>32.30</td><td>100</td><td>218 PEAK</td></tr><tr><td>2</td><td>5650.02</td><td>53.19</td><td>68.31</td><td>-15.12</td><td>38.82</td><td>35.01</td><td>11.69</td><td>32.33</td><td>100</td><td>218 PEAK</td></tr><tr><td>3</td><td>5708.41</td><td>61.24</td><td>107.56</td><td>-46.32</td><td>46.86</td><td>35.09</td><td>11.66</td><td>32.37</td><td>100</td><td>218 PEAK</td></tr><tr><td>4</td><td>5720.31</td><td>61.37</td><td>111.51</td><td>-50.14</td><td>46.98</td><td>35.11</td><td>11.66</td><td>32.38</td><td>100</td><td>218 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5612.71	53.75	68.30	-14.55	39.38	34.96	11.71	32.30	100	218 PEAK	2	5650.02	53.19	68.31	-15.12	38.82	35.01	11.69	32.33	100	218 PEAK	3	5708.41	61.24	107.56	-46.32	46.86	35.09	11.66	32.37	100	218 PEAK	4	5720.31	61.37	111.51	-50.14	46.98	35.11	11.66	32.38	100	218 PEAK	Date: 2023-08-31 Level (dBuV/m) Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5775.00</td><td>99.37</td><td>-----</td><td>-----</td><td>84.99</td><td>35.17</td><td>11.63</td><td>32.42</td><td>100</td><td>218 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5775.00	99.37	-----	-----	84.99	35.17	11.63	32.42	100	218 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5612.71	53.75	68.30	-14.55	39.38	34.96	11.71	32.30	100	218 PEAK																																																																																																											
2	5650.02	53.19	68.31	-15.12	38.82	35.01	11.69	32.33	100	218 PEAK																																																																																																											
3	5708.41	61.24	107.56	-46.32	46.86	35.09	11.66	32.37	100	218 PEAK																																																																																																											
4	5720.31	61.37	111.51	-50.14	46.98	35.11	11.66	32.38	100	218 PEAK																																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5775.00	99.37	-----	-----	84.99	35.17	11.63	32.42	100	218 PEAK																																																																																																											
Avg	Blank	Date: 2023-08-31 Level (dBuV/m) Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5775.00</td><td>87.77</td><td>-----</td><td>-----</td><td>73.38</td><td>35.18</td><td>11.63</td><td>32.42</td><td>100</td><td>218 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5775.00	87.77	-----	-----	73.38	35.18	11.63	32.42	100	218 AVERAGE																																																																										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																															
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																												
1	5775.00	87.77	-----	-----	73.38	35.18	11.63	32.42	100	218 AVERAGE																																																																																																											



Mode	36																																																																											
	Band Edge - R																																																																											
	U-NII-3_5.725-5.85_802.11ac VHT80_CH155_5775MHz																																																																											
ANT	SISO																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5854.91</td><td>52.61</td><td>111.02</td><td>-58.41</td><td>38.28</td><td>35.30</td><td>11.52</td><td>32.49</td><td>100</td><td>218 PEAK</td></tr><tr><td>2</td><td>5874.49</td><td>53.74</td><td>105.34</td><td>-51.60</td><td>39.43</td><td>35.32</td><td>11.49</td><td>32.50</td><td>100</td><td>218 PEAK</td></tr><tr><td>3</td><td>5924.99</td><td>52.38</td><td>68.21</td><td>-15.83</td><td>38.13</td><td>35.39</td><td>11.40</td><td>32.54</td><td>100</td><td>218 PEAK</td></tr><tr><td>4</td><td>5937.31</td><td>54.66</td><td>68.30</td><td>-13.64</td><td>40.42</td><td>35.41</td><td>11.38</td><td>32.55</td><td>100</td><td>218 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.91	52.61	111.02	-58.41	38.28	35.30	11.52	32.49	100	218 PEAK	2	5874.49	53.74	105.34	-51.60	39.43	35.32	11.49	32.50	100	218 PEAK	3	5924.99	52.38	68.21	-15.83	38.13	35.39	11.40	32.54	100	218 PEAK	4	5937.31	54.66	68.30	-13.64	40.42	35.41	11.38	32.55	100	218 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																			
1	5854.91	52.61	111.02	-58.41	38.28	35.30	11.52	32.49	100	218 PEAK																																																																		
2	5874.49	53.74	105.34	-51.60	39.43	35.32	11.49	32.50	100	218 PEAK																																																																		
3	5924.99	52.38	68.21	-15.83	38.13	35.39	11.40	32.54	100	218 PEAK																																																																		
4	5937.31	54.66	68.30	-13.64	40.42	35.41	11.38	32.55	100	218 PEAK																																																																		



Mode	36																																																																																																																												
	Band Edge - L																																																																																																																												
	U-NII-3_5.725-5.85_802.11ac VHT80_CH155_5775MHz																																																																																																																												
ANT	SISO																																																																																																																												
Pol.	Vertical					Fundamental																																																																																																																							
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5650.02</td><td>53.88</td><td>68.31</td><td>-14.43</td><td>39.51</td><td>35.01</td><td>11.69</td><td>32.33</td><td>247</td><td>156 PEAK</td></tr><tr><td>2</td><td>5700.01</td><td>58.94</td><td>105.20</td><td>-46.26</td><td>44.57</td><td>35.08</td><td>11.66</td><td>32.37</td><td>247</td><td>156 PEAK</td></tr><tr><td>3</td><td>5700.01</td><td>58.94</td><td>105.20</td><td>-46.26</td><td>44.57</td><td>35.08</td><td>11.66</td><td>32.37</td><td>247</td><td>156</td></tr><tr><td>4</td><td>5720.02</td><td>60.09</td><td>110.83</td><td>-50.74</td><td>45.70</td><td>35.11</td><td>11.66</td><td>32.38</td><td>247</td><td>156 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5650.02	53.88	68.31	-14.43	39.51	35.01	11.69	32.33	247	156 PEAK	2	5700.01	58.94	105.20	-46.26	44.57	35.08	11.66	32.37	247	156 PEAK	3	5700.01	58.94	105.20	-46.26	44.57	35.08	11.66	32.37	247	156	4	5720.02	60.09	110.83	-50.74	45.70	35.11	11.66	32.38	247	156 PEAK	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5775.00</td><td>96.10</td><td>-----</td><td>-----</td><td>81.72</td><td>35.17</td><td>11.63</td><td>32.42</td><td>247</td><td>156 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5775.00	96.10	-----	-----	81.72	35.17	11.63	32.42	247	156 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	5650.02	53.88	68.31	-14.43	39.51	35.01	11.69	32.33	247	156 PEAK																																																																																																																			
2	5700.01	58.94	105.20	-46.26	44.57	35.08	11.66	32.37	247	156 PEAK																																																																																																																			
3	5700.01	58.94	105.20	-46.26	44.57	35.08	11.66	32.37	247	156																																																																																																																			
4	5720.02	60.09	110.83	-50.74	45.70	35.11	11.66	32.38	247	156 PEAK																																																																																																																			
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	5775.00	96.10	-----	-----	81.72	35.17	11.63	32.42	247	156 PEAK																																																																																																																			
Avg	Blank					Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5775.00</td><td>87.56</td><td>-----</td><td>-----</td><td>73.18</td><td>35.17</td><td>11.63</td><td>32.42</td><td>247</td><td>156 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5775.00	87.56	-----	-----	73.18	35.17	11.63	32.42	247	156 AVERAGE																																																																										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																																																						
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																																																				
1	5775.00	87.56	-----	-----	73.18	35.17	11.63	32.42	247	156 AVERAGE																																																																																																																			



Mode	36																																																																											
	Band Edge - R																																																																											
	U-NII-3_5.725-5.85_802.11ac VHT80_CH155_5775MHz																																																																											
ANT	SISO																																																																											
Pol.	Vertical	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2023-08-31 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5854.99</td><td>52.09</td><td>110.82</td><td>-58.73</td><td>37.76</td><td>35.30</td><td>11.52</td><td>32.49</td><td>247</td><td>156 PEAK</td></tr><tr><td>2</td><td>5875.00</td><td>52.63</td><td>105.20</td><td>-52.57</td><td>38.32</td><td>35.32</td><td>11.49</td><td>32.50</td><td>247</td><td>156 PEAK</td></tr><tr><td>3</td><td>5924.73</td><td>52.83</td><td>68.40</td><td>-15.57</td><td>38.58</td><td>35.39</td><td>11.40</td><td>32.54</td><td>247</td><td>156 PEAK</td></tr><tr><td>4</td><td>5948.36</td><td>54.65</td><td>68.30</td><td>-13.65</td><td>40.42</td><td>35.43</td><td>11.36</td><td>32.56</td><td>247</td><td>156 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5854.99	52.09	110.82	-58.73	37.76	35.30	11.52	32.49	247	156 PEAK	2	5875.00	52.63	105.20	-52.57	38.32	35.32	11.49	32.50	247	156 PEAK	3	5924.73	52.83	68.40	-15.57	38.58	35.39	11.40	32.54	247	156 PEAK	4	5948.36	54.65	68.30	-13.65	40.42	35.43	11.36	32.56	247	156 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																			
1	5854.99	52.09	110.82	-58.73	37.76	35.30	11.52	32.49	247	156 PEAK																																																																		
2	5875.00	52.63	105.20	-52.57	38.32	35.32	11.49	32.50	247	156 PEAK																																																																		
3	5924.73	52.83	68.40	-15.57	38.58	35.39	11.40	32.54	247	156 PEAK																																																																		
4	5948.36	54.65	68.30	-13.65	40.42	35.43	11.36	32.56	247	156 PEAK																																																																		



Mode	36																																																																																																					
	Harmonic																																																																																																					
	U-NII-3_5.725-5.85_802.11ac VHT80_CH155_5775MHz																																																																																																					
ANT	SISO																																																																																																					
Pol.	Horizontal	Vertical																																																																																																				
Peak Avg	Level (dBuV/m) Date: 2023-09-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11550.00</td><td>50.06</td><td>74.00</td><td>-23.94</td><td>47.62</td><td>38.24</td><td>14.87</td><td>50.67</td><td>--- Peak</td></tr><tr><td>2</td><td>17325.00</td><td>50.23</td><td>68.30</td><td>-18.07</td><td>42.89</td><td>41.77</td><td>17.59</td><td>52.02</td><td>--- Peak</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	11550.00	50.06	74.00	-23.94	47.62	38.24	14.87	50.67	--- Peak	2	17325.00	50.23	68.30	-18.07	42.89	41.77	17.59	52.02	--- Peak	Level (dBuV/m) Date: 2023-09-05 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11550.00</td><td>49.89</td><td>74.00</td><td>-24.11</td><td>47.45</td><td>38.24</td><td>14.87</td><td>50.67</td><td>--- Peak</td></tr><tr><td>2</td><td>17325.00</td><td>50.51</td><td>68.30</td><td>-17.79</td><td>43.17</td><td>41.77</td><td>17.59</td><td>52.02</td><td>--- Peak</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	11550.00	49.89	74.00	-24.11	47.45	38.24	14.87	50.67	--- Peak	2	17325.00	50.51	68.30	-17.79	43.17	41.77	17.59	52.02	--- Peak
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																													
	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	11550.00	50.06	74.00	-23.94	47.62	38.24	14.87	50.67	--- Peak																																																																																													
2	17325.00	50.23	68.30	-18.07	42.89	41.77	17.59	52.02	--- Peak																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																													
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	11550.00	49.89	74.00	-24.11	47.45	38.24	14.87	50.67	--- Peak																																																																																													
2	17325.00	50.51	68.30	-17.79	43.17	41.77	17.59	52.02	--- Peak																																																																																													



Mode	38																																																																																																																																																																																									
	LF																																																																																																																																																																																									
	U-NII-3_5.725-5.85_802.11ac VHT80_5775MHz																																																																																																																																																																																									
ANT	SISO																																																																																																																																																																																									
Pol.	Horizontal										Vertical																																																																																																																																																																															
QPI/ Peak	Data: 1 Level (dBuV/m) Date: 2023-09-05 Frequency (MHz) <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>34.850</td><td>18.86</td><td>-21.14</td><td>40.00</td><td>26.49</td><td>22.30</td><td>1.27</td><td>31.20</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>93.050</td><td>25.82</td><td>-17.68</td><td>43.50</td><td>39.62</td><td>15.64</td><td>1.83</td><td>31.27</td><td>---</td><td>Peak</td></tr><tr><td>3</td><td>143.490</td><td>20.30</td><td>-23.20</td><td>43.50</td><td>32.17</td><td>17.07</td><td>2.17</td><td>31.11</td><td>---</td><td>Peak</td></tr><tr><td>4</td><td>299.660</td><td>30.48</td><td>-15.52</td><td>46.00</td><td>39.26</td><td>19.40</td><td>2.72</td><td>30.90</td><td>---</td><td>Peak</td></tr><tr><td>5</td><td>450.980</td><td>25.25</td><td>-20.75</td><td>46.00</td><td>29.63</td><td>23.01</td><td>3.31</td><td>30.70</td><td>---</td><td>Peak</td></tr><tr><td>6</td><td>851.590</td><td>29.34</td><td>-16.66</td><td>46.00</td><td>29.49</td><td>26.51</td><td>4.39</td><td>31.05</td><td>---</td><td>Peak</td></tr></tbody></table> Data: 2 Level (dBuV/m) Date: 2023-09-05 Frequency (MHz) <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>33.880</td><td>32.41</td><td>-7.59</td><td>40.00</td><td>39.48</td><td>22.88</td><td>1.25</td><td>31.20</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>92.080</td><td>31.69</td><td>-11.81</td><td>43.50</td><td>45.67</td><td>15.46</td><td>1.84</td><td>31.28</td><td>---</td><td>Peak</td></tr><tr><td>3</td><td>168.710</td><td>22.11</td><td>-21.39</td><td>43.50</td><td>35.00</td><td>15.85</td><td>2.29</td><td>31.03</td><td>---</td><td>Peak</td></tr><tr><td>4</td><td>289.960</td><td>20.85</td><td>-25.15</td><td>46.00</td><td>29.77</td><td>19.30</td><td>2.68</td><td>30.90</td><td>---</td><td>Peak</td></tr><tr><td>5</td><td>450.010</td><td>27.78</td><td>-18.22</td><td>46.00</td><td>32.17</td><td>23.00</td><td>3.31</td><td>30.70</td><td>---</td><td>Peak</td></tr><tr><td>6</td><td>648.860</td><td>28.74</td><td>-17.26</td><td>46.00</td><td>30.61</td><td>25.19</td><td>3.84</td><td>30.90</td><td>---</td><td>Peak</td></tr></tbody></table>											Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	34.850	18.86	-21.14	40.00	26.49	22.30	1.27	31.20	---	Peak	2	93.050	25.82	-17.68	43.50	39.62	15.64	1.83	31.27	---	Peak	3	143.490	20.30	-23.20	43.50	32.17	17.07	2.17	31.11	---	Peak	4	299.660	30.48	-15.52	46.00	39.26	19.40	2.72	30.90	---	Peak	5	450.980	25.25	-20.75	46.00	29.63	23.01	3.31	30.70	---	Peak	6	851.590	29.34	-16.66	46.00	29.49	26.51	4.39	31.05	---	Peak		Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	33.880	32.41	-7.59	40.00	39.48	22.88	1.25	31.20	---	Peak	2	92.080	31.69	-11.81	43.50	45.67	15.46	1.84	31.28	---	Peak	3	168.710	22.11	-21.39	43.50	35.00	15.85	2.29	31.03	---	Peak	4	289.960	20.85	-25.15	46.00	29.77	19.30	2.68	30.90	---	Peak	5	450.010	27.78	-18.22	46.00	32.17	23.00	3.31	30.70	---	Peak	6	648.860	28.74	-17.26	46.00	30.61	25.19	3.84	30.90	---	Peak
		Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																																																																																																																																															
		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																																															
	1	34.850	18.86	-21.14	40.00	26.49	22.30	1.27	31.20	---	Peak																																																																																																																																																																															
	2	93.050	25.82	-17.68	43.50	39.62	15.64	1.83	31.27	---	Peak																																																																																																																																																																															
	3	143.490	20.30	-23.20	43.50	32.17	17.07	2.17	31.11	---	Peak																																																																																																																																																																															
	4	299.660	30.48	-15.52	46.00	39.26	19.40	2.72	30.90	---	Peak																																																																																																																																																																															
	5	450.980	25.25	-20.75	46.00	29.63	23.01	3.31	30.70	---	Peak																																																																																																																																																																															
	6	851.590	29.34	-16.66	46.00	29.49	26.51	4.39	31.05	---	Peak																																																																																																																																																																															
		Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																																																																																																																																															
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																																																
1	33.880	32.41	-7.59	40.00	39.48	22.88	1.25	31.20	---	Peak																																																																																																																																																																																
2	92.080	31.69	-11.81	43.50	45.67	15.46	1.84	31.28	---	Peak																																																																																																																																																																																
3	168.710	22.11	-21.39	43.50	35.00	15.85	2.29	31.03	---	Peak																																																																																																																																																																																
4	289.960	20.85	-25.15	46.00	29.77	19.30	2.68	30.90	---	Peak																																																																																																																																																																																
5	450.010	27.78	-18.22	46.00	32.17	23.00	3.31	30.70	---	Peak																																																																																																																																																																																
6	648.860	28.74	-17.26	46.00	30.61	25.19	3.84	30.90	---	Peak																																																																																																																																																																																



Mode	39	
	Band Edge	
	Co-location_802.11a_CH64_5320MHz+LTE Band13	
Pol.	Horizontal	Fundamental
Peak	Data: 2 Level (dBuV/m) </	



Mode	39	
	Band Edge	
	Co-location_802.11a_CH64_5320MHz+LTE Band13	
Pol.	Vertical	Fundamental
Peak		



Mode	39									
	Harmonic									
	Co-location_802.11a_CH64_5320MHz+LTE Band13									
ANT										
Pol.	Horizontal					Vertical				
Peak Avg	Data: 11 Level (dBuV/m) <									

Note: the highest signals over limit is WLAN 5G fundamental signal.



Mode	40																																																																							
	Band Edge - L																																																																							
	U-NII-2A_5.25-5.35_802.11a_CH56_5280MHz																																																																							
ANT	SISO																																																																							
Pol.	Horizontal	Pol.																																																																						
Peak	Data: 1 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) HORIZONTAL RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB 6M Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5025.550</td><td>52.36</td><td>-21.64</td><td>74.00</td><td>37.94</td><td>34.89</td><td>11.16</td><td>31.63</td><td>100</td><td>137 Peak</td></tr></table>	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5025.550	52.36	-21.64	74.00	37.94	34.89	11.16	31.63	100	137 Peak	Data: 3 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) HORIZONTAL RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB 6M Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5280.000</td><td>98.81</td><td>30.51</td><td>68.30</td><td>84.93</td><td>34.84</td><td>10.99</td><td>31.95</td><td>100</td><td>137 Peak</td></tr><tr><td>2 5280.000</td><td>91.25</td><td>-----</td><td>-----</td><td>77.37</td><td>34.84</td><td>10.99</td><td>31.95</td><td>100</td><td>137 Average</td></tr></table>	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5280.000	98.81	30.51	68.30	84.93	34.84	10.99	31.95	100	137 Peak	2 5280.000	91.25	-----	-----	77.37	34.84	10.99	31.95	100	137 Average
	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																														
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																															
1 5025.550	52.36	-21.64	74.00	37.94	34.89	11.16	31.63	100	137 Peak																																																															
Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																															
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																															
1 5280.000	98.81	30.51	68.30	84.93	34.84	10.99	31.95	100	137 Peak																																																															
2 5280.000	91.25	-----	-----	77.37	34.84	10.99	31.95	100	137 Average																																																															
Avg	Data: 2 Site : 03CH01-SZ Condition : PART 15.407 AVG 3m HF_ANT(3117) HORIZONTAL RBW:1000.000KHz VBW:1.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB 6M Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5044.450</td><td>42.75</td><td>-11.25</td><td>54.00</td><td>28.38</td><td>34.89</td><td>11.14</td><td>31.66</td><td>100</td><td>137 Average</td></tr></table>	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5044.450	42.75	-11.25	54.00	28.38	34.89	11.14	31.66	100	137 Average	Blank																																								
Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																															
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																															
1 5044.450	42.75	-11.25	54.00	28.38	34.89	11.14	31.66	100	137 Average																																																															



Mode	40																																							
	Band Edge - R																																							
	U-NII-2A_5.25-5.35_802.11a_CH56_5280MHz																																							
ANT	SISO																																							
Pol.	Horizontal					Pol.																																		
Peak	Data: 4 Date: 2023-09-29 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) HORIZONTAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB : 6M Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5351.040</td><td>52.12</td><td>-21.88</td><td>74.00</td><td>38.40</td><td>34.83</td><td>10.93</td><td>32.04</td><td>100</td><td>137 Peak</td></tr></table>					Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5351.040	52.12	-21.88	74.00	38.40	34.83	10.93	32.04	100	137 Peak	Blank				
Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																															
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																															
1 5351.040	52.12	-21.88	74.00	38.40	34.83	10.93	32.04	100	137 Peak																															
Avg	Data: 5 Date: 2023-09-29 Site : 03CH01-SZ Condition : PART 15.407 AVG 3m HF_ANT(3117) HORIZONTAL : RBW:1000.000KHz VBW:1.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB : 6M Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5350.560</td><td>42.71</td><td>-11.29</td><td>54.00</td><td>28.99</td><td>34.83</td><td>10.93</td><td>32.04</td><td>100</td><td>137 Average</td></tr></table>					Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5350.560	42.71	-11.29	54.00	28.99	34.83	10.93	32.04	100	137 Average	Blank				
Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																															
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																															
1 5350.560	42.71	-11.29	54.00	28.99	34.83	10.93	32.04	100	137 Average																															



		40									
Mode		Band Edge - L									
		U-NII-2A_5.25-5.35_802.11a_CH56_5280MHz									
ANT		SISO									
Pol.		Vertical					Pol.				
Peak											



Mode	40																																										
Mode	Band Edge - R																																										
Mode	U-NII-2A_5.25-5.35_802.11a_CH56_5280MHz																																										
ANT	SISO																																										
Pol.	Vertical					Pol.																																					
Peak	Data: 9 Level (dBuV/m) Date: 2023-09-29 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB : 6M Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5350.800</td><td>54.41</td><td>-19.59</td><td>74.00</td><td>40.69</td><td>34.83</td><td>10.93</td><td>32.04</td><td>100</td><td>212 Peak</td></tr></tbody></table>						Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.800	54.41	-19.59	74.00	40.69	34.83	10.93	32.04	100	212 Peak	Peak				
	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																	
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5350.800	54.41	-19.59	74.00	40.69	34.83	10.93	32.04	100	212 Peak																																	
Avg	Data: 10 Level (dBuV/m) Date: 2023-09-29 Site : 03CH01-SZ Condition : PART 15.407 AV6 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:1.000KHz Project : 380711 Mode : 40 IMEI : 868862040702890 Plane : Y with Accessories MDB : 6M Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5350.800</td><td>44.35</td><td>-9.65</td><td>54.00</td><td>30.63</td><td>34.83</td><td>10.93</td><td>32.04</td><td>100</td><td>212 Average</td></tr></tbody></table>						Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.800	44.35	-9.65	54.00	30.63	34.83	10.93	32.04	100	212 Average	Avg				
	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																	
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5350.800	44.35	-9.65	54.00	30.63	34.83	10.93	32.04	100	212 Average																																	



Mode	41																																																																																						
Mode	Band Edge - L																																																																																						
Mode	U-NII-2A_5.25-5.35_802.11n HT20_CH56_5280MHz																																																																																						
ANT	SISO																																																																																						
Pol.	Horizontal					Pol.																																																																																	
Peak	Data: 1 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) HORIZONTAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over Limit</th><th>Limit Line</th><th>ReadAntenna Level</th><th>Cable Loss</th><th>Preamplifier Loss</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5057.050</td><td>52.76</td><td>-21.24</td><td>74.00</td><td>38.39</td><td>34.89</td><td>11.14</td><td>31.66</td><td>270</td><td>135 Peak</td></tr></tbody></table>						Freq	Level	Over Limit	Limit Line	ReadAntenna Level	Cable Loss	Preamplifier Loss	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5057.050	52.76	-21.24	74.00	38.39	34.89	11.14	31.66	270	135 Peak	Data: 3 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) HORIZONTAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over Limit</th><th>Limit Line</th><th>ReadAntenna Level</th><th>Cable Loss</th><th>Preamplifier Loss</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5280.000</td><td>99.63</td><td>31.33</td><td>68.30</td><td>85.75</td><td>34.84</td><td>10.99</td><td>31.95</td><td>270</td><td>135 Peak</td></tr><tr><td>2</td><td>5280.000</td><td>92.16</td><td>-----</td><td>-----</td><td>78.28</td><td>34.84</td><td>10.99</td><td>31.95</td><td>270</td><td>135 Average</td></tr></tbody></table>						Freq	Level	Over Limit	Limit Line	ReadAntenna Level	Cable Loss	Preamplifier Loss	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5280.000	99.63	31.33	68.30	85.75	34.84	10.99	31.95	270	135 Peak	2	5280.000	92.16	-----	-----	78.28	34.84	10.99	31.95	270	135 Average
	Freq	Level	Over Limit	Limit Line	ReadAntenna Level	Cable Loss	Preamplifier Loss	A/Pos	T/Pos	Remark																																																																													
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																													
1	5057.050	52.76	-21.24	74.00	38.39	34.89	11.14	31.66	270	135 Peak																																																																													
	Freq	Level	Over Limit	Limit Line	ReadAntenna Level	Cable Loss	Preamplifier Loss	A/Pos	T/Pos	Remark																																																																													
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																													
1	5280.000	99.63	31.33	68.30	85.75	34.84	10.99	31.95	270	135 Peak																																																																													
2	5280.000	92.16	-----	-----	78.28	34.84	10.99	31.95	270	135 Average																																																																													
Avg	Data: 2 Site : 03CH01-SZ Condition : PART 15.407 AVG 3m HF_ANT(3117) HORIZONTAL : RBW:1000.000KHz VBW:1.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over Limit</th><th>Limit Line</th><th>ReadAntenna Level</th><th>Cable Loss</th><th>Preamplifier Loss</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5045.150</td><td>42.79</td><td>-11.21</td><td>54.00</td><td>28.42</td><td>34.89</td><td>11.14</td><td>31.66</td><td>270</td><td>135 Average</td></tr></tbody></table>						Freq	Level	Over Limit	Limit Line	ReadAntenna Level	Cable Loss	Preamplifier Loss	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5045.150	42.79	-11.21	54.00	28.42	34.89	11.14	31.66	270	135 Average	Blank																																																
	Freq	Level	Over Limit	Limit Line	ReadAntenna Level	Cable Loss	Preamplifier Loss	A/Pos	T/Pos	Remark																																																																													
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																													
1	5045.150	42.79	-11.21	54.00	28.42	34.89	11.14	31.66	270	135 Average																																																																													





Mode	41									
Mode	Band Edge - R									
Mode	U-NII-2A_5.25-5.35_802.11n HT20_CH56_5280MHz									
ANT	SISO									
Pol.	Horizontal					Pol.				
Peak	Data: 4 Level (dBuV/m)									



Mode	41																																																																																						
Mode	Band Edge - L																																																																																						
Mode	U-NII-2A_5.25-5.35_802.11n HT20_CH56_5280MHz																																																																																						
ANT	SISO																																																																																						
Pol.	Vertical					Pol.																																																																																	
Peak	Data: 6 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5045.850</td><td>52.16</td><td>-21.84</td><td>74.00</td><td>37.79</td><td>34.89</td><td>11.14</td><td>31.66</td><td>100</td><td>210 Peak</td></tr></tbody></table>						Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5045.850	52.16	-21.84	74.00	37.79	34.89	11.14	31.66	100	210 Peak	Data: 8 Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5280.000</td><td>100.01</td><td>31.71</td><td>68.30</td><td>86.13</td><td>34.84</td><td>10.99</td><td>31.95</td><td>100</td><td>210 Peak</td></tr><tr><td>2</td><td>5280.000</td><td>93.30</td><td>-----</td><td>-----</td><td>79.42</td><td>34.84</td><td>10.99</td><td>31.95</td><td>100</td><td>210 Average</td></tr></tbody></table>						Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5280.000	100.01	31.71	68.30	86.13	34.84	10.99	31.95	100	210 Peak	2	5280.000	93.30	-----	-----	79.42	34.84	10.99	31.95	100	210 Average
	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																																													
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																													
1	5045.850	52.16	-21.84	74.00	37.79	34.89	11.14	31.66	100	210 Peak																																																																													
	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																																													
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																													
1	5280.000	100.01	31.71	68.30	86.13	34.84	10.99	31.95	100	210 Peak																																																																													
2	5280.000	93.30	-----	-----	79.42	34.84	10.99	31.95	100	210 Average																																																																													
Avg	Data: 7 Site : 03CH01-SZ Condition : PART 15.407 AVG 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:1.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><thead><tr><th></th><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5042.000</td><td>42.72</td><td>-11.28</td><td>54.00</td><td>28.35</td><td>34.89</td><td>11.14</td><td>31.66</td><td>100</td><td>210 Average</td></tr></tbody></table>						Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark		MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5042.000	42.72	-11.28	54.00	28.35	34.89	11.14	31.66	100	210 Average	Blank																																																
	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																																																																													
	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																													
1	5042.000	42.72	-11.28	54.00	28.35	34.89	11.14	31.66	100	210 Average																																																																													




Mode	41																															
	Band Edge - R																															
	U-NII-2A_5.25-5.35_802.11n HT20_CH56_5280MHz																															
ANT	SISO																															
Pol.	Vertical	Fundamental																														
Peak	Data: 9 Date: 2023-09-29  Site : 03CH01-SZ Condition : PART 15.407 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:3000.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5401.440</td><td>52.15</td><td>-21.85</td><td>74.00</td><td>38.54</td><td>34.82</td><td>10.90</td><td>32.11</td><td>100</td><td>210 Peak</td></tr></table>	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5401.440	52.15	-21.85	74.00	38.54	34.82	10.90	32.11	100	210 Peak	Blank
Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																							
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																							
1 5401.440	52.15	-21.85	74.00	38.54	34.82	10.90	32.11	100	210 Peak																							
Avg	Data: 10 Date: 2023-09-29  Site : 03CH01-SZ Condition : PART 15.407 AV6 3m HF_ANT(3117) VERTICAL : RBW:1000.000KHz VBW:1.000KHz Project : 380711 Mode : 41 IMEI : 868862040702890 Plane : Y with Accessories MDB : MCSO Power setting 14 <table><tr><th>Freq</th><th>Level</th><th>Over</th><th>Limit</th><th>ReadAntenna</th><th>Cable</th><th>Preamp</th><th>A/Pos</th><th>T/Pos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dB</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5353.200</td><td>42.35</td><td>-11.65</td><td>54.00</td><td>28.63</td><td>34.83</td><td>10.93</td><td>32.04</td><td>100</td><td>210 Average</td></tr></table>	Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark	MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5353.200	42.35	-11.65	54.00	28.63	34.83	10.93	32.04	100	210 Average	Blank
Freq	Level	Over	Limit	ReadAntenna	Cable	Preamp	A/Pos	T/Pos	Remark																							
MHz	dBuV/m	dB	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																							
1 5353.200	42.35	-11.65	54.00	28.63	34.83	10.93	32.04	100	210 Average																							

Appendix D. Duty Cycle Plots


Band	Duty Cycle(%)	T(ms)	1/T(kHz)	VBW Setting
802.11a	93.33	1.4	0.714	1KHz
802.11ac VHT20	92.25	1.31	0.763	1KHz
802.11n HT40	94.20	0.65	1.538	3KHz
802.11ac VHT80	63.64	0.07	14.286	15KHz

802.11a






802.11ac VHT 20



Date: 22.AUG.2023 19:21:02


802.11n HT40



Date: 22.AUG.2023 19:30:22



802.11ac VHT80



Date: 22.AUG.2023 19:47:43