
Antenna Specification

Product Name : C150 Antennas


Specifications model : C150 Antennas

Date : 2024.04.13


Confirmation of user:

Designed by	Reviewed by	Approved by
Liu Dongshan	Cui Cen	Zhou Xiangyang

Test Equipment



Chamber





Satimo







Shenzhen Ruiqiang Communication Co., Ltd
W2-A 502, Gaoxin Industrial Village, South Fourth Road, Nanshan District, Shenzhen

Item		Describe
Input impedance		50 Ω
VSWR		<2.5
ANT0	antenna	4G&5G
Gain		N7:2dBi N40:2.2dBi N41:2dBi N77:4.6dBi N78:3dBi B7:2dBi B40: 2.2dBi B41:2dBi B42: 3dBi B43: 4.6dBi
ANT1	antenna	4G&5G
Gain		N2:2.6dBi N5:2.7dBi N7:0.8dBi N8:2.3dBi N25:2.6dBi N38:0.8dBi N40:1.2dBi N41:0.8dBi N66:2.6dBi N71:-0.9dBi N77:3.4dBi N78:3.4dBi B2: 2.6dBi B4:1dBi B5:2.7dBi B7:0.8dBi B8: 2.3dBi B12: -0.9dBi B25:2.5dBi B38:0.8dBi B40: 1.2dBi B41: 0.8dBi B42: 2.1dBi B43: 3.4dBi B66:2.6dBi B71:-0.9dBi
ANT2	antenna	4G&5G
Gain		N7:2.8dBi N40:3.5dBi N41:2.8dBi





		N77:4.3dBi N78:1.7dBi B7:2.8dBi B40: 3.5dBi B41:2.8dBi B42: 1.7dBi B43: 4.3dBi
ANT3 Gain	antenna	4G&5G N2:1.3dBi N5:1.1dBi N7:1.2dBi N8:1.5dBi N25:1.3dBi N38:1.2dBi N40:2.5dBi N41:1.2dBi N66:1.9dBi N77: 6.2dBi N78: 4.1dBi B2:1.3dBi B4:1.3dBi B5:1.1dBi B7:1.2dBi B8:1.5dBi B12:0.21dBi B25:1.5dBi B38:1.2dBi B40:2.5dBi B41:1.2dBi B42:4.1dBi B43:6.2dBi B66:1.9dBi B71:0.21dBi
ANT4 Gain	antenna	4G&5G N2:2.3dBi N5:0.8dBi N8:0.2dBi N25:2.3dBi N66:2.1dBi B2:2.3dBi B4:2.3dBi B5:0.8dBi B8: 0.2dBi B12: -0.9dBi B25:0.2dBi B66:2.1dBi

		B71: -0.4dBi
ANT5 Gain	antenna	4G&5G N2:3.1dBi N5:0.3dBi N8:-1.6dBi N25:3.1dBi N66:1.1dBi B2:3.1dBi B4:1.1dBi B5:0.3dBi B8: -1.6dBi B12: -0.4dBi B25:0.3dBi B66:1.1dBi B71: -0.4dBi
WiFi antenna 0 Gain		2.4G: 2.9dBi 5.8G:2.8dBi
WiFi antenna 1 Gain		2.4G: 0.9dBi 5.8G:3.2dBi
Polarization		Linear Polarization





Antenna Shape	Frequency/Type
ANT0 	2300-4200MHz Monopole
ANT1 	700-4200MHz Monopole
ANT2	2300-4200MHz IFA

	
ANT3 	700-4200MHz Monopole
ANT4 	700-2200MHz IFA
ANT5 	700-2200MHz Monopole
WIFI0 	2400-2500MHz 5150-5180MHz IFA
WIFI 1 	2400-2500MHz 5150-5180MHz IFA





ANT0
2350MHz







2590MHz







3500MHz







3700MHz







ANT1
740MHz







840MHz







880MHz







1750MHz







1950MHz







2350MHz







2590MHz



3500MHz







3700MHz







ANT2





2350MHz







2590MHz



3500MHz







3700MHz







ANT3





740MHz







840MHz







880MHz







1750MHz







1950MHz







2350MHz







2590MHz







3500MHz







3700MHz







ANT4 740MHz







840MHz







880MHz







1750MHz





1950MHz





ANT5
740MHz







840MHz









880MHz







1750MHz













1950MHz





WiFi 0
2440MHz





5180MHz







5680MHz







5820MHz







2400MHz



5180MHz



5680MHz



5820MHz

