

# **TEST REPORT**

Product Name	:	HELMET WIRELESS EARPHONE
Brand Name	:	N/A
Model	:	F9
Series Model	:	N/A
FCC ID	:	2BBK5-F9
Applicant	:	Guangzhou Yonghe Electronics Co., Ltd.
Address	:	401, Building A1 East, Hongtu Industrial Park, Dashi Street, Panyu District, Guangzhou City, Guangdong Province, China
Manufacturer	:	Guangzhou Yonghe Electronics Co., Ltd.
Address	:	401, Building A1 East, Hongtu Industrial Park, Dashi Street, Panyu District, Guangzhou City, Guangdong Province, China
Standard(s)	:	FCC CFR Title 47 Part 15 Subpart C Section 15.247
Date of Receipt	:	Mar. 28, 2025
Date of Test	:	Mar. 29, 2025~ Apr. 10, 2025
Issued Date	:	Apr. 11, 2025

Issued By:

**Guangdong Asia Hongke Test Technology Limited** 

B1/F, Building 11, Junfeng Industrial Park, Chongqing Road, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China

Tel.: +86 0755-230967639

Fax.: +86 0755-230967639

Note: This device has been tested and found to comply with the standard(s) listed, this test report merely corresponds to the test sample. It is not permitted to copy extracts of these test result without the written permission of the test laboratory. This report shall not be reproduced except in full, without the written approval of Guangdong Asia Hongke Test Technology Limited. If there is a need to alter or revise this document, the right belongs to Guangdong Asia Hongke Test Technology Limited, and it should give a prior written notice of the revision document. This test report must not be used by the client to claim product endorsement.

#### Guangdong Asia Hongke Test Technology Limited

B1/F, Building 11, Junfeng Industrial Park, Chongqing Road, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China.



Ronort	Roviea	Rocord	

Report Version	Issued Date	Notes	
M1	Apr. 11, 2025	Initial Release	



# Contents

1	TEST	۲ SUMMARY	4
1	1	Test Standards	4
1	2	Test Summary	4
1	3	Τεςτ Εαριμητ	5
1	L.4	MEASUREMENT UNCERTAINTY	5
2	GEN	IGENERAL INFORMATION	6
2	2.1	ENVIRONMENTAL CONDITIONS	6
2	2.2	GENERAL DESCRIPTION OF EUT	6
2	2.3	DESCRIPTION OF TEST MODES AND TEST FREQUENCY	7
2	2.4	Special Accessories	8
2	2.5	EQUIPMENT LIST FOR THE TEST	8
3	TEST	T CONDITIONS AND RESULTS	10
Э	3.1	CONDUCTED EMISSIONS TEST	
З	3.2	RADIATED EMISSIONS AND BAND EDGE	
Э	3.3	MAXIMUM PEAK OUTPUT POWER	20
Э	3.4	20dB Bandwidth	21
Э	3.5	Occupied Bandwidth	22
Э	8.6	FREQUENCY SEPARATION	23
Э	3.7	NUMBER OF HOPPING FREQUENCY	24
3	3.8	TIME OF OCCUPANCY (DWELL TIME)	25
3	3.9	OUT-OF-BAND EMISSIONS	
3	3.10	PSEUDORANDOM FREQUENCY HOPPING SEQUENCE	
Э	3.11	ANTENNA REQUIREMENT	28
4	TEST	T SETUP PHOTOGRAPHS OF EUT	29
5	РНО	DTOS OF EUT	



# **1 TEST SUMMARY**

### 1.1 Test Standards

The tests were performed according to following standards:

FCC Rules Part 15.247: Frequency Hopping, Direct Spread Spectrum and Hybrid Systems that are in operation within the bands of 902-928 MHz, 2400-2483.5 MHz, and 5725-5850 MHz

ANSI C63.10: 2013: American National Standard for Testing Unlicensed Wireless Devices

KDB558074 D01 15.247 Meas Guidance v05r02: Guidance for Compliance Measurements on Digital Transmission System, Frequency Hopping Spreda Spectrum System, and Hybrid System Devices Operating Under Section 15.247 of the FCC Rules

### 1.2 Test Summary

Test Item	Section in 47 CFR	Result
Maximum Conducted Output Power	§15.247(b)	Pass
20dB Bandwidth	§15.247(a)	Pass
Frequency Separation	§15.247(a)	Pass
Number Of Hopping Frequency	§15.247(a)	Pass
Time Of Occupancy (Dwell Time)	§15.247(a)	Pass
Conducted Spurious Emissions and Band Edges Emissions	§15.205, §15.247(d)	Pass
Radiated Spurious Emissions	§15.209, §15.247(d)	Pass
Emissions at Restricted Band	§15.205	Pass
AC Mains Conducted Emissions	§15.207(a)	Pass
Antenna Requirements	§15.203	Pass



### 1.3 Test Facility

#### Test Laboratory:

#### Guangdong Asia Hongke Test Technology Limited

B1/F, Building 11, Junfeng Industrial Park, Chongqing Road, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China

The test facility is recognized, certified or accredited by the following organizations:

#### FCC-Registration No.: 251906 Designation Number: CN1376

Guangdong Asia Hongke Test Technology Limited has been registered and fully described in a report filed with the (FCC) Federal Communications Commission. The acceptance letter from the FCC is maintained in our files.

#### IC — Registration No.: 31737 CAB identifier: CN0165

The 3m Semi-anechoic chamber of Guangdong Asia Hongke Test Technology Limited has been registered by Certification and Engineering Bureau of Industry Canada for radio equipment testing with Registration No.: 31737

#### A2LA-Lab Cert. No.: 7133.01

Guangdong Asia Hongke Test Technology Limited has been accredited by A2LA for technical competence in the field of electrical testing, and proved to be in compliance with ISO/IEC 17025: 2017 General Requirements for the Competence of Testing and Calibration Laboratories and any additional program requirements in the identified field of testing.

#### **1.4 Measurement uncertainty**

The data and results referenced in this document are true and accurate. The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities. The measurement uncertainty was calculated for all measurements listed in this test report according to CISPR 16 - 4 "Specification for radio disturbance and immunity measuring apparatus and methods – Part 4: Uncertainty in EMC Measurements" and is documented in the Guangdong Asia Hongke Test Technology Limited's quality system according to DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

Hereafter the best measurement capability for Asia Hongke laboratory is reported:

Test	Measurement Uncertainty	Notes
Power Line Conducted Emission	9KHz~30MHz ±1.20 dB	(1)
Radiated Emission	9KHz~30MHz ±3.10dB	(1)
Radiated Emission	30MHz ~1GHz ±3.75dB	(1)
Radiated Emission	1GHz~18GHz ±3.88 dB	(1)
Radiated Emission	18GHz-40GHz ±3.88dB	(1)
RF power, conducted	30MHz~6GHz ±0.16dB	(1)
RF power density, conducted	$\pm$ 0.24dB	(1)
Spurious emissions, conducted	$\pm$ 0.21dB	(1)
Temperature	±1℃	(1)
Humidity	±3%	(1)
DC and low frequency voltages	±1.5%	(1)
Time	±2%	(1)
Duty cycle	±2%	(1)

The report uncertainty of measurement  $y \pm U$ , where expended uncertainty U is based on a standard uncertainty Multiplied by a coverage factor of k=2, providing a level of confidence of approximately 95%.



# **2** GENGENERAL INFORMATION

### 2.1 Environmental conditions

During the measurement the environmental conditions were within the listed ranges:

Normal Temperature:	25°C	
Relative Humidity:	55 %	
Air Pressure:	101 kPa	

### 2.2 General Description of EUT

Product Name:	HELMET WIRELESS EARPHONE
Model/Type reference:	F9
Serial Model:	N/A
Model difference:	N/A
Power Rating:	Input: DC 5V DC 3.7V 1000mAh 3.7Wh Rechargeable Li-ion batter
Hardware Version:	N/A
Software Version:	N/A
Sample(s) Status:	AiTSZ-250328003-1(Normal sample) AiTSZ-250328003-2(Engineer sample)
Bluetooth :	
Supported type:	Bluetooth BR/EDR
Modulation:	GFSK, π/4DQPSK, 8DPSK
Operation frequency:	2402MHz~2480MHz
Channel number:	79
Channel separation:	1MHz
Antenna type:	Chip antenna
Antenna gain:	3.54dBi
- ·	

The above DUT's information was declared by manufacturer. For more detailed features description, please refer to the manufacturer's specifications or the User's Manual..



### 2.3 Description of Test Modes and Test Frequency

There are 79 channels provided to the EUT and Channel 00/39/78 were selected to test. **Operation Frequency List:** 

Channel	Frequency (MHz)
00	2402
01	2403
:	÷
38	2440
39	2441
40	2442
:	:
77	2479
78	2480

Note: The line display in grey were the channel selected for testing

Exploratory testing was performed under each mode combination test channel; only the final measurement of the worst combination was made and recorded in this report.

	F	xnloratory measurem	ent	Final measurement Recorded			
Test case			ent	In Report			
	Mode	Date rate	Channel	Mode	Date rate	Channel	
Frequency Separation	GFSK П/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Middle ⊠ Highest	GFSK Π/4DQPSK 8DPSK	DH5 2DH5 3DH5	🛛 Middle	
Number Of Hopping Frequency	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	S Full	GFSK Π/4DQPSK 8DPSK	DH5 2DH5 3DH5	🛛 Full	
Time of Occupancy (dwell time)	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	<ul><li>☑ Lowest</li><li>☑ Middle</li><li>☑ Highest</li></ul>	GFSK N/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	🛛 Middle	
20dB bandwidth	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	<ul> <li>☑ Lowest</li> <li>☑ Middle</li> <li>☑ Highest</li> </ul>	GFSK Π/4DQPSK 8DPSK	DH5 2DH5 3DH5	<ul> <li>☑ Lowest</li> <li>☑ Middle</li> <li>☑ Highest</li> </ul>	
Maximum Conducted Output Power	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Middle ⊠ Highest	GFSK N/4DQPSK 8DPSK	DH5 2DH5 3DH5	⊠ Lowest ⊠ Middle ⊠ Highest	
Conducted Band edge	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Highest	GFSK Π/4DQPSK 8DPSK	DH5 2DH5 3DH5	⊠ Lowest ⊠ Highest	
Radiated Band edge	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Highest	GFSK	DH5	⊠ Lowest ⊠ Highest	
Conducted Spurious Emissions	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	<ul> <li>☑ Lowest</li> <li>☑ Middle</li> <li>☑ Highest</li> </ul>	GFSK Π/4DQPSK 8DPSK	DH5 2DH5 3DH5	<ul> <li>☑ Lowest</li> <li>☑ Middle</li> <li>☑ Highest</li> </ul>	
Radiated Spurious Emissions Above 1GHz	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Middle ⊠ Highest	GFSK	DH5	⊠ Lowest ⊠ Middle ⊠ Highest	
Radiated Spurious Emissions Below 1GHz	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Middle ⊠ Highest	GFSK	DH5	🛛 Middle	
Conducted Emissions 9KHz-30 MHz	GFSK Π/4DQPSK 8DPSK	DH1/DH3/DH5 2DH1/2DH3/2DH5 3DH1/3DH3/3DH5	⊠ Lowest ⊠ Middle ⊠ Highest	GFSK	DH5	Middle	



#### Power setting during the test:

During testing, Channel & Power Controlling Software provided by the customer was used to control the operating channel as well as the output power level. The RF output power selection is for the setting of RF output power expected by the customer and is going to be fixed on the firmware of the final end product.

Power Parameters:

Test Software Version	FCC Assist			
Frequency	2402MHz Frequency		2402MHz	
BR/EDR	Default	BR/EDR	Default	

### 2.4 Special Accessories

Follow auxiliary equipment(s) test with EUT that provided by the manufacturer or laboratory is listed as follow:

Description	Manufacturer Model		Serial No.	Provided by	Other
Adapter	HNT	HNT-QC530	/	Test lab	/
1	/	/	1	/	/

### 2.5 Equipment List for the Test

No	Test Equipment	Manufacturer	Model No	Serial No	Cal. Date	Cal. Due Date
1	EMI Measuring Receiver	R&S	ESR	101160	2024.09.25	2025.09.24
2	Spectrum Analyzer	R&S	FSV40	101470	2024.09.23	2025.09.22
3	Low Noise Pre Amplifier	SCHWARZBECK	BBV 9745	00282	2024.09.25	2025.09.24
4	Low Noise Pre Amplifier	CESHENG	CSKJLNA23101 6A	CSKJLNA231016 A	2024.09.25	2025.09.24
5	Passive Loop	ETS	6512	00165355	2024.08.29	2027.08.28
6	TRILOG Super Broadband test Antenna	SCHWARZBECK	VULB9168	01434	2024.08.29	2027.08.28
7	Broadband Horn Antenna	Schwarzbeck	BBHA 9120D	452	2024.08.29	2027.08.28
8	Horn Antenna 15- 40GHz	SCHWARZBECK	BBHA9170	BBHA9170367	2024.08.28	2027.08.27
9	6dB Attenuator	JFW	50FPE-006	50FPE-006 4360846-949-1		2025.09.23
10	EMI Test Receiver	R&S	ESPI	100771	2024.09.25	2025.09.24
11	LISN	R&S	NNLK 8129	8130179	2024.09.24	2025.09.23
12	LISN	R&S	ESH3-Z5	892785/016	2024.09.23	2025.09.22
13	Pulse Limiter	R&S	ESH3-Z2	102789	2024.09.24	2025.09.23
14	RF Automatic Test system	TST	TSTPASS	21033016	2024.09.25	2025.09.24
15	Vector Signal Generator	Agilent	N5182A	MY50143009	2024.09.25	2025.09.24
16	Analog signal generator	Agilent	E8257	MY51554256	2024.09.25	2025.09.24
17	Spectrum Analyzer	Agilent	N9020A	MY51289843	2024.09.25	2025.09.24
18	Spectrum Analyzer	Agilent	N9020A	MY53421570	2024.09.25	2025.09.24



Page 9 of 34 Report No.: AiTSZ-250328003FW1

19	Power Sensor	Agilent	8481A	MY41097697	2024.09.25	2025.09.24
20	Wideband Radio communication tester	R&S	CMW500	1201.0002K50	2024.09.24	2025.09.23
21	DC power supply	ZHAOXIN	RXN-305D-2	28070002559	2024.09.24	2025.09.23
22	RE Software	EZ	EZ-EMC_RE	Ver.AIT-03A	N/A	N/A
23	CE Software	EZ	EZ-EMC_CE	Ver.AIT-03A	N/A	N/A
24	RF Software	TST	TSTPASS	Version 2.0	N/A	N/A
25	RF Software	cesheng	WCS-WCN	Version 2024.6.20	N/A	N/A
26	temporary antenna connector(Note)	NTS	R001	N/A	N/A	N/A
Note:	The temporary antenna temporary antenna con	a connector is soldere nector is listed in the	d on the PCB board equipment list.	l in order to perform c	onducted tests an	d this



## **3 TEST CONDITIONS AND RESULTS**

### 3.1 Conducted Emissions Test

<u>LIMIT</u>

	Limit (d	BuV)
	Quasi-peak	Average
0.15-0.5	66 to 56*	56 to 46*
0.5-5	56	46
5-30	60	50

\* Decreases with the logarithm of the frequency.

#### **TEST CONFIGURATION**



#### TEST PROCEDURE

- 1. The equipment was set up as per the test configuration to simulate typical actual usage per the user's manual. The EUT is a tabletop system; a wooden table with a height of 0.8 meters is used and is placed on the ground plane as per ANSI C63.10:2013.
- 2. Support equipment, if needed, was placed as per ANSI C63.10:2013.
- 3. All I/O cables were positioned to simulate typical actual usage as per ANSI C63.10:2013.
- 4. The adapter received AC120V/60Hz power through a Line Impedance Stabilization Network (LISN) which supplied power source and was grounded to the ground plane.
- 5. All support equipments received AC power from a second LISN, if any.
- 6. The EUT test program was started. Emissions were measured on each current carrying line of the EUT using a spectrum Analyzer / Receiver connected to the LISN powering the EUT. The LISN has two monitoring points: Line 1 (Hot Side) and Line 2 (Neutral Side). Two scans were taken: one with Line 1 connected to Analyzer / Receiver and Line 2 connected to a 50 ohm load; the second scan had Line 1 connected to a 50 ohm load and Line 2 connected to the Analyzer / Receiver.
- 7. Analyzer / Receiver scanned from 150 KHz to 30MHz for emissions in each of the test modes.
- 8. During the above scans, the emissions were maximized by cable manipulation.



#### TEST RESULTS

Remark: Both 120 VAC, 50/60 Hz and 240 VAC, 50/60 Hz power supply have been tested, only the worst result of 120 VAC, 60 Hz was reported as below:



Remark: Correct Factor = Insertion loss of LISN + Cable loss + Insertion loss of Pulse Limiter; Measurement Result = Reading Level +Correct Factor;

Margin = Measurement Result- Limit

No.	Frequency	Reading	Correct	Result	Limit	Margin	Remark
	(MHz)	(dBuV)	(dB)	(dBuV)	(dBuV)	(dB)	
1	0.1680	44.46	0.00	44.46	65.06	-20.60	QP
2	0.1680	24.36	0.00	24.36	55.06	-30.70	AVG
3	0.2850	33.33	0.00	33.33	60.67	-27.34	QP
4	0.6630	18.97	0.00	18.97	46.00	-27.03	AVG
5	0.6720	29.64	0.00	29.64	56.00	-26.36	QP
6	1.0230	12.67	0.00	12.67	46.00	-33.33	AVG
7	2.0445	19.81	0.00	19.81	56.00	-36.19	QP
8	3.4530	9.21	0.00	9.21	46.00	-36.79	AVG
9	6.9585	19.20	0.00	19.20	60.00	-40.80	QP
10	6.9585	7.92	0.00	7.92	50.00	-42.08	AVG
11	17.6595	26.10	0.00	26.10	60.00	-33.90	QP
12	19.9095	12.65	0.00	12.65	50.00	-37.35	AVG





Remark: Correct Factor = Insertion loss of LISN + Cable loss + Insertion loss of Pulse Limiter; Measurement Result = Reading Level +Correct Factor;

	No.	Frequency	Reading	Correct	Result	Limit	Margin	Remark
		(MHz)	(dBuV)	(dB)	(dBuV)	(dBuV)	(dB)	
	1	0.1590	42.40	0.00	42.40	65.52	-23.12	QP
	2	0.1770	17.91	0.00	17.91	54.63	-36.72	AVG
	3	0.2490	33.29	0.00	33.29	61.79	-28.50	QP
	4	0.6765	20.56	0.00	20.56	46.00	-25.44	AVG
	5	0.6809	32.74	0.00	32.74	56.00	-23.26	QP
	6	1.2570	11.16	0.00	11.16	46.00	-34.84	AVG
	7	3.2730	21.33	0.00	21.33	56.00	-34.67	QP
	8	3.3585	9.01	0.00	9.01	46.00	-36.99	AVG
	9	9.9330	23.72	0.00	23.72	60.00	-36.28	QP
	10	12.1875	11.28	0.00	11.28	50.00	-38.72	AVG
ĺ	11	19.0905	27.09	0.00	27.09	60.00	-32.91	QP
	12	21.5610	13.01	0.00	13.01	50.00	-36.99	AVG



### 3.2 Radiated Emissions and Band Edge

#### <u>Limit</u>

For intentional device, according to § 15.209(a), the general requirement of field strength of radiated emission out of authorized band shall not exceed the following table at a 3 meters measurement distance.

In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a)

Radiated emission limits									
Frequency (MHz)	Distance (Meters)	Radiated (dBµV/m)	Radiated (µV/m)						
0.009-0.49	3	20log(2400/F(KHz))+40log(300/3)	2400/F(KHz)						
0.49-1.705	3	20log(24000/F(KHz))+ 40log(30/3)	24000/F(KHz)						
1.705-30	3	20log(30)+ 40log(30/3)	30						
30-88	3	40.0	100						
88-216	3	43.5	150						
216-960	3	46.0	200						
Above 960	3	54.0	500						

#### **TEST CONFIGURATION**





#### Below 30MHz

(B) Radiated Emission Test Set-Up, Frequency below 1000MHz



Below 1GHz



(C) Radiated Emission Test Set-Up, Frequency above 1000MHz



#### Test Procedure

- 1. Below 1GHz measurement the EUT is placed on a turntable which is 0.8m above ground plane, and above 1GHz measurement EUT was placed on a low permittivity and low loss tangent turn table which is 1.5m above ground plane.
- 2. Maximum procedure was performed by raising the receiving antenna from 1m to 4m and rotating the turn table from 0°℃ to 360°℃ to acquire the highest emissions from EUT
- 3. And also, each emission was to be maximized by changing the polarization of receiving antenna both horizontal and vertical.
- 4. Repeat above procedures until all frequency measurements have been completed.
- 5. Radiated emission test frequency band from 9KHz to 25GHz.
- 6. The distance between test antenna and EUT as following table states:

Test Frequency range	Test Antenna Type	Test Distance
9KHz-30MHz	Active Loop Antenna	3
30MHz-1GHz	Bilog Antenna	3
1GHz-18GHz	Horn Antenna	3
18GHz-25GHz	Horn Anternna	1

7. Setting test receiver/spectrum as following table states:

Test Frequency	Test Receiver/Spectrum Setting	Detector	
range			
9KHz-150KHz	RBW=200Hz/VBW=3KHz,Sweep time=Auto	QP	
150KHz-30MHz	RBW=9KHz/VBW=100KHz,Sweep time=Auto	QP	
	RBW=120KHz/VBW=1000KHz,Sweep	OP	
301WI 12-10112	time=Auto	QF	
	Peak Value: RBW=1MHz/VBW=3MHz,		
	Sweep time=Auto	Book	
	Average Value: RBW=1MHz/VBW=10Hz,	reak	
	Sweep time=Auto		

#### TEST RESULTS

Remark:

- 1. All GFSK,  $\pi/4$  DQPSK and 8DPSK mode were measured from 9 KHz to 25GHz and recorded worst case at GFSK DH5 mode.
- 2. For below 1GHz testing recorded worst at GFSK DH5 middle channel.
- 3. Radiated emission test from 9 KHz to 10th harmonic of fundamental was verified, and The emission levels from 9kHz to 30MHz are attenuated 20dB below the limit and not recorded in report.



#### For 30MHz-1GHz Test mode: ΒT Polarization: Horizontal dBu¥/m 100.0 90 80 70 60 50 40 <u>6</u>. 3 \* 5 peak 30 2 X JAM! 20 " Jululy Munder X merely 10 0 -10 -20 60.00 (MHz) 1000.000 30.000 300.00 Remark:

Emission Level = Reading + Factor;

Factor = Antenna Factor + Cable Loss – Pre-amplifier;

Margin= Emission Level - Limit.

No.	Frequency (MHz)	Reading (dBuV)	Factor (dB/m)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Det.
1	52.2079	34.19	-16.79	17.40	40.00	-22.60	QP
2	155.9101	39.69	-16.53	23.16	43.50	-20.34	QP
3	256.5211	51.26	-18.34	32.92	46.00	-13.08	QP
4	383.9318	45.74	-14.91	30.83	46.00	-15.17	QP
5	576.6443	39.71	-10.33	29.38	46.00	-16.62	QP
6	925.7563	36.07	-4.15	31.92	46.00	-14.08	QP



	Test	mode	:					BT		Polariza	ation:			V	ertic	al		
100.0	) dBuV/n	1																1
90																		
80																		
70																		
60																		
50																	E	
40						Ļ												
30	1 X												5 X				6 A <sup>n ete</sup>	peak
20	<u> </u>	2						3		×.		month	mercult	Wolland				
10	an annarth	which Upper	and the second second	nt your	har white	www.	h	ways the prover should be all the second	wormente	dogun mallendered	alter and and a second second							
0																		
-10																		
-20																		
30	).000		60	).00				(MI	Hz)	30	00.00					1	000.	000

Remark:

Emission Level = Reading + Factor;

Factor = Antenna Factor + Cable Loss – Pre-amplifier;

Margin= Emission Level - Limit.

No.	Frequency (MHz)	Reading (dBuV)	Factor (dB/m)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Det.
1	31.9546	46.26	-17.43	28.83	40.00	-11.17	QP
2	44.1202	36.23	-16.67	19.56	40.00	-20.44	QP
3	147.4036	36.03	-16.72	19.31	43.50	-24.19	QP
4	256.5211	42.97	-18.34	24.63	46.00	-21.37	QP
5	576.6443	39.99	-10.33	29.66	46.00	-16.34	QP
6	912.8620	36.31	-4.48	31.83	46.00	-14.17	QP



### For 1GHz to 25GHz

Note:GFSK, Pi/4 DQPSK and 8DPSK all have been tested, only worse case GFSK is reported as bellow:

Frequence	cy(MHz):	24	02	Polarity:	Horizontal			
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector		
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре		
4803.60	55.07	-7.56	47.51	74	-26.49	PEAK		
		-				AVG		
7206.20	44.78	-1.63	43.15	74	-30.85	PEAK		
						AVG		

Frequency(MHz):		2402		Polarity:	VERT	TICAL
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
4803.60	55.43	-7.56	47.87	74	-26.13	PEAK
						AVG
7206.20	45.94	-1.63	44.31	74	-29.69	PEAK
						AVG

Frequency(MHz):		2441		Polarity:	Horiz	ontal
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
4881.30	54.23	-6.74	47.49	74	-26.51	PEAK
				-	-	AVG
7322.50	46.56	-0.51	46.05	74	-27.95	PEAK
						AVG

Frequency(MHz):		24	41	Polarity:	VERT	TICAL
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
4881.30	54.92	-6.74	48.18	74	-25.82	PEAK
						AVG
7322.50	47.00	-0.51	46.49	74	-27.51	PEAK
						AVG



Page 18 of 34 Report No.: AiTSZ-250328003FW1

Frequency(MHz):		2480		Polarity:	Horiz	ontal
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
4959.45	47.02	-5.78	47.92	74	-26.08	PEAK
						AVG
7440.65	46.47	-0.53	46.13	74	-27.87	PEAK
						AVG

Frequency(MHz):		24	80	Polarity:	VERT	TICAL
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
4959.45	45.63	-5.78	48.84	74	-25.16	PEAK
				-		AVG
7440.65	45.02	-0.53	46.25	74	-27.75	PEAK
						AVG

#### **REMARKS**:

- 1. Emission level (dBuV/m) = Reading (dBuV)+ Factor (dB/m)
- 2. Factor (dB/m) = Antenna Factor (dB/m)+Cable Factor (dB)-Pre-amplifier Factor
- 3. Margin value = Emission level- Limit value.
- 4. -- Mean the PK detector measured value is below average limit.
- 5. Other emission levels are attenuated 20dB below the limit and not recorded in report.
- 6. RBW1MHz VBW3MHz Peak detector is for PK value; RBW 1MHz VBW10Hz Peak detector is for AV value.



#### Radiation Restricted band

Note:GFSK, Pi/4 DQPSK and 8DPSK all have been tested, only worse case GFSK is reported as below:

Frequency(MHz):		24	02	Polarity:	Horiz	ontal
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
2388.48	52.47	-4.08	48.39	74	-25.61	PEAK
						AVG
2390.00	40.62	-4.10	46.46	74	-27.54	PEAK
						AVG

Frequency(MHz):		24	02	Polarity:	Ver	tical
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
2387.06	53.25	-4.06	49.19	74	-24.81	PEAK
						AVG
2390.00	51.74	-4.10	47.64	74	-26.36	PEAK
						AVG

Frequency(MHz):		2480		Polarity:	Horiz	ontal
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
2483.50	52.92	-3.09	49.83	74	-24.17	PEAK
						AVG
2483.64	50.70	-3.09	47.61	74	-26.39	PEAK
						AVG

Frequency(MHz):		2480		Polarity:	Ver	tical
Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector
(MHz)	(dBµV)	(dB/m)	(dBµV/m)	(dBµV/m)	(dB)	Туре
2483.50	54.03	-3.09	50.94	74	-23.06	PEAK
						AVG
2484.23	51.37	-3.08	48.29	74	-25.71	PEAK
						AVG

**REMARKS**:

- 1. Emission level (dBuV/m) = Reading (dBuV)+ Factor (dB/m)
- 2. Factor (dB/m) = Antenna Factor (dB/m)+Cable Factor (dB)-Pre-amplifier Factor
- 3. Margin value = Emission level- Limit value.
- 4. -- Mean the PK detector measured value is below average limit.
- 5. Other emission levels are attenuated 20dB below the limit and not recorded in report.
- 6. RBW1MHz VBW3MHz Peak detector is for PK value; RBW 1MHz VBW10Hz Peak detector is for AV value.



### 3.3 Maximum Peak Output Power

#### <u>Limit</u>

For frequency hopping systems operating in the 2400-2483.5 MHz band employing at least 75 non-overlapping hopping channels: 1 watt.

For all other frequency hopping systems in the 2400-2483.5 MHz band: 0.125 watts.

#### Test Procedure

The transmitter output (antenna port) was connected to the spectrum analyzer. According to ANSI C63.10:2013 Output power test procedure for frequency-hopping spread-spectrum (FHSS) devices; this is an RF-conducted test to evaluate maximum peak output power. Use a direct connection between the antenna port of the unlicensed wireless device and the spectrum analyzer, through suitable attenuation. The hopping shall be disabled for this test:

- a) Use the following spectrum analyzer settings:
  - 1) Span: Approximately five times the 20 dB bandwidth, centered on a hopping channel.
  - 2) RBW > 20 dB bandwidth of the emission being measured.
  - 3) VBW ≥ RBW.
  - 4) Sweep: Auto.
  - 5) Detector function: Peak.
  - 6) Trace: Max hold.
- b) Allow trace to stabilize.
- c) Use the marker-to-peak function to set the marker to the peak of the emission.
- d) The indicated level is the peak output power, after any corrections for external attenuators and cables.

#### **Test Configuration**



**Ground Reference Plane** 

#### Test Results

🛛 Pass

Not Applicable

Note:



### 3.4 20dB Bandwidth

#### <u>Limit</u>

For frequency hopping systems operating in the 2400MHz-2483.5MHz no limit for 20dB bandwidth.

#### Test Procedure

Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the Spectrum Analyzer. Place the EUT on the table and set it in transmitting mode.

Use the following spectrum analyzer settings:

- 1) Span = approximately 2 to 3 times the 20 dB bandwidth, centered on a hopping channel.
- 2) RBW  $\geq$ 1% of the 20 dB bandwidth, VBW  $\geq$ RBW.
- 3) Detector function = peak.
- 4) Trace = max hold.

The 20dB bandwidth is defined as the total spectrum the power of which is higher than peak power minus 20dB.

#### **Test Configuration**



#### **Test Results**

Pass I Not Applicable

Note:



### 3.5 Occupied Bandwidth

#### <u>Limit</u>

N/A

#### Test Procedure

The occupied bandwidth is the frequency bandwidth such that, below its lower and above its upper frequency limits, the mean powers are each equal to 0.5% of the total mean power of the given emission. The following procedure shall be used for measuring 99% power bandwidth:

RBW=1% to 5% of the OBW

VBW=approximately 3 X RBW

Detector=Peak

Trace Mode: Max Hold

Use the 99% power bandwidth function of the instrument to measure the Occupied Bandwidth and recoded.

#### **Test Configuration**



#### Test Results

Pass (

Not Applicable

Note:



### 3.6 Frequency Separation

#### <u>LIMIT</u>

According to 15.247(a)(1), frequency hopping systems shall have hopping channel carrier frequencies separated by minimum of 25KHz or the 2/3\*20dB bandwidth of the hopping channel, whichever is greater.

#### Test Procedure

Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the Spectrum Analyzer. Place the EUT on the table and set it in transmitting mode.

Use the following spectrum analyzer settings:

- 1) Set center frequency of Spectrum Analyzer = middle of hopping channel.
- 2) Set the Spectrum Analyzer as RBW = 100 kHz, VBW =300 kHz, Span = wide enough to capture the peaks of two adjacent channels, Sweep = auto.
- 3) Max hold, mark 2 peaks of hopping channel and record the 2 peaks frequency.

#### **TEST CONFIGURATION**



Ground Reference Plane

#### TEST RESULTS

Pass Interview Interview Not Applicable

Note:



### 3.7 Number of hopping frequency

#### <u>Limit</u>

Frequency hopping systems in the 2400–2483.5 MHz band shall use at least 15 channels.

#### Test Procedure

Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the Spectrum Analyzer. Place the EUT on the table and set it in transmitting mode.

Use the following spectrum analyzer settings:

- 1) Set Spectrum Analyzer Start=2400MHz, Stop = 2483.5MHz, Sweep = auto.
- 2) Set the Spectrum Analyzer as RBW/VBW=100KHz/300KHz.
- 3) Max hold, view and count how many channel in the band.

#### **Test Configuration**



#### **Test Results**

🛛 Pass

Not Applicable

Note:



### 3.8 Time of Occupancy (Dwell Time)

#### <u>Limit</u>

The average time of occupancy on any channel shall not be greater than 0.4 seconds within a period of 0.4 seconds multiplied by the number of hopping channels employed.

#### Test Procedure

Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the Spectrum Analyzer. Place the EUT on the table and set it in transmitting mode.

Use the following spectrum analyzer settings:

- 1) Set center frequency of Spectrum Analyzer = operating frequency.
- 2) Set the Spectrum Analyzer as RBW=1MHz, VBW=3MHz, Span = 0Hz, Sweep = auto.
- 3) Repeat above procedures until all frequency measured was complete.

#### **Test Configuration**



#### Test Results

⊠ Pass

Not Applicable

Note:



### 3.9 Out-of-band Emissions

#### <u>Limit</u>

In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF con-ducted or a radiated measurement, pro-vided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter com-plies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required.

#### Test Procedure

Connect the transmitter output to spectrum analyzer using a low loss RF cable, and set the spectrum analyzer to RBW=100 kHz, VBW= 300 kHz, peak detector, and max hold. Measurements utilizing these setting are made of the in-band reference level, bandedge and out-of-band emissions.

#### **Test Configuration**



Ground Reference Plane

#### **Test Results**

**Pass** 

Not Applicable

Note:



### 3.10 Pseudorandom Frequency Hopping Sequence

#### **TEST APPLICABLE**

#### For 47 CFR Part 15C section 15.247 (a) (1) RSS-247§5.1 requirement:

Frequency hopping systems shall have hopping channel carrier frequencies separated by a minimum of 25 kHz or the 20 dB bandwidth of the hop-ping channel, whichever is greater. Alternatively, frequency hopping systems operating in the 2400–2483.5 MHz band may have hopping channel carrier frequencies that are separated by 25 kHz or two-thirds of the 20 dB bandwidth of the hopping channel, whichever is greater, provided the systems operate with an output power no greater than 125 mW. The system shall hop to channel frequencies that are selected at the system hopping rate from a pseudo randomly ordered list of hopping frequencies. Each frequency must be used equally on the average by each transmitter. The system receivers shall have input bandwidths that match the hop-ping channel bandwidths of their corresponding transmitters and shall shift frequencies in synchronization with the transmitted signals.

#### EUT Pseudorandom Frequency Hopping Sequence Requirement

The pseudorandom frequency hopping sequence may be generated in a nice-stage shift register whose 5<sup>th</sup> and 9<sup>th</sup> stage outputs are added in a modulo-two addition stage. And the result is fed back to the input of the first stage. The sequence begins with the first one of 9 consecutive ones, for example: the shift register is initialized with nine ones.

- Number of shift register stages:9
- Length of pseudo-random sequence:29-1=511 bits
- Longest sequence of zeros:8(non-inverted signal)



Linear Feedback Shift Register for Generation of the PRBS sequence

An example of pseudorandom frequency hopping sequence as follows:

0	2	4	6	62 64	78 1	73 75 77

Each frequency used equally one the average by each transmitter.

The system receiver has input bandwidths that match the hopping channel bandwidths of their corresponding transmitter and shift frequencies in synchronization with the transmitted signals.



### 3.11 Antenna Requirement

#### Standard Applicable

#### For intentional device, according to FCC 47 CFR Section 15.203:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited

#### FCC CFR Title 47 Part 15 Subpart C Section 15.247(b) (4):

(4) The conducted output power limit specified in paragraph (b) of this section is based on the use of antennas with directional gains that do not exceed 6 dBi. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b)(1), (b)(2), and (b)(3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

#### <u>Test Result</u>

The maximum gain of antenna was 3.54dBi with impedance 50 Ω.



# 4 Test Setup Photographs of EUT









# 5 Photos of EUT











Page 32 of 34









Antenna

