

10728	AAC	IEEE 802.11ax (80MHz, MCS9, 90pc dc)	WLAN	8.65	± 9.6 %
10729	AAC	IEEE 802.11ax (80MHz, MCS10, 90pc dc)	WLAN	8.64	± 9.6 %
10730	AAC	IEEE 802.11ax (80MHz, MCS11, 90pc dc)	WLAN	8.67	± 9.6 %
10731	AAC	IEEE 802.11ax (80MHz, MCS0, 99pc dc)	WLAN	8.42	± 9.6 %
10732	AAC	IEEE 802.11ax (80MHz, MCS1, 99pc dc)	WLAN	8.46	± 9.6 %
10733	AAC	IEEE 802.11ax (80MHz, MCS2, 99pc dc)	WLAN	8.40	± 9.6 %
10734	AAC	IEEE 802.11ax (80MHz, MCS3, 99pc dc)	WLAN	8.25	± 9.6 %
10735	AAC	IEEE 802.11ax (80MHz, MCS4, 99pc dc)	WLAN	8.33	± 9.6 %
10736	AAC	IEEE 802.11ax (80MHz, MCS5, 99pc dc)	WLAN	8.27	± 9.6 %
10737	AAC	IEEE 802.11ax (80MHz, MCS6, 99pc dc)	WLAN	8.36	± 9.6 %
10738	AAC	IEEE 802.11ax (80MHz, MCS7, 99pc dc)	WLAN	8.42	± 9.6 %
10739	AAC	IEEE 802.11ax (80MHz, MCS8, 99pc dc)	WLAN	8.29	± 9.6 %
10740	AAC	IEEE 802.11ax (80MHz, MCS9, 99pc dc)	WLAN	8.48	± 9.6 %
10741	AAC	IEEE 802.11ax (80MHz, MCS10, 99pc dc)	WLAN	8.40	± 9.6 %
10742	AAC	IEEE 802.11ax (80MHz, MCS11, 99pc dc)	WLAN	8.43	± 9.6 %
10743	AAC	IEEE 802.11ax (160MHz, MCS0, 90pc dc)	WLAN	8.94	± 9.6 %
10744	AAC	IEEE 802.11ax (160MHz, MCS1, 90pc dc)	WLAN	9.16	± 9.6 %
10745	AAC	IEEE 802.11ax (160MHz, MCS2, 90pc dc)	WLAN	8.93	± 9.6 %
10746	AAC	IEEE 802.11ax (160MHz, MCS3, 90pc dc)	WLAN	9.11	± 9.6 %
10747	AAC	IEEE 802.11ax (160MHz, MCS4, 90pc dc)	WLAN	9.04	± 9.6 %
10748	AAC	IEEE 802.11ax (160MHz, MCS5, 90pc dc)	WLAN	8.93	± 9.6 %
10749	AAC	IEEE 802.11ax (160MHz, MCS6, 90pc dc)	WLAN	8.90	± 9.6 %
10750	AAC	IEEE 802.11ax (160MHz, MCS7, 90pc dc)	WLAN	8.79	± 9.6 %
10751	AAC	IEEE 802.11ax (160MHz, MCS8, 90pc dc)	WLAN	8.82	± 9.6 %
10752	AAC	IEEE 802.11ax (160MHz, MCS9, 90pc dc)	WLAN	8.81	± 9.6 %
10753	AAC	IEEE 802.11ax (160MHz, MCS10, 90pc dc)	WLAN	9.00	± 9.6 %
10754	AAC	IEEE 802.11ax (160MHz, MCS11, 90pc dc)	WLAN	8.94	± 9.6 %
10755	AAC	IEEE 802.11ax (160MHz, MCS0, 99pc dc)	WLAN	8.64	± 9.6 %
10756	AAC	IEEE 802.11ax (160MHz, MCS1, 99pc dc)	WLAN	8.77	± 9.6 %
10757	AAC	IEEE 802.11ax (160MHz, MCS2, 99pc dc)	WLAN	8.77	± 9.6 %
10758	AAC	IEEE 802.11ax (160MHz, MCS3, 99pc dc)	WLAN	8.69	± 9.6 %
10759	AAC	IEEE 802.11ax (160MHz, MCS4, 99pc dc)	WLAN	8.58	± 9.6 %
10760	AAC	IEEE 802.11ax (160MHz, MCS5, 99pc dc)	WLAN	8.49	± 9.6 %
10761	AAC	IEEE 802.11ax (160MHz, MCS6, 99pc dc)	WLAN	8.58	± 9.6 %
10762	AAC	IEEE 802.11ax (160MHz, MCS7, 99pc dc)	WLAN	8.49	± 9.6 %
10763	AAC	IEEE 802.11ax (160MHz, MCS8, 99pc dc)	WLAN	8.53	± 9.6 %
10764	AAC	IEEE 802.11ax (160MHz, MCS9, 99pc dc)	WLAN	8.54	± 9.6 %
10765	AAC	IEEE 802.11ax (160MHz, MCS10, 99pc dc)	WLAN	8.54	± 9.6 %
10766	AAC	IEEE 802.11ax (160MHz, MCS11, 99pc dc)	WLAN	8.51	± 9.6 %
10767	AAC	5G NR (CP-OFDM, 1 RB, 5 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	7.99	± 9.6 %
10768	AAC	5G NR (CP-OFDM, 1 RB, 10 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.01	± 9.6 %
10769	AAC	5G NR (CP-OFDM, 1 RB, 15 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.01	± 9.6 %
10770	AAC	5G NR (CP-OFDM, 1 RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.02	± 9.6 %
10771	AAC	5G NR (CP-OFDM, 1 RB, 25 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.02	± 9.6 %
10772	AAC	5G NR (CP-OFDM, 1 RB, 30 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.23	± 9.6 %
10773	AAC	5G NR (CP-OFDM, 1 RB, 40 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.03	± 9.6 %
10774	AAC	5G NR (CP-OFDM, 1 RB, 50 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.02	± 9.6 %
10775	AAC	5G NR (CP-OFDM, 50% RB, 5 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.31	± 9.6 %
10776	AAC	5G NR (CP-OFDM, 50% RB, 10 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.30	± 9.6 %
10777	AAC	5G NR (CP-OFDM, 50% RB, 15 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.30	± 9.6 %
10778	AAC	5G NR (CP-OFDM, 50% RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10779	AAC	5G NR (CP-OFDM, 50% RB, 25 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.42	± 9.6 %
10780	AAC	5G NR (CP-OFDM, 50% RB, 30 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.38	± 9.6 %
10781	AAC	5G NR (CP-OFDM, 50% RB, 40 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.38	± 9.6 %
10782	AAC	5G NR (CP-OFDM, 50% RB, 50 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.43	± 9.6 %
10783	AAC	5G NR (CP-OFDM, 100% RB, 5 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.31	± 9.6 %

10784	AAC	5G NR (CP-OFDM, 100% RB, 10 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.29	± 9.6 %
10785	AAC	5G NR (CP-OFDM, 100% RB, 15 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.40	± 9.6 %
10786	AAC	5G NR (CP-OFDM, 100% RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.35	± 9.6 %
10787	AAC	5G NR (CP-OFDM, 100% RB, 25 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.44	± 9.6 %
10788	AAC	5G NR (CP-OFDM, 100% RB, 30 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.39	± 9.6 %
10789	AAC	5G NR (CP-OFDM, 100% RB, 40 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.37	± 9.6 %
10790	AAC	5G NR (CP-OFDM, 100% RB, 50 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	8.39	± 9.6 %
10791	AAC	5G NR (CP-OFDM, 1 RB, 5 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.83	± 9.6 %
10792	AAC	5G NR (CP-OFDM, 1 RB, 10 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.92	± 9.6 %
10793	AAC	5G NR (CP-OFDM, 1 RB, 15 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.95	± 9.6 %
10794	AAC	5G NR (CP-OFDM, 1 RB, 20 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.82	± 9.6 %
10795	AAC	5G NR (CP-OFDM, 1 RB, 25 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.84	± 9.6 %
10796	AAC	5G NR (CP-OFDM, 1 RB, 30 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.82	± 9.6 %
10797	AAC	5G NR (CP-OFDM, 1 RB, 40 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.01	± 9.6 %
10798	AAC	5G NR (CP-OFDM, 1 RB, 50 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.89	± 9.6 %
10799	AAC	5G NR (CP-OFDM, 1 RB, 60 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.93	± 9.6 %
10801	AAC	5G NR (CP-OFDM, 1 RB, 80 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.89	± 9.6 %
10802	AAC	5G NR (CP-OFDM, 1 RB, 90 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.87	± 9.6 %
10803	AAE	5G NR (CP-OFDM, 1 RB, 100 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	7.93	± 9.6 %
10805	AAD	5G NR (CP-OFDM, 50% RB, 10 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10806	AAD	5G NR (CP-OFDM, 50% RB, 15 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.37	± 9.6 %
10809	AAD	5G NR (CP-OFDM, 50% RB, 30 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10810	AAD	5G NR (CP-OFDM, 50% RB, 40 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10812	AAD	5G NR (CP-OFDM, 50% RB, 60 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.35	± 9.6 %
10817	AAD	5G NR (CP-OFDM, 100% RB, 5 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.35	± 9.6 %
10818	AAD	5G NR (CP-OFDM, 100% RB, 10 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10819	AAD	5G NR (CP-OFDM, 100% RB, 15 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.33	± 9.6 %
10820	AAD	5G NR (CP-OFDM, 100% RB, 20 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.30	± 9.6 %
10821	AAC	5G NR (CP-OFDM, 100% RB, 25 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10822	AAD	5G NR (CP-OFDM, 100% RB, 30 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10823	AAC	5G NR (CP-OFDM, 100% RB, 40 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.36	± 9.6 %
10824	AAD	5G NR (CP-OFDM, 100% RB, 50 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.39	± 9.6 %
10825	AAD	5G NR (CP-OFDM, 100% RB, 60 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10827	AAD	5G NR (CP-OFDM, 100% RB, 80 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.42	± 9.6 %
10828	AAE	5G NR (CP-OFDM, 100% RB, 90 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.43	± 9.6 %
10829	AAD	5G NR (CP-OFDM, 100% RB, 100 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	8.40	± 9.6 %
10830	AAD	5G NR (CP-OFDM, 1 RB, 10 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.63	± 9.6 %
10831	AAD	5G NR (CP-OFDM, 1 RB, 15 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.73	± 9.6 %
10832	AAD	5G NR (CP-OFDM, 1 RB, 20 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.74	± 9.6 %
10833	AAD	5G NR (CP-OFDM, 1 RB, 25 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.70	± 9.6 %
10834	AAD	5G NR (CP-OFDM, 1 RB, 30 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.75	± 9.6 %
10835	AAD	5G NR (CP-OFDM, 1 RB, 40 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.70	± 9.6 %
10836	AAE	5G NR (CP-OFDM, 1 RB, 50 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.66	± 9.6 %
10837	AAD	5G NR (CP-OFDM, 1 RB, 60 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.68	± 9.6 %
10839	AAD	5G NR (CP-OFDM, 1 RB, 80 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.70	± 9.6 %
10840	AAD	5G NR (CP-OFDM, 1 RB, 90 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.67	± 9.6 %
10841	AAD	5G NR (CP-OFDM, 1 RB, 100 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	7.71	± 9.6 %
10843	AAD	5G NR (CP-OFDM, 50% RB, 15 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.49	± 9.6 %
10844	AAD	5G NR (CP-OFDM, 50% RB, 20 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10846	AAD	5G NR (CP-OFDM, 50% RB, 30 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10854	AAD	5G NR (CP-OFDM, 100% RB, 10 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.34	± 9.6 %
10855	AAD	5G NR (CP-OFDM, 100% RB, 15 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.36	± 9.6 %
10856	AAD	5G NR (CP-OFDM, 100% RB, 20 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.37	± 9.6 %
10857	AAD	5G NR (CP-OFDM, 100% RB, 25 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.35	± 9.6 %
10858	AAD	5G NR (CP-OFDM, 100% RB, 30 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.36	± 9.6 %
10859	AAD	5G NR (CP-OFDM, 100% RB, 40 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.34	± 9.6 %

10860	AAD	5G NR (CP-OFDM, 100% RB, 50 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10861	AAD	5G NR (CP-OFDM, 100% RB, 60 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.40	± 9.6 %
10863	AAD	5G NR (CP-OFDM, 100% RB, 80 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10864	AAE	5G NR (CP-OFDM, 100% RB, 90 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.37	± 9.6 %
10865	AAD	5G NR (CP-OFDM, 100% RB, 100 MHz, QPSK, 60 kHz)	5G NR FR1 TDD	8.41	± 9.6 %
10866	AAD	5G NR (DFT-s-OFDM, 1 RB, 100 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10868	AAD	5G NR (DFT-s-OFDM, 100% RB, 100 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.89	± 9.6 %
10869	AAD	5G NR (DFT-s-OFDM, 1 RB, 100 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	5.75	± 9.6 %
10870	AAD	5G NR (DFT-s-OFDM, 100% RB, 100 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	5.86	± 9.6 %
10871	AAD	5G NR (DFT-s-OFDM, 1 RB, 100 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	5.75	± 9.6 %
10872	AAD	5G NR (DFT-s-OFDM, 100% RB, 100 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	6.52	± 9.6 %
10873	AAD	5G NR (DFT-s-OFDM, 1 RB, 100 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	6.61	± 9.6 %
10874	AAD	5G NR (DFT-s-OFDM, 100% RB, 100 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	6.65	± 9.6 %
10875	AAD	5G NR (CP-OFDM, 1 RB, 100 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	7.78	± 9.6 %
10876	AAD	5G NR (CP-OFDM, 100% RB, 100 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	8.39	± 9.6 %
10877	AAD	5G NR (CP-OFDM, 1 RB, 100 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	7.95	± 9.6 %
10878	AAD	5G NR (CP-OFDM, 100% RB, 100 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	8.41	± 9.6 %
10879	AAD	5G NR (CP-OFDM, 1 RB, 100 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	8.12	± 9.6 %
10880	AAD	5G NR (CP-OFDM, 100% RB, 100 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	8.38	± 9.6 %
10881	AAD	5G NR (DFT-s-OFDM, 1 RB, 50 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	5.75	± 9.6 %
10882	AAD	5G NR (DFT-s-OFDM, 100% RB, 50 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	5.96	± 9.6 %
10883	AAD	5G NR (DFT-s-OFDM, 1 RB, 50 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	6.57	± 9.6 %
10884	AAD	5G NR (DFT-s-OFDM, 100% RB, 50 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	6.53	± 9.6 %
10885	AAD	5G NR (DFT-s-OFDM, 1 RB, 50 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	6.61	± 9.6 %
10886	AAD	5G NR (DFT-s-OFDM, 100% RB, 50 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	6.65	± 9.6 %
10887	AAD	5G NR (CP-OFDM, 1 RB, 50 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	7.78	± 9.6 %
10888	AAD	5G NR (CP-OFDM, 100% RB, 50 MHz, QPSK, 120 kHz)	5G NR FR2 TDD	8.35	± 9.6 %
10889	AAD	5G NR (CP-OFDM, 1 RB, 50 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	8.02	± 9.6 %
10890	AAD	5G NR (CP-OFDM, 100% RB, 50 MHz, 16QAM, 120 kHz)	5G NR FR2 TDD	8.40	± 9.6 %
10891	AAD	5G NR (CP-OFDM, 1 RB, 50 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	8.13	± 9.6 %
10892	AAD	5G NR (CP-OFDM, 100% RB, 50 MHz, 64QAM, 120 kHz)	5G NR FR2 TDD	8.41	± 9.6 %
10897	AAD	5G NR (DFT-s-OFDM, 1 RB, 5 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.66	± 9.6 %
10898	AAD	5G NR (DFT-s-OFDM, 1 RB, 10 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.67	± 9.6 %
10899	AAD	5G NR (DFT-s-OFDM, 1 RB, 15 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.67	± 9.6 %
10900	AAD	5G NR (DFT-s-OFDM, 1 RB, 20 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10901	AAD	5G NR (DFT-s-OFDM, 1 RB, 25 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10902	AAD	5G NR (DFT-s-OFDM, 1 RB, 30 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10903	AAD	5G NR (DFT-s-OFDM, 1 RB, 40 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10904	AAD	5G NR (DFT-s-OFDM, 1 RB, 50 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10905	AAD	5G NR (DFT-s-OFDM, 1 RB, 60 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10906	AAD	5G NR (DFT-s-OFDM, 1 RB, 80 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.68	± 9.6 %
10907	AAD	5G NR (DFT-s-OFDM, 50% RB, 5 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.78	± 9.6 %
10908	AAD	5G NR (DFT-s-OFDM, 50% RB, 10 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.93	± 9.6 %
10909	AAD	5G NR (DFT-s-OFDM, 50% RB, 15 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.96	± 9.6 %
10910	AAD	5G NR (DFT-s-OFDM, 50% RB, 20 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.83	± 9.6 %
10911	AAD	5G NR (DFT-s-OFDM, 50% RB, 25 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.93	± 9.6 %
10912	AAD	5G NR (DFT-s-OFDM, 50% RB, 30 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.84	± 9.6 %
10913	AAD	5G NR (DFT-s-OFDM, 50% RB, 40 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.84	± 9.6 %
10914	AAD	5G NR (DFT-s-OFDM, 50% RB, 50 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.85	± 9.6 %
10915	AAD	5G NR (DFT-s-OFDM, 50% RB, 60 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.83	± 9.6 %
10916	AAD	5G NR (DFT-s-OFDM, 50% RB, 80 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.87	± 9.6 %
10917	AAD	5G NR (DFT-s-OFDM, 50% RB, 100 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.94	± 9.6 %
10918	AAD	5G NR (DFT-s-OFDM, 100% RB, 5 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.86	± 9.6 %
10919	AAD	5G NR (DFT-s-OFDM, 100% RB, 10 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.86	± 9.6 %
10920	AAD	5G NR (DFT-s-OFDM, 100% RB, 15 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.87	± 9.6 %
10921	AAD	5G NR (DFT-s-OFDM, 100% RB, 20 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.84	± 9.6 %

10922	AAD	5G NR (DFT-s-OFDM, 100% RB, 25 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.82	± 9.6 %
10923	AAD	5G NR (DFT-s-OFDM, 100% RB, 30 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.84	± 9.6 %
10924	AAD	5G NR (DFT-s-OFDM, 100% RB, 40 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.84	± 9.6 %
10925	AAD	5G NR (DFT-s-OFDM, 100% RB, 50 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.95	± 9.6 %
10926	AAD	5G NR (DFT-s-OFDM, 100% RB, 60 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.84	± 9.6 %
10927	AAD	5G NR (DFT-s-OFDM, 100% RB, 80 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	5.94	± 9.6 %
10928	AAD	5G NR (DFT-s-OFDM, 1 RB, 5 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.52	± 9.6 %
10929	AAD	5G NR (DFT-s-OFDM, 1 RB, 10 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.52	± 9.6 %
10930	AAD	5G NR (DFT-s-OFDM, 1 RB, 15 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.52	± 9.6 %
10931	AAD	5G NR (DFT-s-OFDM, 1 RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.51	± 9.6 %
10932	AAB	5G NR (DFT-s-OFDM, 1 RB, 25 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.51	± 9.6 %
10933	AAA	5G NR (DFT-s-OFDM, 1 RB, 30 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.51	± 9.6 %
10934	AAA	5G NR (DFT-s-OFDM, 1 RB, 40 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.51	± 9.6 %
10935	AAA	5G NR (DFT-s-OFDM, 1 RB, 50 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.51	± 9.6 %
10936	AAC	5G NR (DFT-s-OFDM, 50% RB, 5 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.90	± 9.6 %
10937	AAB	5G NR (DFT-s-OFDM, 50% RB, 10 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.77	± 9.6 %
10938	AAB	5G NR (DFT-s-OFDM, 50% RB, 15 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.90	± 9.6 %
10939	AAB	5G NR (DFT-s-OFDM, 50% RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.82	± 9.6 %
10940	AAB	5G NR (DFT-s-OFDM, 50% RB, 25 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.89	± 9.6 %
10941	AAB	5G NR (DFT-s-OFDM, 50% RB, 30 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.83	± 9.6 %
10942	AAB	5G NR (DFT-s-OFDM, 50% RB, 40 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.85	± 9.6 %
10943	AAB	5G NR (DFT-s-OFDM, 50% RB, 50 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.95	± 9.6 %
10944	AAB	5G NR (DFT-s-OFDM, 100% RB, 5 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.81	± 9.6 %
10945	AAB	5G NR (DFT-s-OFDM, 100% RB, 10 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.85	± 9.6 %
10946	AAC	5G NR (DFT-s-OFDM, 100% RB, 15 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.83	± 9.6 %
10947	AAB	5G NR (DFT-s-OFDM, 100% RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.87	± 9.6 %
10948	AAB	5G NR (DFT-s-OFDM, 100% RB, 25 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.94	± 9.6 %
10949	AAB	5G NR (DFT-s-OFDM, 100% RB, 30 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.87	± 9.6 %
10950	AAB	5G NR (DFT-s-OFDM, 100% RB, 40 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.94	± 9.6 %
10951	AAB	5G NR (DFT-s-OFDM, 100% RB, 50 MHz, QPSK, 15 kHz)	5G NR FR1 FDD	5.92	± 9.6 %
10952	AAB	5G NR DL (CP-OFDM, TM 3.1, 5 MHz, 64-QAM, 15 kHz)	5G NR FR1 FDD	8.25	± 9.6 %
10953	AAB	5G NR DL (CP-OFDM, TM 3.1, 10 MHz, 64-QAM, 15 kHz)	5G NR FR1 FDD	8.15	± 9.6 %
10954	AAB	5G NR DL (CP-OFDM, TM 3.1, 15 MHz, 64-QAM, 15 kHz)	5G NR FR1 FDD	8.23	± 9.6 %
10955	AAB	5G NR DL (CP-OFDM, TM 3.1, 20 MHz, 64-QAM, 15 kHz)	5G NR FR1 FDD	8.42	± 9.6 %
10956	AAB	5G NR DL (CP-OFDM, TM 3.1, 5 MHz, 64-QAM, 30 kHz)	5G NR FR1 FDD	8.14	± 9.6 %
10957	AAC	5G NR DL (CP-OFDM, TM 3.1, 10 MHz, 64-QAM, 30 kHz)	5G NR FR1 FDD	8.31	± 9.6 %
10958	AAB	5G NR DL (CP-OFDM, TM 3.1, 15 MHz, 64-QAM, 30 kHz)	5G NR FR1 FDD	8.61	± 9.6 %
10959	AAB	5G NR DL (CP-OFDM, TM 3.1, 20 MHz, 64-QAM, 30 kHz)	5G NR FR1 FDD	8.33	± 9.6 %
10960	AAB	5G NR DL (CP-OFDM, TM 3.1, 5 MHz, 64-QAM, 15 kHz)	5G NR FR1 TDD	9.32	± 9.6 %
10961	AAB	5G NR DL (CP-OFDM, TM 3.1, 10 MHz, 64-QAM, 15 kHz)	5G NR FR1 TDD	9.36	± 9.6 %
10962	AAB	5G NR DL (CP-OFDM, TM 3.1, 15 MHz, 64-QAM, 15 kHz)	5G NR FR1 TDD	9.40	± 9.6 %
10963	AAB	5G NR DL (CP-OFDM, TM 3.1, 20 MHz, 64-QAM, 15 kHz)	5G NR FR1 TDD	9.55	± 9.6 %
10964	AAB	5G NR DL (CP-OFDM, TM 3.1, 5 MHz, 64-QAM, 30 kHz)	5G NR FR1 TDD	9.29	± 9.6 %
10965	AAB	5G NR DL (CP-OFDM, TM 3.1, 10 MHz, 64-QAM, 30 kHz)	5G NR FR1 TDD	9.37	± 9.6 %
10966	AAB	5G NR DL (CP-OFDM, TM 3.1, 15 MHz, 64-QAM, 30 kHz)	5G NR FR1 TDD	9.55	± 9.6 %
10967	AAB	5G NR DL (CP-OFDM, TM 3.1, 20 MHz, 64-QAM, 30 kHz)	5G NR FR1 TDD	9.42	± 9.6 %
10968	AAB	5G NR DL (CP-OFDM, TM 3.1, 100 MHz, 64-QAM, 30 kHz)	5G NR FR1 TDD	9.49	± 9.6 %
10972	AAB	5G NR (CP-OFDM, 1 RB, 20 MHz, QPSK, 15 kHz)	5G NR FR1 TDD	11.59	± 9.6 %
10973	AAB	5G NR (DFT-s-OFDM, 1 RB, 100 MHz, QPSK, 30 kHz)	5G NR FR1 TDD	9.06	± 9.6 %
10974	AAB	5G NR (CP-OFDM, 100% RB, 100 MHz, 256-QAM, 30 kHz)	5G NR FR1 TDD	10.28	± 9.6 %

^E Uncertainty is determined using the max. deviation from linear response applying rectangular distribution and is expressed for the square of the field value.



Appendix E. Conducted RF Output Power Table

The detailed power table are shown as follows.

Full Power level/Default Power level for WWAN

GSM850 Ant0 DS1&2&3 Default power								
GSM850	Burst Average Power (dBm)			Tune-up Limit (dBm)	Frame-Average Power (dBm)			Tune-up Limit (dBm)
TX Channel	128	189	251		128	189	251	
Frequency (MHz)	824.2	836.4	848.8		824.2	836.4	848.8	
GSM 1 Tx slot	32.55	32.70	32.54	33.50	23.55	23.70	23.54	24.50
GPRS 1 Tx slot	32.54	32.68	32.62	33.50	23.54	23.68	23.62	24.50
GPRS 2 Tx slots	31.53	31.68	31.56	32.50	25.53	25.68	25.60	26.50
GPRS 3 Tx slots	29.45	29.60	29.49	30.50	25.19	25.34	25.23	26.24
GPRS 4 Tx slots	28.34	28.45	28.35	29.50	25.34	25.45	25.35	26.50
EDGE 1 Tx slot	26.20	26.23	26.17	27.50	17.20	17.23	17.17	18.50
EDGE 2 Tx slots	24.86	24.99	24.93	25.50	18.86	18.99	18.93	19.50
EDGE 3 Tx slots	22.81	22.93	22.90	24.00	18.55	18.67	18.64	19.74
EDGE 4 Tx slots	21.70	21.71	21.64	23.50	18.70	18.71	18.64	20.50

WCDMA V Ant0 DS1&2 Default power				
Band	WCDMA V			Tune-up Limit (dBm)
TX Channel	4132	4182	4233	
Rx Channel	4357	4407	4458	
Frequency (MHz)	826.4	836.4	846.6	
3GPP Rel 99 AMR 12.2Kbps	24.87	25.01	24.98	25.50
3GPP Rel 99 RMC 12.2Kbps	24.90	25.04	25.01	25.50
3GPP Rel 6 HSDPA Subtest-1	24.18	24.12	24.08	24.50
3GPP Rel 6 HSDPA Subtest-2	24.13	24.12	24.05	24.50
3GPP Rel 6 HSDPA Subtest-3	23.67	23.62	23.57	24.00
3GPP Rel 6 HSDPA Subtest-4	23.63	23.60	23.55	24.00
3GPP Rel 8 DC-HSDPA Subtest-1	24.02	23.90	23.97	24.50
3GPP Rel 8 DC-HSDPA Subtest-2	23.98	23.95	23.81	24.50
3GPP Rel 8 DC-HSDPA Subtest-3	23.53	23.32	23.43	24.00
3GPP Rel 8 DC-HSDPA Subtest-4	23.49	23.36	23.33	24.00
3GPP Rel 6 HSUPA Subtest-1	24.13	24.05	24.01	24.50
3GPP Rel 6 HSUPA Subtest-2	22.22	22.05	21.99	23.00
3GPP Rel 6 HSUPA Subtest-3	23.12	23.07	23.03	24.00
3GPP Rel 6 HSUPA Subtest-4	21.66	21.66	21.59	23.00
3GPP Rel 6 HSUPA Subtest-5	23.10	23.10	23.00	25.00

Band 5 Ant0 DSI1&2 Default power										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				20450	20525	20600				
Frequency (MHz)				829	836.5	844				
10	QPSK	1	0	24.20	24.32	24.15	25	0		
10	QPSK	1	25	24.31	24.24	24.16				
10	QPSK	1	49	24.22	24.17	24.12				
10	QPSK	25	0	23.22	23.24	23.16				
10	QPSK	25	12	23.21	23.17	23.16	24	1		
10	QPSK	25	25	23.19	23.15	23.14				
10	QPSK	50	0	23.22	23.23	23.18				
10	16QAM	1	0	23.37	23.41	23.36				
10	16QAM	1	25	23.49	23.45	23.35	24	1		
10	16QAM	1	49	23.40	23.36	23.29				
10	16QAM	25	0	22.19	22.21	22.16				
10	16QAM	25	12	22.20	22.18	22.17				
10	16QAM	25	25	22.18	22.14	22.16	23	2		
10	16QAM	50	0	22.20	22.15	22.15				
10	64QAM	1	0	22.32	22.37	22.31				
10	64QAM	1	25	22.45	22.39	22.30				
10	64QAM	1	49	22.33	22.32	22.27	23	2		
10	64QAM	25	0	21.19	21.20	21.14				
10	64QAM	25	12	21.19	21.17	21.15				
10	64QAM	25	25	21.17	21.14	21.16				
10	64QAM	50	0	21.18	21.14	21.11				
Channel				20425	20525	20625				
Frequency (MHz)				826.5	836.5	846.5				
5	QPSK	1	0	24.23	24.24	24.16	25	0		
5	QPSK	1	12	24.27	24.26	24.18				
5	QPSK	1	24	24.29	24.21	24.14				
5	QPSK	12	0	23.20	23.24	23.20				
5	QPSK	12	7	23.24	23.22	23.13	24	1		
5	QPSK	12	13	23.21	23.11	23.12				
5	QPSK	25	0	23.22	23.18	23.11				
5	16QAM	1	0	23.40	23.43	23.34				
5	16QAM	1	12	23.46	23.43	23.33	24	1		
5	16QAM	1	24	23.48	23.37	23.30				
5	16QAM	12	0	22.18	22.22	22.12				
5	16QAM	12	7	22.18	22.17	22.11				
5	16QAM	12	13	22.17	22.09	22.06	23	2		
5	16QAM	25	0	22.22	22.17	22.13				
5	64QAM	1	0	22.36	22.38	22.33				
5	64QAM	1	12	22.41	22.41	22.32				
5	64QAM	1	24	22.42	22.34	22.30	23	2		
5	64QAM	12	0	21.17	21.17	21.13				
5	64QAM	12	7	21.18	21.15	21.10				
5	64QAM	12	13	21.13	21.06	21.08				
5	64QAM	25	0	21.22	21.14	21.12				
Channel				20415	20525	20635				
Frequency (MHz)				825.5	836.5	847.5				
3	QPSK	1	0	24.24	24.24	24.13	25	0		
3	QPSK	1	8	24.25	24.19	24.12				
3	QPSK	1	14	24.27	24.18	24.10				
3	QPSK	8	0	23.21	23.15	23.12				
3	QPSK	8	4	23.22	23.21	23.14	24	1		
3	QPSK	8	7	23.21	23.19	23.08				
3	QPSK	15	0	23.18	23.17	23.11				
3	16QAM	1	0	23.40	23.42	23.28				
3	16QAM	1	8	23.44	23.36	23.25	24	1		
3	16QAM	1	14	23.46	23.34	23.31				
3	16QAM	8	0	22.25	22.23	22.18				
3	16QAM	8	4	22.26	22.24	22.20				
3	16QAM	8	7	22.25	22.25	22.18	23	2		
3	16QAM	15	0	22.22	22.20	22.15				
3	64QAM	1	0	22.35	22.34	22.29				
3	64QAM	1	8	22.36	22.37	22.26				
3	64QAM	1	14	22.46	22.33	22.28	23	2		
3	64QAM	8	0	21.22	21.21	21.15				
3	64QAM	8	4	21.22	21.19	21.14				
3	64QAM	8	7	21.24	21.17	21.14				
3	64QAM	15	0	21.18	21.18	21.11				
Channel				20407	20525	20643				
Frequency (MHz)				824.7	836.5	848.3				
1.4	QPSK	1	0	24.22	24.18	24.16	25	0		
1.4	QPSK	1	3	24.25	24.24	24.14				
1.4	QPSK	1	5	24.24	24.21	24.15				
1.4	QPSK	3	0	24.23	24.19	24.19				
1.4	QPSK	3	1	24.21	24.24	24.16	24	1		
1.4	QPSK	3	3	24.25	24.21	24.17				
1.4	QPSK	6	0	23.23	23.26	23.19				
1.4	16QAM	1	0	23.39	23.48	23.36				
1.4	16QAM	1	3	23.44	23.46	23.36	24	1		
1.4	16QAM	1	5	23.45	23.44	23.32				
1.4	16QAM	3	0	23.25	23.24	23.22				
1.4	16QAM	3	1	23.22	23.27	23.22				
1.4	16QAM	3	3	23.22	23.22	23.20	23	2		
1.4	16QAM	6	0	22.27	22.26	22.22				
1.4	64QAM	1	0	22.35	22.42	22.38				
1.4	64QAM	1	3	22.36	22.41	22.34				
1.4	64QAM	1	5	22.43	22.45	22.34	23	2		
1.4	64QAM	3	0	22.31	22.31	22.26				
1.4	64QAM	3	1	22.29	22.31	22.25				
1.4	64QAM	3	3	22.26	22.29	22.25				
1.4	64QAM	6	0	21.16	21.22	21.17	22	3		

Band 7 Ant0 DSI1 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				20850	21100	21350			
Frequency (MHz)				2510	2535	2560			
20	QPSK	1	0	24.08	24.12	24.04	25	0	
20	QPSK	1	49	23.93	23.89	23.83			
20	QPSK	1	99	23.81	23.73	23.81			
20	QPSK	50	0	22.88	22.95	22.78			
20	QPSK	50	24	22.94	22.89	22.85	24	1	
20	QPSK	50	50	22.92	22.85	22.82			
20	QPSK	100	0	22.85	22.86	22.80			
20	16QAM	1	0	23.00	23.00	22.94			
20	16QAM	1	49	23.20	23.18	23.10	24	1	
20	16QAM	1	99	23.14	23.06	23.05			
20	16QAM	50	0	21.86	21.86	21.76			
20	16QAM	50	24	21.90	21.91	21.79			
20	16QAM	50	50	21.87	21.84	21.84	23	2	
20	16QAM	100	0	21.83	21.86	21.75			
20	64QAM	1	0	21.85	21.89	21.82			
20	64QAM	1	49	22.10	22.14	22.00			
20	64QAM	1	99	22.02	21.98	21.97	23	2	
20	64QAM	50	0	20.85	20.88	20.72			
20	64QAM	50	24	20.87	20.88	20.80			
20	64QAM	50	50	20.86	20.85	20.80			
20	64QAM	100	0	20.84	20.93	20.79	22	3	
Channel				20825	21100	21375			
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	0	23.88	24.10	23.92			
15	QPSK	1	37	23.91	23.77	23.73			
15	QPSK	1	74	23.62	23.70	23.63			
15	QPSK	36	0	22.79	22.93	22.74			
15	QPSK	36	20	22.91	22.79	22.74	24	1	
15	QPSK	36	39	22.87	22.84	22.61			
15	QPSK	75	0	22.79	22.85	22.64			
15	16QAM	1	0	22.96	22.97	22.92			
15	16QAM	1	37	23.16	23.12	23.02	24	1	
15	16QAM	1	74	23.08	22.88	22.90			
15	16QAM	36	0	21.70	21.71	21.76			
15	16QAM	36	20	21.72	21.89	21.70			
15	16QAM	36	39	21.78	21.86	21.77	23	2	
15	16QAM	75	0	21.72	21.71	21.76			
15	64QAM	1	0	21.68	21.83	21.79			
15	64QAM	1	37	21.94	22.00	21.93			
15	64QAM	1	74	21.93	21.78	21.85	23	2	
15	64QAM	36	0	20.71	20.76	20.52			
15	64QAM	36	20	20.71	20.67	20.67			
15	64QAM	36	39	20.69	20.67	20.62			
15	64QAM	75	0	20.73	20.63	20.60	22	3	
Channel				20800	21100	21400			
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	0	24.03	24.10	23.99			
10	QPSK	1	25	23.88	23.71	23.68			
10	QPSK	1	49	23.77	23.63	23.63			
10	QPSK	25	0	22.88	22.95	22.85			
10	QPSK	25	12	22.72	22.85	22.86	24	1	
10	QPSK	25	25	22.78	22.82	22.70			
10	QPSK	50	0	22.86	22.78	22.68			
10	16QAM	1	0	22.87	22.80	22.93			
10	16QAM	1	25	23.06	23.04	22.96	24	1	
10	16QAM	1	49	22.96	23.01	22.96			
10	16QAM	25	0	21.65	21.88	21.64			
10	16QAM	25	12	21.80	21.89	21.71			
10	16QAM	25	25	21.80	21.84	21.69	23	2	
10	16QAM	50	0	21.73	21.85	21.63			
10	64QAM	1	0	21.65	21.73	21.81			
10	64QAM	1	25	22.11	22.73	21.86			
10	64QAM	1	49	21.84	21.77	21.97	23	2	
10	64QAM	25	0	20.79	20.74	20.71			
10	64QAM	25	12	20.87	20.81	20.64			
10	64QAM	25	25	20.65	20.73	20.59			
10	64QAM	50	0	20.78	20.89	20.73	22	3	
Channel				20775	21100	21425			
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	0	23.97	24.07	24.00			
5	QPSK	1	12	23.75	23.68	23.74			
5	QPSK	1	24	23.83	23.64	23.65			
5	QPSK	12	0	22.75	22.80	22.77			
5	QPSK	12	7	22.83	22.85	22.70	24	1	
5	QPSK	12	13	22.94	22.74	22.67			
5	QPSK	25	0	22.74	22.69	22.67			
5	16QAM	1	0	22.82	22.88	22.83			
5	16QAM	1	12	23.00	23.15	22.88	24	1	
5	16QAM	1	24	23.08	22.87	23.07			
5	16QAM	12	0	21.85	21.65	21.56			
5	16QAM	12	7	21.74	21.79	21.68			
5	16QAM	12	13	21.71	21.62	21.65	23	2	
5	16QAM	25	0	21.76	21.84	21.56			
5	64QAM	1	0	21.66	21.70	21.82			
5	64QAM	1	12	21.92	22.06	22.00			
5	64QAM	1	24	21.94	21.92	21.83	23	2	
5	64QAM	12	0	20.76	20.66	20.52			
5	64QAM	12	7	20.87	20.72	20.81			
5	64QAM	12	13	20.68	20.74	20.71			
5	64QAM	25	0	20.80	20.78	20.75	22	3	

Band 12 Ant0 DSI1&2&3 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				23060	23095	23130	704	707.5 711	
Frequency (MHz)									
10	QPSK	1	0	24.22	24.32	24.18	25	0	
10	QPSK	1	25	24.15	24.20	24.19			
10	QPSK	1	49	24.16	24.21	24.16			
10	QPSK	25	0	23.19	23.27	23.06	24	1	
10	QPSK	25	12	23.17	23.09	23.11			
10	QPSK	25	25	23.21	23.14	23.06			
10	QPSK	50	0	23.20	23.21	23.09	24	1	
10	16QAM	1	0	23.31	23.33	23.28			
10	16QAM	1	25	23.41	23.38	23.39			
10	16QAM	1	49	23.39	23.38	23.35	23	2	
10	16QAM	25	0	22.16	22.06	22.06			
10	16QAM	25	12	22.13	22.09	22.09			
10	16QAM	25	25	22.18	22.13	22.04	23	2	
10	16QAM	50	0	22.14	22.06	22.04			
10	64QAM	1	0	22.22	22.25	22.17			
10	64QAM	1	25	22.36	22.29	22.33	23	2	
10	64QAM	1	49	22.31	22.31	22.28			
10	64QAM	25	0	21.15	21.06	21.06			
10	64QAM	25	12	21.14	21.08	21.08	22	3	
10	64QAM	25	25	21.18	21.11	21.03			
10	64QAM	50	0	21.13	21.04	21.04			
Channel				23035	23095	23155	701.5	707.5 713.5	
Frequency (MHz)									
5	QPSK	1	0	24.14	24.11	24.11	25	0	
5	QPSK	1	12	24.22	24.16	24.18			
5	QPSK	1	24	24.18	24.14	24.14			
5	QPSK	12	0	23.11	23.07	23.13	24	1	
5	QPSK	12	7	23.12	23.09	23.12			
5	QPSK	12	13	23.10	23.06	23.03			
5	QPSK	25	0	23.10	23.03	23.07	24	1	
5	16QAM	1	0	23.26	23.27	23.24			
5	16QAM	1	12	23.35	23.31	23.32			
5	16QAM	1	24	23.33	23.27	23.28	23	2	
5	16QAM	12	0	22.08	22.06	22.08			
5	16QAM	12	7	22.07	22.05	22.07			
5	16QAM	12	13	22.05	22.01	21.98	23	2	
5	16QAM	25	0	22.07	22.02	22.05			
5	64QAM	1	0	22.27	22.23	22.22			
5	64QAM	1	12	22.33	22.26	22.28	23	2	
5	64QAM	1	24	22.28	22.28	22.24			
5	64QAM	12	0	21.04	21.01	21.07			
5	64QAM	12	7	21.03	21.02	21.04	22	3	
5	64QAM	12	13	21.04	21.01	20.97			
5	64QAM	25	0	21.06	21.01	21.06			
Channel				23025	23095	23165	700.5	707.5 714.5	
Frequency (MHz)									
3	QPSK	1	0	24.06	24.06	24.07	25	0	
3	QPSK	1	8	24.14	24.10	24.10			
3	QPSK	1	14	24.13	24.08	24.07			
3	QPSK	8	0	23.05	23.03	23.06	24	1	
3	QPSK	8	4	23.12	23.05	23.06			
3	QPSK	8	7	23.07	23.00	23.04			
3	QPSK	15	0	23.05	23.00	23.03	24	1	
3	16QAM	1	0	23.20	23.24	23.26			
3	16QAM	1	8	23.33	23.24	23.28			
3	16QAM	1	14	23.34	23.24	23.22	23	2	
3	16QAM	8	0	22.08	22.05	22.12			
3	16QAM	8	4	22.14	22.11	22.09			
3	16QAM	8	7	22.11	22.04	22.07	23	2	
3	16QAM	15	0	22.10	22.03	22.05			
3	64QAM	1	0	22.15	22.17	22.23			
3	64QAM	1	8	22.30	22.21	22.21	23	2	
3	64QAM	1	14	22.28	22.21	22.18			
3	64QAM	8	0	21.07	21.02	21.10			
3	64QAM	8	4	21.13	21.06	21.07	22	3	
3	64QAM	8	7	21.08	21.04	21.04			
3	64QAM	15	0	21.04	20.98	21.02			
Channel				23017	23095	23173	699.7	707.5 715.3	
Frequency (MHz)									
1.4	QPSK	1	0	24.06	24.05	24.08	25	0	
1.4	QPSK	1	3	24.09	24.05	24.07			
1.4	QPSK	1	5	24.15	24.07	24.06			
1.4	QPSK	3	0	24.05	24.07	24.06			
1.4	QPSK	3	1	24.08	24.06	24.05			
1.4	QPSK	3	3	24.08	24.04	24.08			
1.4	QPSK	6	0	23.09	23.07	23.04	24	1	
1.4	16QAM	1	0	23.24	23.23	23.26			
1.4	16QAM	1	3	23.25	23.25	23.27			
1.4	16QAM	1	5	23.30	23.25	23.25			
1.4	16QAM	3	0	23.08	23.08	23.06			
1.4	16QAM	3	1	23.10	23.09	23.07			
1.4	16QAM	3	3	23.08	23.04	23.06	23	2	
1.4	16QAM	6	0	22.08	22.08	22.08			
1.4	64QAM	1	0	22.20	22.19	22.24			
1.4	64QAM	1	3	22.22	22.22	22.20			
1.4	64QAM	1	5	22.30	22.22	22.20			
1.4	64QAM	3	0	22.10	22.11	22.10			
1.4	64QAM	3	1	22.17	22.15	22.12	23	2	
1.4	64QAM	3	3	22.16	22.08	22.11			
1.4	64QAM	6	0	21.03	21.02	21.01			

Band 17 Ant0 DS11&2&3 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				23780	23790	23800	709	710 711	
Frequency (MHz)									
10	QPSK	1	0	23.64	23.68	23.52	25	0	
10	QPSK	1	25	23.61	23.57	23.58			
10	QPSK	1	49	23.55	23.55	23.54			
10	QPSK	25	0	22.46	22.53	22.43	24	1	
10	QPSK	25	12	22.49	22.51	22.51			
10	QPSK	25	25	22.51	22.46	22.44			
10	QPSK	50	0	22.51	22.52	22.47	24	1	
10	16QAM	1	0	22.68	22.71	22.64			
10	16QAM	1	25	22.81	22.78	22.79			
10	16QAM	1	49	22.80	22.78	22.78	23	2	
10	16QAM	25	0	21.41	21.41	21.42			
10	16QAM	25	12	21.47	21.50	21.49			
10	16QAM	25	25	21.47	21.45	21.42	23	2	
10	16QAM	50	0	21.46	21.46	21.44			
10	64QAM	1	0	21.62	21.66	21.60			
10	64QAM	1	25	21.74	21.72	21.73	23	2	
10	64QAM	1	49	21.73	21.73	21.72			
10	64QAM	25	0	20.40	20.41	20.41			
10	64QAM	25	12	20.46	20.47	20.48	22	3	
10	64QAM	25	25	20.46	20.44	20.40			
10	64QAM	50	0	20.42	20.44	20.43			
Channel				23755	23790	23825	706.5	710 713.5	
Frequency (MHz)									
5	QPSK	1	0	23.52	23.49	23.53	25	0	
5	QPSK	1	12	23.58	23.60	23.56			
5	QPSK	1	24	23.53	23.60	23.60			
5	QPSK	12	0	22.49	22.51	22.56	24	1	
5	QPSK	12	7	22.49	22.50	22.50			
5	QPSK	12	13	22.50	22.44	22.45			
5	QPSK	25	0	22.50	22.51	22.51	24	1	
5	16QAM	1	0	22.74	22.69	22.76			
5	16QAM	1	12	22.75	22.79	22.82			
5	16QAM	1	24	22.81	22.79	22.76	23	2	
5	16QAM	12	0	21.48	21.45	21.51			
5	16QAM	12	7	21.44	21.48	21.45			
5	16QAM	12	13	21.45	21.40	21.40	23	2	
5	16QAM	25	0	21.48	21.48	21.45			
5	64QAM	1	0	21.62	21.63	21.59			
5	64QAM	1	12	21.71	21.71	21.75	23	2	
5	64QAM	1	24	21.76	21.73	21.74			
5	64QAM	12	0	20.42	20.43	20.45			
5	64QAM	12	7	20.45	20.43	20.42	22	3	
5	64QAM	12	13	20.42	20.39	20.41			
5	64QAM	25	0	20.45	20.47	20.46			

GSM1900 Ant1 DS1&2&3 Default power

	Burst Average Power (dBm)			Tune-up Limit (dBm)	Frame-Average Power (dBm)			Tune-up Limit (dBm)
	512	661	810		512	661	810	
TX Channel	1850.2	1880	1909.8		1850.2	1880	1909.8	
Frequency (MHz)	1850.2	1880	1909.8		1850.2	1880	1909.8	
GSM 1 Tx slot	30.01	30.11	29.94	31.50	21.01	21.11	20.94	22.50
GPRS 1 Tx slot	30.30	30.10	29.93	31.50	21.30	21.10	20.93	22.50
GPRS 2 Tx slots	29.23	29.33	29.01	30.30	23.23	23.33	23.01	24.50
GPRS 3 Tx slots	26.85	26.55	26.46	27.50	22.59	22.29	22.20	23.24
GPRS 4 Tx slots	26.57	25.42	25.34	26.50	22.57	22.42	22.34	23.50
EDGE 1 Tx slot	25.78	25.43	25.33	26.50	16.78	16.43	16.33	17.50
EDGE 2 Tx slots	24.75	24.43	24.68	25.50	18.75	18.43	18.68	19.50
EDGE 3 Tx slots	22.72	22.61	22.55	23.50	18.46	18.35	18.29	19.24
EDGE 4 Tx slots	21.46	21.17	21.57	22.50	18.46	18.17	18.57	19.50

WCDMA II Ant1 DS1&2 Default power

WCDMA IV Ant1 DS1&2 Default power

Band	WCDMA II			Tune-up Limit (dBm)	WCDMA IV			Tune-up Limit (dBm)
	9262	9400	9538		1312	1419	1513	
TX Channel	9262	9400	9538		1312	1419	1513	
Rx Channel	9262	9400	9538		1312	1419	1513	
Frequency (MHz)	1852.4	1880	1907.6		1712.4	1732.6	1752.6	
3GPP Rel 99 AMR 12.2Kbps	23.41	23.43	23.12	24.50	23.79	23.80	23.89	25.00
3GPP Rel 99 RMC 12.2Kbps	23.43	23.45	23.18	24.50	23.94	23.96	23.93	25.00
3GPP Rel 6 HSDPA Subtest-1	22.82	22.83	22.75	23.50	23.40	23.42	23.42	24.00
3GPP Rel 6 HSDPA Subtest-2	22.78	22.80	22.73	23.50	23.44	23.41	23.39	24.00
3GPP Rel 6 HSDPA Subtest-3	22.32	22.33	22.25	23.00	23.13	23.12	22.92	23.50
3GPP Rel 6 HSDPA Subtest-4	22.27	22.30	22.21	23.00	23.08	23.07	22.87	23.50
3GPP Rel 8 DC-HSDPA Subtest-1	22.67	22.62	22.64	23.50	23.25	23.30	23.23	24.00
3GPP Rel 8 DC-HSDPA Subtest-2	22.59	22.58	22.49	23.50	23.24	23.26	23.25	24.00
3GPP Rel 8 DC-HSDPA Subtest-3	22.08	22.14	22.11	23.00	23.00	22.92	22.65	23.50
3GPP Rel 8 DC-HSDPA Subtest-4	22.02	22.13	22.03	23.00	22.97	22.82	22.63	23.50
3GPP Rel 6 HSUPA Subtest-1	21.79	21.75	21.73	23.50	22.54	22.57	22.58	24.00
3GPP Rel 6 HSUPA Subtest-2	20.82	20.77	20.72	21.50	21.53	21.58	21.59	22.00
3GPP Rel 6 HSUPA Subtest-3	21.84	21.79	21.73	22.50	22.60	22.61	22.60	23.00
3GPP Rel 6 HSUPA Subtest-4	20.36	20.36	20.26	21.50	21.12	21.16	21.13	22.00
3GPP Rel 6 HSUPA Subtest-5	21.80	21.80	21.70	23.50	22.50	22.60	22.50	24.00

GSM1900 Ant2 DSI1&2&4 Default power

GSM1900	Burst Average Power (dBm)			Tune-up Limit (dBm)	Frame-Average Power (dBm)			Tune-up Limit (dBm)
	512	661	810		512	661	810	
TX Channel	1850.2	1880	1909.8		1850.2	1880	1909.8	
Frequency (MHz)	1850.2	1880	1909.8		1850.2	1880	1909.8	
GSM 1 Tx slot	28.47	28.50	28.44	29.50	19.47	19.50	19.44	20.50
GPRS 1 Tx slot	28.69	28.48	28.52	29.50	19.69	19.48	19.52	20.50
GPRS 2 Tx slots	27.61	27.73	27.63	28.50	21.61	21.73	21.63	22.50
GPRS 3 Tx slots	25.30	24.93	24.95	25.50	21.04	20.67	20.69	21.24
GPRS 4 Tx slots	24.06	23.81	23.78	24.50	21.06	20.81	20.78	21.50
EDGE 1 Tx slot	24.04	23.70	23.69	24.50	15.04	14.70	14.69	15.50
EDGE 2 Tx slots	23.01	22.76	22.64	23.50	17.01	16.76	16.64	17.50
EDGE 3 Tx slots	20.89	20.62	20.53	21.50	16.63	16.36	16.27	17.24
EDGE 4 Tx slots	19.56	19.47	19.17	20.50	16.56	16.47	16.17	17.50

WCDMA IV Ant2 DSI1&2&4 Default power

Band	WCDMA IV			Tune-up Limit (dBm)
TX Channel	1312	1413	1513	
Rx Channel	1537	1638	1738	
Frequency (MHz)	1712.4	1732.6	1752.6	
3GPP Rel 99 AMR 12.2Kbps	23.07	23.39	23.26	24.50
3GPP Rel 99 RMC 12.2Kbps	23.16	23.50	23.42	24.50
3GPP Rel 6 HSDPA Subtest-1	22.19	22.26	22.40	23.50
3GPP Rel 6 HSDPA Subtest-2	22.16	22.26	22.42	23.50
3GPP Rel 6 HSDPA Subtest-3	21.88	21.97	21.98	23.00
3GPP Rel 6 HSDPA Subtest-4	21.83	21.94	21.90	23.00
3GPP Rel 6 DC-HSDPA Subtest-1	22.02	22.09	22.25	23.50
3GPP Rel 6 DC-HSDPA Subtest-2	21.95	22.03	22.14	23.50
3GPP Rel 6 DC-HSDPA Subtest-3	21.70	21.71	21.80	23.00
3GPP Rel 6 DC-HSDPA Subtest-4	21.67	21.71	21.79	23.00
3GPP Rel 6 HSUPA Subtest-1	22.33	22.46	22.60	23.50
3GPP Rel 6 HSUPA Subtest-2	20.31	20.44	20.55	21.50
3GPP Rel 6 HSUPA Subtest-3	21.36	21.47	21.62	22.50
3GPP Rel 6 HSUPA Subtest-4	19.87	20.00	20.12	21.50
3GPP Rel 6 HSUPA Subtest-5	22.30	22.40	22.50	23.50

GSM850 Ant4 DS1&2&4 Default power

GSM850	Burst Average Power (dBm)			Tune-up Limit (dBm)	Frame-Average Power (dBm)			Tune-up Limit (dBm)
	128	189	251		128	189	251	
TX Channel	824.2	836.4	848.8		824.2	836.4	848.8	
Frequency (MHz)	31.49	31.60	31.36	32.50	22.49	22.60	22.36	23.50
GSM 1 Tx slot	31.48	31.59	31.34	32.50	22.48	22.59	22.34	23.50
GPRS 1 Tx slot	30.48	30.60	30.37	31.50	24.48	24.50	24.37	25.50
GPRS 3 Tx slot	28.43	28.51	28.33	29.50	24.17	24.25	24.07	25.24
GPRS 4 Tx slot	27.28	27.35	27.24	28.50	24.28	24.35	24.24	25.50
EDGE 1 Tx slot	25.17	24.92	24.86	25.50	18.17	15.92	15.86	16.50
EDGE 2 Tx slot	23.91	23.55	23.62	24.50	17.91	17.55	17.62	18.50
EDGE 3 Tx slot	21.80	21.56	21.54	22.50	17.54	17.30	17.28	18.24
EDGE 4 Tx slot	20.65	20.50	20.55	21.50	17.65	17.50	17.55	18.50

GSM1900 Ant4 DS1&2&4 Default power

GSM1900	Burst Average Power (dBm)			Tune-up Limit (dBm)	Frame-Average Power (dBm)			Tune-up Limit (dBm)
	512	681	810		512	681	810	
TX Channel	1850.2	1880	1909.8		1850.2	1880	1909.8	
Frequency (MHz)	28.30	28.04	28.00	29.00	19.30	19.04	19.00	20.00
GSM 1 Tx slot	28.35	28.04	27.91	29.00	19.35	19.04	18.91	20.00
GPRS 1 Tx slot	27.14	27.22	27.20	28.50	21.14	21.22	21.20	22.50
GPRS 2 Tx slot	24.83	24.68	24.56	25.50	20.57	20.42	20.30	21.24
GPRS 4 Tx slot	23.69	23.49	23.40	24.50	20.69	20.49	20.40	21.50
EDGE 1 Tx slot	23.91	23.71	23.41	24.50	14.91	14.71	14.41	15.50
EDGE 2 Tx slot	22.79	22.66	22.45	23.50	16.79	16.66	16.45	17.50
EDGE 3 Tx slot	20.78	20.62	20.51	21.50	16.52	16.36	16.25	17.24
EDGE 4 Tx slot	19.50	19.32	19.13	20.50	16.50	16.32	16.13	17.50

WCDMA II Ant4 DS1&2 Default power

WCDMA IV Ant4 DS1&2 Default power

WCDMA V Ant4 DS1&2 Default power

Band	WCDMA II			Tune-up Limit (dBm)	WCDMA IV			Tune-up Limit (dBm)	WCDMA V			Tune-up Limit (dBm)	
	TX Channel	9262	9400		9538	1312	1413		1513	4132	4182		4233
TX Channel	9662	9800	9938		1537	1638	1738		4357	4407	4458		
Frequency (MHz)	1852.4	1880	1907.6		1712.4	1732.6	1752.6		826.4	836.4	846.6		
3GPP Rel 99	AMR 12.2Kbps	24.78	25.19	25.06	25.50	23.21	23.35	23.27	24.50	23.41	23.55	23.48	24.50
3GPP Rel 99	RMC 12.2Kbps	24.80	25.20	25.10	25.50	23.22	23.39	23.29	24.50	23.45	23.57	23.51	24.50
3GPP Rel 6	HSDPA Subtest-1	24.37	24.23	24.04	24.50	22.27	22.29	22.37	23.50	23.44	23.04	23.06	23.50
3GPP Rel 6	HSDPA Subtest-2	24.34	24.19	24.03	24.50	22.29	22.30	22.37	23.50	22.46	22.55	22.60	23.50
3GPP Rel 6	HSDPA Subtest-3	23.87	23.75	23.55	24.00	21.97	22.01	21.90	23.00	22.42	22.52	22.59	23.00
3GPP Rel 6	HSDPA Subtest-4	23.80	23.68	23.51	24.00	21.96	21.98	21.87	23.00	22.00	22.03	22.11	23.00
3GPP Rel 8	DC-HSDPA Subtest-1	24.26	24.16	23.95	24.50	22.16	22.11	22.28	23.50	23.32	23.35	23.40	23.50
3GPP Rel 8	DC-HSDPA Subtest-2	24.20	24.09	23.80	24.50	22.21	22.20	22.13	23.50	22.23	22.44	22.42	23.50
3GPP Rel 8	DC-HSDPA Subtest-3	23.76	23.59	23.31	24.00	21.92	21.84	21.68	23.00	22.19	22.32	22.51	23.00
3GPP Rel 8	DC-HSDPA Subtest-4	23.71	23.54	23.36	24.00	21.74	21.78	21.77	23.00	21.94	21.96	22.06	23.00
3GPP Rel 6	HSUPA Subtest-1	23.33	23.23	23.04	24.50	22.44	22.47	22.58	23.50	20.40	20.53	20.52	23.50
3GPP Rel 6	HSUPA Subtest-2	22.32	22.21	21.98	22.50	20.42	20.44	20.55	21.50	20.43	20.50	20.53	21.50
3GPP Rel 6	HSUPA Subtest-3	23.33	23.21	23.03	23.50	21.62	21.50	21.62	22.50	21.46	21.52	21.56	22.50
3GPP Rel 6	HSUPA Subtest-4	21.89	21.72	21.51	22.50	20.01	20.02	20.11	21.50	20.00	20.10	20.14	21.50
3GPP Rel 6	HSUPA Subtest-5	23.30	23.20	23.00	24.50	22.40	22.40	22.50	23.50	21.40	21.50	21.50	23.50

Reduced power level for WWAN

		WCDMA V Arit0 DS3			
Band		WCDMA V			Tune-up Limit (dBm)
TX Channel		4132	4182	4233	
Rx Channel		4357	4407	4458	
Frequency (MHz)		826.4	836.4	846.6	
3GPP Rel 99	AMR 12.2Kbps	24.08	24.10	24.10	25.00
3GPP Rel 99	RMC 12.2Kbps	24.16	24.37	24.30	25.00
3GPP Rel 6	HSDPA Subtest-1	23.05	23.47	23.36	24.00
3GPP Rel 6	HSDPA Subtest-2	23.16	23.28	23.35	24.00
3GPP Rel 6	HSDPA Subtest-3	22.71	22.97	22.85	23.50
3GPP Rel 6	HSDPA Subtest-4	22.65	22.86	22.80	23.50
3GPP Rel 8	DC-HSDPA Subtest-1	23.14	23.36	23.25	24.00
3GPP Rel 8	DC-HSDPA Subtest-2	23.27	23.41	23.36	24.00
3GPP Rel 8	DC-HSDPA Subtest-3	22.66	22.85	22.70	23.50
3GPP Rel 8	DC-HSDPA Subtest-4	22.61	22.88	22.85	23.50
3GPP Rel 6	HSUPA Subtest-1	23.06	23.36	23.36	24.00
3GPP Rel 6	HSUPA Subtest-2	21.15	21.44	21.33	22.50
3GPP Rel 6	HSUPA Subtest-3	22.05	22.34	22.36	23.50
3GPP Rel 6	HSUPA Subtest-4	21.16	21.29	21.24	22.50
3GPP Rel 6	HSUPA Subtest-5	23.28	23.30	23.26	24.50

		WCDMA II Ant1 DS13				WCDMA IV Ant1 DS13			
Band		WCDMA II			Tune-up Limit (dBm)	WCDMA IV			Tune-up Limit (dBm)
TX Channel		9262	9400	9538		1312	1413	1513	
Rx Channel		9662	9800	9938		1537	1638	1738	
Frequency (MHz)		1852.4	1880	1907.6		1712.4	1732.6	1752.6	
3GPP Rel 99	AMR 12.2Kbps	21.39	21.51	21.24	22.50	21.81	21.81	21.75	23.00
3GPP Rel 99	RMC 12.2Kbps	21.42	21.53	21.21	22.50	22.01	22.03	21.91	23.00
3GPP Rel 6	HSDPA Subtest-1	20.78	20.84	20.86	21.50	21.32	21.49	21.42	22.00
3GPP Rel 6	HSDPA Subtest-2	20.80	20.89	20.65	21.50	21.35	21.49	21.42	22.00
3GPP Rel 6	HSDPA Subtest-3	20.39	20.36	20.25	21.00	21.14	21.15	21.02	21.50
3GPP Rel 6	HSDPA Subtest-4	20.31	20.22	20.21	21.00	21.18	21.13	20.95	21.50
3GPP Rel 6	DC-HSDPA Subtest-1	20.63	20.69	20.66	21.50	21.19	21.32	21.25	22.00
3GPP Rel 6	DC-HSDPA Subtest-2	20.55	20.61	20.53	21.50	21.34	21.32	21.22	22.00
3GPP Rel 6	DC-HSDPA Subtest-3	20.00	20.07	20.11	21.00	20.95	20.97	20.61	21.50
3GPP Rel 6	DC-HSDPA Subtest-4	19.90	20.16	19.92	21.00	20.93	20.73	20.52	21.50
3GPP Rel 6	HSUPA Subtest-1	19.67	19.88	19.68	21.50	20.51	20.68	20.52	22.00
3GPP Rel 6	HSUPA Subtest-2	18.76	18.69	18.74	19.50	19.50	19.55	19.71	20.00
3GPP Rel 6	HSUPA Subtest-3	19.83	19.78	19.65	20.50	20.57	20.72	20.71	21.00
3GPP Rel 6	HSUPA Subtest-4	18.24	18.28	18.21	19.50	19.04	19.18	19.04	20.00
3GPP Rel 6	HSUPA Subtest-5	19.68	19.74	19.79	21.50	20.41	20.48	20.47	22.00

		GSM1900 AnH DSI1							
GSM1900		Burst Average Power (dBm)			Tuneup Limit (dBm)	Frame-Average Power (dBm)			Tuneup Limit (dBm)
TX Channel		512	561	810		512	561	810	
Frequency (MHz)		1850.2	1880	1909.8		1850.2	1880	1909.8	
GSM 1 Tx slot		26.17	26.20	26.14	27.00	17.17	17.20	17.14	18.00
GPRS 1 Tx slot		26.35	26.19	26.13	27.00	17.35	17.19	17.13	18.00
GPRS 2 Tx slot		27.14	27.12	27.20	28.50	21.14	21.12	21.20	22.50
GPRS 3 Tx slot		24.83	24.68	24.56	25.50	20.57	20.42	20.30	21.24
GPRS 4 Tx slot		23.69	23.49	23.40	24.50	20.69	20.49	20.40	21.50
EDGE 1 Tx slot		23.91	23.71	23.41	24.50	14.91	14.71	14.41	15.50
EDGE 2 Tx slot		22.79	22.66	22.45	23.50	16.79	16.66	16.45	17.50
EDGE 3 Tx slot		20.78	20.62	20.51	21.50	16.52	16.36	16.25	17.24
EDGE 4 Tx slot		19.50	19.32	19.13	20.50	16.50	16.32	16.13	17.50

WCDMA II AnH DSI1					WCDMA IV AnH DSI1					WCDMA V AnH DSI1				
Band		WCDMA II			Tune-up Limit (dBm)	WCDMA IV			Tune-up Limit (dBm)	WCDMA V			Tuneup Limit (dBm)	
TX Channel		9262	9400	9538		1312	1413	1513		4132	4182	4233		
Rx Channel		9662	9800	9938		1537	1638	1738		4357	4407	4458		
Frequency (MHz)		1852.4	1880	1907.6		1712.4	1732.6	1752.6		826.4	836.4	846.6		
3GPP Rel 99	AMR 12.2Kbps	18.94	19.24	19.05	19.50	18.02	17.98	17.95	19.50	22.26	22.44	22.33	23.50	
3GPP Rel 99	RMC 12.2Kbps	18.95	19.26	19.07	19.50	18.06	18.16	18.10	19.50	22.47	22.55	22.46	23.50	
3GPP Rel 6	HSMDA Subtest-1	17.99	18.31	18.01	18.50	17.06	17.10	17.04	18.50	21.57	21.56	21.57	22.50	
3GPP Rel 6	HSMDA Subtest-2	17.87	18.22	18.08	18.50	17.13	17.17	16.99	18.50	21.44	21.55	21.54	22.50	
3GPP Rel 6	HSMDA Subtest-3	17.39	17.65	17.59	18.00	16.59	16.68	16.56	18.00	20.96	21.08	21.04	22.00	
3GPP Rel 6	HSMDA Subtest-4	17.56	17.80	17.48	18.00	16.49	16.69	16.64	18.00	21.05	21.17	20.86	22.00	
3GPP Rel 8	DC-HSDPA Subtest-1	17.85	18.24	18.16	18.50	16.97	17.10	17.03	18.50	21.44	21.56	21.39	22.50	
3GPP Rel 8	DC-HSDPA Subtest-2	17.89	18.23	18.07	18.50	17.16	17.18	17.07	18.50	21.41	21.48	21.46	22.50	
3GPP Rel 8	DC-HSDPA Subtest-3	17.42	17.79	17.62	18.00	16.64	16.70	16.58	18.00	20.87	21.09	21.01	22.00	
3GPP Rel 8	DC-HSDPA Subtest-4	17.49	17.67	17.65	18.00	16.46	16.67	16.64	18.00	20.86	20.94	20.90	22.00	
3GPP Rel 6	HSUPA Subtest-1	17.99	18.21	18.08	18.50	16.95	17.16	17.13	18.50	21.52	21.52	21.55	22.50	
3GPP Rel 6	HSUPA Subtest-2	15.92	16.36	16.03	16.50	15.17	15.26	15.18	16.50	19.37	19.66	19.58	20.50	
3GPP Rel 6	HSUPA Subtest-3	17.05	17.28	17.15	17.50	16.18	16.05	16.07	17.50	20.37	20.60	20.45	21.50	
3GPP Rel 6	HSUPA Subtest-4	15.98	16.18	16.10	16.50	15.05	15.24	15.22	16.50	19.40	19.67	19.41	20.50	
3GPP Rel 6	HSUPA Subtest-5	17.83	18.16	18.16	18.50	17.17	17.20	16.98	18.50	21.41	21.54	21.40	22.50	

		WCDMA II Ant4 DSII4			WCDMA IV Ant4 DSII4			
Band		WCDMA II			Tune-up Limit (dBm)	WCDMA IV		
TX Channel		9262	9400	9538		1312	1419	1513
Rx Channel		9662	9800	9938		1537	1638	1738
Frequency (MHz)		1852.4	1880	1907.6		1712.4	1732.6	1752.6
3GPP Rel 99	AMR 12.2Kbps	22.60	22.78	22.57	23.00	22.00	22.09	22.10
3GPP Rel 99	RMC 12.2Kbps	22.69	22.87	22.62	23.00	21.93	22.29	22.19
3GPP Rel 6	HSDPA Subtest-1	21.78	21.86	21.73	22.00	21.11	21.21	21.25
3GPP Rel 6	HSDPA Subtest-2	21.65	21.72	21.60	22.00	21.10	21.17	21.25
3GPP Rel 6	HSDPA Subtest-3	21.21	21.25	21.09	21.50	20.73	20.87	20.79
3GPP Rel 6	HSDPA Subtest-4	21.44	21.37	21.07	21.50	20.69	20.80	20.66
3GPP Rel 8	DC-HSDPA Subtest-1	21.89	21.79	21.60	22.00	21.08	20.81	21.09
3GPP Rel 8	DC-HSDPA Subtest-2	21.84	21.63	21.38	22.00	20.96	20.88	20.99
3GPP Rel 8	DC-HSDPA Subtest-3	21.32	21.07	20.83	21.50	20.68	20.76	20.46
3GPP Rel 8	DC-HSDPA Subtest-4	21.29	21.16	21.04	21.50	20.51	20.66	20.58
3GPP Rel 6	HSUPA Subtest-1	20.96	20.75	20.64	22.00	21.29	21.17	21.42
3GPP Rel 6	HSUPA Subtest-2	19.90	19.76	19.70	20.00	19.13	19.15	19.30
3GPP Rel 6	HSUPA Subtest-3	20.92	20.84	20.61	21.00	20.31	20.19	20.49
3GPP Rel 6	HSUPA Subtest-4	19.38	19.40	19.16	20.00	18.75	18.81	18.91
3GPP Rel 6	HSUPA Subtest-5	20.82	20.74	20.88	22.00	21.26	21.19	21.27
3GPP Rel 6								22.50

Full Power level/Default Power level for 5G NR For DFT-15

n5_Ant0 DSI1&2&3 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				166800	167300	167800	25.0	0.0	
Frequency (MHz)				834	836.5	839			
20	PI/2 BPSK	1	1	23.29	23.38	23.05			
20	PI/2 BPSK	1	53	23.55	23.76	23.43	25.0	0.0	
20	PI/2 BPSK	1	104	23.41	23.49	23.20			
20	PI/2 BPSK	50	0	23.02	23.34	23.03		0.5	
20	PI/2 BPSK	50	28	23.63	23.80	23.53	25.0	0.0	
20	PI/2 BPSK	50	56	23.10	23.27	22.92	24.5	0.5	
20	PI/2 BPSK	100	0	23.18	23.30	22.93			
20	QPSK	1	1	23.80	23.84	23.66			
20	QPSK	1	53	23.85	23.89	23.64	25.0	0.0	
20	QPSK	1	104	23.62	23.67	23.39			
20	QPSK	50	0	22.70	22.75	22.78		1.0	
20	QPSK	50	28	23.58	23.77	23.40	25.0	0.0	
20	QPSK	50	56	22.64	22.73	22.54	24.0	1.0	
20	QPSK	100	0	22.55	22.73	22.35			
20	16QAM	1	1	22.02	22.18	22.09		1.0	
20	64QAM	1	1	20.54	20.65	20.56	22.5	2.5	
20	256QAM	1	1	19.32	19.38	19.26	20.5	4.5	
Channel				166300	167300	168300	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				831.5	836.5	841.5	25.0	0.0	
15	QPSK	1	40	23.68	23.61	23.51	25.0	0.0	
Channel				165800	167300	168800	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				829	836.5	844	25.0	0.0	
10	QPSK	1	26	23.69	23.78	23.61	25.0	0.0	
Channel				165300	167300	169300	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				826.5	836.5	846.5	25.0	0.0	
5	QPSK	1	13	23.59	23.61	23.72	25.0	0.0	

n7_DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	25.0	0.0	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	23.02	23.14	23.12			
20	PI/2 BPSK	1	53	23.08	23.36	23.23	25.0	0.0	
20	PI/2 BPSK	1	104	23.05	23.09	23.06			
20	PI/2 BPSK	50	0	22.62	22.97	22.86		0.5	
20	PI/2 BPSK	50	28	23.11	23.36	23.42	25.0	0.0	
20	PI/2 BPSK	50	56	22.61	22.75	22.69	24.5	0.5	
20	PI/2 BPSK	100	0	22.75	22.83	22.79			
20	QPSK	1	1	23.38	23.45	23.48			
20	QPSK	1	53	23.36	23.63	23.54	25.0	0.0	
20	QPSK	1	104	23.16	23.28	23.30			
20	QPSK	50	0	22.50	22.57	22.50		1.0	
20	QPSK	50	28	23.11	23.44	23.28	25.0	0.0	
20	QPSK	50	56	22.17	22.36	22.25	24.0	1.0	
20	QPSK	100	0	22.24	22.43	22.29			
20	16QAM	1	1	22.35	22.37	22.32		1.0	
20	64QAM	1	1	20.52	20.62	20.61	22.5	2.5	
20	256QAM	1	1	18.82	18.94	18.93	20.5	4.5	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5	25.0	0.0	
15	QPSK	1	40	23.27	23.45	23.44	25.0	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565	25.0	0.0	
10	QPSK	1	26	23.16	23.44	23.40	25.0	0.0	
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5	25.0	0.0	
5	QPSK	1	13	23.21	23.41	23.34	25.0	0.0	

n66_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346000	349000	352000			
Frequency (MHz)				1730	1745	1760			
40	PI/2 BPSK	1	1	23.82	24.07	23.89			
40	PI/2 BPSK	1	108	24.09	24.35	24.15	25.5	0.0	
40	PI/2 BPSK	1	214	23.79	24.07	23.92			
40	PI/2 BPSK	108	0	23.26	23.53	23.53	25.0	0.5	
40	PI/2 BPSK	108	54	24.20	24.33	24.23	25.5	0.0	
40	PI/2 BPSK	108	108	23.25	23.48	23.32	25.0	0.5	
40	PI/2 BPSK	216	0	23.21	23.43	23.40			
40	QPSK	1	1	23.93	23.85	23.80			
40	QPSK	1	108	24.16	24.37	24.19	25.5	0.0	
40	QPSK	1	214	23.93	24.13	24.02			
40	QPSK	108	0	23.09	23.10	23.00	24.5	1.0	
40	QPSK	108	54	23.96	24.18	24.12	25.5	0.0	
40	QPSK	108	108	23.05	23.06	22.89	24.5	1.0	
40	QPSK	216	0	23.17	23.19	23.14			
40	16QAM	1	1	22.91	23.17	22.99	24.5	1.0	
40	64QAM	1	1	21.52	21.67	21.50	23.0	2.5	
40	256QAM	1	1	19.66	19.87	19.78	21.0	4.5	
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	PI/2 BPSK	1	80	24.05	24.18	24.02	25.5	0.0	
Channel				344500	349000	353500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	PI/2 BPSK	1	67	24.12	24.21	24.06	25.5	0.0	
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	53	24.14	24.27	24.13	25.5	0.0	
Channel				343500	349000	354500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	40	24.14	24.17	24.00	25.5	0.0	
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	26	24.07	24.32	24.12	25.5	0.0	
Channel				342500	349000	355500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	13	24.12	24.35	24.16	25.5	0.0	



PC3 n77_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663666			
Frequency (MHz)				3725.01	3840	3955.02			
50	Pl2 BPSK	1	1	18.56	18.59	18.59			
50	Pl2 BPSK	1	135	19.35	19.46	19.41	20.5		
50	Pl2 BPSK	1	268	18.63	18.50	18.64			
50	Pl2 BPSK	135	0	19.19	18.38	19.36	20.5	0.0	
50	Pl2 BPSK	135	68	19.29	19.55	19.48	20.5	0.0	
50	Pl2 BPSK	135	135	19.35	19.59	19.22	20.5	0.0	
50	Pl2 BPSK	270	0	19.25	19.49	19.25			
50	QPSK	1	1	18.59	18.63	18.52			
50	QPSK	1	135	19.50	19.08	19.56	20.5	0.0	
50	QPSK	1	268	18.80	18.64	18.56			
50	QPSK	135	0	19.44	19.51	19.51	20.5	0.0	
50	QPSK	135	68	19.36	19.57	19.53	20.5	0.0	
50	QPSK	135	135	19.37	19.40	19.25			
50	QPSK	270	0	18.27	19.28	19.25			
50	16QAM	1	1	19.11	19.26	19.23	20.5	0.0	
50	64QAM	1	1	19.16	19.34	19.15	20.5	0.0	
50	256QAM	1	1	18.17	18.13	18.04	19.0	1.5	
Channel				648000	656000	664000	Tune-up limit	MPR	
Frequency (MHz)				3720	3840	3960	(dBm)	(dB)	
40	QPSK	1	53	19.53	19.69	19.47	20.5	0.0	
Channel				647334	656000	664668	Tune-up limit	MPR	
Frequency (MHz)				3719.01	3840	3970.02	(dBm)	(dB)	
20	QPSK	1	26	19.30	19.48	19.50	20.5	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3840	3972.51	(dBm)	(dB)	
15	QPSK	1	19	19.45	19.48	19.54	20.5	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3705	3840	3975	(dBm)	(dB)	
10	QPSK	1	12	19.51	19.65	19.50	20.5	0.0	

Par27Q PC3 n77_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	Pl2 BPSK	1	1	18.57	18.53	18.54			
50	Pl2 BPSK	1	135	19.36	19.11	19.36	20.5	0.0	
50	Pl2 BPSK	1	268	18.59	18.59	18.56			
50	Pl2 BPSK	135	0	19.45	19.31	19.20	20.5	0.0	
50	Pl2 BPSK	135	68	19.10	19.28	19.33	20.5	0.0	
50	Pl2 BPSK	135	135	19.28	19.11	19.31	20.5	0.0	
50	Pl2 BPSK	270	0	19.29	19.06	19.28			
50	QPSK	1	1	18.61	18.56	18.61			
50	QPSK	1	135	19.31	19.66	19.15	20.5	0.0	
50	QPSK	1	268	18.52	18.91	18.83			
50	QPSK	135	0	19.11	19.12	19.03	20.5	0.0	
50	QPSK	135	68	19.11	19.26	19.22	20.5	0.0	
50	QPSK	135	135	19.21	19.14	19.11			
50	QPSK	270	0	18.68	18.99	18.86			
50	16QAM	1	1	19.23	19.02	19.12	20.5	0.0	
50	64QAM	1	1	19.16	19.07	19.10	20.5	0.0	
50	256QAM	1	1	18.01	18.15	18.15	19.0	1.5	
Channel				631334	633334	635352	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)	
40	QPSK	1	53	19.10	19.08	18.97	20.5	0.0	
Channel				630668	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	18.99	19.26	18.81	20.5	0.0	
Channel				630334	633334	636352	Tune-up limit	MPR	
Frequency (MHz)				3497.5	3500.01	3542.48	(dBm)	(dB)	
15	QPSK	1	19	19.09	19.14	18.93	20.5	0.0	
Channel				630334	633334	636352	Tune-up limit	MPR	
Frequency (MHz)				3494.91	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	19.10	19.24	18.91	20.5	0.0	

PC2 n77_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	Pl2 BPSK	1	1	21.53	21.52	21.58			
50	Pl2 BPSK	1	135	22.47	22.44	22.51	23.5	0.0	
50	Pl2 BPSK	1	268	21.56	21.69	21.59			
50	Pl2 BPSK	135	0	21.90	21.82	21.76	23.0	0.5	
50	Pl2 BPSK	135	68	22.53	22.38	22.42	23.5	0.0	
50	Pl2 BPSK	135	135	21.94	21.98	21.69	23.0	0.5	
50	Pl2 BPSK	270	0	21.97	21.82	21.74			
50	QPSK	1	1	21.59	21.53	21.58			
50	QPSK	1	135	22.38	22.66	22.38	23.5	0.0	
50	QPSK	1	268	21.57	21.51	21.51			
50	QPSK	135	0	21.06	21.24	21.28	22.5	1.0	
50	QPSK	135	68	22.28	22.46	22.21	23.5	0.0	
50	QPSK	135	135	21.35	21.35	21.42			
50	QPSK	270	0	21.20	21.24	21.18			
50	16QAM	1	1	20.96	21.21	20.90	22.5	1.0	
50	64QAM	1	1	19.83	20.61	19.91	21.0	2.5	
50	256QAM	1	1	18.27	18.17	18.24	19.0	4.5	
Channel				648000	656000	664000	Tune-up limit	MPR	
Frequency (MHz)				3720	3840	3960	(dBm)	(dB)	
40	QPSK	1	53	22.25	22.46	22.27	23.5	0.0	
Channel				647334	656000	664668	Tune-up limit	MPR	
Frequency (MHz)				3719.01	3840	3970.02	(dBm)	(dB)	
20	QPSK	1	26	22.21	22.47	22.27	23.5	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3840	3972.51	(dBm)	(dB)	
15	QPSK	1	19	22.33	22.56	22.18	23.5	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3705	3840	3975	(dBm)	(dB)	
10	QPSK	1	12	22.37	22.46	22.39	23.5	0.0	



Par27Q PC2 n77_Ant1 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000		
Frequency (MHz)				3475.02	3500.01	3525		
50	PI2 BPSK	1	1	21.61	21.59	21.68	23.5	0.0
50	PI2 BPSK	1	135	22.30	22.29	22.38		
50	PI2 BPSK	1	268	21.48	21.51	21.52		
50	PI2 BPSK	135	0	21.66	21.67	21.72	23.0	0.5
50	PI2 BPSK	135	68	22.26	22.28	22.27	23.5	0.0
50	PI2 BPSK	135	135	21.87	21.89	21.95	23.0	0.5
50	PI2 BPSK	270	0	21.71	21.75	21.76	23.5	0.0
50	QPSK	1	1	21.52	21.54	21.62		
50	QPSK	1	135	22.31	22.40	22.26		
50	QPSK	1	268	21.60	21.56	21.59	22.5	1.0
50	QPSK	135	0	21.24	21.28	21.27		
50	QPSK	135	68	22.16	22.27	22.06		
50	QPSK	135	135	21.21	21.18	21.24	22.5	1.0
50	QPSK	270	0	21.28	21.30	21.35		
50	16QAM	1	1	21.02	20.99	21.05	22.5	1.0
50	64QAM	1	1	19.95	19.90	19.87	21.0	2.5
50	256QAM	1	1	18.23	18.20	18.17	19.0	4.5
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)
40	QPSK	1	53	22.31	22.23	22.62	23.5	0.0
Channel				630668	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)
20	QPSK	1	26	22.30	22.29	22.06	23.5	0.0
Channel				635500	633334	631305	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)
15	QPSK	1	19	22.31	22.28	22.12	23.5	0.0
Channel				630334	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)
10	QPSK	1	12	22.29	22.29	22.06	23.5	0.0

PC3 n78_Ant1 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power			Tune-up limit (dBm)	MPR (dB)
				Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.		
Channel				648334	650000	651668		
Frequency (MHz)				3725.01	3750	3775.02		
50	PI2 BPSK	1	1	18.54	18.59	18.58	20.5	0.0
50	PI2 BPSK	1	135	19.32	19.43	19.38		
50	PI2 BPSK	1	268	18.60	18.61	18.63		
50	PI2 BPSK	135	0	19.17	19.35	19.35	20.5	0.0
50	PI2 BPSK	135	68	19.29	19.54	19.44	20.5	0.0
50	PI2 BPSK	135	135	19.34	19.59	19.21	20.5	0.0
50	PI2 BPSK	270	0	19.21	19.49	19.22		
50	QPSK	1	1	18.56	18.59	18.52		
50	QPSK	1	135	19.47	19.60	19.58	20.5	0.0
50	QPSK	1	268	18.59	18.65	18.55	20.5	0.0
50	QPSK	135	0	19.41	19.51	19.49		
50	QPSK	135	68	19.34	19.54	19.52		
50	QPSK	135	135	19.35	19.40	19.23	20.5	0.0
50	QPSK	270	0	19.27	19.28	19.23		
50	16QAM	1	1	19.10	19.22	19.22	20.5	0.0
50	64QAM	1	1	19.07	19.34	19.10	20.5	0.0
50	256QAM	1	1	18.16	18.12	18.04	19.0	1.5
Channel				648000	650000	652000	Tune-up limit	MPR
Frequency (MHz)				3720	3750	3780	(dBm)	(dB)
40	QPSK	1	53	19.73	19.72	19.74	20.5	0.0
Channel				647334	650000	652668	Tune-up limit	MPR
Frequency (MHz)				3710.01	3750	3760.02	(dBm)	(dB)
20	QPSK	1	26	19.68	19.66	19.70	20.5	0.0
Channel				647166	650000	652815	Tune-up limit	MPR
Frequency (MHz)				3707.52	3750	3762.51	(dBm)	(dB)
15	QPSK	1	19	19.70	19.73	19.68	20.5	0.0
Channel				647000	650000	653000	Tune-up limit	MPR
Frequency (MHz)				3705	3750	3765	(dBm)	(dB)
10	QPSK	1	12	19.67	19.69	19.64	20.5	0.0

Par27Q PC3 n78_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.		Power Middle Ch. / Freq.		Power High Ch. / Freq.	
				631668	633334	635334	636000	635000	3525
Channel				3475.02	3500.01	3500.01	3525	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3475.02	3500.01	3500.01	3525		
50	PI2 BPSK	1	1	18.52	18.51	18.61		20.5	0.0
50	PI2 BPSK	1	135	19.32	19.07	19.34			
50	PI2 BPSK	1	268	18.56	18.58	18.53			
50	PI2 BPSK	135	0	19.40	19.32	19.20	20.5	0.0	
50	PI2 BPSK	135	68	19.06	19.27	19.33	20.5	0.0	
50	PI2 BPSK	135	135	19.28	19.09	19.29	20.5	0.0	
50	PI2 BPSK	270	0	19.26	19.02	19.29	20.5	0.0	
50	QPSK	1	1	18.59	18.51	18.60		20.5	0.0
50	QPSK	1	135	19.29	18.63	19.10			
50	QPSK	1	268	18.50	18.61	18.60			
50	QPSK	135	0	19.07	19.08	19.02	20.5	0.0	
50	QPSK	135	68	19.11	19.26	19.17	20.5	0.0	
50	QPSK	135	135	19.17	19.13	19.06	20.5	0.0	
50	QPSK	270	0	18.68	18.06	18.82	20.5	0.0	
50	16QAM	1	1	19.18	18.99	19.09	20.5	0.0	
50	64QAM	1	1	19.19	19.06	19.08	20.5	0.0	
50	256QAM	1	1	17.98	18.11	18.16	19.0	1.5	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)	
40	QPSK	1	53	19.24	19.22	19.28	20.5	0.0	
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	19.17	19.29	19.30	20.5	0.0	
Channel				635500	633334	631305	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	19.13	19.23	19.22	20.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	19.16	19.27	19.23	20.5	0.0	

PC2 n78_Ant1 DSI1&2 Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	MPR (dB)
Channel				648334	650000	651666	
Frequency (MHz)				3725.01	3750	3775.02	
50	Pl2 BPSK	1	1	21.53	21.54	21.52	
50	Pl2 BPSK	1	135	22.44	22.53	22.48	23.5
50	Pl2 BPSK	1	268	21.55	21.80	21.55	
50	Pl2 BPSK	135	0	21.91	21.98	21.76	23.0
50	Pl2 BPSK	135	68	22.53	22.54	22.42	23.5
50	Pl2 BPSK	135	135	21.94	21.98	21.88	
50	Pl2 BPSK	270	0	21.93	21.99	21.72	23.0
50	QPSK	1	1	21.57	21.56	21.54	
50	QPSK	1	135	22.38	22.55	22.37	23.5
50	QPSK	1	268	21.57	21.80	21.51	
50	QPSK	135	0	21.04	21.50	21.27	22.5
50	QPSK	135	68	22.27	22.51	22.21	23.5
50	QPSK	135	135	21.34	21.57	21.38	
50	QPSK	270	0	21.17	21.60	21.18	22.5
50	16QAM	1	1	20.92	21.41	20.89	22.5
50	16QAM	1	1	19.80	20.05	19.88	21.0
50	256QAM	1	1	18.25	18.20	18.20	19.0
Channel				648000	650000	650000	Tune-up limit
Frequency (MHz)				3720	3750	3780	MPR (dB)
40	QPSK	1	53	22.59	22.29	22.27	23.5
Channel				647334	650000	650666	Tune-up limit
Frequency (MHz)				3710.01	3750	3790.02	MPR (dB)
20	QPSK	1	26	22.32	22.33	22.16	23.5
Channel				647100	650000	650350	Tune-up limit
Frequency (MHz)				3707.52	3750	3792.51	MPR (dB)
15	QPSK	1	19	22.35	22.27	22.27	23.5
Channel				647000	650000	650000	Tune-up limit
Frequency (MHz)				3705	3750	3795	MPR (dB)
10	QPSK	1	12	22.40	22.35	22.17	23.5

Par27Q PC2 n78_Ant1 DSI1&2 Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	MPR (dB)
Channel				631668	633334	635000	
Frequency (MHz)				3475.02	3500.01	3525	
50	Pl2 BPSK	1	1	21.54	21.53	21.59	
50	Pl2 BPSK	1	135	22.25	22.36	22.30	23.5
50	Pl2 BPSK	1	268	21.53	21.55	21.56	
50	Pl2 BPSK	135	0	21.67	22.07	21.81	23.0
50	Pl2 BPSK	135	68	22.28	21.99	22.23	23.5
50	Pl2 BPSK	135	135	21.87	21.42	21.84	
50	Pl2 BPSK	270	0	21.74	21.53	21.72	23.0
50	QPSK	1	1	21.50	21.53	21.56	
50	QPSK	1	135	22.37	22.38	22.30	23.5
50	QPSK	1	268	21.53	21.80	21.55	
50	QPSK	135	0	21.24	21.28	21.21	22.5
50	QPSK	135	68	22.21	22.07	22.13	23.5
50	QPSK	135	135	21.16	21.53	21.19	
50	QPSK	270	0	21.35	21.58	21.26	22.5
50	16QAM	1	1	20.99	21.58	21.01	22.5
50	16QAM	1	1	19.86	19.41	19.82	21.0
50	256QAM	1	1	18.15	18.06	18.23	19.0
Channel				631334	633334	635332	Tune-up limit
Frequency (MHz)				3470.01	3500.01	3528.98	MPR (dB)
40	QPSK	1	53	22.29	22.25	21.88	23.5
Channel				630668	633334	636000	Tune-up limit
Frequency (MHz)				3460.02	3500.01	3540	MPR (dB)
20	QPSK	1	26	22.14	22.25	22.28	23.5
Channel				630100	633334	636100	Tune-up limit
Frequency (MHz)				3457.5	3500.01	3542.49	MPR (dB)
15	QPSK	1	19	22.27	22.28	22.29	23.5
Channel				630334	633334	636332	Tune-up limit
Frequency (MHz)				3455.01	3500.01	3544.98	MPR (dB)
10	QPSK	1	12	22.24	22.38	21.92	23.5

n7_Ant2 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	22.95	22.97	23.01	24.5	0.0	
20	PI/2 BPSK	1	53	22.94	23.06	22.97			
20	PI/2 BPSK	1	104	22.94	23.02	23.02			
20	PI/2 BPSK	50	0	22.53	22.67	22.44	24.0	0.5	
20	PI/2 BPSK	50	28	23.03	22.99	23.00	24.5	0.0	
20	PI/2 BPSK	50	56	22.43	22.65	22.35	24.0	0.5	
20	PI/2 BPSK	100	0	22.46	22.67	22.70			
20	QPSK	1	1	22.86	23.20	22.90			
20	QPSK	1	53	22.97	23.22	23.12	24.5	0.0	
20	QPSK	1	104	23.05	22.94	22.87			
20	QPSK	50	0	21.96	22.08	22.01		23.5	
20	QPSK	50	28	22.92	23.11	22.95	24.5	0.0	
20	QPSK	50	56	22.08	22.05	22.04	23.5	1.0	
20	QPSK	100	0	21.87	21.89	21.84			
20	16QAM	1	1	21.93	22.03	22.02		23.5	
20	64QAM	1	1	20.47	20.77	20.63	22.0	2.5	
20	256QAM	1	1	18.71	18.84	18.82	20.0	4.5	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	22.85	23.15	23.01	24.5	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	22.89	23.09	22.99	24.5	0.0	
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	22.88	23.09	23.01	24.5	0.0	

n66_Ant2 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346000	349000	352000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	PI/2 BPSK	1	1	22.63	22.89	22.88	24.5	0.0	
40	PI/2 BPSK	1	108	23.18	23.01	22.91			
40	PI/2 BPSK	1	214	22.65	22.88	22.86			
40	PI/2 BPSK	108	0	22.19	22.29	22.01	24.0	0.5	
40	PI/2 BPSK	108	54	22.82	23.03	22.72	24.5	0.0	
40	PI/2 BPSK	108	108	22.25	22.25	22.12	24.0	0.5	
40	PI/2 BPSK	216	0	22.41	22.36	22.17			
40	QPSK	1	1	22.85	22.88	22.75			
40	QPSK	1	108	23.06	23.21	23.08	24.5	0.0	
40	QPSK	1	214	22.72	22.80	22.83			
40	QPSK	108	0	21.74	21.93	21.97		23.5	
40	QPSK	108	54	22.76	22.86	22.85	24.5	0.0	
40	QPSK	108	108	21.80	21.74	21.86	23.5	1.0	
40	QPSK	216	0	21.63	21.78	21.70			
40	16QAM	1	1	21.80	21.90	21.84		23.5	
40	64QAM	1	1	20.53	20.29	20.16	22.0	2.5	
40	256QAM	1	1	18.32	18.23	18.25	20.0	4.5	
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	PI/2 BPSK	1	80	22.91	23.13	22.86	24.5	0.0	
Channel				344500	349000	353500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	PI/2 BPSK	1	67	22.92	23.13	23.02	24.5	0.0	
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	53	22.93	23.05	22.95	24.5	0.0	
Channel				343500	349000	354500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	40	22.96	23.12	22.95	24.5	0.0	
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	26	22.92	23.10	22.93	24.5	0.0	
Channel				342500	349000	355500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	13	22.91	23.11	22.96	24.5	0.0	

n38_Ant2 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	519000	519996	24.0	0.0
Frequency (MHz)				2590.02	2595	2599.98		
40	PI/2 BPSK	1	1	23.21	23.33	23.15		
40	PI/2 BPSK	1	53	23.63	23.73	23.72		
40	PI/2 BPSK	1	104	23.29	23.30	23.39	23.5	0.5
40	PI/2 BPSK	50	0	23.10	23.16	22.97		
40	PI/2 BPSK	50	28	23.48	23.52	23.56	24.0	0.0
40	PI/2 BPSK	50	56	22.90	22.99	22.84	23.5	0.5
40	PI/2 BPSK	100	0	23.06	22.91	22.84		
40	QPSK	1	1	23.34	23.40	23.41	24.0	0.0
40	QPSK	1	53	23.75	23.86	23.82		
40	QPSK	1	104	23.26	23.30	23.18	23.0	1.0
40	QPSK	50	0	22.49	22.33	22.43		
40	QPSK	50	28	23.23	23.31	23.23	24.0	0.0
40	QPSK	50	56	22.44	22.53	22.45	23.0	1.0
40	QPSK	100	0	22.25	22.30	22.27		
40	16QAM	1	1	22.34	22.46	22.17	23.0	1.0
40	64QAM	1	1	20.92	20.95	20.93	21.5	2.5
40	256QAM	1	1	19.08	19.14	18.87	19.5	4.5
Channel				516000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2595	2610	24.0	0.0
20	QPSK	1	53	23.60	23.85	23.67		
Channel				515502	519000	522498	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49	24.0	0.0
15	QPSK	1	40	23.58	23.66	23.64		
Channel				515004	519000	522596	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2575.02	2595	2614.98	24.0	0.0
10	QPSK	1	26	23.85	23.72	23.70		
Channel				514506	519000	523494	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2572.53	2595	2617.47	24.0	0.0
5	QPSK	1	13	23.61	23.63	23.70		

PC2 n41_Ant2 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				504204	518598	532998	25.0	0.0
Frequency (MHz)				2521.02	2592.99	2664.99		
50	PI/2 BPSK	1	1	23.10	23.12	23.29		
50	PI/2 BPSK	1	135	23.55	23.48	23.63		
50	PI/2 BPSK	1	268	23.52	23.45	23.32	24.5	0.5
50	PI/2 BPSK	135	0	23.49	23.57	23.67		
50	PI/2 BPSK	135	68	23.66	23.57	23.60	25.0	0.0
50	PI/2 BPSK	135	135	23.85	23.80	23.82	24.5	0.5
50	PI/2 BPSK	270	0	23.56	23.59	23.71		
50	QPSK	1	1	23.45	23.51	23.42	25.0	0.0
50	QPSK	1	135	23.96	24.11	23.75		
50	QPSK	1	268	23.60	23.55	23.60	25.0	0.0
50	QPSK	135	0	23.76	23.77	23.76		
50	QPSK	135	68	23.74	23.88	23.74	25.0	0.0
50	QPSK	135	135	23.68	23.71	23.84	25.0	0.0
50	QPSK	270	0	23.56	23.72	23.58		
50	16QAM	1	1	23.28	23.23	23.16	24.0	1.0
50	64QAM	1	1	22.33	22.16	22.32	22.5	2.5
50	256QAM	1	1	20.25	20.16	20.21	20.5	4.5
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670	25.0	0.0
40	PI/2 BPSK	1	108	23.86	23.99	23.64		
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98	25.0	0.0
30	PI/2 BPSK	1	80	23.96	23.93	23.67		
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99	25.0	0.0
20	QPSK	1	53	23.85	23.84	23.58		
Channel				500700	518598	536496	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48	25.0	0.0
15	QPSK	1	40	23.90	24.01	23.65		
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685	25.0	0.0
10	QPSK	1	26	23.84	23.89	23.63		



PC3 n77_Ant3 DSI1&2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	Pl2 BPSK	1	1	20.84	20.78	20.68			
50	Pl2 BPSK	1	135	21.90	21.81	21.59	22.5		
50	Pl2 BPSK	1	268	20.56	20.81	20.78			
50	Pl2 BPSK	135	0	21.84	21.72	21.72	22.5	0.0	
50	Pl2 BPSK	135	68	21.05	21.61	21.65	22.5	0.0	
50	Pl2 BPSK	135	135	21.47	21.81	21.79	22.5	0.0	
50	Pl2 BPSK	270	0	21.88	21.77	21.92			
50	QPSK	1	1	20.75	20.72	20.79			
50	QPSK	1	135	21.78	21.98	21.84	22.5	0.0	
50	QPSK	1	268	20.81	20.78	20.67			
50	QPSK	135	0	21.88	21.84	21.51	22.5	0.0	
50	QPSK	135	68	21.80	21.87	21.53	22.5	0.0	
50	QPSK	135	135	21.70	21.79	21.67	22.5	0.0	
50	QPSK	270	0	21.86	21.71	21.67			
50	16QAM	1	1	21.44	21.53	21.73	22.5	0.0	
50	64QAM	1	1	21.89	21.82	21.58	22.5	0.0	
50	256QAM	1	1	19.98	19.97	19.93	21.0	1.5	
Channel				648000	656000	664000	Tune-up limit	MPR	
Frequency (MHz)				3720	3840	3960	(dBm)	(dB)	
40	QPSK	1	53	21.25	21.57	21.44	22.5	0.0	
Channel				647334	656000	664668	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3840	3970.02	(dBm)	(dB)	
20	QPSK	1	26	21.47	21.49	21.34	22.5	0.0	
Channel				647105	656000	664331	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3840	3972.51	(dBm)	(dB)	
15	QPSK	1	19	21.49	21.44	21.54	22.5	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3705	3840	3975	(dBm)	(dB)	
10	QPSK	1	12	21.39	21.58	21.51	22.5	0.0	

Par27Q PC3 n77_Ant3 DSI1&2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	Pl2 BPSK	1	1	20.84	20.89	20.73			
50	Pl2 BPSK	1	135	21.92	21.89	21.81	22.5	0.0	
50	Pl2 BPSK	1	268	20.81	20.82	20.79			
50	Pl2 BPSK	135	0	21.71	21.77	21.73	22.5	0.0	
50	Pl2 BPSK	135	68	21.71	21.69	21.71	22.5	0.0	
50	Pl2 BPSK	135	135	21.56	21.88	21.83	22.5	0.0	
50	Pl2 BPSK	270	0	21.94	21.79	22.02			
50	QPSK	1	1	20.82	20.73	20.81			
50	QPSK	1	135	21.97	22.08	21.92	22.5	0.0	
50	QPSK	1	268	20.85	20.98	20.73			
50	QPSK	135	0	21.74	21.90	21.80	22.5	0.0	
50	QPSK	135	68	21.87	21.86	21.54	22.5	0.0	
50	QPSK	135	135	21.78	21.79	21.74	22.5	0.0	
50	QPSK	270	0	21.88	21.78	21.67			
50	16QAM	1	1	21.47	21.56	21.81	22.5	0.0	
50	64QAM	1	1	21.73	21.68	21.58	22.5	0.0	
50	256QAM	1	1	19.93	19.97	19.95	21.0	1.5	
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3525.98	(dBm)	(dB)	
40	QPSK	1	53	21.07	21.20	21.14	22.5	0.0	
Channel				630668	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	21.01	21.22	21.19	22.5	0.0	
Channel				630333	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3497.5	3500.01	3542.48	(dBm)	(dB)	
15	QPSK	1	19	21.11	21.20	21.17	22.5	0.0	
Channel				630333	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3495.01	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	21.12	21.21	21.18	22.5	0.0	

PC2 n77_Ant3 DSI1 For SA / DSI2 For SA&NSA Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	Pl2 BPSK	1	1	21.53	21.52	21.51			
50	Pl2 BPSK	1	135	24.00	24.11	24.02	25.5	0.0	
50	Pl2 BPSK	1	268	23.50	23.51	23.55			
50	Pl2 BPSK	135	0	23.90	23.94	23.94	25.0	0.5	
50	Pl2 BPSK	135	68	24.17	24.37	24.35	25.5	0.0	
50	Pl2 BPSK	135	135	23.99	24.09	23.88	25.0	0.5	
50	Pl2 BPSK	270	0	23.83	24.07	23.89			
50	QPSK	1	1	23.58	23.50	23.53			
50	QPSK	1	135	24.33	24.45	24.31	25.5	0.0	
50	QPSK	1	268	23.51	23.58	23.55			
50	QPSK	135	0	23.55	23.45	23.38	24.5	1.0	
50	QPSK	135	68	24.21	24.40	24.24	25.5	0.0	
50	QPSK	135	135	23.25	23.47	23.28	24.5	1.0	
50	QPSK	270	0	23.43	23.58	23.38			
50	16QAM	1	1	23.40	23.42	23.42	24.5	1.0	
50	64QAM	1	1	22.03	21.81	21.76	23.0	2.5	
50	256QAM	1	1	19.92	20.01	19.99	21.0	4.5	
Channel				648000	656000	664000	Tune-up limit	MPR	
Frequency (MHz)				3720	3840	3960	(dBm)	(dB)	
40	QPSK	1	53	24.17	24.39	24.29	25.5	0.0	
Channel				647334	656000	664668	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3840	3970.02	(dBm)	(dB)	
20	QPSK	1	26	24.21	24.46	24.22	25.5	0.0	
Channel				647105	656000	664331	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3840	3972.51	(dBm)	(dB)	
15	QPSK	1	19	24.21	24.32	24.17	25.5	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3705	3840	3975	(dBm)	(dB)	
10	QPSK	1	12	24.28	24.40	24.21	25.5	0.0	



Par27Q PC2 n77_Ant3 DSI1 For SA / DSI2 For SA&NSA Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power			Tune-up limit (dBm)	MPR (dB)	
				Low Ch. / Freq.	Middle Ch. / Freq.	High Ch. / Freq.			
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	PI2 BPSK	1	1	23.57	23.69	23.54	25.5	0.0	
50	PI2 BPSK	1	135	23.81	23.92	23.87			
50	PI2 BPSK	1	268	23.50	23.58	23.53			
50	PI2 BPSK	135	0	23.82	23.95	23.90	25.0	0.5	
50	PI2 BPSK	135	68	24.34	24.43	24.33	25.5	0.0	
50	PI2 BPSK	135	135	23.85	23.99	23.88	25.0	0.5	
50	PI2 BPSK	270	0	23.76	23.87	23.76			
50	QPSK	1	1	23.56	23.70	23.61			
50	QPSK	1	135	23.47	23.54	23.47	25.5	0.0	
50	QPSK	1	268	23.51	23.60	23.58	24.5	1.0	
50	QPSK	135	0	23.31	23.42	23.29			
50	QPSK	135	68	24.12	24.27	24.19			
50	QPSK	135	135	23.08	23.19	23.13	24.5	1.0	
50	QPSK	270	0	23.39	23.53	23.45			
50	16QAM	1	1	23.17	23.31	23.19	24.5	1.0	
50	64QAM	1	1	21.66	21.76	21.63	23.0	2.5	
50	256QAM	1	1	19.82	19.95	19.88	21.0	4.5	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)	
40	QPSK	1	53	24.24	24.37	24.18	25.5	0.0	
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	24.32	24.37	24.29	25.5	0.0	
Channel				635540	633334	631332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	24.33	24.33	24.20	25.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	24.29	24.31	24.30	25.5	0.0	

PC3 n78_Ant3 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power			Tune-up limit (dBm)	MPR (dB)	
				Low Ch. / Freq.	Middle Ch. / Freq.	Power High Ch. / Freq.			
Channel				648334	650000	651668			
Frequency (MHz)				3725.01	3750	3775.02			
50	PI2 BPSK	1	1	20.53	20.69	20.58	22.5	0.0	
50	PI2 BPSK	1	135	21.59	21.69	21.60			
50	PI2 BPSK	1	268	20.84	20.94	20.88			
50	PI2 BPSK	135	0	21.58	21.64	21.55	22.5	0.0	
50	PI2 BPSK	135	68	21.69	21.80	21.72	22.5	0.0	
50	PI2 BPSK	135	135	21.64	21.73	21.64	22.5	0.0	
50	PI2 BPSK	270	0	21.53	21.66	21.54			
50	QPSK	1	1	20.54	20.66	20.54			
50	QPSK	1	135	21.81	21.91	21.85	22.5	0.0	
50	QPSK	1	268	20.71	20.84	20.77	22.5	0.0	
50	QPSK	135	0	21.41	21.48	21.46			
50	QPSK	135	68	21.49	21.55	21.51			
50	QPSK	135	135	21.37	21.49	21.37	22.5	0.0	
50	QPSK	270	0	21.43	21.51	21.44	22.5	0.0	
50	16QAM	1	1	21.55	21.68	21.58			
50	64QAM	1	1	21.51	21.59	21.55			
50	256QAM	1	1	19.83	19.92	19.82	21.0	1.5	
Channel				648000	650000	652000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3750	3780	(dBm)	(dB)	
40	QPSK	1	53	21.50	21.63	21.47	22.5	0.0	
Channel				647334	650000	652668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3750	3790.02	(dBm)	(dB)	
20	QPSK	1	26	21.48	21.47	21.60	22.5	0.0	
Channel				647166	650000	652819	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3750	3792.51	(dBm)	(dB)	
15	QPSK	1	19	21.51	21.64	21.61	22.5	0.0	
Channel				647000	650000	653000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)	
10	QPSK	1	12	21.39	21.63	21.56	22.5	0.0	

Par27Q PC3 n78_Ant3 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.		Power Middle Ch. / Freq.		Power High Ch. / Freq.	
				631668	633334	635334	636000	638000	
Channel				3475.02	3500.01	3525	Tune-up limit (dBm)		MPR (dB)
Frequency (MHz)				3475.02	3500.01	3525			
50	PI2 BPSK	1	1	20.86	20.90	20.90	20.71	22.5	0.0
50	PI2 BPSK	1	135	21.91	21.87	21.59			
50	PI2 BPSK	1	268	20.64	20.86	20.83			
50	PI2 BPSK	135	0	21.71	21.75	21.78	22.5	0.0	
50	PI2 BPSK	135	68	21.75	21.70	21.71	22.5	0.0	
50	PI2 BPSK	135	135	21.53	21.86	21.81	22.5	0.0	
50	PI2 BPSK	270	0	21.91	21.78	22.08			
50	QPSK	1	1	20.85	20.78	20.88			
50	QPSK	1	135	21.50	22.07	21.89	22.5	0.0	
50	QPSK	1	268	20.50	20.53	20.78			
50	QPSK	135	0	21.74	21.90	21.60	22.5	0.0	
50	QPSK	135	68	21.69	21.86	21.61	22.5	0.0	
50	QPSK	135	135	21.84	21.86	21.72	22.5	0.0	
50	QPSK	270	0	21.74	21.83	21.71			
50	16QAM	1	1	21.51	21.55	21.83	22.5	0.0	
50	64QAM	1	1	21.76	21.67	21.98	22.5	0.0	
50	256QAM	1	1	19.85	19.69	19.89	21.0	1.5	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)	
40	QPSK	1	53	21.52	21.50	21.48	22.5	0.0	
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	21.40	21.53	21.52	22.5	0.0	
Channel				635540	633334	631332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	21.43	21.57	21.29	22.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	21.42	21.62	21.36	22.5	0.0	

PC2 n78_Ant3 DSI1 For SA / DSI2 For SA&NSA							
Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq	Power Middle Ch. / Freq	Power High Ch. / Freq	MPR (dB)
Channel				648334	650000	651666	
Frequency (MHz)				3725.01	3750	3775.02	
50	Pl2 BPSK	1	1	23.55	23.55	23.55	25.5
50	Pl2 BPSK	1	135	23.97	24.12	24.08	
50	Pl2 BPSK	1	268	23.55	23.51	23.60	
50	Pl2 BPSK	135	0	23.95	24.01	23.97	25.0
50	Pl2 BPSK	135	68	24.16	24.38	24.38	25.5
50	Pl2 BPSK	135	135	24.03	24.08	23.89	25.0
50	Pl2 BPSK	270	0	23.89	24.09	23.88	25.0
50	QPSK	1	1	23.60	23.52	23.50	25.5
50	QPSK	1	135	24.36	24.42	24.36	
50	QPSK	1	268	23.53	23.58	23.56	
50	QPSK	135	0	23.55	23.48	23.37	24.5
50	QPSK	135	68	24.23	24.41	24.23	25.5
50	QPSK	135	135	23.25	23.46	23.25	24.5
50	QPSK	270	0	23.45	23.65	23.37	24.5
50	16QAM	1	1	23.44	23.42	23.47	24.5
50	16QAM	1	1	22.10	21.80	21.62	23.0
50	256QAM	1	1	19.90	20.03	19.88	21.0
Channel				648000	650000	650000	Tune-up limit
Frequency (MHz)				3720	3750	3780	MPR (dB)
40	QPSK	1	53	24.59	24.40	24.40	25.5
Channel				547334	550000	552666	Tune-up limit
Frequency (MHz)				3710.01	3750	3790.02	MPR (dB)
20	QPSK	1	26	24.20	24.40	24.20	25.5
Channel				547103	550000	552900	Tune-up limit
Frequency (MHz)				3707.52	3750	3792.51	MPR (dB)
15	QPSK	1	19	24.30	24.41	24.39	25.5
Channel				647000	650000	653000	Tune-up limit
Frequency (MHz)				3705	3750	3795	MPR (dB)
10	QPSK	1	12	24.23	24.41	24.19	25.5

Par27Q PC2 n78_Ant3 DSI1 For SA&DSI2 For SA&ENDC Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq	Power Middle Ch. / Freq	Power High Ch. / Freq	MPR (dB)
Channel				631668	633334	635000	
Frequency (MHz)				3475.02	3500.01	3525	
50	Pl2 BPSK	1	1	23.03	23.71	23.58	25.5
50	Pl2 BPSK	1	135	23.76	23.97	23.85	
50	Pl2 BPSK	1	268	23.54	23.63	23.52	
50	Pl2 BPSK	135	0	23.87	24.00	23.97	25.0
50	Pl2 BPSK	135	68	24.35	24.48	24.37	25.5
50	Pl2 BPSK	135	135	23.84	24.01	23.93	25.0
50	Pl2 BPSK	270	0	23.82	23.91	23.83	25.0
50	QPSK	1	1	23.57	23.70	23.62	25.5
50	QPSK	1	135	24.51	24.50	24.47	
50	QPSK	1	268	23.48	23.65	23.56	
50	QPSK	135	0	23.35	23.43	23.29	24.5
50	QPSK	135	68	24.15	24.27	24.21	25.5
50	QPSK	135	135	23.10	23.17	23.13	24.5
50	QPSK	270	0	23.37	23.52	23.50	24.5
50	16QAM	1	1	23.22	23.35	23.25	24.5
50	16QAM	1	1	21.74	21.74	21.60	23.0
50	256QAM	1	1	19.86	19.94	19.88	21.0
Channel				631334	633334	635332	Tune-up limit
Frequency (MHz)				3470.01	3500.01	3528.98	MPR (dB)
40	QPSK	1	53	24.39	24.54	24.42	25.5
Channel				630668	633334	636000	Tune-up limit
Frequency (MHz)				3460.02	3500.01	3540	MPR (dB)
20	QPSK	1	26	24.21	24.39	24.19	25.5
Channel				630103	633334	636166	Tune-up limit
Frequency (MHz)				3457.5	3500.01	3542.49	MPR (dB)
15	QPSK	1	19	24.33	24.29	24.26	25.5
Channel				630334	633334	636332	Tune-up limit
Frequency (MHz)				3455.01	3500.01	3544.98	MPR (dB)
10	QPSK	1	12	24.19	24.25	24.43	25.5



n5_Ant4 DSI1&2&4 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				168300	167300	167600	24.0	0.0
Frequency (MHz)				834	836.5	839		
20	PI2 BPSK	1	1	22.77	22.75	22.57		
20	PI2 BPSK	1	53	22.71	22.72	22.79		
20	PI2 BPSK	1	104	22.52	22.74	22.57	23.5	0.5
20	PI2 BPSK	50	0	22.30	22.20	22.33	24.0	0.0
20	PI2 BPSK	50	28	22.80	22.65	22.62	24.0	0.0
20	PI2 BPSK	50	56	22.23	22.17	22.28	23.5	0.5
20	PI2 BPSK	100	0	22.27	22.16	22.36		
20	QPSK	1	1	22.75	22.79	22.85	24.0	0.0
20	QPSK	1	53	22.70	22.87	22.82		
20	QPSK	1	104	22.63	22.64	22.67		
20	QPSK	50	0	21.51	21.82	21.51	23.0	1.0
20	QPSK	50	28	22.66	22.76	22.74	24.0	0.0
20	QPSK	50	56	21.68	21.69	21.69	23.0	1.0
20	QPSK	100	0	21.72	21.79	21.74	23.0	1.0
20	16QAM	1	1	21.59	21.63	21.70		
20	64QAM	1	1	20.35	20.31	20.23		
20	256QAM	1	1	18.21	18.37	18.23		
Channel				168300	167300	168300	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				831.5	836.5	841.5	24.0	0.0
15	QPSK	1	40	22.57	22.85	22.77	24.0	0.0
Channel				165300	167300	165300	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				829	836.5	844	24.0	0.0
10	QPSK	1	26	22.62	22.67	22.63	24.0	0.0
Channel				165300	167300	169300	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				841.5	836.5	844.5	24.0	0.0
5	QPSK	1	13	22.58	22.63	22.55	24.0	0.0

n7_Ant4 DSI2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				502000	507000	512000	24.0	0.0
Frequency (MHz)				2510	2535	2560		
20	PI2 BPSK	1	1	22.77	22.83	22.53		
20	PI2 BPSK	1	53	22.71	22.82	22.78		
20	PI2 BPSK	1	104	22.71	22.78	22.57	23.5	0.5
20	PI2 BPSK	50	0	22.27	22.36	22.33	24.0	0.0
20	PI2 BPSK	50	28	22.67	22.65	22.73	24.0	0.0
20	PI2 BPSK	50	56	22.27	22.15	22.19	23.5	0.5
20	PI2 BPSK	100	0	22.16	22.35	22.11		
20	QPSK	1	1	22.70	22.86	22.58	24.0	0.0
20	QPSK	1	53	22.58	22.87	22.81		
20	QPSK	1	104	22.63	22.63	22.68		
20	QPSK	50	0	21.64	21.63	21.64	23.0	1.0
20	QPSK	50	28	22.63	22.68	22.61	24.0	0.0
20	QPSK	50	56	21.69	21.74	21.74	23.0	1.0
20	QPSK	100	0	21.56	21.74	21.66	23.0	1.0
20	16QAM	1	1	21.71	21.78	21.79		
20	64QAM	1	1	20.36	20.24	20.08		
20	256QAM	1	1	18.14	18.28	18.05		
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	24.0	0.0
15	QPSK	1	40	22.50	22.70	22.77	24.0	0.0
Channel				511000	512000	513500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565	24.0	0.0
10	QPSK	1	26	22.52	22.77	22.80	24.0	0.0
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2502.5	2535	2567.5	24.0	0.0
5	QPSK	1	13	22.43	22.64	22.58	24.0	0.0

n66_Ant4 DSI2&4 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				346000	349000	353000	24.0	0.0
Frequency (MHz)				1730	1745	1760		
40	PI2 BPSK	1	1	22.39	22.46	22.40		
40	PI2 BPSK	1	108	22.51	22.60	22.41		
40	PI2 BPSK	1	214	22.36	22.49	22.50	23.5	0.5
40	PI2 BPSK	108	0	21.76	21.87	22.00	23.5	0.5
40	PI2 BPSK	108	54	22.40	22.35	22.37	24.0	0.0
40	PI2 BPSK	108	108	21.66	21.88	21.72	23.5	0.5
40	PI2 BPSK	216	0	21.89	21.80	21.86	24.0	0.0
40	QPSK	1	1	22.38	22.58	22.34		
40	QPSK	1	108	22.26	22.62	22.42		
40	QPSK	1	214	22.25	22.42	22.39		
40	QPSK	108	0	21.48	21.50	21.48	23.0	1.0
40	QPSK	108	54	22.35	22.48	22.35	24.0	0.0
40	QPSK	108	108	21.31	21.39	21.24	23.0	1.0
40	QPSK	216	0	21.24	21.39	21.28	23.0	1.0
40	16QAM	1	1	21.22	21.39	21.50		
40	64QAM	1	1	19.85	19.98	19.91		
40	256QAM	1	1	17.95	17.92	17.84		
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1725	1745	1765	24.0	0.0
30	PI2 BPSK	1	80	22.10	22.56	22.40	24.0	0.0
Channel				345000	349000	353500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1722.5	1745	1767.5	24.0	0.0
25	PI2 BPSK	1	67	22.14	22.61	22.38	24.0	0.0
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1720	1745	1770	24.0	0.0
20	QPSK	1	53	22.13	22.49	22.36	24.0	0.0
Channel				343000	349000	354500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1717.5	1745	1772.5	24.0	0.0
15	QPSK	1	40	22.19	22.46	22.37	24.0	0.0
Channel				342000	349000	355000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1715	1745	1775	24.0	0.0
10	QPSK	1	26	22.22	22.48	22.26	24.0	0.0
Channel				342500	349000	355500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1712.5	1745	1777.5	24.0	0.0
5	QPSK	1	13	22.25	22.43	22.15	24.0	0.0



n38_Ant4 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (dB)	
Channel				518004	518000	518996			
Frequency (MHz)				2580.02	2595	2599.98			
40	PQ2 BPSK	1	1	23.64	23.52	23.59		25.5	0.0
40	PQ2 BPSK	1	53	23.97	23.96	24.04			
40	PQ2 BPSK	1	104	23.51	23.57	23.51			
40	PQ2 BPSK	50	0	23.18	23.12	23.14		25.0	0.5
40	PQ2 BPSK	50	28	23.58	23.55	23.55		25.5	0.0
40	PQ2 BPSK	50	56	23.28	23.08	23.17		25.0	0.5
40	PQ2 BPSK	100	0	23.02	23.18	23.10			
40	QPSK	1	1	23.53	23.85	23.54			
40	QPSK	1	53	23.94	24.12	23.87		25.5	0.0
40	QPSK	1	104	23.61	23.53	23.54		24.5	1.0
40	QPSK	50	0	22.51	22.61	22.52			
40	QPSK	50	28	23.61	23.64	23.55			
40	QPSK	50	56	22.51	22.55	22.67		24.5	1.0
40	QPSK	100	0	22.53	22.55	22.51		24.5	1.0
40	16QAM	1	1	22.76	22.73	22.77			
40	64QAM	1	1	21.05	21.19	21.31			
40	256QAM	1	1	19.01	19.14	19.06		21.0	4.5
Channel				518000	519000	522000	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	53	23.88	23.96	23.76		25.5	0.0
Channel				518002	519200	522400	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	40	23.93	24.00	23.77		25.5	0.0
Channel				518004	519000	522996	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2581.02	2595	2614.98			
10	QPSK	1	28	23.75	24.01	23.70		25.5	0.0
Channel				518506	519000	523494	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2572.53	2595	2617.47			
5	QPSK	1	13	23.73	24.05	23.65		25.5	0.0

PC3 n41_Ant4 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (dB)	
Channel				500204	518598	532098			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	PQ2 BPSK	1	1	22.64	22.70	22.84		24.0	0.0
50	PQ2 BPSK	1	135	22.74	22.83	22.76			
50	PQ2 BPSK	1	268	22.74	22.75	22.87			
50	PQ2 BPSK	135	0	22.76	22.78	22.90		23.5	0.5
50	PQ2 BPSK	135	68	23.13	23.02	23.00		24.0	0.0
50	PQ2 BPSK	135	135	22.94	22.94	23.04		23.5	0.5
50	PQ2 BPSK	270	0	22.76	22.99	22.85			
50	QPSK	1	1	22.81	23.94	23.98			
50	QPSK	1	135	23.27	23.43	23.27		24.0	0.0
50	QPSK	1	268	22.22	22.20	22.17		24.0	0.0
50	QPSK	135	0	22.81	22.82	22.87			
50	QPSK	135	68	22.69	22.95	22.91			
50	QPSK	135	135	22.90	22.71	22.59		24.0	0.0
50	QPSK	270	0	22.76	22.95	22.78		24.0	0.0
50	16QAM	1	1	22.07	22.03	22.05			
50	64QAM	1	1	22.48	22.50	22.40			
50	256QAM	1	1	21.53	21.59	21.48		19.5	4.5
Channel				503202	518598	534000	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	PQ2 BPSK	1	108	23.17	23.32	23.12		24.0	0.0
Channel				502202	511598	531598	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	PQ2 BPSK	1	80	23.11	23.38	23.25		24.0	0.0
Channel				501204	518598	535998	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2508.02	2592.99	2679.99			
20	QPSK	1	53	23.11	23.43	23.20		24.0	0.0
Channel				500700	518598	536498	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	40	23.06	23.23	23.21		24.0	0.0
Channel				500202	511598	537000	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	26	23.13	23.23	23.24		24.0	0.0

PC2 n41_Ant4 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (dB)	
Channel				504204	518598	532598			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	PQ2 BPSK	1	1	23.58	23.51	23.59		25.5	0.0
50	PQ2 BPSK	1	135	23.99	23.67	23.90			
50	PQ2 BPSK	1	268	23.71	23.58	23.58			
50	PQ2 BPSK	135	0	23.65	23.57	23.65		25.5	0.0
50	PQ2 BPSK	135	68	23.73	23.67	24.10		25.5	0.0
50	PQ2 BPSK	135	135	23.95	23.90	23.81		25.5	0.0
50	PQ2 BPSK	270	0	23.76	23.73	23.85			
50	QPSK	1	1	23.57	23.53	23.59			
50	QPSK	1	135	23.83	24.17	23.98		25.5	0.0
50	QPSK	1	268	23.77	23.59	23.64		25.5	0.0
50	QPSK	135	0	23.56	23.87	23.91			
50	QPSK	135	68	23.91	24.07	24.01			
50	QPSK	135	135	24.03	23.84	23.92		25.5	0.0
50	QPSK	270	0	23.77	23.86	23.67		25.5	0.0
50	16QAM	1	1	23.50	23.74	23.57			
50	64QAM	1	1	23.87	23.55	23.51			
50	256QAM	1	1	23.53	23.60	23.62		25.5	0.0
Channel				503202	518598	534000	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	PQ2 BPSK	1	108	23.68	24.14	23.70		25.5	0.0
Channel				502202	511598	531598	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	PQ2 BPSK	1	80	23.84	24.16	23.78		25.5	0.0
Channel				501204	518598	535998	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2508.02	2592.99	2679.99			
20	QPSK	1	53	23.83	24.16	23.92		25.5	0.0
Channel				500700	518598	536498	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	40	23.66	24.04	23.80		25.5	0.0
Channel				500202	511598	537000	Tune-up limit (dbm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	26	23.72	24.02	23.91		25.5	0.0



PC3 n77_Ant5 DS1&2&3 Default power											
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune-up limit (dBm)	MPR (dB)			
Channel											
Frequency (MHz)											
50	Pl2 BPSK	1	1	21.03	20.59	20.81	22.0	0.0			
50	Pl2 BPSK	1	135	21.51	21.52	21.37					
50	Pl2 BPSK	1	268	21.08	20.68	20.81					
50	Pl2 BPSK	135	0	21.38	21.38	21.27	22.0	0.0			
50	Pl2 BPSK	135	68	21.58	21.62	21.50	22.0	0.0			
50	Pl2 BPSK	135	135	21.32	21.47	21.41	22.0	0.0			
50	Pl2 BPSK	270	0	21.37	21.38	21.32					
50	QPSK	1	1	21.13	20.64	20.58					
50	QPSK	1	135	21.34	21.63	21.44	22.0	0.0			
50	QPSK	1	268	20.35	20.57	20.53	22.0	0.0			
50	QPSK	135	0	21.55	21.51	21.42					
50	QPSK	135	68	21.34	21.56	21.34		0.0			
50	QPSK	135	135	21.47	21.46	21.40	22.0	0.0			
50	QPSK	270	0	21.33	21.43	21.31	22.0	0.0			
50	16QAM	1	1	21.43	21.47	21.30					
50	64QAM	1	1	21.21	21.38	21.30		22.0			
50	256QAM	1	1	19.86	20.08	20.00	20.5	1.5			
Channel											
Frequency (MHz)											
40	QPSK	1	53	37.05	37.00	36.80	22.0	0.0			
Channel											
Frequency (MHz)											
20	QPSK	1	26	37.10.01	36.80	36.70.02	22.0	0.0			
Channel											
Frequency (MHz)											
15	QPSK	1	19	37.07.52	36.80	36.72.51	22.0	0.0			
Channel											
Frequency (MHz)											
10	QPSK	1	12	20.73	20.95	20.80	22.0	0.0			

Par27Q PC3 n77_Ant5 DS11&2&3 Default power											
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune-up limit (dBm)	MPR (dB)			
Channel											
Frequency (MHz)											
50	Pl2 BPSK	1	1	20.31	20.11	20.16	22.0	0.0			
50	Pl2 BPSK	1	135	21.01	20.99	20.87					
50	Pl2 BPSK	1	268	19.88	19.88	19.68					
50	Pl2 BPSK	135	0	20.88	20.88	20.77	22.0	0.0			
50	Pl2 BPSK	135	68	21.08	21.12	21.00	22.0	0.0			
50	Pl2 BPSK	135	135	20.82	20.97	20.91	22.0	0.0			
50	Pl2 BPSK	270	0	20.87	20.88	20.82					
50	QPSK	1	1	19.74	19.87	19.73					
50	QPSK	1	135	20.84	21.40	20.94	22.0	0.0			
50	QPSK	1	268	19.93	19.84	19.69	22.0	0.0			
50	QPSK	135	0	21.05	21.01	20.92					
50	QPSK	135	68	20.84	21.06	20.84		0.0			
50	QPSK	135	135	20.97	20.96	20.90	22.0	0.0			
50	QPSK	270	0	20.83	20.93	20.81	22.0	0.0			
50	16QAM	1	1	20.93	20.97	20.80					
50	64QAM	1	1	20.71	20.88	20.80		22.0			
50	256QAM	1	1	19.76	19.42	19.67	20.5	1.5			
Channel											
Frequency (MHz)											
40	QPSK	1	53	34.701	35.001	35.009	Tune-up limit (dBm)	MPR (dB)			
Channel											
Frequency (MHz)											
20	QPSK	1	26	34.002	33.001	33.000	Tune-up limit (dBm)	MPR (dB)			
Channel											
Frequency (MHz)											
15	QPSK	1	19	34.075	33.001	33.000	Tune-up limit (dBm)	MPR (dB)			
Channel											
Frequency (MHz)											
10	QPSK	1	12	20.69	20.84	20.76	22.0	0.0			

PC2 n77_Ant5 DS1&2&3 Default power											
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune-up limit (dBm)	MPR (dB)			
Channel											
Frequency (MHz)											
50	Pl2 BPSK	1	1	23.00	23.10	23.01	25.0	0.0			
50	Pl2 BPSK	1	135	23.86	24.01	23.84					
50	Pl2 BPSK	1	268	23.11	23.07	23.13					
50	Pl2 BPSK	135	0	23.54	23.45	23.54	24.5	0.5			
50	Pl2 BPSK	135	68	23.71	23.99	23.86	25.0	0.0			
50	Pl2 BPSK	135	135	23.17	23.40	23.25	24.5	0.5			
50	Pl2 BPSK	270	0	23.41	23.42	23.28					
50	QPSK	1	1	23.18	23.05	23.04					
50	QPSK	1	135	23.78	24.33	23.86	25.0	0.0			
50	QPSK	1	268	23.00	23.16	23.13	24.0	1.0			
50	QPSK	135	0	22.87	23.01	23.04					
50	QPSK	135	68	23.97	24.02	23.86		0.0			
50	QPSK	135	135	22.96	23.06	22.81	24.0	1.0			
50	QPSK	270	0	22.75	23.01	22.78	24.0	1.0			
50	16QAM	1	1	22.74	22.95	22.86					
50	64QAM	1	1	21.19	21.31	21.34		22.5			
50	256QAM	1	1	19.34	19.37	19.19	20.5	4.5			
Channel											
Frequency (MHz)											
40	QPSK	1	53	24.08	24.40	23.58	25.0	0.0			
Channel											
Frequency (MHz)											
20	QPSK	1	26	37.10.01	36.80	36.70.02	23.0	0.0			
Channel											
Frequency (MHz)											
15	QPSK	1	19	37.07.52	36.80	36.72.51	23.0	0.0			
Channel											
Frequency (MHz)											
10	QPSK	1	12	23.97	23.99	23.66	25.0	0.0			



Par27Q PC2 n77_Ant5 DSI1&2&3 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631068	633334	636000			
Frequency (MHz)				3475.02	3500.01	3525.02			
50	PI2 BPSK	1	1	23.17	23.24	23.05			
50	PI2 BPSK	1	135	23.78	23.87	23.67			
50	PI2 BPSK	1	268	23.14	23.20	23.00	25.0		
50	PI2 BPSK	135	0	23.23	23.32	23.11	24.5	0.5	
50	PI2 BPSK	135	68	23.76	23.85	23.65	25.0	0.0	
50	PI2 BPSK	135	135	23.30	23.35	23.16			
50	PI2 BPSK	270	0	23.20	23.28	23.08	24.5	0.5	
50	QPSK	1	1	23.16	23.24	23.04			
50	QPSK	1	135	23.86	23.92	23.73	25.0	0.0	
50	QPSK	1	268	23.15	23.24	23.01			
50	QPSK	135	0	22.69	22.77	22.56	24.0	1.0	
50	QPSK	135	68	23.74	23.79	23.60	25.0	0.0	
50	QPSK	135	135	22.71	22.86	22.63	24.0	1.0	
50	QPSK	270	0	22.75	22.84	22.66			
50	16QAM	1	1	22.62	22.68	22.50	24.0	1.0	
50	64QAM	1	1	21.27	21.34	21.15	22.5	2.5	
50	256QAM	1	1	19.16	19.25	19.00	20.5	4.5	
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)		
40	QPSK	1	53	23.23	23.73	23.62	25.0	0.0	
Channel				636068	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)		
20	QPSK	1	26	23.32	23.60	23.50	25.0	0.0	
Channel				636060	633334	636166	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)		
15	QPSK	1	19	23.32	23.71	23.54	25.0	0.0	
Channel				636034	633334	636132	Tune-up limit	MPR	
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)		
10	QPSK	1	12	23.32	23.68	23.55	25.0	0.0	

PC3 n78_Ant5 DSI1&2&3 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				646334	650000	653666			
Frequency (MHz)				3725.01	3750	3775.02			
50	PI2 BPSK	1	1	20.50	20.16	20.28			
50	PI2 BPSK	1	135	21.16	21.09	20.97	22.0	0.0	
50	PI2 BPSK	1	268	20.07	20.10	20.11			
50	PI2 BPSK	135	0	21.01	20.96	20.85	22.0	0.0	
50	PI2 BPSK	135	68	21.26	21.25	21.15	22.0	0.0	
50	PI2 BPSK	135	135	20.95	21.12	21.04			
50	PI2 BPSK	270	0	21.00	20.95	20.98	22.0	0.0	
50	QPSK	1	1	20.03	20.05	20.16			
50	QPSK	1	135	21.01	21.23	21.02	22.0	0.0	
50	QPSK	1	268	20.05	20.14	20.08			
50	QPSK	135	0	21.18	21.08	20.99	22.0	0.0	
50	QPSK	135	68	20.91	21.25	20.99	22.0	0.0	
50	QPSK	135	135	21.00	21.14	21.07	22.0	0.0	
50	QPSK	270	0	20.94	20.95	20.96			
50	16QAM	1	1	21.06	21.10	20.86	22.0	0.0	
50	64QAM	1	1	20.88	20.93	20.92	22.0	0.0	
50	256QAM	1	1	19.94	19.91	19.91	20.5	1.5	
Channel				648000	650000	652000	Tune-up limit	MPR	
Frequency (MHz)				3720	3750	3780	(dBm)		
40	QPSK	1	53	20.84	21.52	21.55	22.0	0.0	
Channel				647334	650000	652066	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3750	3790.02	(dBm)		
20	QPSK	1	26	20.91	20.89	20.92	22.0	0.0	
Channel				647168	650000	652034	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3750	3792.51	(dBm)		
15	QPSK	1	19	20.89	20.86	20.85	22.0	0.0	
Channel				647000	650000	652000	Tune-up limit	MPR	
Frequency (MHz)				3705	3750	3795	(dBm)		
10	QPSK	1	12	20.87	20.86	20.96	22.0	0.0	

Par27Q PC3 n78_Ant5 DSI1&2&3 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631768	633334	636000			
Frequency (MHz)				3475.02	3500.01	3525.02			
50	PI2 BPSK	1	1	20.79	20.38	20.49			
50	PI2 BPSK	1	135	21.24	21.30	21.16			
50	PI2 BPSK	1	268	20.30	20.39	20.33	22.0	0.0	
50	PI2 BPSK	135	0	21.17	21.22	21.09	22.0	0.0	
50	PI2 BPSK	135	68	21.16	21.31	21.24	22.0	0.0	
50	PI2 BPSK	135	135	21.13	21.39	21.20			
50	PI2 BPSK	270	0	21.29	21.20	21.23	22.0	0.0	
50	QPSK	1	1	20.19	20.27	20.43			
50	QPSK	1	135	21.18	21.38	21.20	22.0	0.0	
50	QPSK	1	268	20.29	20.35	20.32			
50	QPSK	135	0	21.36	21.36	21.26	22.0	0.0	
50	QPSK	135	68	21.14	21.37	21.20	22.0	0.0	
50	QPSK	135	135	21.28	21.38	21.28			
50	QPSK	270	0	21.15	21.24	21.13	22.0	0.0	
50	16QAM	1	1	21.32	21.27	21.14	22.0	0.0	
50	64QAM	1	1	21.08	21.15	21.20	22.0	0.0	
50	256QAM	1	1	19.86	19.69	19.86	20.5	1.5	
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)		
40	QPSK	1	53	21.01	21.54	21.09	22.0	0.0	
Channel				636068	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)		
20	QPSK	1	26	20.94	20.92	20.97	22.0	0.0	
Channel				636060	633334	636166	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)		
15	QPSK	1	19	21.02	20.97	20.95	22.0	0.0	
Channel				636034	633334	636132	Tune-up limit	MPR	
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)		
10	QPSK	1	12	21.02	21.03	20.87	22.0	0.0	

PC2 n78_Ant5 DS1&2&3 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				646334	650000	653666	25.0	0.0
Frequency (MHz)				3725.01	3750	3775.02		
50	Plr2 BPSK	1	1	23.00	23.18	23.15		
50	Plr2 BPSK	1	135	23.96	24.20	24.11	25.0	0.0
50	Plr2 BPSK	1	268	23.25	23.48	23.50		
50	Plr2 BPSK	135	0	23.39	23.64	23.63		
50	Plr2 BPSK	135	68	23.99	24.28	24.26	24.5	0.5
50	Plr2 BPSK	135	135	23.43	23.62	23.63		
50	Plr2 BPSK	270	0	23.48	23.68	23.76		
50	QPSK	1	1	23.24	23.49	23.47	25.0	0.0
50	QPSK	1	135	24.06	24.32	24.28		
50	QPSK	1	268	23.28	23.48	23.48		
50	QPSK	135	0	23.12	23.40	23.38	24.0	1.0
50	QPSK	135	68	23.93	24.18	24.10		
50	QPSK	135	135	23.10	23.30	23.26		
50	QPSK	270	0	23.12	23.37	23.31	24.0	1.0
50	16QAM	1	1	23.06	23.30	23.30		
50	16QAM	1	1	21.79	22.07	22.01		
50	256QAM	1	1	19.06	19.90	19.91	22.5	2.5
50	256QAM	1	1	19.06	19.90	19.91	20.5	4.5
Channel				646900	650000	653000	Tune-up limit	MPR
Frequency (MHz)				3720	3750	3780	(dBm)	(dB)
40	QPSK	1	53	23.67	23.76	23.73	25.0	0.0
Channel				647334	650000	650968	Tune-up limit	MPR
Frequency (MHz)				3710.01	3750	3790.02	(dBm)	(dB)
20	QPSK	1	26	23.43	23.87	23.71	25.0	0.0
Channel				647168	650000	650334	Tune-up limit	MPR
Frequency (MHz)				3707.52	3750	3762.51	(dBm)	(dB)
15	QPSK	1	19	23.00	23.82	23.71	25.0	0.0
Channel				645100	650000	652000	Tune-up limit	MPR
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)
10	QPSK	1	12	23.82	23.74	23.70	25.0	0.0

Par27Q PC2 n78_Ant5 DS1&2&3 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000	25.0	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	Plr2 BPSK	1	1	23.24	23.17	23.30		
50	Plr2 BPSK	1	135	23.81	23.80	23.80	24.5	0.5
50	Plr2 BPSK	1	268	23.10	23.09	23.17		
50	Plr2 BPSK	135	0	23.02	23.07	23.13		
50	Plr2 BPSK	135	68	23.43	23.77	23.84	24.5	0.5
50	Plr2 BPSK	135	135	23.01	23.06	23.15		
50	Plr2 BPSK	270	0	23.13	23.25	23.41		
50	QPSK	1	1	23.11	23.10	23.24	25.0	0.0
50	QPSK	1	135	23.76	23.80	23.80		
50	QPSK	1	268	23.21	23.14	23.24		
50	QPSK	135	0	22.91	22.88	23.04	24.0	1.0
50	QPSK	135	68	23.50	23.66	23.43		
50	QPSK	135	135	22.86	22.86	23.02		
50	QPSK	270	0	22.85	22.84	22.80	24.0	1.0
50	16QAM	1	1	22.81	22.86	22.85		
50	16QAM	1	1	21.32	21.36	21.45		
50	256QAM	1	1	19.34	19.29	19.48	22.5	2.5
50	256QAM	1	1	19.34	19.29	19.48	20.5	4.5
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)
40	QPSK	1	53	23.50	23.69	23.70	25.0	0.0
Channel				630968	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)
20	QPSK	1	26	23.61	23.66	23.73	25.0	0.0
Channel				630500	633334	636168	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.48	(dBm)	(dB)
15	QPSK	1	19	23.51	23.66	23.76	25.0	0.0
Channel				630134	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)
10	QPSK	1	12	23.52	23.69	23.81	25.0	0.0



PC3 n77_Ant8 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	650000	660668	20.0	0.0	
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	18.16	18.28	18.19	20.0	0.0	
50	PI2 BPSK	1	135	19.32	19.41	19.32			
50	PI2 BPSK	1	268	18.34	18.31	18.26	20.0	0.0	
50	PI2 BPSK	135	0	19.40	19.23	19.30			
50	PI2 BPSK	135	68	19.18	19.39	19.49	20.0	0.0	
50	PI2 BPSK	135	135	19.38	19.48	19.39			
50	PI2 BPSK	270	0	19.22	19.36	19.42	20.0	0.0	
50	QPSK	1	1	18.15	18.39	18.14			
50	QPSK	1	135	19.38	19.70	19.50	20.0	0.0	
50	QPSK	1	268	18.23	18.39	18.15			
50	QPSK	135	0	19.23	19.26	19.24	20.0	0.0	
50	QPSK	135	68	19.35	19.45	19.27			
50	QPSK	135	135	19.19	19.36	19.12	20.0	0.0	
50	QPSK	270	0	19.42	19.47	19.26			
50	16QAM	1	1	19.21	19.42	19.49	20.0	0.0	
50	64QAM	1	1	19.43	19.43	19.27			
50	256QAM	1	1	17.88	18.06	18.01	18.5	1.5	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3720	3840	3960	20.0	0.0	
40	QPSK	1	53	18.85	18.97	18.79	20.0	0.0	
Channel				647334	656000	664668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3710.01	3840	3970.02	20.0	0.0	
20	QPSK	1	26	18.87	19.02	18.85	20.0	0.0	
Channel				647168	656000	664834	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3707.52	3840	3972.51	20.0	0.0	
15	QPSK	1	19	19.00	18.80	18.80	20.0	0.0	
Channel				645000	650000	655000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3705	3840	3975	20.0	0.0	
10	QPSK	1	12	18.82	18.94	18.74	20.0	0.0	

Par27Q PC3 n77_Ant8 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000	20.0	0.0	
Frequency (MHz)				3475.02	3500.01	3525			
50	PI2 BPSK	1	1	18.13	18.30	18.26	20.0	0.0	
50	PI2 BPSK	1	135	19.31	19.39	19.31			
50	PI2 BPSK	1	268	18.31	18.39	18.15	20.0	0.0	
50	PI2 BPSK	135	0	19.48	19.32	19.22			
50	PI2 BPSK	135	68	19.04	19.47	19.40	20.0	0.0	
50	PI2 BPSK	135	135	19.45	19.42	19.28			
50	PI2 BPSK	270	0	19.30	19.25	19.41	20.0	0.0	
50	QPSK	1	1	18.23	18.24	18.07			
50	QPSK	1	135	19.29	19.53	19.42	20.0	0.0	
50	QPSK	1	268	18.29	18.30	18.01			
50	QPSK	135	0	19.09	19.31	19.26	20.0	0.0	
50	QPSK	135	68	19.24	19.36	19.16			
50	QPSK	135	135	19.20	19.35	19.12	20.0	0.0	
50	QPSK	270	0	19.28	19.50	19.31			
50	16QAM	1	1	19.19	19.34	19.50	20.0	0.0	
50	64QAM	1	1	19.46	19.45	19.24			
50	256QAM	1	1	17.64	17.58	17.78	18.5	1.5	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3470.01	3500.01	3530.00	20.0	0.0	
40	QPSK	1	53	18.78	18.84	18.91	20.0	0.0	
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3460.02	3500.01	3540	20.0	0.0	
20	QPSK	1	26	18.85	19.04	18.92	20.0	0.0	
Channel				630500	633334	636166	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3457.5	3500.01	3542.48	20.0	0.0	
15	QPSK	1	19	18.80	19.00	18.90	20.0	0.0	
Channel				630334	633334	635332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3455.01	3500.01	3544.96	20.0	0.0	
10	QPSK	1	12	18.79	18.90	18.92	20.0	0.0	

PC2 n77_Ant8 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	650000	660668	23.0	0.0	
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	21.14	21.17	21.14	23.0	0.5	
50	PI2 BPSK	1	135	21.84	21.98	21.96			
50	PI2 BPSK	1	268	21.03	21.07	21.00	22.5	0.0	
50	PI2 BPSK	135	0	21.45	21.49	21.40			
50	PI2 BPSK	135	68	21.76	21.98	21.74	23.0	0.0	
50	PI2 BPSK	135	135	21.53	21.46	21.40			
50	PI2 BPSK	270	0	21.21	21.46	21.20	22.5	0.5	
50	QPSK	1	1	21.15	21.12	21.23			
50	QPSK	1	135	21.89	22.05	21.93	23.0	0.0	
50	QPSK	1	268	21.00	21.00	21.11			
50	QPSK	135	0	20.96	21.03	21.01	22.0	1.0	
50	QPSK	135	68	21.85	22.00	21.85			
50	QPSK	135	135	20.83	20.90	20.75	22.0	1.0	
50	QPSK	270	0	20.98	21.11	20.93			
50	16QAM	1	1	20.98	21.06	20.84	22.0	1.0	
50	64QAM	1	1	19.55	19.57	19.83			
50	256QAM	1	1	17.50	17.70	17.73	18.5	4.5	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3720	3840	3960	23.0	0.0	
40	QPSK	1	53	21.83	21.88	21.90	23.0	0.0	
Channel				647334	656000	664668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3710.01	3840	3970.02	23.0	0.0	
20	QPSK	1	26	21.01	21.93	21.56	23.0	0.0	
Channel				647168	656000	664834	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3707.52	3840	3972.51	23.0	0.0	
15	QPSK	1	19	21.77	21.85	21.92	23.0	0.0	
Channel				645000	650000	655000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3705	3840	3975	23.0	0.0	
10	QPSK	1	12	22.00	21.89	21.92	23.0	0.0	

Par27Q PC2 n77_Ant8 DSI1&2&4 Default power

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000	23.0	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	PV2 BPSK	1	1	21.00	21.09	21.11	22.5	0.5
50	PV2 BPSK	1	135	21.84	21.89	21.71		
50	PV2 BPSK	1	268	21.17	21.23	21.02	22.0	1.0
50	PV2 BPSK	135	0	21.31	21.37	21.20		
50	PV2 BPSK	135	68	21.66	21.73	21.52	22.5	0.5
50	PV2 BPSK	135	135	21.42	21.50	21.27		
50	PV2 BPSK	270	0	21.47	21.52	21.36	23.0	0.0
50	QPSK	1	1	21.08	21.17	21.23		
50	QPSK	1	135	22.01	22.09	21.90	22.0	1.0
50	QPSK	1	268	21.07	21.12	21.16		
50	QPSK	135	0	20.94	21.01	20.82	22.0	1.0
50	QPSK	135	68	21.95	22.02	21.80		
50	QPSK	135	135	20.81	20.88	20.67	22.0	1.0
50	QPSK	270	0	21.02	21.10	20.91		
50	16QAM	1	1	20.86	20.96	20.76	22.0	1.0
50	64QAM	1	1	19.55	19.64	19.41		
50	256QAM	1	1	17.58	17.65	17.44	18.5	4.5
Channel				631334	633334	635332		
Frequency (MHz)				3473.01	3500.01	3529.98	23.0	0.0
40	QPSK	1	53	21.98	22.09	21.75		
Channel				630968	633334	636000	23.0	0.0
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	26	21.82	21.92	21.82	23.0	0.0
Channel				630500	633334	636168		
Frequency (MHz)				3457.5	3500.01	3542.49	23.0	0.0
15	QPSK	1	19	21.99	22.07	21.76		
Channel				630334	633334	635332	23.0	0.0
Frequency (MHz)				3455.01	3500.01	3544.98		
10	QPSK	1	12	21.83	21.98	21.83	23.0	0.0

PC3 n78_Ant8 DSI1&2&4 Default power

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				648334	650000	651668	20.0	0.0
Frequency (MHz)				3725.01	3750	3775.02		
50	PV2 BPSK	1	1	18.36	18.49	18.38	20.0	0.0
50	PV2 BPSK	1	135	19.63	19.59	19.51		
50	PV2 BPSK	1	268	18.54	18.49	18.46	20.0	0.0
50	PV2 BPSK	135	0	19.58	19.42	19.48		
50	PV2 BPSK	135	68	19.39	19.59	19.59	20.0	0.0
50	PV2 BPSK	135	135	19.67	19.38	19.67		
50	PV2 BPSK	270	0	19.40	19.58	19.61	20.0	0.0
50	QPSK	1	1	18.34	18.61	18.32		
50	QPSK	1	135	19.58	19.67	19.54	20.0	0.0
50	QPSK	1	268	18.45	18.59	18.34		
50	QPSK	135	0	19.44	19.47	19.44	20.0	0.0
50	QPSK	135	68	19.63	19.64	19.47		
50	QPSK	135	135	19.38	19.57	19.32	20.0	0.0
50	QPSK	270	0	19.63	19.66	19.45		
50	16QAM	1	1	19.46	19.62	19.34	20.0	0.0
50	64QAM	1	1	19.82	19.61	19.46		
50	256QAM	1	1	18.05	18.27	18.22	18.5	1.5
Channel				648000	650000	652000		
Frequency (MHz)				3720	3750	3780	20.0	0.0
40	QPSK	1	53	18.90	18.97	18.62		
Channel				647334	650000	652668	20.0	0.0
Frequency (MHz)				3710.01	3750	3790.02		
20	QPSK	1	26	18.82	18.94	18.70	20.0	0.0
Channel				647168	650000	652834		
Frequency (MHz)				3707.52	3750	3792.51	20.0	0.0
15	QPSK	1	19	18.72	19.02	18.82		
Channel				645000	650000	655000	20.0	0.0
Frequency (MHz)				3705	3750	3795		
10	QPSK	1	12	18.81	18.96	18.66	20.0	0.0

Par27Q PC3 n78_Ant8 DSI1&2&4 Default power

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000	20.0	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	PV2 BPSK	1	1	18.01	18.18	18.04	20.0	0.0
50	PV2 BPSK	1	135	19.20	19.26	19.18		
50	PV2 BPSK	1	268	18.22	18.17	18.14	20.0	0.0
50	PV2 BPSK	135	0	19.24	19.09	19.15		
50	PV2 BPSK	135	68	19.08	19.26	19.25	20.0	0.0
50	PV2 BPSK	135	135	19.25	19.03	19.23		
50	PV2 BPSK	270	0	19.06	19.26	19.29	20.0	0.0
50	QPSK	1	1	18.05	18.29	18.06		
50	QPSK	1	135	19.24	19.33	19.21	20.0	0.0
50	QPSK	1	268	18.12	18.28	18.08		
50	QPSK	135	0	19.13	19.14	19.12	20.0	0.0
50	QPSK	135	68	19.18	19.35	19.16		
50	QPSK	135	135	19.04	19.26	19.00	20.0	0.0
50	QPSK	270	0	19.32	19.34	19.13		
50	16QAM	1	1	19.07	19.26	19.00	20.0	0.0
50	64QAM	1	1	19.29	19.14	19.14		
50	256QAM	1	1	17.71	17.98	17.89	18.5	1.5
Channel				631334	633334	635332		
Frequency (MHz)				3470.01	3500.01	3529.98	20.0	0.0
40	QPSK	1	53	18.74	19.15	18.95		
Channel				630968	633334	636000	20.0	0.0
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	26	18.70	18.90	18.69	20.0	0.0
Channel				630500	633334	636168		
Frequency (MHz)				3457.5	3500.01	3542.49	20.0	0.0
15	QPSK	1	19	18.79	19.07	18.76		
Channel				630334	633334	635332	20.0	0.0
Frequency (MHz)				3455.01	3500.01	3544.98		
10	QPSK	1	12	18.67	18.94	18.95	20.0	0.0



PC2 n78_Ant8 DSI1&2&4 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				648333	650000	651666	23.0	0.0
Frequency (MHz)				3750.01	3750	3750.02		
50	PI2 BPSK	1	1	21.06	21.16	21.28	22.5	0.5
50	PI2 BPSK	1	135	21.62	21.65	21.65		
50	PI2 BPSK	1	268	21.04	21.16	21.28	22.5	0.5
50	PI2 BPSK	135	0	21.13	21.16	21.06		
50	PI2 BPSK	135	68	21.43	21.66	21.42	22.5	0.5
50	PI2 BPSK	135	135	21.18	21.14	21.08		
50	PI2 BPSK	270	0	20.89	21.13	20.88	23.0	0.0
50	QPSK	1	1	21.06	21.25	21.31		
50	QPSK	1	135	21.54	21.73	21.81	23.0	0.0
50	QPSK	1	268	21.15	21.30	21.15		
50	QPSK	135	0	20.56	20.66	20.56	22.0	1.0
50	QPSK	135	68	21.31	21.65	21.52		
50	QPSK	135	135	20.50	20.55	20.42	22.0	1.0
50	QPSK	270	0	20.64	20.79	20.62		
50	16QAM	1	1	20.58	20.77	20.51	22.0	1.0
50	64QAM	1	1	19.22	19.25	19.30		
50	256QAM	1	1	17.16	17.37	17.39	18.5	4.5
Channel				648000	650000	652000	Tune-up limit	MPR
Frequency (MHz)				3750	3750	3750	(dBm)	(dB)
40	QPSK	1	53	21.59	21.80	21.79	23.0	0.0
Channel				647334	650000	652666	Tune-up limit	MPR
Frequency (MHz)				3710.01	3750	3750.02	(dBm)	(dB)
20	QPSK	1	26	21.59	21.80	21.85	23.0	0.0
Channel				647168	650000	652834	Tune-up limit	MPR
Frequency (MHz)				3707.52	3750	3750.51	(dBm)	(dB)
15	QPSK	1	19	21.58	21.88	21.83	23.0	0.0
Channel				645000	650000	655000	Tune-up limit	MPR
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)
10	QPSK	1	12	21.64	21.78	21.90	23.0	0.0

Par27Q PC2 n78_Ant8 DSI1&2&4 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000	23.0	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	PI2 BPSK	1	1	21.16	21.12	21.29	22.5	0.5
50	PI2 BPSK	1	135	21.49	21.54	21.37		
50	PI2 BPSK	1	268	21.31	21.50	21.16	22.5	0.5
50	PI2 BPSK	135	0	21.00	21.08	20.88		
50	PI2 BPSK	135	68	21.32	21.40	21.19	22.5	0.5
50	PI2 BPSK	135	135	21.09	21.16	20.95		
50	PI2 BPSK	270	0	21.14	21.20	21.01	23.0	0.0
50	QPSK	1	1	21.16	21.15	21.11		
50	QPSK	1	135	21.70	21.77	21.58	22.0	1.0
50	QPSK	1	268	21.32	21.19	21.23		
50	QPSK	135	0	20.63	20.67	20.48	22.0	1.0
50	QPSK	135	68	21.61	21.70	21.47		
50	QPSK	135	135	20.48	20.54	20.35	22.0	1.0
50	QPSK	270	0	20.69	20.77	20.58		
50	16QAM	1	1	20.54	20.62	20.44	22.0	1.0
50	64QAM	1	1	19.22	19.32	19.06		
50	256QAM	1	1	17.23	17.31	17.11	18.5	4.5
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.06	(dBm)	(dB)
40	QPSK	1	53	21.63	21.81	21.80	23.0	0.0
Channel				630668	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)
20	QPSK	1	26	21.71	21.71	21.61	23.0	0.0
Channel				630500	633334	636166	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)
15	QPSK	1	19	21.71	21.74	21.64	23.0	0.0
Channel				630334	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3456.01	3500.01	3544.88	(dBm)	(dB)
10	QPSK	1	12	21.83	21.85	21.80	23.0	0.0

For DFT-30

n5_Ant0 DSI1&2&3 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				166800	167300	167800	25.0	0.0
Frequency (MHz)				834	836.5	839		
20	PI/2 BPSK	1	1	23.36	23.55	23.25	25.0	0.0
20	PI/2 BPSK	1	26	23.62	23.81	23.51		
20	PI/2 BPSK	1	49	23.49	23.68	23.38		
20	PI/2 BPSK	25	0	23.16	23.36	23.06	24.5	0.5
20	PI/2 BPSK	25	13	23.67	23.88	23.58	25.0	0.0
20	PI/2 BPSK	25	26	23.15	23.35	23.05	24.5	0.5
20	PI/2 BPSK	50	0	23.18	23.37	23.06		
20	QPSK	1	1	23.88	23.98	23.79	25.0	0.0
20	QPSK	1	26	23.89	23.99	23.78		
20	QPSK	1	49	23.65	23.85	23.56		
20	QPSK	25	0	22.86	22.88	22.90	24.0	1.0
20	QPSK	25	13	23.68	23.89	23.59	25.0	0.0
20	QPSK	25	26	22.65	22.85	22.55	24.0	1.0
20	QPSK	50	0	22.63	22.82	22.53		
20	16QAM	1	1	22.13	22.34	22.04	24.0	1.0
20	64QAM	1	1	20.64	20.85	20.55	22.5	2.5
20	256QAM	1	1	19.38	19.49	19.26	20.5	4.5
Channel				166300	167300	168300	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				831.5	836.5	841.5		
15	QPSK	1	40	23.65	23.90	23.68	25.0	0.0
Channel				166800	167300	168300	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				829	836.5	844		
10	QPSK	1	26	23.78	23.84	23.61	25.0	0.0

n7_ DSI1 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2510	2535	2560		
20	PI/2 BPSK	1	1	23.06	23.26	23.24	25.0	0.0
20	PI/2 BPSK	1	26	23.21	23.40	23.38		
20	PI/2 BPSK	1	49	23.02	23.20	23.18		
20	PI/2 BPSK	25	0	22.80	22.99	22.96	24.5	0.5
20	PI/2 BPSK	25	13	23.26	23.46	23.43	25.0	0.0
20	PI/2 BPSK	25	26	22.71	22.90	22.88	24.5	0.5
20	PI/2 BPSK	50	0	22.79	22.99	22.97		
20	QPSK	1	1	23.41	23.61	23.60	25.0	0.0
20	QPSK	1	26	23.49	23.68	23.65		
20	QPSK	1	49	23.25	23.44	23.42		
20	QPSK	25	0	22.57	22.59	22.60	24.0	1.0
20	QPSK	25	13	23.30	23.49	23.46	25.0	0.0
20	QPSK	25	26	22.18	22.39	22.37	24.0	1.0
20	QPSK	50	0	22.26	22.45	22.44		
20	16QAM	1	1	22.37	22.44	22.36	24.0	1.0
20	64QAM	1	1	20.56	20.55	20.53	22.5	2.5
20	256QAM	1	1	18.94	19.14	19.11	20.5	4.5
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5		
15	QPSK	1	40	23.39	23.48	23.40	25.0	0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565		
10	QPSK	1	26	23.40	23.41	23.50	25.0	0.0



n38_Ant0 DSI1&2 Default power								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	518000	518996	25.0	0.0
Frequency (MHz)				2580.02	2595	2599.98		
40	PQ2 BPSK	1	1	24.09	24.06	24.00		
40	PQ2 BPSK	1	53	24.47	24.49	24.37		
40	PQ2 BPSK	1	104	24.02	24.04	24.02	24.5	0.5
40	PQ2 BPSK	50	0	23.67	23.69	23.58		
40	PQ2 BPSK	50	28	24.21	24.28	24.12		
40	PQ2 BPSK	50	56	23.56	23.58	23.46		
40	PQ2 BPSK	100	0	23.63	23.66	23.55	25.0	0.0
40	QPSK	1	1	24.07	24.20	24.08		
40	QPSK	1	53	24.47	24.55	24.37		
40	QPSK	1	104	23.75	23.76	23.63		
40	QPSK	50	0	23.13	23.16	23.03	24.0	1.0
40	QPSK	50	28	24.16	24.19	24.07		
40	QPSK	50	56	23.00	23.02	22.91		
40	QPSK	100	0	23.10	23.11	22.99		
40	16QAM	1	1	22.44	22.48	22.34	24.0	1.0
40	64QAM	1	1	21.73	21.86	21.63		
40	256QAM	1	1	19.62	19.64	19.52		
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2595	2610	25.0	0.0
20	QPSK	1	26	24.22	24.41	24.19	25.0	0.0
Channel				518202	519200	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49	25.0	0.0
15	QPSK	1	19	24.25	24.30	24.18	25.0	0.0
Channel				518004	519000	522996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2581.02	2595	2614.98	25.0	0.0
10	QPSK	1	12	24.37	24.44	24.21	25.0	0.0

PC3 n41_Ant0 DSI1 Default power								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				509002	518598	528000	23.0	0.0
Frequency (MHz)				2546.01	2592.99	2640		
100	PQ2 BPSK	1	1	21.88	22.06	22.04		
100	PQ2 BPSK	1	137	21.95	22.12	22.12		
100	PQ2 BPSK	1	271	21.91	21.92	21.76	23.0	0.0
100	PQ2 BPSK	135	0	22.03	22.05	21.90		
100	PQ2 BPSK	135	69	22.00	22.03	21.89		
100	PQ2 BPSK	135	138	21.99	22.08	22.05		
100	PQ2 BPSK	270	0	21.93	22.08	21.96	23.0	0.0
100	QPSK	1	1	21.94	22.10	22.09		
100	QPSK	1	137	21.89	22.18	21.78		
100	QPSK	1	271	21.94	22.01	21.98		
100	QPSK	135	0	21.88	22.03	21.82	23.0	0.0
100	QPSK	135	69	22.00	22.10	22.05		
100	QPSK	135	138	22.04	22.08	22.03		
100	QPSK	270	0	21.92	22.00	21.84		
100	16QAM	1	1	21.78	21.96	21.82	23.0	0.0
100	64QAM	1	1	21.79	21.87	21.69		
100	256QAM	1	1	20.51	20.68	20.52		
Channel				508200	518598	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2541	2592.99	2644.98	23.0	0.0
90	QPSK	1	123	21.87	21.97	21.63	23.0	0.0
Channel				509204	518598	529596	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536.02	2592.99	2649.99	23.0	0.0
80	QPSK	1	109	21.89	22.15	21.66	23.0	0.0
Channel				508200	518598	531996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536	2592.99	2659.98	23.0	0.0
60	QPSK	1	81	21.78	22.00	21.55	23.0	0.0
Channel				504204	518598	532996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2521.02	2592.99	2664.99	23.0	0.0
50	QPSK	1	67	21.73	22.14	21.60	23.0	0.0
Channel				504204	518598	533000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670	23.0	0.0
40	QPSK	1	53	21.72	22.04	21.74	23.0	0.0
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98	23.0	0.0
30	QPSK	1	39	21.82	22.08	21.63	23.0	0.0
Channel				501204	518598	535996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99	23.0	0.0
20	QPSK	1	26	21.79	22.02	21.74	23.0	0.0
Channel				500200	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48	23.0	0.0
15	QPSK	1	19	21.67	22.09	21.76	23.0	0.0
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685	23.0	0.0
10	QPSK	1	12	21.83	22.09	21.59	23.0	0.0

PC2 n41_Ant0 DSI1 Default power								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				509002	518598	528000	25.5	0.0
Frequency (MHz)				2546.01	2592.99	2640		
100	PQ2 BPSK	1	1	25.19	25.25	25.25		
100	PQ2 BPSK	1	137	24.97	25.13	24.96		
100	PQ2 BPSK	1	271	25.04	25.17	25.02	25.0	0.5
100	PQ2 BPSK	135	0	24.43	24.63	24.63		
100	PQ2 BPSK	135	69	24.81	24.95	24.86		
100	PQ2 BPSK	135	138	24.22	24.42	24.28		
100	PQ2 BPSK	270	0	24.25	24.25	24.25	25.0	0.5
100	QPSK	1	1	25.08	25.19	25.13		
100	QPSK	1	137	24.95	25.26	24.84		
100	QPSK	1	271	25.17	25.21	25.13		
100	QPSK	135	0	24.04	24.05	23.83	24.5	1.0
100	QPSK	135	69	24.93	25.15	24.96		
100	QPSK	135	138	23.95	24.08	23.97		
100	QPSK	270	0	23.78	23.80	23.76		
100	16QAM	1	1	23.59	23.79	23.74	24.5	1.0
100	64QAM	1	1	22.47	22.59	22.56		
100	256QAM	1	1	20.52	20.53	20.48		
Channel				508200	518598	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2541	2592.99	2644.98	25.5	0.0
90	QPSK	1	123	24.95	25.08	24.74	25.5	0.0
Channel				509204	518598	529596	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536.02	2592.99	2649.99	25.5	0.0
80	QPSK	1	109	24.88	25.24	24.67	25.5	0.0
Channel				508200	518598	531996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536	2592.99	2659.98	25.5	0.0
60	QPSK	1	81	24.88	25.11	24.64	25.5	0.0
Channel				504204	518598	532996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2521.02	2592.99	2664.99	25.5	0.0
50	QPSK	1	67	24.90	25.10	24.74	25.5	0.0
Channel				504204	518598	533000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670	25.5	0.0
40	QPSK	1	53	24.78	25.20	24.83	25.5	0.0
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98	25.5	0.0
30	QPSK	1	39	24.90	25.18	24.70	25.5	0.0
Channel				501204	518598	535996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99	25.5	0.0
20	QPSK	1	26	24.87	25.12	24.74	25.5	0.0
Channel				500200	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48	25.5	0.0
15	QPSK	1	19	24.82	25.10	24.79	25.5	0.0
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685	25.5	0.0
10	QPSK	1	12	24.79	25.23	24.67	25.5	0.0

n66_Ant1 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				346000	349000	352000	25.5	0.0
Frequency (MHz)				1730	1745	1760		
40	PI/2 BPSK	1	1	23.99	24.13	23.91	25.5	0.0
40	PI/2 BPSK	1	53	24.27	24.42	24.30		
40	PI/2 BPSK	1	104	23.96	24.14	24.01	25.0	0.5
40	PI/2 BPSK	50	0	23.45	23.63	23.60		
40	PI/2 BPSK	50	28	24.28	24.34	24.26	25.5	0.0
40	PI/2 BPSK	50	56	23.41	23.54	23.40		
40	PI/2 BPSK	100	0	23.33	23.58	23.48	25.0	0.5
40	QPSK	1	1	23.95	23.97	23.94		
40	QPSK	1	53	24.29	24.44	24.32	25.5	0.0
40	QPSK	1	104	24.12	24.21	24.06		
40	QPSK	50	0	23.19	23.24	23.04	24.5	1.0
40	QPSK	50	28	24.09	24.24	24.15		
40	QPSK	50	56	23.06	23.20	22.98	24.5	1.0
40	QPSK	100	0	23.21	23.28	23.24		
40	16QAM	1	1	23.10	23.20	23.05	24.5	1.0
40	64QAM	1	1	21.61	21.68	21.57		
40	256QAM	1	1	19.84	19.92	19.82	21.0	4.5
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1725	1745	1765		
30	QPSK	1	80	24.05	24.35	24.12	25.5	0.0
Channel				344500	349000	353500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1722.5	1745	1767.5		
25	QPSK	1	67	24.18	24.30	24.23	25.5	0.0
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1720	1745	1770		
20	QPSK	1	26	24.07	24.29	24.18	25.5	0.0
Channel				343500	349000	354500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1717.5	1745	1772.5		
15	QPSK	1	19	24.16	24.18	24.21	25.5	0.0
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1715	1745	1775		
10	QPSK	1	12	24.15	24.29	24.08	25.5	0.0



PC3 n77_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	Pl2 BPSK	1	1	19.53	19.69	19.84			
100	Pl2 BPSK	1	137	19.34	19.55	19.43	20.5	0.0	
100	Pl2 BPSK	1	271	19.63	19.81	19.81			
100	Pl2 BPSK	136	0	19.37	19.54	19.46	20.5	0.0	
100	Pl2 BPSK	136	69	19.39	19.60	19.47	20.5	0.0	
100	Pl2 BPSK	136	138	19.52	19.59	19.43	20.5	0.0	
100	Pl2 BPSK	270	0	19.44	19.59	19.46			
100	QPSK	1	1	19.59	19.59	19.53			
100	QPSK	1	137	19.65	19.71	19.68	20.5	0.0	
100	QPSK	1	271	19.65	19.64	19.50			
100	QPSK	136	0	19.55	19.58	19.56	20.5	0.0	
100	QPSK	136	69	19.45	19.62	19.50	20.5	0.0	
100	QPSK	136	138	19.39	19.45	19.39			
100	QPSK	270	0	19.36	19.42	19.40	20.5	0.0	
100	16QAM	1	1	19.22	19.39	19.28	20.5	0.0	
100	64QAM	1	1	19.20	19.37	19.30	20.5	0.0	
100	256QAM	1	1	19.18	19.33	19.14	19.0	1.5	
Channel									
Frequency (MHz)				649698	650000	662334	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	3745.02	3840	3935.01			
Channel									
Frequency (MHz)				3745.02	3840	3940.02	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	19.49	19.53	19.61	20.5	0.0	
Channel									
Frequency (MHz)				3735	3840	3945	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	96	19.45	19.64	19.70	20.5	0.0	
Channel									
Frequency (MHz)				648968	650000	663334	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	19.63	19.64	19.49	20.5	0.0	
Channel									
Frequency (MHz)				648334	650000	663668	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	19.54	19.58	19.50	20.5	0.0	
Channel									
Frequency (MHz)				648000	650000	664000	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	19.61	19.65	19.67	20.5	0.0	
Channel									
Frequency (MHz)				647334	650000	663668	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	19.51	19.70	19.68	20.5	0.0	
Channel									
Frequency (MHz)				3707.52	3840	3972.51	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	19.65	19.52	19.54	20.5	0.0	
Channel									
Frequency (MHz)				647000	650000	665000	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	19.47	19.69	19.54	20.5	0.0	

Par27Q PC3 n77_Ant1 DSI1&2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)					3500.01				
100	Pl2 BPSK	1	1		19.52				
100	Pl2 BPSK	1	137		19.33		20.5	0.0	
100	Pl2 BPSK	1	271		19.63				
100	Pl2 BPSK	136	0		19.31		20.5	0.0	
100	Pl2 BPSK	136	69		19.27		20.5	0.0	
100	Pl2 BPSK	136	138		19.23		20.5	0.0	
100	Pl2 BPSK	270	0		19.24				
100	QPSK	1	1		19.64				
100	QPSK	1	137		19.68		20.5	0.0	
100	QPSK	1	271		19.56				
100	QPSK	136	0		19.26		20.5	0.0	
100	QPSK	136	69		19.36		20.5	0.0	
100	QPSK	136	138		19.24		20.5	0.0	
100	QPSK	270	0		19.01				
100	16QAM	1	1		19.19		20.5	0.0	
100	64QAM	1	1		19.13		20.5	0.0	
100	256QAM	1	1		19.15		19.0	1.5	
Channel									
Frequency (MHz)				633000	633334	633668	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	3495	3500.01	3504.98			
Channel									
Frequency (MHz)				3495.02	3500.01	3510	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	19.16	19.11	18.89	20.5	0.0	
Channel									
Frequency (MHz)				3485.01	3500.01	3514.98	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	96	19.16	19.15	19.04	20.5	0.0	
Channel									
Frequency (MHz)				632000	633334	633668	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	19.27	19.09	19.07	20.5	0.0	
Channel									
Frequency (MHz)				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	19.21	19.11	19.00	20.5	0.0	
Channel									
Frequency (MHz)				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	19.26	19.27	19.58	20.5	0.0	
Channel									
Frequency (MHz)				630668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	19.29	19.29	19.08	20.5	0.0	
Channel									
Frequency (MHz)				630334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	19.27	19.09	19.04	20.5	0.0	
Channel									
Frequency (MHz)				630000	633334	635332	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	19.22	19.12	18.99	20.5	0.0	

PC2 n77_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	Pl2 BPSK	1	1	21.55	21.75	21.63			
100	Pl2 BPSK	1	137	22.46	22.80	22.52	23.5	0.0	
100	Pl2 BPSK	1	271	21.54	21.70	21.50			
100	Pl2 BPSK	136	0	21.50	21.97	21.89	23.0	0.5	
100	Pl2 BPSK	136	69	22.51	22.54	22.43	23.5	0.0	
100	Pl2 BPSK	136	138	21.94	22.01	21.90	23.0	0.5	
100	Pl2 BPSK	270	0	21.97	21.98	21.87			
100	QPSK	1	1	21.65	21.74	21.67			
100	QPSK	1	137	22.41	22.61	22.55	23.5	0.0	
100	QPSK	1	271	21.78	21.69	21.60			
100	QPSK	136	0	21.27	21.45	21.29	22.5	1.0	
100	QPSK	136	69	22.26	22.51	22.56	23.5	0.0	
100	QPSK	136	138	21.44	21.49	21.47	22.5	1.0	
100	QPSK	270	0	21.27	21.46	21.27			
100	16QAM	1	1	21.10	21.24	21.10	22.5	1.0	
100	64QAM	1	1	19.90	20.08	20.03	21.0	2.5	
100	256QAM	1	1	19.39	19.38	19.38	19.0	4.5	
Channel									
Frequency (MHz)				648968	650000	662334	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	3745.02	3840	3935.01			
Channel									
Frequency (MHz)				648334	650000	662668	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	22.41	22.47	22.39	23.5	0.0	
Channel									
Frequency (MHz)				3735	3840	3945	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	95	22.26	22.52	22.52	23.5	0.0	
Channel									
Frequency (MHz)				648968	650000	663334	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	22.40	22.52	22.39	23.5	0.0	
Channel									
Frequency (MHz)				648334	650000	663668	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	22.39	22.59	22.47	23.5	0.0	
Channel									
Frequency (MHz)				648000	650000	664000	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	22.32	22.42	22.30	23.5	0.0	
Channel									
Frequency (MHz)				647334	650000	664668	Tune-up limit (dBm)	MPR (dB)	
30	QPSK	1	26	22.37	22.47	22.52	23.5	0.0	
Channel									
Frequency (MHz)				3707.52	3840	3972.51	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	22.27	22.47	22.43	23.5	0.0	
Channel									
Frequency (MHz)				647000	650000	665000	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	22.25	22.41	22.36	23.5	0.0	



Par27Q PC2 n77_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
100	PQ2 BPSK	1	1	21.54	3600.01				
100	PQ2 BPSK	1	137	22.39			23.5	0.0	
100	PQ2 BPSK	1	271	21.50					
100	PQ2 BPSK	135	0	21.79			23.0	0.5	
100	PQ2 BPSK	135	69	22.44			23.5	0.0	
100	PQ2 BPSK	135	138	21.97			23.0	0.5	
100	PQ2 BPSK	270	0	21.92					
100	QPSK	1	1	21.62					
100	QPSK	1	137	22.53			23.5	0.0	
100	QPSK	1	271	21.50					
100	QPSK	135	0	21.36			22.5	1.0	
100	QPSK	135	69	22.37			23.0	0.0	
100	QPSK	135	138	21.32			22.5	1.0	
100	QPSK	270	0	21.45					
100	16QAM	1	1	21.14			22.5	1.0	
100	64QAM	1	1	19.96			21.0	2.5	
100	256QAM	1	1	18.33			19.0	4.5	
Channel									
Frequency (MHz)									
90	QPSK	1	123	22.42	3633.54	3604.99	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
80	QPSK	1	109	22.43	3633.54	3610.00	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
70	QPSK	1	95	22.42	3633.54	3594.08	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
60	QPSK	1	81	22.27	3633.54	3569.96	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
50	QPSK	1	67	22.23	3633.54	3548.88	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
40	QPSK	1	53	22.39	3633.54	3520.88	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
20	QPSK	1	26	22.43	3633.54	3500.00	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
15	QPSK	1	19	22.31	3633.54	3492.49	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
10	QPSK	1	12	22.34	3633.54	3484.88	Tune-up limit (dBm)	MPR (dB)	

PC3 n78_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750					
100	PQ2 BPSK	1	1	18.74					
100	PQ2 BPSK	1	137	19.89	20.5 0.0				
100	PQ2 BPSK	1	271	18.02					
100	PQ2 BPSK	135	0	19.70	20.5 0.0				
100	PQ2 BPSK	135	69	19.85	20.5 0.0				
100	PQ2 BPSK	135	138	19.78	20.5 0.0				
100	PQ2 BPSK	270	0	19.52					
100	QPSK	1	1	18.77					
100	QPSK	1	137	19.51	20.5 0.0				
100	QPSK	1	271	19.04					
100	QPSK	135	0	19.73	20.5 0.0				
100	QPSK	135	69	19.88	20.5 0.0				
100	QPSK	135	138	19.82	20.5 0.0				
100	QPSK	270	0	19.79					
100	16QAM	1	1	19.56	20.5 0.0				
100	64QAM	1	1	18.61	20.5 0.0				
100	256QAM	1	1	18.71	19.0 1.5				
Channel									
Frequency (MHz)				64968	65000	650334	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	19.84	19.81	19.80	20.5	0.0	
Channel									
Frequency (MHz)				649334	650000	650086	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	19.77	19.80	19.75	20.5	0.0	
Channel									
Frequency (MHz)				649000	650000	650092	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	95	19.84	19.87	19.68	20.5	0.0	
Channel									
Frequency (MHz)				648668	650000	651134	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	19.79	19.75	19.85	20.5	0.0	
Channel									
Frequency (MHz)				648334	650000	651608	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	19.70	19.88	19.74	20.5	0.0	
Channel									
Frequency (MHz)				648000	650000	652000	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	19.83	19.80	19.73	20.5	0.0	
Channel									
Frequency (MHz)				647334	650000	652698	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	19.83	19.86	19.83	20.5	0.0	
Channel									
Frequency (MHz)				647000	650000	653924	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	19.76	19.72	19.81	20.5	0.0	
Channel									
Frequency (MHz)				647000	650000	653924	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	19.72	19.78	19.80	20.5	0.0	

Par27Q PC3 n78_Ant1 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	PQ2 BPSK	1	1	18.63					
100	PQ2 BPSK	1	137	19.38			20.5	0.0	
100	PQ2 BPSK	1	271	18.72					
100	PQ2 BPSK	135	0	19.18			20.5	0.0	
100	PQ2 BPSK	135	69	19.41			20.5	0.0	
100	PQ2 BPSK	135	138	19.33			20.5	0.0	
100	PQ2 BPSK	270	0	19.22					
100	QPSK	1	1	18.53					
100	QPSK	1	137	19.52			20.5	0.0	
100	QPSK	1	271	18.60					
100	QPSK	135	0	19.36			20.5	0.0	
100	QPSK	135	69	19.44			20.5	0.0	
100	QPSK	135	138	19.33			20.5	0.0	
100	QPSK	270	0	19.47					
100	16QAM	1	1	19.18			20.5	0.0	
100	64QAM	1	1	19.17			20.5	0.0	
100	256QAM	1	1	18.32			19.0	1.5	
Channel									
Frequency (MHz)				633000	633534	633666	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	19.31	19.40	19.38	20.5	0.0	
Channel									
Frequency (MHz)				3460.02	3500.01	3510	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	19.35	19.47	19.20	20.5	0.0	
Channel									
Frequency (MHz)				3485.01	3500.01	3514.98	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	95	19.32	19.31	19.25	20.5	0.0	
Channel									
Frequency (MHz)				632000	633334	634666	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	19.44	19.36	19.20	20.5	0.0	
Channel									
Frequency (MHz)				631668	633534	635000	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	19.35	19.40	19.35	20.5	0.0	
Channel									
Frequency (MHz)				3475.01	3500.01	3529.98	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	19.38	19.48	19.22	20.5	0.0	
Channel									
Frequency (MHz)				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	18.38	19.30	19.23	20.5	0.0	
Channel									
Frequency (MHz)				3467.5	3500.01	3542.49	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	19.31	19.48	19.37	20.5	0.0	
Channel									
Frequency (MHz)				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	19.29	19.32	19.30	20.5	0.0	

PC2 n78_Ant1 DSI1&2 Default power										
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)		
Channel				650000						
Frequency (MHz)				3750						
100	Pl2 BPSK	1	1		21.51					
100	Pl2 BPSK	1	137		22.59		23.5	0.0		
100	Pl2 BPSK	1	271		21.81		23.0	0.5		
100	Pl2 BPSK	135	0		22.01		23.0	0.5		
100	Pl2 BPSK	135	69		22.57		23.5	0.0		
100	Pl2 BPSK	135	138		22.07		23.0	0.5		
100	Pl2 BPSK	270	0		22.07					
100	QPSK	1	1		21.46					
100	QPSK	1	137		22.00		23.5	0.0		
100	QPSK	1	271		21.91					
100	QPSK	135	0		21.48		22.5	1.0		
100	QPSK	135	69		22.58		23.5	0.0		
100	QPSK	135	138		21.57		22.5	1.0		
100	QPSK	270	0		21.58					
100	16QAM	1	1		21.48		22.5	1.0		
100	64QAM	1	1		20.14		21.0	2.5		
100	256QAM	1	1		19.23		19.0	4.5		
Channel				649968	650000	650034	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3745.02	3750	3755.01				
90	QPSK	1	123		22.52	22.41	22.39	23.5	0.0	
Channel				649334	650000	650668	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3740.01	3750	3760.02				
80	QPSK	1	109		22.55	22.40	22.30	23.5	0.0	
Channel				649000	650000	651000	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3735	3750	3765				
70	QPSK	1	95		22.49	22.57	22.35	23.5	0.0	
Channel				648668	650000	651334	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3730.02	3750	3770.02				
60	QPSK	1	81		22.58	22.39	22.40	23.5	0.0	
Channel				648334	650000	651668	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3725.01	3750	3775.02				
50	QPSK	1	67		22.55	22.43	22.28	23.5	0.0	
Channel				648000	650000	652000	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3720	3750	3785				
40	QPSK	1	53		22.42	22.39	22.45	23.5	0.0	
Channel				647334	650000	652668	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3710.01	3750	3790.02				
20	QPSK	1	26		22.40	22.57	22.38	23.5	0.0	
Channel				647168	650000	652834	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3707.52	3750	3792.51				
15	QPSK	1	19		22.43	22.50	22.47	23.5	0.0	
Channel				647000	650000	653000	Tune-up limit (dbm)	MPR (db)		
Frequency (MHz)				3705	3750	3795				
10	QPSK	1	12		22.59	22.48	22.40	23.5	0.0	

Par27Q PC2 n78_Ant1 DSI1&2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)	
Channel				633334					
Frequency (MHz)				3500.01					
100	Pl2 BPSK	1	1		21.65				
100	Pl2 BPSK	1	137		22.30		23.5	0.0	
100	Pl2 BPSK	1	271		21.52				
100	Pl2 BPSK	135	0		21.79		23.0	0.5	
100	Pl2 BPSK	135	69		22.35		23.5	0.0	
100	Pl2 BPSK	135	138		21.79		23.0	0.5	
100	Pl2 BPSK	270	0		21.90				
100	QPSK	1	1		21.58				
100	QPSK	1	137		22.44		23.5	0.0	
100	QPSK	1	271		21.52				
100	QPSK	135	0		21.23		22.5	1.0	
100	QPSK	135	69		22.41		23.5	0.0	
100	QPSK	135	138		21.48		22.5	1.0	
100	QPSK	270	0		21.35				
100	16QAM	1	1		21.33		22.5	1.0	
100	64QAM	1	1		19.82		21.0	2.5	
100	256QAM	1	1		18.11		19.0	4.5	
Channel				633000	633334	633668	Tune-up limit	MPR	
Frequency (MHz)				3495	3500.01	3504.99	(dbm)	(db)	
90	QPSK	1	123		22.20	22.42	22.07	23.5	0.0
Channel				632668	633334	634000	Tune-up limit	MPR	
Frequency (MHz)				3490.02	3500.01	3510	(dbm)	(db)	
80	QPSK	1	109		22.33	22.25	22.18	23.5	0.0
Channel				632334	633334	634332	Tune-up limit	MPR	
Frequency (MHz)				3485.01	3500.01	3514.98	(dbm)	(db)	
70	QPSK	1	95		22.31	22.28	22.05	23.5	0.0
Channel				632000	633334	634668	Tune-up limit	MPR	
Frequency (MHz)				3480	3500.01	3519.96	(dbm)	(db)	
60	QPSK	1	81		22.34	22.41	22.25	23.5	0.0
Channel				631668	633334	635000	Tune-up limit	MPR	
Frequency (MHz)				3475.02	3500.01	3525	(dbm)	(db)	
50	QPSK	1	67		22.33	22.40	22.11	23.5	0.0
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dbm)	(db)	
40	QPSK	1	53		22.39	22.43	22.17	23.5	0.0
Channel				630998	633334	635668	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dbm)	(db)	
20	QPSK	1	26		22.33	22.30	22.08	23.5	0.0
Channel				630668	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dbm)	(db)	
15	QPSK	1	19		22.24	22.35	22.08	23.5	0.0
Channel				630334	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3448.01	3500.01	3544.98	(dbm)	(db)	
10	QPSK	1	12		22.36	22.28	22.19	23.5	0.0

n7_Ant2 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	23.07	23.17	23.09	24.5	0.0	
20	PI/2 BPSK	1	26	23.15	23.19	23.18			
20	PI/2 BPSK	1	49	23.07	23.15	23.14			
20	PI/2 BPSK	25	0	22.71	22.66	22.66	24.0	0.5	
20	PI/2 BPSK	25	13	23.12	23.12	23.01	24.5	0.0	
20	PI/2 BPSK	25	26	22.58	22.67	22.56	24.0	0.5	
20	PI/2 BPSK	50	0	22.62	22.71	22.76			
20	QPSK	1	1	23.05	23.26	23.12			
20	QPSK	1	26	23.16	23.31	23.25	24.5	0.0	
20	QPSK	1	49	23.09	23.16	23.01			
20	QPSK	25	0	22.05	22.12	22.01	23.5	1.0	
20	QPSK	25	13	23.03	23.11	23.08	24.5	0.0	
20	QPSK	25	26	22.09	22.11	22.10	23.5	1.0	
20	QPSK	50	0	22.04	22.10	22.02			
20	16QAM	1	1	22.03	22.06	22.05	23.5	1.0	
20	64QAM	1	1	20.69	20.78	20.80	22.0	2.5	
20	256QAM	1	1	18.81	18.85	18.89	20.0	4.5	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	22.81	23.11	23.01	24.5	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	22.91	23.11	23.03	24.5	0.0	

n66_Ant2 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346000	349000	352000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1730	1745	1760			
40	PI/2 BPSK	1	1	22.85	22.88	22.87	24.5	0.0	
40	PI/2 BPSK	1	53	23.23	23.19	23.13			
40	PI/2 BPSK	1	104	22.75	22.88	22.93			
40	PI/2 BPSK	50	0	22.23	22.34	22.21	24.0	0.5	
40	PI/2 BPSK	50	28	23.01	23.04	22.93	24.0	0.5	
40	PI/2 BPSK	50	56	22.37	22.36	22.31			
40	PI/2 BPSK	100	0	22.44	22.41	22.39			
40	QPSK	1	1	22.87	23.08	22.86	24.5	0.0	
40	QPSK	1	53	23.14	23.27	23.16			
40	QPSK	1	104	22.86	22.94	22.83			
40	QPSK	50	0	21.89	21.92	21.97	23.5	1.0	
40	QPSK	50	28	22.95	23.02	22.77	24.5	0.0	
40	QPSK	50	56	21.83	21.90	21.95	23.5	1.0	
40	QPSK	100	0	21.73	21.93	21.92			
40	16QAM	1	1	21.84	21.99	21.84	23.5	1.0	
40	64QAM	1	1	20.51	20.48	20.38	22.0	2.5	
40	256QAM	1	1	18.46	18.41	18.38	20.0	4.5	
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	QPSK	1	39	22.98	23.11	22.96	24.5	0.0	
Channel				344500	349000	353500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	QPSK	1	32	22.86	23.05	23.06	24.5	0.0	
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	26	22.92	23.10	22.93	24.5	0.0	
Channel				343500	349000	354500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	19	23.06	23.08	22.96	24.5	0.0	
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	12	22.96	23.12	22.95	24.5	0.0	



n38_Ant2 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	518000	518096		
Frequency (MHz)				2590.02	2595	2599.98		
40	PI/2 BPSK	1	1	23.38	23.39	23.32		
40	PI/2 BPSK	1	33	23.79	23.79	23.82	24.0	0.0
40	PI/2 BPSK	1	104	23.42	23.46	23.51		
40	PI/2 BPSK	50	0	23.08	23.16	23.04	23.5	0.5
40	PI/2 BPSK	50	26	23.59	23.64	23.58	24.0	0.0
40	PI/2 BPSK	50	58	22.96	23.01	23.00		
40	PI/2 BPSK	100	0	23.09	23.08	23.00	23.5	0.5
40	QPSK	1	1	23.47	23.54	23.51		
40	QPSK	1	53	23.83	23.90	23.86	24.0	0.0
40	QPSK	1	104	23.47	23.47	23.32		
40	QPSK	50	0	22.48	22.52	22.51	23.0	1.0
40	QPSK	50	26	23.36	23.32	23.51	24.0	0.0
40	QPSK	50	58	22.53	22.57	22.50	23.0	1.0
40	QPSK	100	0	22.34	22.46	22.37		
40	16QAM	1	1	22.36	22.48	22.35	23.0	1.0
40	16QAM	1	1	20.98	20.99	20.93	21.5	2.5
40	256QAM	1	1	19.16	19.13	19.09	19.5	4.5
Channel				516000	518000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2560	2595	2610	24.0	0.0
20	QPSK	1	26	23.57	23.62	23.66	24.0	0.0
Channel				515002	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49	24.0	0.0
15	QPSK	1	19	23.55	23.62	23.65	24.0	0.0
Channel				515004	518000	525096	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2578.02	2595	2614.98	24.0	0.0
10	QPSK	1	12	23.68	23.77	23.89	24.0	0.0

PC3 n41_Ant2 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				505002	518998	529000		
Frequency (MHz)				2546.01	2592.99	2640		
100	PI/2 BPSK	1	1	22.73	22.72	22.70		
100	PI/2 BPSK	1	137	23.18	23.12	23.16	24.0	0.0
100	PI/2 BPSK	1	271	23.10	23.05	23.00		
100	PI/2 BPSK	135	0	23.10	23.08	23.08	24.0	0.0
100	PI/2 BPSK	135	69	23.07	23.13	23.12	24.0	0.0
100	PI/2 BPSK	135	138	23.23	23.17	23.24	24.0	0.0
100	PI/2 BPSK	270	0	23.25	23.19	23.25	24.0	0.0
100	QPSK	1	1	23.01	22.99	23.08		
100	QPSK	1	137	23.24	23.33	23.26	24.0	0.0
100	QPSK	1	271	23.06	23.01	23.02		
100	QPSK	135	0	23.11	23.26	23.17	24.0	0.0
100	QPSK	135	69	23.21	23.07	22.93	24.0	0.0
100	QPSK	135	138	23.26	23.24	23.23	24.0	0.0
100	QPSK	270	0	23.21	23.26	23.06		
100	16QAM	1	1	22.75	22.76	22.76	24.0	0.0
100	16QAM	1	1	22.69	22.73	22.75	24.0	0.0
100	256QAM	1	1	22.31	22.24	22.20	22.5	1.5
Channel				508000	518998	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2541	2592.99	2644.98	24.0	0.0
90	QPSK	1	123	23.24	23.25	23.11	24.0	0.0
Channel				507204	518998	529000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536.02	2592.99	2649.99	24.0	0.0
80	QPSK	1	109	23.12	23.28	23.01	24.0	0.0
Channel				505000	518998	531996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2554	2592.99	2659.98	24.0	0.0
60	QPSK	1	81	23.26	23.29	23.16	24.0	0.0
Channel				504204	518998	532998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2521.02	2592.99	2664.99	24.0	0.0
50	QPSK	1	67	23.10	23.13	23.08	24.0	0.0
Channel				503502	518998	534000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670	24.0	0.0
40	QPSK	1	53	23.23	23.34	23.32	24.0	0.0
Channel				502200	518998	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98	24.0	0.0
30	QPSK	1	39	23.13	23.23	23.23	24.0	0.0
Channel				501204	518998	535998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99	24.0	0.0
20	QPSK	1	26	23.22	23.22	23.32	24.0	0.0
Channel				500700	518998	536996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48	24.0	0.0
15	QPSK	1	19	23.34	23.29	23.21	24.0	0.0
Channel				500202	518998	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685	24.0	0.0
10	QPSK	1	12	23.28	23.28	23.29	24.0	0.0

PC2 n41_Ant2 DSI1&2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				505002	518998	529000		
Frequency (MHz)				2546.01	2592.99	2640		
100	PI/2 BPSK	1	1	23.22	23.28	23.32		
100	PI/2 BPSK	1	137	23.61	23.68	23.78	25.0	0.0
100	PI/2 BPSK	1	271	23.57	23.60	23.52		
100	PI/2 BPSK	135	0	23.60	23.70	23.70	24.5	0.5
100	PI/2 BPSK	135	69	23.73	23.71	23.70	25.0	0.0
100	PI/2 BPSK	135	138	23.99	24.02	23.96	24.5	0.5
100	PI/2 BPSK	270	0	23.72	23.78	23.81	24.5	0.5
100	QPSK	1	1	23.57	23.51	23.50		
100	QPSK	1	137	23.99	24.16	23.95	25.0	0.0
100	QPSK	1	271	23.80	23.73	23.68		
100	QPSK	135	0	23.82	23.84	23.82	24.0	1.0
100	QPSK	135	69	23.90	23.93	23.87	25.0	0.0
100	QPSK	135	138	23.91	23.91	23.86	24.0	1.0
100	QPSK	270	0	23.76	23.85	23.77		
100	16QAM	1	1	23.43	23.35	23.28	24.0	1.0
100	16QAM	1	1	22.36	22.33	22.26	22.5	2.5
100	256QAM	1	1	20.27	20.29	20.30	20.5	4.5
Channel				508000	518998	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2541	2592.99	2644.98	24.0	0.0
90	QPSK	1	123	23.96	24.14	23.67	25.0	0.0
Channel				507204	518998	532998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536.02	2592.99	2649.99	24.0	0.0
80	QPSK	1	109	23.87	23.96	23.51	25.0	0.0
Channel				505000	518998	531996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2554	2592.99	2659.98	24.0	0.0
60	QPSK	1	81	23.95	23.91	23.49	25.0	0.0
Channel				504204	518998	532998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2521.02	2592.99	2664.99	24.0	0.0
50	QPSK	1	67	23.95	24.02	24.03	25.0	0.0
Channel				503502	518998	534000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670	24.0	0.0
40	QPSK	1	53	23.87	24.00	23.68	25.0	0.0
Channel				502200	518998	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98	24.0	0.0
30	QPSK	1	39	23.94	23.96	23.65	25.0	0.0
Channel				501204	518998	535998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99	24.0	0.0
20	QPSK	1	26	23.86	23.91	23.61	25.0	0.0
Channel				500700	518998	535996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48	24.0	0.0
15	QPSK	1	19	23.87	23.98	23.68	25.0	0.0
Channel				500202	518998	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685	25.0	0.0
10	QPSK	1	12	23.84	23.91	23.62	25.0	0.0



PC3 n77_Ant3 DSI1&2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	Pl2 BPSK	1	1	20.52	20.53	20.51			
100	Pl2 BPSK	1	137	21.56	21.55	21.38	22.5	0.0	
100	Pl2 BPSK	1	271	20.53	20.58	20.58			
100	Pl2 BPSK	136	0	21.42	21.49	21.48	22.5	0.0	
100	Pl2 BPSK	136	69	21.37	21.42	21.37	22.5	0.0	
100	Pl2 BPSK	136	138	21.29	21.44	21.44	22.5	0.0	
100	Pl2 BPSK	270	0	21.49	21.50	21.52			
100	QPSK	1	1	20.59	20.52	20.59			
100	QPSK	1	137	21.49	21.58	21.54	22.5	0.0	
100	QPSK	1	271	20.59	20.59	20.56			
100	QPSK	136	0	21.38	21.49	21.30	22.5	0.0	
100	QPSK	136	69	21.37	21.50	21.31	22.5	0.0	
100	QPSK	136	138	21.31	21.43	21.45	22.5	0.0	
100	QPSK	270	0	21.43	21.52	21.37			
100	16QAM	1	1	21.12	21.31	21.32	22.5	0.0	
100	64QAM	1	1	21.30	21.41	21.22	22.5	0.0	
100	256QAM	1	1	19.90	20.09	19.94	21.0	1.5	
Channel									
Frequency (MHz)				648668	656000	662334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	123	21.49	21.57	21.33	22.5	0.0	
Channel									
Frequency (MHz)				648334	656000	662068	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	109	21.37	21.37	21.32	22.5	0.0	
Channel									
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	96	21.27	21.55	21.45	22.5	0.0	
Channel									
Frequency (MHz)				648668	656000	663334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3723.01	3840	3953.02			
60	QPSK	1	81	21.32	21.45	21.44	22.5	0.0	
Channel									
Frequency (MHz)				648334	656000	660668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3723.01	3840	3953.02			
50	QPSK	1	67	21.33	21.47	21.33	22.5	0.0	
Channel									
Frequency (MHz)				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	21.48	21.50	21.56	22.5	0.0	
Channel									
Frequency (MHz)				647334	656000	661668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	26	21.47	21.42	21.34	22.5	0.0	
Channel									
Frequency (MHz)				647168	656000	661334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	21.35	21.37	21.36	22.5	0.0	
Channel									
Frequency (MHz)				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	21.47	21.50	21.52	22.5	0.0	

Par27Q PC3 n77_Ant3 DSI1&2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)					3500.01				
100	Pl2 BPSK	1	1		20.59				
100	Pl2 BPSK	1	137		21.19		22.5	0.0	
100	Pl2 BPSK	1	271		20.63				
100	Pl2 BPSK	136	0		21.24		22.5	0.0	
100	Pl2 BPSK	136	69		21.10		22.5	0.0	
100	Pl2 BPSK	136	138		21.12		22.5	0.0	
100	Pl2 BPSK	270	0		21.16				
100	QPSK	1	1		20.58				
100	QPSK	1	137		21.36		22.5	0.0	
100	QPSK	1	271		20.59				
100	QPSK	136	0		21.09		22.5	0.0	
100	QPSK	136	69		21.16		22.5	0.0	
100	QPSK	136	138		21.08		22.5	0.0	
100	QPSK	270	0		21.14				
100	16QAM	1	1		20.92		22.5	0.0	
100	64QAM	1	1		21.62		22.5	0.0	
100	256QAM	1	1		19.75		21.0	1.5	
Channel									
Frequency (MHz)				633000	633334	633668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3495	3500.01	3504.98			
90	QPSK	1	123	21.16	21.31	21.19	22.5	0.0	
Channel									
Frequency (MHz)				632668	633334	634000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	109	21.26	21.26	21.33	22.5	0.0	
Channel									
Frequency (MHz)				632334	633334	633332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3514.98			
70	QPSK	1	96	21.15	21.23	21.12	22.5	0.0	
Channel									
Frequency (MHz)				632000	633334	634668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3480	3500.01	3519.98			
60	QPSK	1	81	21.29	21.27	21.24	22.5	0.0	
Channel									
Frequency (MHz)				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	67	21.16	21.27	21.27	22.5	0.0	
Channel									
Frequency (MHz)				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3525.98			
40	QPSK	1	53	21.07	21.32	21.28	22.5	0.0	
Channel									
Frequency (MHz)				630668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	26	21.08	21.18	21.14	22.5	0.0	
Channel									
Frequency (MHz)				630300	633334	635168	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.52	3500.01	3522.49			
15	QPSK	1	19	21.23	21.26	21.21	22.5	0.0	
Channel									
Frequency (MHz)				630334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3544.98			
10	QPSK	1	12	21.19	21.19	21.18	22.5	0.0	

PC2 n77_Ant3 DSI1 For SA / DSI2 For SA&NSA									
Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	Pl2 BPSK	1	1	21.55	21.58	21.50			
100	Pl2 BPSK	1	137	24.12	24.22	24.15	25.5	0.0	
100	Pl2 BPSK	1	271	23.59	23.58	23.56			
100	Pl2 BPSK	136	0	24.09	24.11	24.04	25.0	0.5	
100	Pl2 BPSK	136	69	24.37	24.54	24.38	25.5	0.0	
100	Pl2 BPSK	136	138	24.05	24.09	24.06	25.0	0.5	
100	Pl2 BPSK	270	0	24.00	24.11	24.00			
100	QPSK	1	1	21.56	21.55	21.57			
100	QPSK	1	137	24.53	24.56	24.57	25.5	0.0	
100	QPSK	1	271	23.51	23.62	23.62			
100	QPSK	136	0	23.60	23.58	23.44	25.4	1.0	
100	QPSK	136	69	24.36	24.44	24.26	25.5	0.0	
100	QPSK	136	138	23.34	23.35	23.44	25.4	1.0	
100	QPSK	270	0	23.53	23.58	23.57			
100	16QAM	1	1	21.39	21.42	21.43	24.5	1.0	
100	16QAM	1	1	21.03	21.01	21.00	24.0	2.5	
100	256QAM	1	1	20.03	20.03	20.04	21.0	4.5	
Channel									
Frequency (MHz)				64968	65800	662334	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	24.52	24.54	24.50	25.0	0.0	
Channel									
Frequency (MHz)				64933	65800	66268	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	24.46	24.37	24.38	25.5	0.0	
Channel									
Frequency (MHz)				3795	3840	3945			
70	QPSK	1	95	24.37	24.54	24.21	25.5	0.0	
Channel									
Frequency (MHz)				64968	65800	66334	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	90	24.37	24.40	24.02	25.0	0.0	
Channel									
Frequency (MHz)				64833	65900	66368	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	24.34	24.36	24.21	25.5	0.0	
Channel									
Frequency (MHz)				64800	65800	66400	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	24.30	24.40	24.21	25.0	0.0	
Channel									
Frequency (MHz)				64734	65800	66468	Tune-up limit (dBm)	MPR (dB)	
30	QPSK	1	26	24.35	24.47	24.38	25.5	0.0	
Channel									
Frequency (MHz)				3707.52	3840	3972.51	(dBm)	(dB)	
15	QPSK	1	19	24.53	24.38	24.25	25.5	0.0	
Channel									
Frequency (MHz)				64700	65800	66500	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	24.48	24.39	24.38	25.5	0.0	



Par27Q PC2 n77_Ant3 DSI1 For SA / DSI2 For SA&NSA Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	
Channel				633334	633334		
Frequency (MHz)				3500.01			
100	PQ2 BPSK	1	1	23.51			
100	PQ2 BPSK	1	137	23.91			25.5
100	PQ2 BPSK	1	271	23.53			
100	PQ2 BPSK	135	0	23.53			25.0
100	PQ2 BPSK	135	69	24.39			25.5
100	PQ2 BPSK	135	138	23.99			25.0
100	PQ2 BPSK	270	0	23.81			
100	QPSK	1	1	23.58			
100	QPSK	1	137	24.17			25.5
100	QPSK	1	271	23.59			
100	QPSK	135	0	23.40			24.5
100	QPSK	135	69	24.22			25.0
100	QPSK	135	138	23.24			
100	QPSK	270	0	23.38			24.5
100	16QAM	1	1	23.24			24.5
100	64QAM	1	1	21.79			23.0
100	256QAM	1	1	19.83			21.0
Channel				633000	633334	633966	
Frequency (MHz)				3495	3500.01	3504.99	
90	QPSK	1	123	24.31	24.44	24.35	25.5
Channel				632688	633334	634000	
Frequency (MHz)				3460.02	3500.01	3510	
80	QPSK	1	109	24.34	24.25	24.40	25.5
Channel				3465.01	3500.01	3514.98	
Frequency (MHz)				3465.01	3500.01	3514.98	
70	QPSK	1	95	24.26	24.35	24.36	25.5
Channel				632000	633334	634666	
Frequency (MHz)				3460	3500.01	3516.99	
60	QPSK	1	81	24.33	24.38	24.33	25.5
Channel				631668	633334	635000	
Frequency (MHz)				3475.02	3500.01	3505	
50	QPSK	1	67	24.25	24.35	24.37	25.5
Channel				631334	633334	635332	
Frequency (MHz)				3470.01	3500.01	3509.98	
40	QPSK	1	53	24.24	24.25	24.41	25.5
Channel				630968	633334	635000	
Frequency (MHz)				3460.02	3500.01	3540	
20	QPSK	1	26	24.27	24.39	24.38	25.5
Channel				630500	633334	635166	
Frequency (MHz)				3457.5	3500.01	3542.49	
15	QPSK	1	19	24.14	24.43	24.28	25.5
Channel				630334	633334	635332	
Frequency (MHz)				3465.01	3500.01	3544.98	
10	QPSK	1	12	24.23	24.35	24.43	25.5

PC3 n78_Ant3 DSI1&2 Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	
Channel					630000		
Frequency (MHz)					3750		
100	PQ2 BPSK	1	1		20.53		
100	PQ2 BPSK	1	137		21.63		22.5
100	PQ2 BPSK	1	271		20.92		
100	PQ2 BPSK	135	0		21.58		22.5
100	PQ2 BPSK	135	69		21.70		22.5
100	PQ2 BPSK	135	138		21.68		22.5
100	PQ2 BPSK	270	0		21.70		
100	QPSK	1	1		20.55		
100	QPSK	1	137		21.71		22.5
100	QPSK	1	271		20.50		
100	QPSK	135	0		21.62		22.5
100	QPSK	135	69		21.69		22.5
100	QPSK	135	138		21.63		22.5
100	QPSK	270	0		21.60		22.5
100	16QAM	1	1		21.67		22.5
100	64QAM	1	1		21.53		22.5
100	256QAM	1	1		20.95		21.0
Channel				649668	650000	650334	
Frequency (MHz)				3745.02	3750	3755.01	
90	QPSK	1	123	21.50	21.63	21.68	22.5
Channel				649334	650000	650668	
Frequency (MHz)				3740.01	3750	3760.02	
80	QPSK	1	109	21.45	21.58	21.59	22.5
Channel				649000	650000	651000	
Frequency (MHz)				3735	3750	3765	
70	QPSK	1	95	21.43	21.52	21.48	22.5
Channel				648668	650000	651334	
Frequency (MHz)				3730.02	3750	3770.01	
60	QPSK	1	81	21.51	21.51	21.53	22.5
Channel				648334	650000	651668	
Frequency (MHz)				3725.01	3750	3775.02	
50	QPSK	1	67	21.50	21.52	21.57	22.5
Channel				648000	650000	652000	
Frequency (MHz)				3720	3750	3780	
40	QPSK	1	53	21.64	21.54	21.49	22.5
Channel				647634	650000	652568	
Frequency (MHz)				3710.01	3750	3790.02	
20	QPSK	1	26	21.60	21.65	21.61	22.5
Channel				647168	650000	653034	
Frequency (MHz)				3707.52	3750	3792.51	
15	QPSK	1	19	21.56	21.63	21.53	22.5
Channel				647000	650000	653000	
Frequency (MHz)				3705	3750	3795	
10	QPSK	1	12	21.59	21.54	21.48	22.5

Par27Q PC3 n78_Ant3 DSI1&2 Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	
Channel					633334		
Frequency (MHz)					3500.01		
100	PQ2 BPSK	1	1		20.53		
100	PQ2 BPSK	1	137		21.46		22.5
100	PQ2 BPSK	1	271		20.82		
100	PQ2 BPSK	135	0		21.51		22.5
100	PQ2 BPSK	135	69		21.66		22.5
100	PQ2 BPSK	135	138		21.65		22.5
100	PQ2 BPSK	270	0		21.59		
100	QPSK	1	1		20.52		
100	QPSK	1	137		21.68		22.5
100	QPSK	1	271		20.83		
100	QPSK	135	0		21.48		22.5
100	QPSK	135	69		21.52		22.5
100	QPSK	135	138		21.50		22.5
100	QPSK	270	0		21.39		22.5
100	16QAM	1	1		21.67		22.5
100	64QAM	1	1		21.49		22.5
100	256QAM	1	1		19.99		21.0
Channel				633000	633334	633966	
Frequency (MHz)				3495	3500.01	3504.99	
90	QPSK	1	123	21.57	21.67	21.50	22.5
Channel				632688	633334	634000	
Frequency (MHz)				3460.02	3500.01	3510	
80	QPSK	1	109	21.48	21.60	21.33	22.5
Channel				632314	633334	634332	
Frequency (MHz)				3465.01	3500.01	3514.98	
70	QPSK	1	95	21.43	21.50	21.35	22.5
Channel				632000	633334	634666	
Frequency (MHz)				3460	3500.01	3516.99	
60	QPSK	1	81	21.43	21.61	21.31	22.5
Channel				631668	633334	635000	
Frequency (MHz)				3475.02	3500.01	3505	
50	QPSK	1	67	21.43	21.55	21.33	22.5
Channel				631334	633334	635332	
Frequency (MHz)				3470.01	3500.01	3509.98	
40	QPSK	1	53	21.44	21.54	21.51	22.5
Channel				630968	633334	635000	
Frequency (MHz)				3460.02	3500.01	3540	
20	QPSK	1	26	21.51	21.63	21.38	22.5
Channel				630500	633334	635166	
Frequency (MHz)				3457.5	3500.01	3542.49	
15	QPSK	1	19	21.52	21.49	21.35	22.5
Channel				630334	633334	635332	
Frequency (MHz)				3465.01	3500.01	3544.98	
10	QPSK	1	12	21.54	21.53	21.52	22.5

PC2 n78_Ant3 DSI1 For SA / DSI2 For SA&NSA									
Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Mode Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	Pl2 BPSK	1	1		23.55			25.5	0.0
100	Pl2 BPSK	1	137		24.29				
100	Pl2 BPSK	1	271		23.97				
100	Pl2 BPSK	135	0		24.00		25.0		
100	Pl2 BPSK	135	69		24.36		25.5	0.0	
100	Pl2 BPSK	135	138		24.21		25.0	0.5	
100	Pl2 BPSK	270	0		24.11				
100	QPSK	1	1		23.55			25.5	0.0
100	QPSK	1	137		24.54				
100	QPSK	1	271		23.95				
100	QPSK	135	0		23.50		24.5		
100	QPSK	135	69		24.54		25.5	0.0	
100	QPSK	135	138		23.05		24.5	1.0	
100	QPSK	270	0		23.61				
100	16QAM	1	1		23.52		24.5	1.0	
100	64QAM	1	1		21.96		23.0	2.5	
100	256QAM	1	1		20.00		21.0	4.5	
Channel				648668	650000	650334	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)	
90	QPSK	1	123	24.40	24.50	24.40	25.5	0.0	
Channel				648334	650000	650668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3740.01	3750	3760.02	(dBm)	(dB)	
80	QPSK	1	109	24.49	24.49	24.38	25.5	0.0	
Channel				648000	650000	651000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3735	3750	3765	(dBm)	(dB)	
70	QPSK	1	95	24.49	24.43	24.33	25.5	0.0	
Channel				648668	650000	651334	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3730.02	3750	3770.02	(dBm)	(dB)	
60	QPSK	1	81	24.48	24.51	24.36	25.5	0.0	
Channel				648334	650000	651668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3725.01	3750	3785.02	(dBm)	(dB)	
50	QPSK	1	67	24.46	24.53	24.50	25.5	0.0	
Channel				648000	650000	652000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3720	3750	3785	(dBm)	(dB)	
40	QPSK	1	53	24.53	24.58	24.42	25.5	0.0	
Channel				647334	650000	652668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3710.01	3750	3790.02	(dBm)	(dB)	
20	QPSK	1	26	24.29	24.51	24.45	25.5	0.0	
Channel				647168	650000	652334	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3707.52	3750	3792.51	(dBm)	(dB)	
15	QPSK	1	19	24.42	24.53	24.39	25.5	0.0	
Channel				647000	650000	653000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)	
10	QPSK	1	12	24.47	24.41	24.46	25.5	0.0	

Par27Q PC2 n78_Ant3 DSI1 For SA / DSI2 For SA&NSA Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Mode Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334					
Frequency (MHz)				3500.01					
100	Pl2 BPSK	1	1		23.39			25.5	0.0
100	Pl2 BPSK	1	137		24.30				
100	Pl2 BPSK	1	271		23.73				
100	Pl2 BPSK	135	0		23.77		25.0		
100	Pl2 BPSK	135	69		24.40		25.5	0.0	
100	Pl2 BPSK	135	138		23.99		25.0	0.5	
100	Pl2 BPSK	270	0		23.99				
100	QPSK	1	1		23.44			25.5	0.0
100	QPSK	1	137		24.66				
100	QPSK	1	271		23.77				
100	QPSK	135	0		23.32		24.5		
100	QPSK	135	69		24.34		25.5	0.0	
100	QPSK	135	138		23.97		24.5	1.0	
100	QPSK	270	0		23.41				
100	16QAM	1	1		23.20		24.5	1.0	
100	64QAM	1	1		21.75		23.0	2.5	
100	256QAM	1	1		19.85		21.0	4.5	
Channel				633000	633334	633668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3495	3500.01	3504.69	(dBm)	(dB)	
90	QPSK	1	123	24.42	24.40	24.44	25.5	0.0	
Channel				632668	633334	634000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3490.02	3500.01	3510	(dBm)	(dB)	
80	QPSK	1	109	24.46	24.40	24.38	25.5	0.0	
Channel				632334	633334	634332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3485.01	3500.01	3514.68	(dBm)	(dB)	
70	QPSK	1	95	24.42	24.41	24.41	25.5	0.0	
Channel				632000	633334	634668	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3480	3500.01	3519.66	(dBm)	(dB)	
60	QPSK	1	81	24.42	24.43	24.38	25.5	0.0	
Channel				631668	633334	635000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3475.02	3500.01	3525	(dBm)	(dB)	
50	QPSK	1	67	24.44	24.44	24.36	25.5	0.0	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3470.01	3500.01	3529.68	(dBm)	(dB)	
40	QPSK	1	53	24.39	24.29	24.42	25.5	0.0	
Channel				630998	633334	636000	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	24.42	24.34	24.43	25.5	0.0	
Channel				630200	633334	636168	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	24.33	24.41	24.42	25.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR	
Frequency (MHz)				3455.01	3500.01	3544.68	(dBm)	(dB)	
10	QPSK	1	12	24.24	24.19	24.43	25.5	0.0	



n5_Ant4 DSI1&2&4 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)
Channel				166300	167300	167600	24.0	0.0
Frequency (MHz)				834	836.5	839		
20	PI2 BPSK	1	1	22.78	22.83	22.78		
20	PI2 BPSK	1	26	22.81	22.91	22.88		
20	PI2 BPSK	1	49	22.71	22.79	22.73	23.5	0.5
20	PI2 BPSK	25	0	22.35	22.38	22.32	24.0	0.0
20	PI2 BPSK	25	13	22.83	22.87	22.82	24.0	0.5
20	PI2 BPSK	25	26	22.29	22.38	22.40	23.5	0.5
20	PI2 BPSK	50	0	22.35	22.34	22.35	24.0	0.0
20	QPSK	1	1	22.80	22.84	22.91		
20	QPSK	1	26	22.94	22.95	22.96		
20	QPSK	1	49	22.71	22.83	22.89		
20	QPSK	25	0	21.73	21.86	21.51	23.0	1.0
20	QPSK	25	13	22.81	22.86	22.80	24.0	0.0
20	QPSK	25	26	21.87	21.85	21.83	23.0	1.0
20	QPSK	50	0	21.76	21.89	21.76	23.0	1.0
20	16QAM	1	1	21.72	21.83	21.86		
20	64QAM	1	1	20.43	20.36	20.33		
20	256QAM	1	1	18.34	18.47	18.45		
Channel				166300	167300	168300	Tune-up limit (dbm)	MPR (db)
Frequency (MHz)				831.5	836.5	841.5	24.0	0.0
15	QPSK	1	19	22.62	22.67	22.63		
Channel				169300	167300	169300	Tune-up limit (dbm)	MPR (db)
Frequency (MHz)				829	836.5	844	24.0	0.0
10	QPSK	1	12	22.68	22.64	22.61		

n7_Ant4 DS2 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				502000	507000	512000	24.0	0.0
Frequency (MHz)				2510	2535	2560		
20	PI2 BPSK	1	1	22.76	22.82	22.74		
20	PI2 BPSK	1	26	22.76	22.87	22.80		
20	PI2 BPSK	1	49	22.81	22.82	22.76	23.5	0.5
20	PI2 BPSK	25	0	22.43	22.38	22.44	24.0	0.0
20	PI2 BPSK	25	13	22.84	22.84	22.82	24.0	0.0
20	PI2 BPSK	25	26	22.29	22.29	22.30	23.5	0.5
20	PI2 BPSK	50	0	22.32	22.41	22.36	24.0	0.0
20	QPSK	1	1	22.74	22.87	22.75		
20	QPSK	1	26	22.77	22.85	22.83		
20	QPSK	1	49	22.75	22.83	22.84		
20	QPSK	25	0	21.79	21.84	21.85	23.0	1.0
20	QPSK	25	13	22.83	22.85	22.80	24.0	0.0
20	QPSK	25	26	21.85	21.83	21.83	23.0	1.0
20	QPSK	50	0	21.73	21.84	21.85	23.0	1.0
20	16QAM	1	1	21.89	21.85	21.81		
20	64QAM	1	1	20.39	20.33	20.28		
20	256QAM	1	1	18.35	18.30	18.18		
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	24.0	0.0
15	QPSK	1	19	22.52	22.77	22.80		
Channel				511000	512000	513000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565	24.0	0.0
10	QPSK	1	12	22.50	22.82	22.83		


n66_Ant4 DSI2&4 Default power								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				346000	348000	350000	24.0	0.0
Frequency (MHz)				1730	1745	1760		
40	PI2 BPSK	1	1	22.49	22.57	22.54	24.0	0.0
40	PI2 BPSK	1	53	22.56	22.63	22.59		
40	PI2 BPSK	1	104	22.48	22.60	22.59		
40	PI2 BPSK	50	0	21.91	22.02	22.04	23.5	0.5
40	PI2 BPSK	50	26	22.45	22.54	22.39	24.0	0.0
40	PI2 BPSK	50	56	21.85	22.03	21.88	23.5	0.5
40	PI2 BPSK	100	0	22.07	22.06	22.03	24.0	0.0
40	QPSK	1	1	22.43	22.61	22.48		
40	QPSK	1	53	22.45	22.64	22.51		
40	QPSK	1	104	22.43	22.43	22.55		
40	QPSK	50	0	21.49	21.58	21.59	23.0	1.0
40	QPSK	50	26	22.50	22.54	22.38	24.0	0.0
40	QPSK	50	56	21.47	21.47	21.39	23.0	1.0
40	QPSK	100	0	21.38	21.51	21.47	23.0	1.0
40	16QAM	1	1	21.39	21.54	21.56		
40	64QAM	1	1	19.94	20.05	20.05		
40	256QAM	1	1	18.05	18.06	17.91		
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1725	1745	1765	24.0	0.0
30	QPSK	1	39	22.19	22.46	22.27		
Channel				344000	349000	353500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1722.5	1745	1767.5	24.0	0.0
25	QPSK	1	32	22.13	22.49	22.38		
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1720	1745	1770	24.0	0.0
20	QPSK	1	26	22.15	22.58	22.41		
Channel				343000	349000	354500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1717.5	1745	1772.5	24.0	0.0
15	QPSK	1	19	22.22	22.56	22.31		
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1715	1745	1775	24.0	0.0
10	QPSK	1	12	22.14	22.61	22.38		



n38_Ant4 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	518000	518996	25.5	0.0	
Frequency (MHz)				2580.02	2595	2599.98			
40	PQ2 BPSK	1	1	23.66	23.66	23.68			
40	PQ2 BPSK	1	53	24.08	24.15	24.12			
40	PQ2 BPSK	1	104	23.59	23.64	23.52	25.0	0.5	
40	PQ2 BPSK	50	0	23.29	23.25	23.29			
40	PQ2 BPSK	50	28	23.68	23.66	23.63			
40	PQ2 BPSK	50	56	23.29	23.27	23.35			
40	PQ2 BPSK	100	0	23.18	23.25	23.24	25.5	0.0	
40	QPSK	1	1	23.58	23.70	23.59			
40	QPSK	1	53	24.06	24.15	24.08			
40	QPSK	1	104	23.64	23.66	23.56			
40	QPSK	50	0	22.68	22.76	22.63	24.5	1.0	
40	QPSK	50	28	23.66	23.68	23.67			
40	QPSK	50	56	22.58	22.69	22.69			
40	QPSK	100	0	22.64	22.66	22.62			
40	16QAM	1	1	22.88	22.86	22.81	24.5	1.0	
40	64QAM	1	1	21.14	21.21	21.15			
40	256QAM	1	1	19.19	19.22	19.14			
Channel				518000	519000	522000		Tune-up limit (dBm)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	26	23.91	24.00	23.79		25.5	
Channel				515004	515000	522000			
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	19	23.96	24.11	23.82		25.5	
Channel				515004	519000	522996			
Frequency (MHz)				2577.02	2595	2614.98			
10	QPSK	1	12	23.83	24.15	23.91		25.5	

PC3 n41_Ant4 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509002	518598	528000	24.5	0.0	
Frequency (MHz)				2546.01	2592.99	2640			
100	PQ2 BPSK	1	1	22.82	22.77	22.84			
100	PQ2 BPSK	1	137	22.90	22.96	22.86			
100	PQ2 BPSK	1	271	22.90	22.89	22.97	24.5	0.0	
100	PQ2 BPSK	135	0	22.95	22.99	23.06			
100	PQ2 BPSK	135	69	23.15	23.13	23.13			
100	PQ2 BPSK	135	138	23.03	23.06	23.13			
100	PQ2 BPSK	270	0	22.98	23.06	23.06	24.5	0.0	
100	QPSK	1	1	22.96	23.04	23.10			
100	QPSK	1	137	23.30	23.45	23.27			
100	QPSK	1	271	22.56	22.58	22.64			
100	QPSK	135	0	22.90	22.95	23.02	24.5	0.0	
100	QPSK	135	69	23.01	23.17	23.07			
100	QPSK	135	138	22.96	23.11	23.08			
100	QPSK	270	0	22.93	23.00	22.96			
100	16QAM	1	1	22.58	22.64	22.63	24.5	0.0	
100	64QAM	1	1	22.55	22.58	22.61			
100	256QAM	1	1	21.62	21.67	21.64			
Channel				508000	518598	528996		Tune-up limit (dBm)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	23.33	23.35	23.18		24.5	
Channel				507204	511599	525996			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	109	23.29	23.41	23.35		24.5	
Channel				505200	518598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	81	23.29	23.28	23.25		24.5	
Channel				504204	518598	532996			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	67	23.29	23.40	23.21		24.5	
Channel				503202	511599	535000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	53	23.24	23.40	23.30		24.5	
Channel				502200	518598	534996			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	23.37	23.34	23.31		24.5	
Channel				501204	518598	535996			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	26	23.37	23.38	23.21		24.5	
Channel				500202	511599	535996			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	19	23.37	23.36	23.23		24.5	
Channel				500202	518598	537000			
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	12	23.28	23.36	23.24		24.5	

PC2 n41_Ant4 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				508002	518598	530000	25.5	0.0	
Frequency (MHz)				2546.01	2592.99	2640			
100	PQ2 BPSK	1	1	23.53	23.52	23.50			
100	PQ2 BPSK	1	137	24.01	23.99	23.97			
100	PQ2 BPSK	1	271	23.93	23.88	23.92	25.5	0.0	
100	PQ2 BPSK	135	0	23.80	23.83	23.84			
100	PQ2 BPSK	135	69	23.98	24.00	24.08			
100	PQ2 BPSK	135	138	24.07	24.10	24.07			
100	PQ2 BPSK	270	0	24.04	23.97	23.92	25.5	0.0	
100	QPSK	1	1	23.59	23.54	23.54			
100	QPSK	1	137	24.12	24.25	24.16			
100	QPSK	1	271	23.90	23.96	24.04			
100	QPSK	135	0	23.93	23.93	23.88	25.5	0.0	
100	QPSK	135	69	24.11	24.21	24.19			
100	QPSK	135	138	24.10	24.09	24.13			
100	QPSK	270	0	24.09	24.19	24.13			
100	16QAM	1	1	23.71	23.76	23.77	25.5	0.0	
100	64QAM	1	1	23.72	23.68	23.74			
100	256QAM	1	1	23.56	23.52	23.53			
Channel				508000	518598	528996			
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	23.83	24.16	23.92	25.5		
Channel				507204	511599	529996			
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	109	23.88	24.11	23.83	25.5		
Channel				505200	518598	531996			
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	81	23.82	24.09	23.81	25.5		
Channel				504204	518598	532996			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	67	23.76	24.13	23.95	25.5		
Channel				503202	511599	535000			
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	53	23.86	24.11	24.05	25.5		
Channel				502200	518598	534996			
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	23.98	24.23	23.89	25.5		
Channel				501204	518598	535996			
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	26	23.64	24.08	23.96	25.5		
Channel				500202	511599	535996			
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	19	23.88	24.10	23.98	25.5		
Channel				500202	511599	537000			
Frequency (MHz)				2503.5	2592.99	2685			
10	QPSK	1	12	23.86	24.05	23.99	25.5		
Channel				500201	511599	537000			
Frequency (MHz)				2503.5	2592.99	2685			



Par27Q PC3 n77_Ant5 DS16 Default power								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low On / Freq	Power Middle On / Freq	Power High On / Freq	Turn-up limit (dBm)	MPR (dB)
Channel								
	Frequency (MHz)				3560.01			
100	PQ2 BPSK	1	1	20.12				
100	PQ2 BPSK	1	137	20.20			22.0	0.0
100	PQ2 BPSK	135	0	20.90			22.0	0.0
100	PQ2 BPSK	135	69	21.08			22.0	0.0
100	PQ2 BPSK	135	138	20.99			22.0	0.0
100	PQ2 BPSK	276	0	20.21				
100	QPSK	1	1	20.79				
100	QPSK	1	137	21.03			22.0	0.0
100	QPSK	1	271	20.18				
100	QPSK	135	0	20.92			22.0	0.0
100	QPSK	135	69	20.89			22.0	0.0
100	QPSK	135	138	20.92			22.0	0.0
100	QPSK	270	0	20.78				
100	16QAM	1	1	20.81			22.0	0.0
100	64QAM	1	1	20.81			22.0	0.0
100	256QAM	1	1	19.50			22.5	1.5
Channel								
	Frequency (MHz)			633000	633534	633966	Turn-up limit (dBm)	MPR (dB)
90	QPSK	1	123	20.46	3560.01	3564.99	22.0	0.0
Channel								
	Frequency (MHz)			632668	633234	634000	Turn-up limit (dBm)	MPR (dB)
80	QPSK	1	109	20.91	3560.02	35610	22.0	0.0
Channel								
	Frequency (MHz)			634851	635334	635148	Turn-up limit (dBm)	MPR (dB)
70	QPSK	1	95	20.74	20.86	20.94	22.0	0.0
Channel								
	Frequency (MHz)			632000	632334	634996	Turn-up limit (dBm)	MPR (dB)
60	QPSK	1	81	20.92	21.05	20.99	22.0	0.0
Channel								
	Frequency (MHz)			631668	633334	635000	Turn-up limit (dBm)	MPR (dB)
50	QPSK	1	67	20.88	21.06	20.83	22.0	0.0
Channel								
	Frequency (MHz)			631334	633534	635332	Turn-up limit (dBm)	MPR (dB)
40	QPSK	1	53	20.77	20.97	20.81	22.0	0.0
Channel								
	Frequency (MHz)			632668	633234	634000	Turn-up limit (dBm)	MPR (dB)
30	QPSK	1	26	20.93	20.90	20.82	22.0	0.0
Channel								
	Frequency (MHz)			634575	635001	3542.49	Turn-up limit (dBm)	MPR (dB)
15	QPSK	1	19	20.91	21.00	20.87	22.0	0.0
Channel								
	Frequency (MHz)			633034	633334	636332	Turn-up limit (dBm)	MPR (dB)
10	QPSK	1	12	20.74	21.04	21.01	22.0	0.0

PC2 n77_Ant5 DSI2 Default power								
RFW [MHz]	Modulation	RB Size	RF Offset	Power Low Ch. Freq. 650000	Power Middle Ch. Freq. 656000	Power High Ch. Freq. 662000	Turn-up time (dtm)	MPR (dB)
Channel								
	Frequency (MHz)			3755	3840	3930		
100	PQ2 BPSK	1	1	23.03	23.14	23.01		
100	PQ2 BPSK	1	137	24.03	24.10	23.88	25.0	0.0
100	PQ2 BPSK	1	271	23.02	23.08	23.00		
100	PQ2 BPSK	135	0	23.59	23.61	23.58	24.5	0.5
100	PQ2 BPSK	135	69	23.58	23.60	23.57	25.0	0.0
100	PQ2 BPSK	135	135	23.31	23.53	23.31	24.5	0.5
100	PQ2 BPSK	270	0	23.51	23.58	23.45		
100	QPSK	1	1	23.15	23.18	23.08		
100	QPSK	1	137	24.02	24.05	23.86	25.0	0.0
100	QPSK	1	271	23.08	23.18	23.06		
100	QPSK	135	0	23.01	23.08	23.10	24.0	1.0
100	QPSK	135	69	24.06	24.11	23.97	25.0	0.0
100	QPSK	135	135	23.04	23.05	22.93		
100	QPSK	270	0	22.89	23.00	22.87		
100	16QAM	1	1	22.84	23.01	22.97		
100	16QAM	1	137	23.53	23.49	23.17	22.5	2.5
100	256QAM	1	1	19.47	19.47	19.34	20.5	4.5
Channel								
	Frequency (MHz)			64668	65600	662334	Turn-up time (dtm)	MPR (dB)
90	QPSK	1	123	24.53	24.46	23.74	25.0	0.0
Channel								
	Frequency (MHz)			645334	656000	662608	Turn-up time (dtm)	MPR (dB)
80	QPSK	1	109	24.07	24.13	23.91	25.0	0.0
Channel								
	Frequency (MHz)			645500	656000	662003	Turn-up time (dtm)	MPR (dB)
70	QPSK	1	95	3735	3840	3945		
70	QPSK	1	95	23.96	24.14	23.82	25.0	0.0
Channel								
	Frequency (MHz)			64668	656000	663334	Turn-up time (dtm)	MPR (dB)
60	QPSK	1	392	3702	3840	3960	25.0	0.0
60	QPSK	1	81	24.16	24.09	23.77	25.0	0.5
Channel								
	Frequency (MHz)			645334	656000	663668	Turn-up time (dtm)	MPR (dB)
50	QPSK	1	67	24.07	24.06	23.95	25.0	0.0
Channel								
	Frequency (MHz)			648000	656000	664000	Turn-up time (dtm)	MPR (dB)
40	QPSK	1	53	3725	3840	3960		
40	QPSK	1	53	23.43	23.40	23.30	25.0	0.0
40	QPSK	1	53	647334	656000	664668	Turn-up time (dtm)	MPR (dB)
40	QPSK	1	53	3715.01	3840	3970.02		
Channel								
	Frequency (MHz)			647812	656000	663512	Turn-up time (dtm)	MPR (dB)
20	QPSK	1	26	24.09	23.96	23.76	25.0	0.0
Channel								
	Frequency (MHz)			3707.52	3840	3972.51		
15	QPSK	1	19	23.96	24.14	23.85	25.0	0.0
Channel								
	Frequency (MHz)			647000	656000	665000	Turn-up time (dtm)	MPR (dB)
10	QPSK	1	12	24.01	24.00	23.94	25.0	0.0



Par27Q PC2 n77_Ant5 DSI2 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)	
Channel					3500.01				
Frequency (MHz)					23.03				
100	Pi2 BPSK	1	1		23.02		25.0	0.0	
100	Pi2 BPSK	1	137		23.82		25.0	0.0	
100	Pi2 BPSK	1	271		23.02		25.0	0.0	
100	Pi2 BPSK	135	0		23.38		24.5	0.5	
100	Pi2 BPSK	135	66		23.95		25.0	0.0	
100	Pi2 BPSK	135	138		23.37		24.5	0.5	
100	Pi2 BPSK	270	0		23.34		24.5	0.5	
100	QPSK	1	1		23.06				
100	QPSK	1	137		23.96		25.0	0.0	
100	QPSK	1	271		23.03				
100	QPSK	135	0		22.77		24.0	1.0	
100	QPSK	135	66		22.88		25.0	0.0	
100	QPSK	135	138		22.81		24.0	1.0	
100	QPSK	270	0		22.88		24.0	1.0	
100	16QAM	1	1		22.75		24.0	1.5	
100	64QAM	1	1		21.40		22.5	2.5	
100	256QAM	1	1		19.26		20.5	4.5	
Channel				633000	633334	633666	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3495	3500.01	3504.99			
90	QPSK	1	123		23.44	23.82	23.07	25.0	0.0
Channel				632668	633334	634000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	109		23.04	23.84	23.78	25.0	0.0
Channel				633000	633334	633666	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3485.01	3500.01	3514.98			
70	QPSK	1	95		23.45	23.83	23.80	25.0	0.0
Channel				632000	633334	634666	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3480	3500.01	3519.99			
60	QPSK	1	81		23.81	23.74	23.68	25.0	0.0
Channel				631668	633334	635000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	67		23.99	23.90	23.68	25.0	0.0
Channel				631334	633334	635332	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3470.01	3500.01	3529.98			
40	QPSK	1	53		23.44	23.84	23.84	25.0	0.0
Channel				632668	633334	635000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3490.02	3500.01	3540			
20	QPSK	1	26		23.57	23.78	23.77	25.0	0.0
Channel				632000	633334	635666	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3497.5	3500.01	3542.49			
15	QPSK	1	19		23.41	23.90	23.67	25.0	0.0
Channel				630334	633334	636332	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3465.01	3500.01	3544.99			
10	QPSK	1	12		23.48	23.84	23.60	25.0	0.0

PC3 n78_Ant5 DSI2 Default power										
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				650000	650000					
Frequency (MHz)				3750						
100	Pi2 BPSK	1	1		20.06					
100	Pi2 BPSK	1	137		21.24		22.0	0.0		
100	Pi2 BPSK	1	271		20.46					
100	Pi2 BPSK	135	0		21.02		22.0	0.0		
100	Pi2 BPSK	135	66		21.11		22.0	0.0		
100	Pi2 BPSK	135	138		21.22		22.0	0.0		
100	Pi2 BPSK	270	0		21.12					
100	QPSK	1	1		20.11					
100	QPSK	1	137		21.27		22.0	0.0		
100	QPSK	1	271		20.49					
100	QPSK	135	0		21.12		22.0	0.0		
100	QPSK	135	66		21.26		22.0	0.0		
100	QPSK	135	138		21.25		22.0	0.0		
100	QPSK	270	0		21.20					
100	16QAM	1	1		21.05		22.0	0.0		
100	64QAM	1	1		21.16		22.0	0.0		
100	256QAM	1	1		19.77		20.5	1.5		
Channel				649668	650000	650334	Tune-up limit	MPR		
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)		
90	QPSK	1	123		21.13	21.17	21.07	22.0	0.0	
Channel				649334	650000	650666	Tune-up limit	MPR		
Frequency (MHz)				3740.01	3750	3760.02	(dBm)	(dB)		
80	QPSK	1	109		21.14	21.12	21.01	22.0	0.0	
Channel				649000	650000	651000	Tune-up limit	MPR		
Frequency (MHz)				3735	3750	3765	(dBm)	(dB)		
70	QPSK	1	95		21.14	21.26	21.16	22.0	0.0	
Channel				648668	650000	651334	Tune-up limit	MPR		
Frequency (MHz)				3730.02	3750	3763.03	(dBm)	(dB)		
60	QPSK	1	81		21.12	21.22	21.10	22.0	0.0	
Channel				648334	650000	651668	Tune-up limit	MPR		
Frequency (MHz)				3725.01	3750	3769.02	(dBm)	(dB)		
50	QPSK	1	67		20.97	21.19	20.99	22.0	0.0	
Channel				648000	650000	652000	Tune-up limit	MPR		
Frequency (MHz)				3720	3750	3785	(dBm)	(dB)		
40	QPSK	1	53		21.10	21.21	21.06	22.0	0.0	
Channel				647334	650000	652666	Tune-up limit	MPR		
Frequency (MHz)				3710.01	3750	3790.02	(dBm)	(dB)		
20	QPSK	1	26		20.99	21.12	21.10	22.0	0.0	
Channel				647168	650000	653154	Tune-up limit	MPR		
Frequency (MHz)				3707.52	3750	3792.53	(dBm)	(dB)		
15	QPSK	1	19		21.08	21.26	21.20	22.0	0.0	
Channel				647000	650000	653000	Tune-up limit	MPR		
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)		
10	QPSK	1	12		21.02	21.16	20.99	22.0	0.0	

Par27Q PC3 n78_Ant5 DSI2 Default power										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)		
Channel				633000	633334		Tune-up limit	MPR		
Frequency (MHz)					3500.01					
100	Pi2 BPSK	1	1		20.26					
100	Pi2 BPSK	1	137		21.00		22.0		0.0	
100	Pi2 BPSK	1	271		20.32					
100	Pi2 BPSK	135	0		20.75		22.0		0.0	
100	Pi2 BPSK	135	66		21.00		22.0		0.0	
100	Pi2 BPSK	135	138		20.98		22.0		0.0	
100	Pi2 BPSK	270	0		21.04					
100	QPSK	1	1		20.11					
100	QPSK	1	137		21.15		22.0		0.0	
100	QPSK	1	271		20.21					
100	QPSK	135	0		20.90		22.0		0.0	
100	QPSK	135	66		21.13		22.0		0.0	
100	QPSK	135	138		21.12		22.0		0.0	
100	QPSK	270	0		20.88					
100	16QAM	1	1		20.92		22.0		0.0	
100	64QAM	1	1		20.66		22.0		0.0	
100	256QAM	1	1		19.97		20.5		1.5	
Channel				633000	633334	633666	Tune-up limit	MPR		
Frequency (MHz)				3495	3500.01	3504.99	(dbm)	(db)		
90	QPSK	1	123		21.07	21.01	21.01	22.0	0.0	
Channel				632668	633334	634000	Tune-up limit	MPR		
Frequency (MHz)				3490.02	3500.01	3510	(dbm)	(db)		
80	QPSK	1	109		21.10	21.06	20.97	22.0	0.0	
Channel				632000	633334	634666	Tune-up limit	MPR		
Frequency (MHz)				3485.01	3500.01	3514.98	(dbm)	(db)		
70	QPSK	1	95		20.94	21.15	21.14	22.0	0.0	
Channel				631668	633334	634996	Tune-up limit	MPR		
Frequency (MHz)				632534	633334	634996	(dbm)	(db)		
60	QPSK	1	81		21.10	21.05	21.05	22.0	MPR	
Channel				631668	633334	635000	Tune-up limit	MPR		
Frequency (MHz)				3485.02	3500.01	3520.02	(dbm)	(db)		
50	QPSK	1	67		20.96	21.02	21.13	22.0	0.0	
Channel				631334	633334	635332	Tune-up limit	MPR		
Frequency (MHz)				3470.01	3500.01	3520.08	(dbm)	(db)		
40	QPSK	1	53		21.06	21.00	21.00	22.0	MPR	
Channel				630668	633334	635800	Tune-up limit	MPR		
Frequency (MHz)				3490.02	3500.01	3540	(dbm)	(db)		
20	QPSK	1	26		21.13	21.14	21.11	22.0	0.0	
Channel				630334	633334	636332	Tune-up limit	MPR		
Frequency (MHz)				3485.01	3500.01	3544.88	(dbm)	(db)		
15	QPSK	1	19		20.93	21.06	21.07	22.0	0.0	
Channel				630334	633334	636332	Tune-up limit	MPR		
Frequency (MHz)				3485.01	3500.01	3544.88	(dbm)	(db)		
10	QPSK	1	12		20.91	21.14	20.98	22.0	0.0	

PC2 n78_Ant5 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648000	650000	652000			
Frequency (MHz)				3750	3750	3750			
100	Pl2 BPSK	1	1	23.02					
100	Pl2 BPSK	1	137	24.10			25.0	0.0	
100	Pl2 BPSK	1	271	23.29					
100	Pl2 BPSK	135	0	23.45			24.5	0.5	
100	Pl2 BPSK	135	69	24.10			25.0	0.0	
100	Pl2 BPSK	135	138	23.49			24.5	0.5	
100	Pl2 BPSK	270	0	23.51					
100	QPSK	1	1	23.02					
100	QPSK	1	137	24.11			25.0	0.0	
100	QPSK	1	271	23.31					
100	QPSK	135	0	23.15			24.0	1.0	
100	QPSK	135	69	24.01			25.0	0.0	
100	QPSK	135	138	23.28			24.0	1.0	
100	QPSK	270	0	23.22					
100	16QAM	1	1	23.12			24.0	1.0	
100	64QAM	1	1	21.87			22.5	2.5	
100	256QAM	1	1	19.71			20.5	4.5	
Channel				648000	650000	650334	Tune-up limit	MPR	
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)	
90	QPSK	1	123	23.00	23.90	23.84	25.0	0.0	
Channel				648334	650000	650000	Tune-up limit	MPR	
Frequency (MHz)				3740.01	3750	3760.02	(dBm)	(dB)	
80	QPSK	1	109	23.85	24.04	23.98	25.0	0.0	
Channel				648000	650000	651000	Tune-up limit	MPR	
Frequency (MHz)				3735	3750	3765	(dBm)	(dB)	
70	QPSK	1	95	23.95	23.91	24.02	25.0	0.0	
Channel				648000	650000	651334	Tune-up limit	MPR	
Frequency (MHz)				3730.02	3750	3770.02	(dBm)	(dB)	
60	QPSK	1	81	23.79	24.01	23.91	25.0	0.0	
Channel				648334	650000	651668	Tune-up limit	MPR	
Frequency (MHz)				3725.01	3750	3775.02	(dBm)	(dB)	
50	QPSK	1	67	23.78	23.92	23.88	25.0	0.0	
Channel				648000	650000	650000	Tune-up limit	MPR	
Frequency (MHz)				3720	3750	3785	(dBm)	(dB)	
40	QPSK	1	53	23.88	24.07	23.92	25.0	0.0	
Channel				647334	650000	650000	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3750	3760.02	(dBm)	(dB)	
20	QPSK	1	26	23.92	23.97	23.99	25.0	0.0	
Channel				647168	650000	650235	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3750	3762.51	(dBm)	(dB)	
15	QPSK	1	19	23.98	23.97	23.96	25.0	0.0	
Channel				647000	650000	650000	Tune-up limit	MPR	
Frequency (MHz)				3705	3750	3765	(dBm)	(dB)	
10	QPSK	1	12	23.91	24.03	23.87	25.0	0.0	

Par27Q PC2 n78_Ant5 DSI2 Default power									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				630000	633334	633668			
Frequency (MHz)				3500.01	3500.01	3504.00			
100	Pl2 BPSK	1	1	23.21					
100	Pl2 BPSK	1	137	23.83			25.0	0.0	
100	Pl2 BPSK	1	271	23.07					
100	Pl2 BPSK	135	0	23.10			24.5	0.5	
100	Pl2 BPSK	135	69	23.86			25.0	0.0	
100	Pl2 BPSK	135	138	23.09			24.5	0.5	
100	Pl2 BPSK	270	0	23.31					
100	QPSK	1	1	23.03					
100	QPSK	1	137	23.85			25.0	0.0	
100	QPSK	1	271	23.06					
100	QPSK	135	0	22.91			24.0	1.0	
100	QPSK	135	69	23.61			25.0	0.0	
100	QPSK	135	138	22.94			24.0	1.0	
100	QPSK	270	0	22.95					
100	16QAM	1	1	22.83			24.0	1.0	
100	64QAM	1	1	21.53			22.5	2.5	
100	256QAM	1	1	19.33			20.5	4.5	
Channel				630000	633334	633668	Tune-up limit	MPR	
Frequency (MHz)				3495	3500.01	3504.00	(dBm)	(dB)	
90	QPSK	1	123	23.05	23.79	23.98	25.0	0.0	
Channel				630000	633334	634000	Tune-up limit	MPR	
Frequency (MHz)				3490.02	3500.01	3510	(dBm)	(dB)	
80	QPSK	1	109	23.61	23.82	23.83	25.0	0.0	
Channel				630000	633334	634332	Tune-up limit	MPR	
Frequency (MHz)				3485.01	3500.01	3514.68	(dBm)	(dB)	
70	QPSK	1	95	23.64	23.77	23.68	25.0	0.0	
Channel				630000	633334	634666	Tune-up limit	MPR	
Frequency (MHz)				3480	3500.01	3519.86	(dBm)	(dB)	
60	QPSK	1	81	23.55	23.80	23.86	25.0	0.0	
Channel				631668	633334	635000	Tune-up limit	MPR	
Frequency (MHz)				3475.02	3500.01	3525	(dBm)	(dB)	
50	QPSK	1	67	23.55	23.74	23.76	25.0	0.0	
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3528.98	(dBm)	(dB)	
40	QPSK	1	53	23.68	23.68	23.68	25.0	0.0	
Channel				630000	633334	635000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	23.71	23.68	23.82	25.0	0.0	
Channel				630000	633334	635166	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	23.64	23.74	23.70	25.0	0.0	
Channel				630334	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3448.01	3500.01	3544.88	(dBm)	(dB)	
10	QPSK	1	12	23.74	23.71	23.76	25.0	0.0	



PC3 n77_Ant8 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	650000	650000			
Frequency (MHz)				3750	3840	3930			
100	PI2 BPSK	1	1	18.13	18.34	18.16	20.0	0.0	
100	PI2 BPSK	1	137	19.04	19.16	19.06			
100	PI2 BPSK	1	271	18.06	18.03	18.11			
100	PI2 BPSK	135	0	19.01	19.00	18.89	20.0	0.0	
100	PI2 BPSK	135	69	18.99	19.18	19.17	20.0	0.0	
100	PI2 BPSK	135	138	18.98	19.12	19.00	20.0	0.0	
100	PI2 BPSK	270	0	18.97	18.16	19.17			
100	QPSK	1	1	18.06	18.02	18.11			
100	QPSK	1	137	19.14	19.10	19.18	20.0	0.0	
100	QPSK	1	271	18.06	18.02	18.03	20.0	0.0	
100	QPSK	135	0	18.96	19.02	19.04			
100	QPSK	135	69	18.99	19.16	19.02			
100	QPSK	135	138	18.86	19.03	18.92	20.0	0.0	
100	QPSK	270	0	19.01	19.07	19.02	20.0	0.0	
100	16QAM	1	1	18.87	19.09	19.09	20.0	0.0	
100	64QAM	1	1	19.06	18.16	19.09	20.0	0.0	
100	256QAM	1	1	17.58	17.77	17.67	18.5	1.5	
Channel				649668	650000	662334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	123	18.25	18.09	18.21	20.0	0.0	
Channel				645334	650000	652506	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	109	18.99	19.00	19.18	20.0	0.0	
Channel				649000	650000	663000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725	3840	3945			
70	QPSK	1	95	18.96	19.14	19.15	20.0	0.0	
Channel				648668	650000	663334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3730.02	3840	3950.01			
60	QPSK	1	81	19.02	19.16	19.10	20.0	0.0	
Channel				645334	650000	655006	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	67	19.09	19.09	19.15	20.0	0.0	
Channel				648000	650000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	19.06	19.14	18.99	20.0	0.0	
Channel				647334	650000	664668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	26	19.13	19.08	19.01	20.0	0.0	
Channel				645162	650000	655334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	19.07	19.09	19.03	20.0	0.0	
Channel				647000	650000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	18.93	18.99	19.04	20.0	0.0	

Par27Q PC3 n77_Ant8 DSI1&2&4 Default power										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel				633334						
Frequency (MHz)				3500.01						
100	PI2 BPSK	1	1	18.03			20.0	0.0		
100	PI2 BPSK	1	137	19.19						
100	PI2 BPSK	1	271	19.21						
100	PI2 BPSK	135	0	18.82			20.0	0.0		
100	PI2 BPSK	135	69	19.03			20.0	0.0		
100	PI2 BPSK	135	138	18.92			20.0	0.0		
100	PI2 BPSK	270	0	19.07						
100	QPSK	1	1	19.17						
100	QPSK	1	137	19.20			20.0	0.0		
100	QPSK	1	271	18.26						
100	QPSK	135	0	18.96			20.0	0.0		
100	QPSK	135	69	19.09			20.0	0.0		
100	QPSK	135	138	18.84			20.0	0.0		
100	QPSK	270	0	19.02						
100	16QAM	1	1	19.08			20.0	0.0		
100	64QAM	1	1	19.13			20.0	0.0		
100	256QAM	1	1	17.68			18.5	1.5		
Channel				633000	633334	633666	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3495	3500.01	3504.98				
90	QPSK	1	123	19.00	19.02	18.96	20.0	0.0		
Channel				632666	633334	633999	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3490.02	3500.01	3510				
80	QPSK	1	109	19.04	19.00	19.03	20.0	0.0		
Channel				632334	633334	634332	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3485.01	3500.01	3514.99				
70	QPSK	1	95	19.10	19.00	19.04	20.0	0.0		
Channel				632000	633334	634666	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3480	3500.01	3519.98				
60	QPSK	1	81	19.04	19.05	18.97	20.0	0.0		
Channel				631666	633334	635000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3475.02	3500.01	3525				
50	QPSK	1	67	18.99	19.05	19.12	20.0	0.0		
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3470.01	3500.01	3529.99				
40	QPSK	1	53	18.93	19.00	18.95	20.0	0.0		
Channel				630666	633334	636000	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3460.02	3500.01	3540				
20	QPSK	1	26	18.93	19.16	19.04	20.0	0.0		
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3457.52	3500.01	3542.49				
15	QPSK	1	19	18.90	19.12	19.04	20.0	0.0		
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)		
Frequency (MHz)				3455.01	3500.01	3544.98				
10	QPSK	1	12	19.02	19.01	19.07	20.0	0.0		

PC2 n77_Ant8 DSI1&2&4 Default power									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	650000	650000			
Frequency (MHz)				3750	3840	3930			
100	PI2 BPSK	1	1	21.05	21.12	21.13	23.0	0.0	
100	PI2 BPSK	1	137	22.09	22.11	22.07			
100	PI2 BPSK	1	271	21.02	21.12	21.10			
100	PI2 BPSK	135	0	21.56	21.60	21.44	22.5	0.5	
100	PI2 BPSK	135	69	21.87	22.08	21.95	23.0	0.0	
100	PI2 BPSK	135	138	21.54	21.58	21.41	22.5	0.5	
100	PI2 BPSK	270	0	21.34	21.54	21.34			
100	QPSK	1	1	21.01	21.11	21.03			
100	QPSK	1	137	21.98	22.14	22.08	23.0	0.0	
100	QPSK	1	271	21.05	21.11	21.12			
100	QPSK	135	0	20.96	21.17	21.07	22.0	1.0	
100	QPSK	135	69	21.96	22.03	21.90	23.0	0.0	
100	QPSK	135	138	20.99	21.09	20.95	22.0	1.0	
100	QPSK	270	0	21.00	21.15	21.12			
100	16QAM	1	1	20.99	21.06	20.89	22.0	1.0	
100	64QAM	1	1	19.82	19.78	19.69	20.5	2.5	
100	256QAM	1	1	17.70	17.73	17.71	18.5	4.5	
Channel				649668	650000	652334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01	23.0	0.0	
90	QPSK	1	123	21.96	21.96	21.94	23.0	0.0	
Channel				653334	655000	656668			
Frequency (MHz)				3740.01	3840	3940.02	23.0	0.0	
80	QPSK	1	109	21.81	22.02	21.86	23.0	0.0	
Channel				649000	650000	653000			
Frequency (MHz)				3735.34	3840	3945.35	23.0	0.0	
70	QPSK	1	95	21.92	22.03	21.98	23.0	0.0	
Channel				648668	650000	653334			
Frequency (MHz)				3730.02	3840	3950.01	23.0	0.0	
60	QPSK	1	81	21.76	22.03	21.82	23.0	0.0	
Channel				645334	650000	653668			
Frequency (MHz)				3725.01	3840	3955.02	23.0	0.0	
50	QPSK	1	67	21.96	22.04	21.88	23.0	0.0	
Channel				645000	650000	654000			
Frequency (MHz)				3720.34	3840	3960.35	23.0	0.0	
40	QPSK	1	53	21.99	21.94	21.99	23.0	0.0	
Channel				643734	650000	656668			
Frequency (MHz)				3710.01	3840	3970.02	23.0	0.0	
30	QPSK	1	26	21.98	21.90	22.04	23.0	0.0	
Channel				647168	650000	654334			
Frequency (MHz)				3707.52	3840	3972.51	23.0	0.0	
15	QPSK	1	19	21.95	21.95	21.91	23.0	0.0	
Channel				643000	650000	655000			
Frequency (MHz)				3705.34	3840	3975.35	23.0	0.0	
10	QPSK	1	12	21.89	22.00	21.88	23.0	0.0	
Channel				640000	650000	656000			

Par27Q PC2 n77_Ant8 DSI1&2&4 Default power

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334	3500.01				
Frequency (MHz)					3500.01				
100	PV2 BPSK	1	1		21.05				
100	PV2 BPSK	1	137		22.06		23.0	0.0	
100	PV2 BPSK	1	271		21.06				
100	PV2 BPSK	135	0		21.42		22.5	0.5	
100	PV2 BPSK	135	69		21.88		23.0	0.0	
100	PV2 BPSK	135	138		21.41		22.5	0.5	
100	PV2 BPSK	270	0		21.50		22.5	0.5	
100	QPSK	1	1		21.05				
100	QPSK	1	137		22.12		23.0	0.0	
100	QPSK	1	271		21.11				
100	QPSK	135	0		20.97		22.0	1.0	
100	QPSK	135	69		21.98		23.0	0.0	
100	QPSK	135	138		20.90		22.0	1.0	
100	QPSK	270	0		21.07				
100	16QAM	1	1		20.94		22.0	1.0	
100	64QAM	1	1		19.72		20.5	2.5	
100	256QAM	1	1		17.72		18.5	4.5	
Channel				633000	633334	633698	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3495	3500.01	3504.99	23.0	0.0	
90	QPSK	1	123		22.04	22.08	21.84	23.0	0.0
Channel				632662	633334	634000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510	23.0	0.0	
80	QPSK	1	109		22.02	22.05	22.00	23.0	0.0
Channel				632334	633334	634332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3514.99	23.0	0.0	
70	QPSK	1	95		21.99	22.08	21.84	23.0	0.0
Channel				632000	633334	634698	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3480	3500.01	3519.99	23.0	0.0	
60	QPSK	1	81		21.87	21.90	22.01	23.0	0.0
Channel				631662	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525	23.0	0.0	
50	QPSK	1	67		21.98	22.03	21.84	23.0	0.0
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3529.99	23.0	0.0	
40	QPSK	1	53		21.94	22.08	21.87	23.0	0.0
Channel				630998	633334	636000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540	23.0	0.0	
20	QPSK	1	26		22.01	21.97	22.01	23.0	0.0
Channel				630500	633334	636398	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49	23.0	0.0	
15	QPSK	1	19		21.90	21.93	21.90	23.0	0.0
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3544.99	23.0	0.0	
10	QPSK	1	12		21.84	22.03	22.02	23.0	0.0

PC3 n78_Ant8 DSI1&2&4 Default power

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000					
Frequency (MHz)				3750					
100	PV2 BPSK	1	1		18.09				
100	PV2 BPSK	1	137		19.18		20.0	0.0	
100	PV2 BPSK	1	271		18.27				
100	PV2 BPSK	135	0		19.05		20.0	0.0	
100	PV2 BPSK	135	69		19.08		20.0	0.0	
100	PV2 BPSK	135	138		19.08		20.0	0.0	
100	PV2 BPSK	270	0		19.08		20.0	0.0	
100	QPSK	1	1		18.06				
100	QPSK	1	137		19.19		20.0	0.0	
100	QPSK	1	271		18.28				
100	QPSK	135	0		19.06		20.0	0.0	
100	QPSK	135	69		19.12		20.0	0.0	
100	QPSK	135	138		19.11		20.0	0.0	
100	QPSK	270	0		19.11				
100	16QAM	1	1		19.17		20.0	0.0	
100	64QAM	1	1		19.11		20.0	0.0	
100	256QAM	1	1		17.73		18.5	1.5	
Channel				649668	650000	650334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3745.02	3750	3755.01	20.0	0.0	
90	QPSK	1	123		18.01	19.08	18.81	20.0	0.0
Channel				649334	650000	650668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3740.01	3750	3760.02	20.0	0.0	
80	QPSK	1	109		18.84	18.98	18.96	20.0	0.0
Channel				649000	650000	651000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3735	3750	3765	20.0	0.0	
70	QPSK	1	95		18.80	19.02	18.78	20.0	0.0
Channel				648668	650000	651334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3730.02	3750	3770.01	20.0	0.0	
60	QPSK	1	81		18.79	19.12	18.85	20.0	0.0
Channel				648334	650000	651668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3750	3775.02	20.0	0.0	
50	QPSK	1	67		18.94	19.11	18.91	20.0	0.0
Channel				648000	650000	652000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3750	3760	20.0	0.0	
40	QPSK	1	53		18.78	19.02	18.78	20.0	0.0
Channel				647334	650000	652668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3750	3790.02	20.0	0.0	
20	QPSK	1	26		18.76	19.03	18.99	20.0	0.0
Channel				647000	650000	653000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3750	3792.51	20.0	0.0	
15	QPSK	1	19		18.88	18.99	18.95	20.0	0.0
Channel				647000	650000	653000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3750	3795	20.0	0.0	
10	QPSK	1	12		18.82	19.06	18.90	20.0	0.0

Par27Q PC3 n78_Ant8 DSI1&2&4 Default power

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334	3500.01				
Frequency (MHz)				3500.01					
100	PV2 BPSK	1	1		18.05				
100	PV2 BPSK	1	137		19.02		20.0	0.0	
100	PV2 BPSK	1	271		18.17				
100	PV2 BPSK	135	0		18.93		20.0	0.0	
100	PV2 BPSK	135	69		19.04		20.0	0.0	
100	PV2 BPSK	135	138		18.91		20.0	0.0	
100	PV2 BPSK	270	0		18.92			0.0	
100	QPSK	1	1		18.06				
100	QPSK	1	137		19.17		20.0	0.0	
100	QPSK	1	271		18.15				
100	QPSK	135	0		18.98		20.0	0.0	
100	QPSK	135	69		19.00		20.0	0.0	
100	QPSK	135	138		18.97		20.0	0.0	
100	QPSK	270	0		19.06				
100	16QAM	1	1		19.15		20.0	0.0	
100	64QAM	1	1		18.93		20.0	0.0	
100	256QAM	1	1		17.75		18.5	1.5	
Channel				633000	633334	633698	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3485	3500.01	3504.99	20.0	0.0	
90	QPSK	1	123		18.87	19.14	18.85	20.0	0.0
Channel				632662	633334	634000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3480.02	3500.01	3510	20.0	0.0	
80	QPSK	1	109		19.04	19.15	19.05	20.0	0.0
Channel				632334	633334	634332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3514.99	20.0	0.0	
70	QPSK	1	95		18.85	19.04	19.10	20.0	0.0
Channel				632000	633334	634698	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3480	3500.01	3519.99	20.0	0.0	
60	QPSK	1	81		18.91	19.04	18.84	20.0	0.0
Channel				631662	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525	20.0	0.0	
50	QPSK	1	67		19.08	19.14	19.13	20.0	0.0
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3529.99	20.0	0.0	
40	QPSK	1	53		18.92	18.98	19.13	20.0	0.0
Channel				630998	633334	636000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540	20.0	0.0	
20	QPSK	1	26		19.05	19.00	18.94	20.0	0.0
Channel				630500	633334	636398	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49	20.0	0.0	
15	QPSK	1	19		19.01	19.03	19.08	20.0	0.0
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3544.99	20.0	0.0	
10	QPSK	1	12		19.03	19.06	18.92	20.0	0.0

PC2 n78_Ant8 DSI1&2&4 Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	MPR (dB)
Channel				650000	650000		
Frequency (MHz)				3750			
100	PI2 BPSK	1	1		21.08		
100	PI2 BPSK	1	137		22.10		
100	PI2 BPSK	1	231		21.11		23.0
100	PI2 BPSK	135	0		21.57		22.5 0.5
100	PI2 BPSK	135	69		22.02		23.0 0.0
100	PI2 BPSK	135	138		21.56		22.5 0.5
100	PI2 BPSK	270	0		21.53		
100	QPSK	1	1		21.09		
100	QPSK	1	137		22.11		23.0 0.0
100	QPSK	1	271		21.16		
100	QPSK	135	0		21.06		22.0 1.0
100	QPSK	135	69		22.05		23.0 0.0
100	QPSK	135	138		21.09		22.0 1.0
100	QPSK	270	0		21.12		
100	16QAM	1	1		21.07		22.0 1.0
100	64QAM	1	1		19.74		20.5 2.5
100	256QAM	1	1		17.77		18.5 4.5
Channel				649668	650000	650334	MPR (dB)
Frequency (MHz)				3745.02	3750	3755.01	
90	QPSK	1	123		21.77	21.89	23.0 0.0
Channel				649334	650000	650668	MPR (dB)
Frequency (MHz)				3740.01	3750	3760.02	
80	QPSK	1	109		21.70	21.77	23.0 0.0
Channel				649000	650000	651000	MPR (dB)
Frequency (MHz)				3735	3750	3765	
70	QPSK	1	95		21.80	21.93	23.0 0.0
Channel				648668	650000	651334	MPR (dB)
Frequency (MHz)				3730.02	3750	3770.01	
60	QPSK	1	81		21.83	22.05	23.0 0.0
Channel				648334	650000	651668	MPR (dB)
Frequency (MHz)				3725.01	3750	3775.02	
50	QPSK	1	67		21.85	21.97	23.0 0.0
Channel				648000	650000	652000	MPR (dB)
Frequency (MHz)				3720	3750	3780	
40	QPSK	1	53		21.85	21.91	23.0 0.0
Channel				647334	650000	652668	MPR (dB)
Frequency (MHz)				3716.01	3750	3790.02	
20	QPSK	1	26		21.85	22.08	23.0 0.0
Channel				647000	650000	653000	MPR (dB)
Frequency (MHz)				3707.52	3750	3792.51	
15	QPSK	1	19		21.74	22.05	23.0 0.0
Channel				647000	650000	653000	MPR (dB)
Frequency (MHz)				3705	3750	3795	
10	QPSK	1	12		21.73	22.10	23.0 0.0

Par27Q PC2 n78_Ant8 DSI1&2&4 Default power							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	MPR (dB)
Channel				633334	633334		
Frequency (MHz)				3600.01			
100	PI2 BPSK	1	1		21.08		
100	PI2 BPSK	1	137		21.90		
100	PI2 BPSK	1	271		21.07		23.0 0.0
100	PI2 BPSK	135	0		21.48		22.5 0.5
100	PI2 BPSK	135	69		21.80		23.0 0.0
100	PI2 BPSK	135	138		21.55		22.5 0.5
100	PI2 BPSK	270	0		21.40		
100	QPSK	1	1		21.14		
100	QPSK	1	137		21.08		23.0 0.0
100	QPSK	1	271		21.08		
100	QPSK	135	0		20.84		22.0 1.0
100	QPSK	135	69		21.05		23.0 0.0
100	QPSK	135	138		20.93		22.0 1.0
100	QPSK	270	0		20.99		
100	16QAM	1	1		20.91		22.0 1.0
100	64QAM	1	1		19.59		20.5 2.5
100	256QAM	1	1		17.78		18.5 4.5
Channel				633000	633334	633666	MPR (dB)
Frequency (MHz)				3495	3500.01	3504.99	
90	QPSK	1	123		21.83	21.85	23.0 0.0
Channel				632666	633334	634000	MPR (dB)
Frequency (MHz)				3490.02	3500.01	3510	
80	QPSK	1	109		21.79	21.96	23.0 0.0
Channel				632334	633334	634332	MPR (dB)
Frequency (MHz)				3485.01	3500.01	3514.98	
70	QPSK	1	95		21.85	21.91	23.0 0.0
Channel				632000	633334	634666	MPR (dB)
Frequency (MHz)				3480	3500.01	3519.99	
60	QPSK	1	81		21.91	21.94	23.0 0.0
Channel				631666	633334	635000	MPR (dB)
Frequency (MHz)				3475.02	3500.01	3525	
50	QPSK	1	67		21.92	21.91	23.0 0.0
Channel				631334	633334	635332	MPR (dB)
Frequency (MHz)				3470.01	3500.01	3529.98	
40	QPSK	1	53		21.95	21.92	23.0 0.0
Channel				630668	633334	636000	MPR (dB)
Frequency (MHz)				3460.02	3500.01	3540	
20	QPSK	1	26		21.80	21.92	23.0 0.0
Channel				630334	633334	636332	MPR (dB)
Frequency (MHz)				3457.5	3500.01	3542.49	
15	QPSK	1	19		21.85	21.80	23.0 0.0
Channel				630334	633334	636332	MPR (dB)
Frequency (MHz)				3455.01	3500.01	3544.98	
10	QPSK	1	12		21.81	21.84	23.0 0.0



Reduced power level for 5G NR
For DFT-15

n7_Ant0 DSI3 For SA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	P12 BPSK	1	1	15.88	15.97	16.08	17.5	0.0	
20	P12 BPSK	1	53	15.71	15.02	15.83			
20	P12 BPSK	1	104	15.74	15.98	16.02			
20	P12 BPSK	50	0	15.72	15.89	15.84	17.5	0.0	
20	P12 BPSK	50	28	15.79	16.06	15.93	17.5	0.0	
20	P12 BPSK	50	56	15.89	16.04	15.85	17.5	0.0	
20	P12 BPSK	100	0	15.78	15.93	16.03			
20	P12 BPSK	100	0	15.78	15.93	16.03			
20	QPSK	1	1	15.90	16.07	16.05	17.5	0.0	
20	QPSK	1	53	15.96	16.11	16.03			
20	QPSK	1	104	15.84	16.07	16.02			
20	QPSK	50	0	15.76	15.97	15.81	17.5	0.0	
20	QPSK	50	28	15.93	16.05	15.99	17.5	0.0	
20	QPSK	50	56	15.74	16.01	15.93	17.5	0.0	
20	QPSK	100	0	15.74	16.02	15.97	17.5	0.0	
20	16QAM	1	1	15.83	16.10	15.95			
20	64QAM	1	1	15.72	15.98	15.82			
20	256QAM	1	1	15.92	15.94	16.03	17.5	0.0	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	15.89	15.07	15.90	17.5	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	15.87	16.01	15.92	17.5	0.0	
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	15.86	16.06	15.91	17.5	0.0	

n7_Ant0 DSI3 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	P12 BPSK	1	1	12.82	12.96	13.00	14.5	0.0	
20	P12 BPSK	1	53	12.63	12.91	12.79			
20	P12 BPSK	1	104	12.76	12.91	12.91			
20	P12 BPSK	50	0	12.73	12.96	12.86	14.5	0.0	
20	P12 BPSK	50	28	13.01	12.98	12.98	14.5	0.0	
20	P12 BPSK	50	56	12.83	13.01	12.94	14.5	0.0	
20	P12 BPSK	100	0	12.94	12.92	13.11			
20	P12 BPSK	100	0	12.94	12.92	13.11			
20	QPSK	1	1	12.89	13.19	13.12	14.5	0.0	
20	QPSK	1	53	13.08	13.23	12.95			
20	QPSK	1	104	12.74	13.19	13.13			
20	QPSK	50	0	12.77	12.97	12.87	14.5	0.0	
20	QPSK	50	28	12.98	13.09	13.03	14.5	0.0	
20	QPSK	50	56	12.88	13.04	13.00	14.5	0.0	
20	QPSK	100	0	12.76	13.15	13.01	14.5	0.0	
20	16QAM	1	1	12.83	13.15	12.98			
20	64QAM	1	1	12.78	13.12	12.78			
20	256QAM	1	1	12.75	12.93	13.06	14.5	0.0	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	12.96	13.13	12.84	14.5	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	12.98	13.10	12.88	14.5	0.0	
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	12.92	13.05	12.81	14.5	0.0	

n7_Ant0 DSI2 For SA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	P12 BPSK	1	1	20.60	20.57	20.56	22.0	0.0	
20	P12 BPSK	1	53	20.34	20.51	20.36			
20	P12 BPSK	1	104	20.49	20.45	20.82			
20	P12 BPSK	50	0	20.41	20.79	20.68	22.0	0.0	
20	P12 BPSK	50	28	20.55	20.74	20.60	22.0	0.0	
20	P12 BPSK	50	56	20.26	20.75	20.35	22.0	0.0	
20	P12 BPSK	100	0	20.45	20.72	20.75			
20	P12 BPSK	100	0	20.45	20.72	20.75			
20	QPSK	1	1	20.39	20.78	20.89	22.0	0.0	
20	QPSK	1	53	20.61	20.94	20.65			
20	QPSK	1	104	20.32	21.01	20.69			
20	QPSK	50	0	20.42	20.68	20.49	22.0	0.0	
20	QPSK	50	28	20.70	20.94	20.64	22.0	0.0	
20	QPSK	50	56	20.38	20.61	20.92	22.0	0.0	
20	QPSK	100	0	20.14	20.89	20.64	22.0	0.0	
20	16QAM	1	1	20.47	20.84	20.57			
20	64QAM	1	1	19.77	19.88	19.86			
20	256QAM	1	1	17.73	17.96	17.78	19.0	3.0	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	20.46	20.99	20.75	22.0	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	20.70	20.90	20.73	22.0	0.0	
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	20.63	20.88	20.69	23.5	0.0	

n7_Ant0 DSI2 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	17.74	17.54	17.54	19.0	0.0	
20	PI/2 BPSK	1	53	17.43	17.50	17.48			
20	PI/2 BPSK	1	104	17.70	17.42	17.77			
20	PI/2 BPSK	50	0	17.56	17.60	17.44			
20	PI/2 BPSK	50	28	17.40	17.83	17.42	19.0	0.0	
20	PI/2 BPSK	50	56	17.56	17.76	17.48	19.0	0.0	
20	PI/2 BPSK	100	0	17.67	17.70	17.70			
20	QPSK	1	1	17.61	17.74	17.86	19.0	0.0	
20	QPSK	1	53	17.68	18.15	17.83			
20	QPSK	1	104	17.26	18.01	17.87			
20	QPSK	50	0	17.47	17.59	17.51			
20	QPSK	50	28	17.72	17.92	17.57	19.0	0.0	
20	QPSK	50	56	17.23	17.89	17.78	19.0	0.0	
20	QPSK	100	0	17.21	17.95	17.57			
20	16QAM	1	1	17.62	17.73	17.46	19.0	0.0	
20	64QAM	1	1	17.68	18.01	17.68	19.0	0.0	
20	256QAM	1	1	17.62	18.00	17.63	19.0	0.0	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	17.29	17.88	17.27	19.0	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	17.35	17.74	17.25	19.0	0.0	
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	17.41	17.94	17.26	20.5	0.0	



n38_Ant0 DS13 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	PI2 BPSK	1	1	14.09	14.00	14.01			
40	PI2 BPSK	1	53	14.56	14.41	14.47	15.0	0.0	
40	PI2 BPSK	1	104	13.98	13.89	13.91	15.0	0.0	
40	PI2 BPSK	50	0	14.00	13.91	13.89	15.0	0.0	
40	PI2 BPSK	50	28	14.04	13.90	14.05	15.0	0.0	
40	PI2 BPSK	50	56	14.51	14.33	14.39			
40	PI2 BPSK	100	0	14.02	13.83	13.85	15.0	0.0	
40	QPSK	1	1	14.04	14.07	14.15			
40	QPSK	1	53	14.39	14.57	14.40	15.0	0.0	
40	QPSK	1	104	14.02	13.98	14.09			
40	QPSK	50	0	13.92	14.05	13.88	15.0	0.0	
40	QPSK	50	28	14.20	14.33	14.29	15.0	0.0	
40	QPSK	50	56	14.00	13.88	13.99	15.0	0.0	
40	QPSK	100	0	13.90	13.97	13.96			
40	16QAM	1	1	14.05	14.13	14.14	15.0	0.0	
40	64QAM	1	1	14.15	14.41	14.22	15.0	0.0	
40	256QAM	1	1	13.98	14.04	13.98	15.0	0.0	
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	53	14.31	14.51	14.24	15.0	0.0	
Channel				518250	519200	522300	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	40	14.33	14.49	14.40	15.0	0.0	
Channel				518004	519000	522996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2593.02	2595	2614.98			
10	QPSK	1	28	14.34	14.55	14.41	15.0	0.0	
Channel				514506	519000	523494	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2572.53	2595	2617.47			
5	QPSK	1	13	14.34	14.52	14.43	15.0	0.0	

n38_Ant0 DS13 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	PI2 BPSK	1	1	11.24	11.00	11.13			
40	PI2 BPSK	1	53	11.55	11.39	11.37	12.0	0.0	
40	PI2 BPSK	1	104	10.96	10.85	10.96	12.0	0.0	
40	PI2 BPSK	50	0	11.09	11.62	11.31	12.0	0.0	
40	PI2 BPSK	50	28	11.15	11.59	11.32	12.0	0.0	
40	PI2 BPSK	50	56	11.50	11.30	11.36			
40	PI2 BPSK	100	0	11.10	10.89	10.86	12.0	0.0	
40	QPSK	1	1	11.02	10.98	11.07			
40	QPSK	1	53	11.28	11.63	11.32	12.0	0.0	
40	QPSK	1	104	11.09	11.50	11.29			
40	QPSK	50	0	11.02	10.82	10.89	12.0	0.0	
40	QPSK	50	28	11.06	11.62	11.40	12.0	0.0	
40	QPSK	50	56	11.18	11.53	11.33	12.0	0.0	
40	QPSK	100	0	11.26	11.40	11.24			
40	16QAM	1	1	11.15	11.04	11.21	12.0	0.0	
40	64QAM	1	1	11.25	11.35	11.11	12.0	0.0	
40	256QAM	1	1	11.08	11.54	11.27	12.0	0.0	
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	53	11.18	11.57	11.23	12.0	0.0	
Channel				518250	519200	522300	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	40	11.21	11.59	11.25	12.0	0.0	
Channel				518004	519000	522996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2593.02	2595	2614.98			
10	QPSK	1	28	11.19	11.59	11.31	12.0	0.0	
Channel				514506	519000	523494	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2572.53	2595	2617.47			
5	QPSK	1	13	11.16	11.61	11.27	12.0	0.0	

n41_Ant0 DS13 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				504004	518598	532998			
Frequency (MHz)				2521.02	2592.99	2694.99			
50	PI2 BPSK	1	1	16.21	16.32	16.24			
50	PI2 BPSK	1	135	16.22	16.22	16.13	18.0	0.0	
50	PI2 BPSK	1	268	16.02	16.11	16.18			
50	PI2 BPSK	135	0	16.16	16.25	16.29	18.0	0.0	
50	PI2 BPSK	135	68	16.26	16.43	16.34	18.0	0.0	
50	PI2 BPSK	135	135	16.10	16.35	16.11	18.0	0.0	
50	PI2 BPSK	270	0	16.42	16.25	16.35			
50	QPSK	1	1	16.05	16.10	16.11			
50	QPSK	1	135	16.29	16.70	16.09	18.0	0.0	
50	QPSK	1	268	16.13	16.05	16.04			
50	QPSK	135	0	16.19	16.46	16.48	18.0	0.0	
50	QPSK	135	68	16.18	16.56	16.04	18.0	0.0	
50	QPSK	135	135	16.23	16.51	16.48	18.0	0.0	
50	QPSK	270	0	16.15	16.68	16.06			
50	16QAM	1	1	16.28	16.30	16.51	18.0	0.0	
50	64QAM	1	1	16.16	16.49	16.39	18.0	0.0	
50	256QAM	1	1	16.41	16.24	16.30	18.0	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	PI2 BPSK	1	108	16.21	16.65	15.90	18.0	0.0	
Channel				502203	518598	535596	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	PI2 BPSK	1	80	16.14	16.51	16.10	18.0	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2504.02	2592.99	2679.99			
20	QPSK	1	53	16.28	16.52	15.93	18.0	0.0	
Channel				500700	518598	536496	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	40	16.07	16.61	16.05	18.0	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	28	16.19	16.71	15.88	18.0	0.0	

n41_Ant0 DSI3 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				584504	518598	535098	15.5	0.0	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	PI2 BPSK	1	1	13.56	13.66	13.62			
50	PI2 BPSK	1	135	13.63	14.05	13.78	15.5	0.0	
50	PI2 BPSK	1	268	13.59	13.52	13.61			
50	PI2 BPSK	135	0	13.69	14.03	13.80		0.0	
50	PI2 BPSK	135	68	13.87	13.91	13.85	15.5	0.0	
50	PI2 BPSK	135	135	13.80	13.89	13.85	15.5	0.0	
50	PI2 BPSK	270	0	14.01	14.01	13.87			
50	QPSK	1	1	13.51	13.55	13.63		0.0	
50	QPSK	1	135	13.73	14.25	13.78	15.5	0.0	
50	QPSK	1	268	13.55	13.72	13.56			
50	QPSK	135	0	13.88	14.16	13.56		0.0	
50	QPSK	135	68	13.60	14.23	13.66	15.5	0.0	
50	QPSK	135	135	13.69	13.92	14.08	15.5	0.0	
50	QPSK	270	0	13.86	14.15	13.77			
50	16QAM	1	1	13.89	13.77	14.07		0.0	
50	84QAM	1	1	13.79	14.04	13.85	15.5	0.0	
50	256QAM	1	1	14.10	13.90	13.85	15.5	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670	(dBm)	(dB)	
40	PI2 BPSK	1	108	13.68	14.23	13.57	15.5	0.0	
Channel				522203	518598	535098	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98	(dBm)	(dB)	
30	PI2 BPSK	1	80	13.52	14.16	13.57	15.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2504.02	2592.99	2679.99	(dBm)	(dB)	
20	QPSK	1	53	13.57	14.05	13.80	15.5	0.0	
Channel				500700	518598	536498	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48	(dBm)	(dB)	
15	QPSK	1	40	13.54	14.08	13.65	15.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685	(dBm)	(dB)	
10	QPSK	1	26	13.68	14.23	13.61	15.5	0.0	

n41_Ant0 DSI2 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				584504	518598	535098	22.5	0.0	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	PI2 BPSK	1	1	21.92	22.01	21.87			
50	PI2 BPSK	1	135	21.89	21.93	22.02	22.5	0.0	
50	PI2 BPSK	1	268	21.81	21.90	21.54			
50	PI2 BPSK	135	0	21.84	22.03	21.74		0.0	
50	PI2 BPSK	135	68	21.95	21.82	21.90	22.5	0.0	
50	PI2 BPSK	135	135	21.95	21.85	21.94	22.5	0.0	
50	PI2 BPSK	270	0	21.84	22.01	21.96			
50	QPSK	1	1	21.80	22.03	21.91		0.0	
50	QPSK	1	135	21.75	22.19	21.59	22.5	0.0	
50	QPSK	1	268	21.76	21.80	21.82			
50	QPSK	135	0	21.88	21.87	21.61		0.0	
50	QPSK	135	68	21.91	21.94	21.85	22.5	0.0	
50	QPSK	135	135	21.74	21.87	21.90	22.5	0.0	
50	QPSK	270	0	21.88	21.90	21.69			
50	16QAM	1	1	21.74	21.92	21.70		0.0	
50	84QAM	1	1	21.77	21.79	21.67	22.5	0.0	
50	256QAM	1	1	20.48	20.59	20.52	21.0	1.5	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670	(dBm)	(dB)	
40	PI2 BPSK	1	108	21.67	22.18	21.59	22.5	0.0	
Channel				522203	518598	535098	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98	(dBm)	(dB)	
30	PI2 BPSK	1	80	21.60	22.18	21.52	22.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2504.02	2592.99	2679.99	(dBm)	(dB)	
20	QPSK	1	53	21.73	22.17	21.40	22.5	0.0	
Channel				500700	518598	536498	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48	(dBm)	(dB)	
15	QPSK	1	40	21.56	22.01	21.53	22.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685	(dBm)	(dB)	
10	QPSK	1	26	21.63	22.15	21.48	22.5	0.0	

n66_Ant1 DSI3 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346000	349000	352000			
Frequency (MHz)				1730	1745	1760			
40	PI/2 BPSK	1	1	22.08	21.91	21.84			
40	PI/2 BPSK	1	108	22.31	22.25	22.18	23.5	0.0	
40	PI/2 BPSK	1	214	22.08	22.34	22.03			
40	PI/2 BPSK	108	0	21.86	21.86	22.06	23.5	0.0	
40	PI/2 BPSK	108	54	21.95	21.80	21.84	23.5	0.0	
40	PI/2 BPSK	108	108	22.29	22.39	22.14	23.5	0.0	
40	PI/2 BPSK	216	0	22.06	22.25	22.01			
40	QPSK	1	1	21.99	21.82	21.68			
40	QPSK	1	108	22.34	22.52	22.24	23.5	0.0	
40	QPSK	1	214	22.13	22.25	21.99			
40	QPSK	108	0	21.73	21.69	21.91	23.5	0.0	
40	QPSK	108	54	22.05	22.39	21.89	23.5	0.0	
40	QPSK	108	108	22.26	22.37	22.20			
40	QPSK	216	0	21.90	22.31	21.92	23.5	0.0	
40	16QAM	1	1	21.94	21.84	22.05	23.5	0.0	
40	64QAM	1	1	21.84	21.87	21.82	23.0	0.5	
40	256QAM	1	1	19.88	19.95	19.65	21.0	2.5	
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1725	1745	1765			
30	PI/2 BPSK	1	80	22.24	22.38	22.13	23.5	0.0	
Channel				344500	349000	353500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5			
25	PI/2 BPSK	1	67	22.29	22.33	22.15	23.5	0.0	
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1720	1745	1770			
20	QPSK	1	53	22.23	22.30	22.10	23.5	0.0	
Channel				343500	349000	354500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5			
15	QPSK	1	40	22.26	22.37	22.18	23.5	0.0	
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1715	1745	1775			
10	QPSK	1	26	22.22	22.37	22.13	23.5	0.0	
Channel				342500	349000	355500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1712.5	1745	1777.5			
5	QPSK	1	13	22.12	22.12	22.12	23.5	0.0	



n77_Ant1 DS13 For SA&ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	650000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	20.11	20.23	20.44			
50	PI2 BPSK	1	135	20.08	20.55	20.32	22.0	0.0	
50	PI2 BPSK	1	268	20.20	20.40	20.64			
50	PI2 BPSK	135	0	20.27	20.80	20.30	22.0	0.0	
50	PI2 BPSK	135	68	20.24	20.63	20.29	22.0	0.0	
50	PI2 BPSK	135	135	20.08	20.68	20.46			
50	PI2 BPSK	270	0	20.21	20.61	20.40	22.0	0.0	
50	QPSK	1	1	20.02	20.15	20.13			
50	QPSK	1	135	20.28	20.83	20.51	22.0	0.0	
50	QPSK	1	268	20.17	20.12	20.34			
50	QPSK	135	0	20.16	20.72	20.53	22.0	0.0	
50	QPSK	135	68	20.12	20.73	20.35	22.0	0.0	
50	QPSK	135	135	20.34	20.54	20.51	22.0	0.0	
50	QPSK	270	0	20.14	20.65	20.47			
50	16QAM	1	1	20.17	20.21	20.39	22.0	0.0	
50	64QAM	1	1	20.03	20.26	20.35	22.0	0.0	
50	256QAM	1	1	19.58	19.55	19.74	21.5	0.5	
Channel				648334	650000	663668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
40	QPSK	1	53	20.35	20.51	20.36	22.0	0.0	
Channel				647254	650000	665008	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	26	20.34	20.68	20.43	22.0	0.0	
Channel				647168	650000	664834	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	20.27	20.54	20.37	22.0	0.0	
Channel				647000	650000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	20.13	20.58	20.32	22.0	0.0	

Par27Q n77_Ant1 DS13 For SA&ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	PI2 BPSK	1	1	20.10	20.11	20.07			
50	PI2 BPSK	1	135	20.60	20.61	20.58	22.0	0.0	
50	PI2 BPSK	1	268	20.16	20.23	20.18			
50	PI2 BPSK	135	0	20.44	20.48	20.44	22.0	0.0	
50	PI2 BPSK	135	68	20.35	20.39	20.36	22.0	0.0	
50	PI2 BPSK	135	135	20.27	20.32	20.31			
50	PI2 BPSK	270	0	20.64	20.67	20.64	22.0	0.0	
50	QPSK	1	1	20.22	20.23	20.22			
50	QPSK	1	135	20.79	20.81	20.78	22.0	0.0	
50	QPSK	1	268	20.11	20.12	20.11			
50	QPSK	135	0	20.52	20.55	20.52	22.0	0.0	
50	QPSK	135	68	20.66	20.71	20.65	22.0	0.0	
50	QPSK	135	135	20.36	20.37	20.32	22.0	0.0	
50	QPSK	270	0	20.45	20.51	20.49			
50	16QAM	1	1	20.06	20.11	20.06	22.0	0.0	
50	64QAM	1	1	20.11	20.16	20.10	22.0	0.0	
50	256QAM	1	1	19.51	19.56	19.54	21.5	0.5	
Channel				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
40	QPSK	1	53	20.50	20.54	20.37	22.0	0.0	
Channel				632668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	26	20.57	20.45	20.52	22.0	0.0	
Channel				630500	633334	636166	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3447.5	3500.01	3542.49			
15	QPSK	1	19	20.61	20.46	20.37	22.0	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3544.98			
10	QPSK	1	12	20.55	20.58	20.44	22.0	0.0	

n78_Ant1 DS13 For SA&ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	650000	661668			
Frequency (MHz)				3725.01	3750	3775.02			
50	PI2 BPSK	1	1	20.16	20.23	20.14			
50	PI2 BPSK	1	135	20.46	20.46	20.47	22.0	0.0	
50	PI2 BPSK	1	268	20.37	20.15	20.37			
50	PI2 BPSK	135	0	20.73	20.62	20.71	22.0	0.0	
50	PI2 BPSK	135	68	20.56	20.51	20.56	22.0	0.0	
50	PI2 BPSK	135	135	20.62	20.39	20.61			
50	PI2 BPSK	270	0	20.52	20.53	20.53	22.0	0.0	
50	QPSK	1	1	20.04	20.26	20.07			
50	QPSK	1	135	20.76	20.82	20.77	22.0	0.0	
50	QPSK	1	268	20.02	20.16	20.04			
50	QPSK	135	0	20.66	20.41	20.63	22.0	0.0	
50	QPSK	135	68	20.45	20.66	20.65	22.0	0.0	
50	QPSK	135	135	20.42	20.43	20.45	22.0	0.0	
50	QPSK	270	0	20.56	20.57	20.51			
50	16QAM	1	1	20.09	20.25	20.12	22.0	0.0	
50	64QAM	1	1	20.14	20.16	20.14	22.0	0.0	
50	256QAM	1	1	19.47	19.07	19.46	21.5	0.5	
Channel				648334	650000	661668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3750	3775.02			
40	QPSK	1	53	20.30	20.60	20.57	22.0	0.0	
Channel				647334	650000	662008	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3750	3790.02			
20	QPSK	1	26	20.40	20.58	20.49	22.0	0.0	
Channel				647168	650000	662634	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3750	3782.41			
15	QPSK	1	19	20.39	20.50	20.50	22.0	0.0	
Channel				647000	650000	663000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3750	3795			
10	QPSK	1	12	20.39	20.60	20.50	22.0	0.0	



Par27Q n78_Ant1 DSI3 For SA&ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000	22.0	0.0
Frequency (MHz)				3475.02	3500.01	3525		
50	PI2 BPSK	1	1	20.02	20.26	20.15	22.0	0.0
50	PI2 BPSK	1	135	20.50	20.73	20.04		
50	PI2 BPSK	1	268	20.12	20.14	20.38	22.0	0.0
50	PI2 BPSK	135	0	20.38	20.48	20.00		
50	PI2 BPSK	135	68	20.32	20.50	20.02	22.0	0.0
50	PI2 BPSK	135	135	20.26	20.41	20.18		
50	PI2 BPSK	270	0	20.59	20.42	20.11	22.0	0.0
50	QPSK	1	1	20.17	20.31	20.05		
50	QPSK	1	135	20.71	20.77	20.21	22.0	0.0
50	QPSK	1	268	20.05	20.52	20.08		
50	QPSK	135	0	20.48	20.50	20.25	22.0	0.0
50	QPSK	135	68	20.61	20.04	20.09		
50	QPSK	135	135	20.26	20.82	20.20	22.0	0.0
50	QPSK	270	0	20.44	20.46	20.15		
50	16QAM	1	1	20.06	20.15	20.09	22.0	0.0
50	16QAM	1	1	20.09	20.26	20.06		
50	256QAM	1	1	19.49	19.75	19.45	21.5	0.5
Channel				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3475.02	3500.01	3525		
40	QPSK	1	53	20.68	20.59	20.49	22.0	0.0
Channel				630505	633334	635000		
Frequency (MHz)				3460.02	3500.01	3540	Tune-up limit (dBm)	MPR (dB)
20	QPSK	1	26	20.59	20.61	20.42		
Channel				630500	633334	636166	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3459.5	3500.01	3542.48		
15	QPSK	1	19	20.59	20.66	20.48	22.0	0.0
Channel				630334	633334	636332		
Frequency (MHz)				3455.01	3500.01	3544.98	Tune-up limit (dBm)	MPR (dB)
10	QPSK	1	12	20.74	20.67	20.43		

n7_Ant2 DS14 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	17.89	18.22	18.01	19.5	0.0	
20	PI/2 BPSK	1	53	18.03	18.07	18.14			
20	PI/2 BPSK	1	104	18.06	18.08	17.97			
20	PI/2 BPSK	50	0	17.80	18.01	17.96			
20	PI/2 BPSK	50	28	17.89	18.10	18.20	19.5		0.0
20	PI/2 BPSK	50	56	17.83	17.97	18.03	19.5	0.0	
20	PI/2 BPSK	100	0	18.00	18.14	17.96			
20	QPSK	1	1	18.10	18.32	18.22	19.5	0.0	
20	QPSK	1	53	17.94	18.38	17.87			
20	QPSK	1	104	17.88	18.21	18.00			
20	QPSK	50	0	17.92	18.17	18.07			
20	QPSK	50	28	17.92	18.23	17.88	19.5		0.0
20	QPSK	50	56	17.93	18.00	17.96	19.5	0.0	
20	QPSK	100	0	18.05	18.24	18.16			
20	16QAM	1	1	17.79	18.13	18.07	19.5		0.0
20	64QAM	1	1	18.19	18.19	18.06	19.5		0.0
20	256QAM	1	1	18.04	18.02	17.92	19.5		0.0
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	17.81	18.21	17.77	19.5		0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	17.82	18.28	17.76	19.5		0.0
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	17.81	18.23	17.81	19.5		0.0

n7_Ant2 DS14 For ENDG									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	15.02	15.19	15.12	16.5	0.0	
20	PI/2 BPSK	1	53	15.24	15.10	15.21			
20	PI/2 BPSK	1	104	15.00	15.11	15.04			
20	PI/2 BPSK	50	0	14.81	15.13	14.91			
20	PI/2 BPSK	50	28	14.84	15.15	15.17	16.5		0.0
20	PI/2 BPSK	50	56	14.87	14.92	14.99	16.5	0.0	
20	PI/2 BPSK	100	0	14.95	15.10	14.91			
20	QPSK	1	1	15.14	15.31	15.17	16.5	0.0	
20	QPSK	1	53	14.93	15.53	15.02			
20	QPSK	1	104	14.86	15.22	15.01			
20	QPSK	50	0	14.99	15.13	15.05			
20	QPSK	50	28	14.95	15.15	14.90	16.5		0.0
20	QPSK	50	56	14.95	15.12	14.90	16.5	0.0	
20	QPSK	100	0	15.05	15.24	15.11			
20	16QAM	1	1	14.86	15.10	15.23	16.5		0.0
20	64QAM	1	1	15.17	15.17	14.95	16.5		0.0
20	256QAM	1	1	15.17	15.16	15.03	16.5		0.0
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	14.84	15.43	14.92	16.5		0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	14.81	15.43	14.91	16.5		0.0
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	14.80	15.28	14.90	16.5		0.0



n38_Ant2 DS14 For SA

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	519000	519996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PV2 BPSK	1	1	15.42	15.42	15.36		
40	PV2 BPSK	1	53	15.70	15.79	15.76	16.0	0.0
40	PV2 BPSK	1	104	15.35	15.31	15.23		
40	PV2 BPSK	50	0	15.27	15.41	15.37	16.0	0.0
40	PV2 BPSK	50	26	15.57	15.75	15.75	16.0	0.0
40	PV2 BPSK	50	56	15.43	15.40	15.09		
40	PV2 BPSK	100	0	15.38	15.43	15.51	16.0	0.0
40	QPSK	1	1	15.25	15.30	15.45		
40	QPSK	1	53	15.78	15.88	15.70	16.0	0.0
40	QPSK	1	104	15.55	15.69	15.28		
40	QPSK	50	0	15.69	15.75	15.74	16.0	0.0
40	QPSK	50	26	15.52	15.65	15.05	16.0	0.0
40	QPSK	50	56	15.37	15.38	15.31	16.0	0.0
40	QPSK	100	0	15.75	15.80	15.61		
40	19QAM	1	1	15.42	15.44	15.40	16.0	0.0
40	84QAM	1	1	15.78	15.89	15.61	16.0	0.0
40	259QAM	1	1	15.47	15.42	15.41	16.0	0.0
Channel				516000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2595	2610		
20	QPSK	1	53	15.63	15.81	15.72	16.0	0.0
Channel				515002	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	40	15.63	15.78	15.63	16.0	0.0
Channel				515004	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2578.02	2595	2614.98		
10	QPSK	1	26	15.79	15.80	15.76	16.0	0.0
Channel				514506	519000	523494	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2572.53	2595	2617.47		
5	QPSK	1	13	15.68	15.82	15.62	16.0	0.0

n38_Ant2 DS14 For ENDC

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				519004	519000	519996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PV2 BPSK	1	1	12.40	12.39	12.23		
40	PV2 BPSK	1	53	12.76	12.94	12.74	13.0	0.0
40	PV2 BPSK	1	104	12.43	12.38	12.30		
40	PV2 BPSK	50	0	12.34	12.45	12.24	13.0	0.0
40	PV2 BPSK	50	26	12.59	12.75	12.68	13.0	0.0
40	PV2 BPSK	50	56	12.25	12.35	12.20		
40	PV2 BPSK	100	0	12.57	12.44	12.36	13.0	0.0
40	QPSK	1	1	12.28	12.50	12.60		
40	QPSK	1	53	12.73	12.89	12.74	13.0	0.0
40	QPSK	1	104	12.38	12.90	12.19		
40	QPSK	50	0	12.74	12.81	12.84	13.0	0.0
40	QPSK	50	26	12.46	12.92	12.10	13.0	0.0
40	QPSK	50	56	12.41	12.51	12.32		
40	QPSK	100	0	12.71	12.88	12.73	13.0	0.0
40	19QAM	1	1	12.42	12.49	12.38	13.0	0.0
40	84QAM	1	1	12.72	12.87	12.59	13.0	0.0
40	259QAM	1	1	12.38	12.34	12.33	13.0	0.0
Channel				516000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2595	2610		
20	QPSK	1	53	12.62	12.90	12.67	13.0	0.0
Channel				515002	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	40	12.63	12.89	12.65	13.0	0.0
Channel				515004	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2578.02	2595	2614.98		
10	QPSK	1	26	12.63	12.90	12.65	13.0	0.0
Channel				514506	519000	523494	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2572.53	2595	2617.47		
5	QPSK	1	13	12.56	12.82	12.69	13.0	0.0

n41_Ant2 DS14 For SA&ENDC

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				503004	518598	535998		
Frequency (MHz)				2521.02	2592.99	2664.99		
50	PV2 BPSK	1	1	18.53	18.51	18.61		
50	PV2 BPSK	1	135	18.86	18.87	18.92	20.5	0.0
50	PV2 BPSK	1	268	18.69	18.78	19.68		
50	PV2 BPSK	135	0	18.62	18.86	18.74	20.5	0.0
50	PV2 BPSK	135	68	18.82	19.02	19.00	20.5	0.0
50	PV2 BPSK	135	135	19.05	19.15	19.08		
50	PV2 BPSK	270	0	18.93	18.74	18.91	20.5	0.0
50	QPSK	1	1	18.50	19.21	19.38		
50	QPSK	1	135	19.00	19.23	19.14	20.5	0.0
50	QPSK	1	268	18.92	18.98	18.79		
50	QPSK	135	0	18.72	18.89	18.87	20.5	0.0
50	QPSK	135	68	19.00	19.16	19.08	20.5	0.0
50	QPSK	135	135	19.02	18.99	19.08	20.5	0.0
50	QPSK	270	0	19.04	19.14	19.08		
50	19QAM	1	1	18.90	18.97	18.88	20.5	0.0
50	84QAM	1	1	19.18	19.03	19.12	20.5	0.0
50	259QAM	1	1	18.85	18.78	19.00	20.5	0.0
Channel				503002	518598	534000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670		
40	PV2 BPSK	1	108	19.07	19.07	19.22	20.5	0.0
Channel				522002	518598	531998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98		
30	PV2 BPSK	1	80	19.18	19.04	19.12	20.5	0.0
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2504.02	2592.99	2679.99		
20	QPSK	1	53	19.13	19.04	19.16	20.5	0.0
Channel				500700	518598	536498	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48		
15	QPSK	1	40	19.21	19.12	19.22	20.5	0.0
Channel				520002	518598	532000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685		
10	QPSK	1	26	19.11	19.17	19.14	20.5	0.0



n77_Ant3 DS14 For SA&ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	22.23	22.21	22.16	23.5	0.0	
50	PI2 BPSK	1	135	22.36	22.31	21.98			
50	PI2 BPSK	1	268	22.11	22.47	21.98			
50	PI2 BPSK	135	0	22.11	22.33	22.07	23.5	0.0	
50	PI2 BPSK	135	68	22.14	22.24	22.28	23.5	0.0	
50	PI2 BPSK	135	135	22.49	22.51	22.15	23.5	0.0	
50	PI2 BPSK	270	0	22.20	22.39	22.19	23.5	0.0	
50	QPSK	1	1	22.23	22.46	22.45			
50	QPSK	1	135	22.34	22.35	22.06			
50	QPSK	1	268	22.28	22.47	22.14	23.5	0.0	
50	QPSK	135	0	22.19	22.31	22.03			
50	QPSK	135	68	22.26	22.36	22.00			
50	QPSK	135	135	22.17	22.28	22.20	23.5	0.0	
50	QPSK	270	0	22.16	22.40	22.11	23.5	0.0	
50	16QAM	1	1	22.05	22.33	22.13			
50	64QAM	1	1	22.01	22.08	21.80		0.5	
50	256QAM	1	1	20.06	20.07	19.73	23.0	2.5	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960	(dB)		
40	QPSK	1	53	22.29	22.24	22.07	23.5	0.0	
Channel				647334	655000	662668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02	(dB)		
20	QPSK	1	26	22.38	22.28	22.08	23.5	0.0	
Channel				647000	655000	663000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51	(dB)		
15	QPSK	1	19	22.29	22.36	22.13	23.5	0.0	
Channel				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975	(dB)		
10	QPSK	1	12	22.38	22.26	22.21	23.5	0.0	

Par27Q n77_Ant3 DS14 For SA&ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	PI2 BPSK	1	1	22.32	22.39	22.33	23.5	0.0	
50	PI2 BPSK	1	135	22.41	22.38	22.48			
50	PI2 BPSK	1	268	22.38	22.46	22.46			
50	PI2 BPSK	135	0	22.37	22.35	22.44	23.5	0.0	
50	PI2 BPSK	135	68	22.36	22.41	22.34	23.5	0.0	
50	PI2 BPSK	135	135	22.45	22.52	22.47	23.5	0.0	
50	PI2 BPSK	270	0	22.49	22.50	22.48	23.5	0.0	
50	QPSK	1	1	22.26	22.37	22.25			
50	QPSK	1	135	22.52	22.52	22.54			
50	QPSK	1	268	22.52	22.49	22.53	23.5	0.0	
50	QPSK	135	0	22.30	22.19	22.16			
50	QPSK	135	68	22.42	22.49	22.36			
50	QPSK	135	135	22.19	22.19	22.19	23.5	0.0	
50	QPSK	270	0	22.54	22.48	22.48	23.5	0.0	
50	16QAM	1	1	22.37	22.35	22.29			
50	64QAM	1	1	22.19	22.20	22.14		0.5	
50	256QAM	1	1	20.11	20.21	20.16	23.0	2.5	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3525.98	(dB)		
40	QPSK	1	53	22.30	22.35	22.27	23.5	0.0	
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540	(dB)		
20	QPSK	1	26	22.30	22.42	22.32	23.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49	(dB)		
15	QPSK	1	19	22.20	22.41	22.21	23.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3454.01	3500.01	3544.98	(dB)		
10	QPSK	1	12	22.30	22.39	22.29	23.5	0.0	

n77_Ant3 DS11 For EndC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	21.09	21.19	21.19	22.5	0.0	
50	PI2 BPSK	1	135	21.39	21.45	21.09			
50	PI2 BPSK	1	268	21.25	21.49	20.90			
50	PI2 BPSK	135	0	21.17	21.31	21.17	22.5	0.0	
50	PI2 BPSK	135	68	21.08	21.40	21.29	22.5	0.0	
50	PI2 BPSK	135	135	21.44	21.49	21.23	22.5	0.0	
50	PI2 BPSK	270	0	21.10	21.38	21.27	22.5	0.0	
50	QPSK	1	1	21.42	21.46	21.27			
50	QPSK	1	135	21.41	21.53	21.13			
50	QPSK	1	268	21.32	21.51	21.34	22.5	0.0	
50	QPSK	135	0	21.18	21.36	21.04			
50	QPSK	135	68	21.31	21.49	20.98			
50	QPSK	135	135	21.38	21.51	21.10	22.5	0.0	
50	QPSK	270	0	21.27	21.43	21.06	22.5	0.0	
50	16QAM	1	1	21.16	21.22	21.17			
50	64QAM	1	1	20.95	21.16	20.78		0.5	
50	256QAM	1	1	19.12	19.96	19.59	23.0	1.5	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960	(dB)		
40	QPSK	1	53	21.25	21.34	21.04	22.5	0.0	
Channel				647334	655000	662668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02	(dB)		
20	QPSK	1	26	21.34	21.37	21.12	22.5	0.0	
Channel				647000	655000	663000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51	(dB)		
15	QPSK	1	19	21.34	21.30	21.10	22.5	0.0	
Channel				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975	(dB)		
10	QPSK	1	12	21.39	21.40	21.08	22.5	0.0	



Par27Q n77_Ant3 DSI1 For ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Mid Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				3475.02	3533.34	3550.00		
Frequency (MHz)				3475.02	3500.01	3525		
50	PI2 BPSK	1	1	21.26	21.29	21.25		
50	PI2 BPSK	1	135	21.54	21.49	21.49	22.5	0.0
50	PI2 BPSK	1	268	21.35	21.45	21.37		
50	PI2 BPSK	135	0	21.27	21.37	21.35	22.5	0.0
50	PI2 BPSK	135	68	21.11	21.06	21.20	22.5	0.0
50	PI2 BPSK	135	135	21.39	21.48	21.45	22.5	0.0
50	PI2 BPSK	270	0	21.21	21.27	21.32		
50	QPSK	1	1	21.35	21.36	21.48		
50	QPSK	1	135	21.54	21.57	21.69	22.5	0.0
50	QPSK	1	268	21.41	21.40	21.42		
50	QPSK	135	0	21.39	21.39	21.28	22.5	0.0
50	QPSK	135	68	21.36	21.32	21.34	22.5	0.0
50	QPSK	135	135	21.25	21.35	21.34	22.5	0.0
50	QPSK	270	0	21.47	21.35	21.38	22.5	0.0
50	16QAM	1	1	21.27	21.28	21.27	22.5	0.0
50	64QAM	1	1	21.59	21.66	21.55	22.5	0.0
50	256QAM	1	1	20.16	20.10	20.21	21.0	1.5
Channel				631334	633334	636332	Tune-Up limit (dBm)	MPR (dB)
Frequency (MHz)				3470.01	3500.01	3529.98		
40	QPSK	1	53	21.34	21.35	21.27	22.5	0.0
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3460.02	3500.01	3540		
20	QPSK	1	26	21.42	21.21	21.30	22.5	0.0
Channel				637550	633334	635166	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3467.5	3500.01	3542.49		
15	QPSK	1	19	21.37	21.30	21.10	22.5	0.0
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3465.01	3500.01	3544.98		
10	QPSK	1	12	21.28	21.22	21.25	22.5	0.0

n78_Ant3 DSI4 For SA&ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Mid Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				648334	650000	652668		
Frequency (MHz)				3725.01	3750	3775.02		
50	PI2 BPSK	1	1	22.03	22.19	22.05		
50	PI2 BPSK	1	135	22.23	22.10	22.19	23.5	22.5
50	PI2 BPSK	1	268	22.42	22.47	22.40		
50	PI2 BPSK	135	0	22.12	22.20	22.24	23.5	0.0
50	PI2 BPSK	135	68	22.26	22.19	22.22	23.5	22.5
50	PI2 BPSK	135	135	22.16	22.30	22.24	23.5	0.0
50	PI2 BPSK	270	0	22.37	22.36	22.23		
50	QPSK	1	1	22.23	22.19	22.26		
50	QPSK	1	135	22.41	22.45	22.37	23.5	0.0
50	QPSK	1	268	22.31	22.29	22.20		
50	QPSK	135	0	22.11	22.12	22.14	23.5	0.0
50	QPSK	135	68	22.30	22.34	22.41	23.5	0.0
50	QPSK	135	135	22.27	22.34	22.34	23.5	0.0
50	QPSK	270	0	22.34	22.28	22.30	23.5	0.0
50	16QAM	1	1	22.35	22.44	22.46	23.5	0.0
50	64QAM	1	1	22.04	21.98	22.03	23.0	0.5
50	256QAM	1	1	19.97	19.92	20.00	21.0	1.5
Channel				648000	650000	652000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3720	3750	3780		
40	QPSK	1	53	22.39	22.28	22.17	23.5	22.5
Channel				647334	650000	652668	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3710.01	3750	3790.02		
20	QPSK	1	26	22.35	22.32	22.23	23.5	22.5
Channel				647168	650000	652191	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3707.52	3750	3792.51		
15	QPSK	1	19	22.31	22.35	22.28	23.5	22.5
Channel				647000	650000	653000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3705	3750	3795		
10	QPSK	1	12	22.36	22.39	22.19	23.5	22.5

Par27Q n78_Ant3 DSI4 For SA&ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631663	633334	636000		
Frequency (MHz)				3475.02	3500.01	3525		
50	PI2 BPSK	1	1	22.09	22.08	22.16		
50	PI2 BPSK	1	135	22.10	22.04	22.07	23.5	0.0
50	PI2 BPSK	1	268	22.28	22.39	22.24		
50	PI2 BPSK	135	0	22.21	22.19	22.15	23.5	0.0
50	PI2 BPSK	135	68	22.04	22.01	22.06	23.5	0.0
50	PI2 BPSK	135	135	22.22	22.23	22.14	23.5	0.0
50	PI2 BPSK	270	0	22.14	22.17	22.09		
50	QPSK	1	1	22.36	22.34	22.36		
50	QPSK	1	135	22.43	22.36	22.47	23.5	0.0
50	QPSK	1	268	22.14	22.21	22.14		
50	QPSK	135	0	22.28	22.20	22.22	23.5	0.0
50	QPSK	135	68	22.29	22.34	22.27	23.5	0.0
50	QPSK	135	135	22.13	22.17	22.21	23.5	0.0
50	QPSK	270	0	22.19	22.19	22.27	23.5	0.0
50	16QAM	1	1	22.20	22.29	22.30	23.5	0.0
50	64QAM	1	1	21.94	22.02	22.02	23.0	0.5
50	256QAM	1	1	19.92	19.95	19.94	21.0	1.5
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3470.01	3500.01	3529.98	23.5 <td>0.0</td>	0.0
40	QPSK	1	53	22.27	22.28	22.12	23.5	0.0
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3460.02	3500.01	3540	<td></td>	
20	QPSK	1	26	22.22	22.25	22.11	23.5	0.0
Channel				637550	633334	635166	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3467.5	3500.01	3542.49	<td></td>	
15	QPSK	1	19	22.22	22.32	22.16	23.5	0.0
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				3465.01	3500.01	3544.98	<td></td>	
10	QPSK	1	12	22.12	22.32	22.12	23.5	0.0

n78_Ant3 DS1 For ENDC									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	650000	651668			
Frequency (MHz)				3725.01	3750	3775.02			
50	PI2 BPSK	1	1	21.20	21.14	21.19			
50	PI2 BPSK	1	135	21.16	21.17	21.08	22.5		
50	PI2 BPSK	1	268	21.34	21.36	21.38			
50	PI2 BPSK	135	0	21.23	21.18	21.23	22.5		
50	PI2 BPSK	135	68	21.11	21.05	21.08	22.5		
50	PI2 BPSK	135	135	21.25	21.21	21.22	22.5		
50	PI2 BPSK	270	0	21.19	21.06	21.15			
50	QPSK	1	1	21.36	21.31	21.25			
50	QPSK	1	135	21.03	21.06	21.01	22.5		
50	QPSK	1	268	21.03	21.05	21.02			
50	QPSK	135	0	21.33	21.41	21.32	22.5		
50	QPSK	135	68	21.54	21.49	21.59	22.5		
50	QPSK	135	135	21.07	21.18	21.13	22.5		
50	QPSK	270	0	21.40	21.34	21.37			
50	16QAM	1	1	21.28	21.21	21.16	22.5		
50	64QAM	1	1	21.50	21.36	21.50	22.5		
50	256QAM	1	1	19.04	19.03	19.00	21.0		
Channel				648000	650000	652000	Tune-up limit	MPR	
Frequency (MHz)				3720	3750	3780	(dB)		
40	QPSK	1	53	21.28	21.19	21.31	22.5		
Channel				647334	650000	652668	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3750	3790.02	(dB)		
20	QPSK	1	26	21.27	21.29	21.33	22.5		
Channel				647100	650000	652900	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3750	3792.51	(dB)		
15	QPSK	1	19	21.14	21.20	21.33	22.5		
Channel				647000	650000	653000	Tune-up limit	MPR	
Frequency (MHz)				3705	3750	3795	(dB)		
10	QPSK	1	12	21.19	21.31	21.21	22.5		

Par27Q n78_Ant3 DS1 For ENDC									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525.02			
50	PI2 BPSK	1	1	20.91	20.89	21.00			
50	PI2 BPSK	1	135	21.15	21.09	21.19	22.5		
50	PI2 BPSK	1	268	21.23	21.31	21.26			
50	PI2 BPSK	135	0	21.06	21.10	21.20	22.5		
50	PI2 BPSK	135	68	21.11	21.10	21.08	22.5		
50	PI2 BPSK	135	135	21.19	21.30	21.31	22.5		
50	PI2 BPSK	270	0	21.14	21.14	21.21			
50	QPSK	1	1	21.39	21.36	21.33			
50	QPSK	1	135	21.48	21.44	21.40	22.5		
50	QPSK	1	268	21.15	21.05	21.13			
50	QPSK	135	0	21.18	21.20	21.16	22.5		
50	QPSK	135	68	21.54	21.21	21.23	22.5		
50	QPSK	135	135	21.17	21.16	21.11	22.5		
50	QPSK	270	0	21.48	21.44	21.47			
50	16QAM	1	1	21.40	21.41	21.39	22.5		
50	64QAM	1	1	21.56	21.36	21.57	22.5		
50	256QAM	1	1	19.03	19.03	19.00	21.0		
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dB)		
40	QPSK	1	53	21.23	21.53	21.12	22.5		
Channel				630668	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dB)		
20	QPSK	1	26	21.12	21.35	21.13	22.5		
Channel				630500	633334	636100	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dB)		
15	QPSK	1	19	21.13	21.34	21.11	22.5		
Channel				630334	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3445.01	3500.01	3544.96	(dB)		
10	QPSK	1	12	21.20	21.27	21.09	22.5		



n7_Ant4 DSI4 For SA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	Pl2 BPSK	1	1	19.22	19.58	19.57	21.0	0.0	
20	Pl2 BPSK	1	26	19.53	19.63	19.42			
20	Pl2 BPSK	1	49	19.33	19.54	19.30			
20	Pl2 BPSK	25	0	19.49	19.62	19.29	21.0	0.0	
20	Pl2 BPSK	25	13	19.52	19.70	19.68	21.0	0.0	
20	Pl2 BPSK	25	26	19.18	19.53	19.48	21.0	0.0	
20	Pl2 BPSK	50	0	19.37	19.48	19.42			
20	QPSK	1	1	19.44	19.59	19.70			
20	QPSK	1	26	19.58	19.57	19.45	21.0	0.0	
20	QPSK	1	49	19.38	19.56	19.15			
20	QPSK	25	0	19.32	19.29	19.40			
20	QPSK	25	13	19.38	19.70	19.45	21.0	0.0	
20	QPSK	25	26	19.43	19.50	19.38	21.0	0.0	
20	QPSK	50	0	19.27	19.78	19.36			
20	16QAM	1	1	19.54	19.23	19.51	21.0	0.0	
20	64QAM	1	1	19.51	19.72	19.36	21.0	0.0	
20	256QAM	1	1	17.90	18.39	18.02	19.5	1.5	
Channel				501800	507000	512600	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	19	19.51	19.71	19.50	21.0	0.0	
Channel				507000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	12	19.65	19.72	19.43	21.0	0.0	
Channel				2502.5	2535	2567.5	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	19.43	19.70	19.53	21.0	0.0	

n7_Ant4 DSI1 For SA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	Pl2 BPSK	1	1	17.57	17.68	17.53	19.0	0.0	
20	Pl2 BPSK	1	53	17.63	17.72	17.68			
20	Pl2 BPSK	1	104	17.58	17.78	17.53			
20	Pl2 BPSK	50	0	17.75	17.79	17.57	19.0	0.0	
20	Pl2 BPSK	50	26	17.60	17.74	17.60	19.0	0.0	
20	Pl2 BPSK	50	56	17.42	17.75	17.73	19.0	0.0	
20	Pl2 BPSK	100	0	17.64	17.65	17.84			
20	QPSK	1	1	17.71	17.70	17.60			
20	QPSK	1	53	17.74	17.81	17.75	19.0	0.0	
20	QPSK	1	104	17.57	17.72	17.44			
20	QPSK	50	0	17.63	17.68	17.54			
20	QPSK	50	26	17.66	17.79	17.76	19.0	0.0	
20	QPSK	50	56	17.49	17.76	17.53	19.0	0.0	
20	QPSK	100	0	17.68	17.72	17.50			
20	16QAM	1	1	17.76	17.58	17.70	19.0	0.0	
20	64QAM	1	1	17.71	17.79	17.54	19.0	0.0	
20	256QAM	1	1	17.68	17.75	17.74	19.0	0.0	
Channel				501800	507000	512600	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	19	17.62	17.68	17.61	19.0	0.0	
Channel				507000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	12	17.60	17.66	17.60	19.0	0.0	
Channel				2502.5	2535	2567.5	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	17.53	17.56	17.66	19.0	0.0	

n7_Ant4 DSI4 For END C									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	Pl2 BPSK	1	1	16.33	16.58	16.33	18.0	0.0	
20	Pl2 BPSK	1	53	16.52	16.47	16.41			
20	Pl2 BPSK	1	104	16.41	16.51	16.26			
20	Pl2 BPSK	50	0	16.50	16.68	16.43	18.0	0.0	
20	Pl2 BPSK	50	26	16.46	16.61	16.70	18.0	0.0	
20	Pl2 BPSK	50	56	16.15	16.52	16.51	18.0	0.0	
20	Pl2 BPSK	100	0	16.41	16.51	16.43			
20	QPSK	1	1	16.43	16.53	16.55			
20	QPSK	1	53	16.46	16.74	16.58	18.0	0.0	
20	QPSK	1	104	16.37	16.58	16.23			
20	QPSK	50	0	16.41	16.40	16.40			
20	QPSK	50	26	16.53	16.69	16.49	18.0	0.0	
20	QPSK	50	56	16.43	16.56	16.21	18.0	0.0	
20	QPSK	100	0	16.42	16.67	16.32			
20	16QAM	1	1	16.62	16.33	16.59	18.0	0.0	
20	64QAM	1	1	16.56	16.58	16.36	18.0	0.0	
20	256QAM	1	1	16.48	16.60	16.49	18.0	0.0	
Channel				501800	507000	512600	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	16.39	16.63	16.47	18.0	0.0	
Channel				507000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	16.40	16.64	16.48	18.0	0.0	
Channel				2502.5	2535	2567.5	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2502.5	2535	2567.5			
5	QPSK	1	13	16.43	16.64	16.58	18.0	0.0	



n7_Ant4 DSI1 For ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2510	2535	2560		
20	PB2 BPSK	1	1	14.41	14.35	14.29		
20	PB2 BPSK	1	53	14.35	14.40	14.40	16.0	0.0
20	PB2 BPSK	1	104	14.13	14.60	14.48		
20	PB2 BPSK	50	0	14.42	14.58	14.21	16.0	0.0
20	PB2 BPSK	50	28	14.44	14.51	14.30	16.0	0.0
20	PB2 BPSK	50	56	14.21	14.71	14.67		
20	PB2 BPSK	100	0	14.27	14.56	14.53	16.0	0.0
20	QPSK	1	1	14.35	14.47	14.50		
20	QPSK	1	53	14.45	14.73	14.40	16.0	0.0
20	QPSK	1	104	14.21	14.44	14.09		
20	QPSK	50	0	14.36	14.53	14.28	16.0	0.0
20	QPSK	50	28	14.36	14.46	14.42	16.0	0.0
20	QPSK	50	56	14.26	14.44	14.24		
20	QPSK	100	0	14.24	14.45	14.40	16.0	0.0
20	16QAM	1	1	14.44	14.44	14.27	16.0	0.0
20	64QAM	1	1	14.50	14.53	14.31	16.0	0.0
20	256QAM	1	1	14.52	14.47	14.51	16.0	0.0
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	(dBm)	(dB)
15	QPSK	1	40	14.40	14.53	14.37	16.0	0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565	(dBm)	(dB)
10	QPSK	1	26	14.30	14.68	14.28	16.0	0.0
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2502.5	2535	2567.5	(dBm)	(dB)
5	QPSK	1	13	14.28	14.61	14.23	16.0	0.0

n7_Ant4 DSI2 For NSA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2510	2535	2560		(dB)
20	PB2 BPSK	1	1	21.48	21.67	21.32		
20	PB2 BPSK	1	53	21.58	21.59	21.44	23.0	0.0
20	PB2 BPSK	1	104	21.43	21.65	21.43		
20	PB2 BPSK	50	0	21.39	21.38	21.41	23.0	0.0
20	PB2 BPSK	50	28	21.47	21.65	21.48	23.0	0.0
20	PB2 BPSK	50	56	21.50	21.54	21.65		
20	PB2 BPSK	100	0	21.65	21.61	21.44	23.0	0.0
20	QPSK	1	1	21.16	21.64	21.48		
20	QPSK	1	53	21.38	21.71	21.45	23.0	0.0
20	QPSK	1	104	21.65	21.75	21.73		
20	QPSK	50	0	21.42	21.42	21.36	23.0	0.0
20	QPSK	50	28	21.56	21.65	21.66	23.0	0.0
20	QPSK	50	56	21.63	21.63	21.58		
20	QPSK	100	0	21.48	21.66	21.58	23.0	0.0
20	16QAM	1	1	21.56	21.62	21.50	23.0	0.0
20	64QAM	1	1	19.95	20.09	19.95	21.5	1.5
20	256QAM	1	1	18.87	18.86	18.89	19.5	3.5
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	(dBm)	(dB)
15	QPSK	1	40	21.54	21.72	21.55	23.0	0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565	(dBm)	(dB)
10	QPSK	1	26	21.52	21.71	21.29	23.0	0.0
Channel				500500	507000	513500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2502.5	2535	2567.5	(dBm)	(dB)
5	QPSK	1	13	21.35	21.59	21.41	16.0	0.0

n66_Ant4 DSI1 For SA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				346000	349000	352000		
Frequency (MHz)				1725	1745	1760		
40	PB2 BPSK	1	1	18.49	18.54	18.54		
40	PB2 BPSK	1	108	18.26	18.68	18.57	20.0	0.0
40	PB2 BPSK	1	214	18.36	18.56	18.31		
40	PB2 BPSK	108	0	18.29	18.63	18.39	20.0	0.0
40	PB2 BPSK	108	54	18.40	18.64	18.46	20.0	0.0
40	PB2 BPSK	108	108	18.21	18.54	18.36	20.0	0.0
40	PB2 BPSK	216	0	18.32	18.73	18.39		
40	QPSK	1	1	18.41	18.58	18.49		
40	QPSK	1	108	18.45	18.76	18.52	20.0	0.0
40	QPSK	1	214	18.41	18.64	18.37		
40	QPSK	108	0	18.13	18.54	18.28	20.0	0.0
40	QPSK	108	54	18.46	18.72	18.38	20.0	0.0
40	QPSK	108	108	18.22	18.61	18.44		
40	QPSK	216	0	18.34	18.67	18.45	20.0	0.0
40	16QAM	1	1	18.37	18.47	18.41	20.0	0.0
40	64QAM	1	1	18.46	18.44	18.45	20.0	0.0
40	256QAM	1	1	18.22	18.51	18.36	20.0	0.0
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1725	1745	1765	(dBm)	(dB)
30	PB2 BPSK	1	80	18.32	18.73	18.40	20.0	0.0
Channel				344000	349000	353000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1722.5	1745	1767.5	(dBm)	(dB)
25	PB2 BPSK	1	67	18.31	18.67	18.44	20.0	0.0
Channel				343000	349000	354000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1720	1745	1770	(dBm)	(dB)
20	QPSK	1	53	18.37	18.74	18.43	20.0	0.0
Channel				342000	349000	355000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1717.5	1745	1772.5	(dBm)	(dB)
15	QPSK	1	40	18.32	18.72	18.31	20.0	0.0
Channel				341000	349000	356000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1714	1745	1775	(dBm)	(dB)
10	QPSK	1	26	18.39	18.64	18.52	20.0	0.0
Channel				340000	349000	357000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1712.5	1745	1777.5	(dBm)	(dB)
5	QPSK	1	13	18.40	18.61	18.29	20.0	0.0

n66_Ant4 DSI1 For ENDC							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)
Channel				346000	349000	352000	MPR (dB)
Frequency (MHz)				1720	1745	1760	
40	Pl2 BPSK	1	1	15.40	15.59	15.47	
40	Pl2 BPSK	1	108	15.14	15.51	15.44	17.0
40	Pl2 BPSK	1	214	15.33	15.56	15.25	
40	Pl2 BPSK	108	0	15.21	15.53	15.29	17.0
40	Pl2 BPSK	108	54	15.42	15.59	15.33	17.0
40	Pl2 BPSK	108	108	15.14	15.53	15.25	
40	Pl2 BPSK	216	0	15.45	15.56	15.60	17.0
40	QPSK	1	1	15.53	15.50	15.38	
40	QPSK	1	108	15.41	15.70	15.46	17.0
40	QPSK	1	214	15.29	15.51	15.27	
40	QPSK	108	0	15.39	15.63	15.56	17.0
40	QPSK	108	54	15.26	15.67	15.58	17.0
40	QPSK	108	108	15.26	15.57	15.36	
40	QPSK	216	0	15.45	15.62	15.46	17.0
40	16QAM	1	1	15.10	15.36	15.44	17.0
40	16QAM	1	1	15.27	15.51	15.52	17.0
40	256QAM	1	1	15.19	15.38	15.46	17.0
Channel				346000	349000	353000	Tune-up limit (dBm)
Frequency (MHz)				1725	1745	1765	MPR (dB)
30	Pl2 BPSK	1	80	15.49	15.65	15.48	17.0
Channel				345000	349000	353000	Tune-up limit (dBm)
Frequency (MHz)				1722.5	1745	1767.5	MPR (dB)
25	Pl2 BPSK	1	67	15.46	15.48	15.55	17.0
Channel				345000	349000	353000	Tune-up limit (dBm)
Frequency (MHz)				1720	1745	1770	MPR (dB)
20	QPSK	1	53	15.40	15.62	15.52	17.0
Channel				343000	349000	354000	Tune-up limit (dBm)
Frequency (MHz)				1717.5	1745	1772.5	MPR (dB)
15	QPSK	1	40	15.41	15.62	15.52	17.0
Channel				343000	349000	355000	Tune-up limit (dBm)
Frequency (MHz)				1715	1745	1775	MPR (dB)
10	QPSK	1	26	15.31	15.52	15.64	17.0
Channel				342000	349000	356000	Tune-up limit (dBm)
Frequency (MHz)				1712.5	1745	1777.5	MPR (dB)
5	QPSK	1	13	15.52	15.59	15.61	17.0

n66_Ant4 DSI1 For ENDC							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)
Channel				346000	349000	352000	MPR (dB)
Frequency (MHz)				1720	1745	1760	
40	Pl2 BPSK	1	1	19.12	19.50	19.31	
40	Pl2 BPSK	1	108	19.10	19.33	19.57	21.0
40	Pl2 BPSK	1	214	19.33	19.57	19.34	
40	Pl2 BPSK	108	0	19.19	19.31	19.29	21.0
40	Pl2 BPSK	108	54	19.23	19.63	19.17	21.0
40	Pl2 BPSK	108	108	19.05	19.50	19.44	
40	Pl2 BPSK	216	0	19.13	19.52	19.25	21.0
40	QPSK	1	1	19.26	19.34	19.34	
40	QPSK	1	108	19.24	19.66	19.36	21.0
40	QPSK	1	214	19.13	19.34	19.23	
40	QPSK	108	0	19.19	19.32	19.49	21.0
40	QPSK	108	54	19.27	19.68	19.26	21.0
40	QPSK	108	108	19.36	19.36	19.36	21.0
40	QPSK	216	0	19.23	19.45	19.41	
40	16QAM	1	1	19.19	19.34	19.25	21.0
40	16QAM	1	1	19.41	19.56	19.17	21.0
40	256QAM	1	1	17.71	18.32	17.81	1.5
Channel				346000	349000	353000	Tune-up limit (dBm)
Frequency (MHz)				1725	1745	1765	MPR (dB)
30	Pl2 BPSK	1	80	19.03	19.62	19.39	21.0
Channel				345000	349000	353000	Tune-up limit (dBm)
Frequency (MHz)				1722.5	1745	1767.5	MPR (dB)
25	Pl2 BPSK	1	67	19.15	19.57	19.30	21.0
Channel				345000	349000	353000	Tune-up limit (dBm)
Frequency (MHz)				1720	1745	1770	MPR (dB)
20	QPSK	1	53	19.22	19.66	19.24	21.0
Channel				343000	349000	354000	Tune-up limit (dBm)
Frequency (MHz)				1717.5	1745	1772.5	MPR (dB)
15	QPSK	1	40	19.10	19.67	19.26	21.0
Channel				343000	349000	355000	Tune-up limit (dBm)
Frequency (MHz)				1715	1745	1775	MPR (dB)
10	QPSK	1	26	19.08	19.56	19.31	21.0
Channel				342000	349000	356000	Tune-up limit (dBm)
Frequency (MHz)				1712.5	1745	1777.5	MPR (dB)
5	QPSK	1	13	19.11	19.61	19.26	21.0



n38_Ant4 DSI1&4 For SA								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	518000	518996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PQ2 BPSK	1	1	18.53	18.55	18.52		
40	PQ2 BPSK	1	53	18.78	18.51	18.77	20.5	0.0
40	PQ2 BPSK	1	104	18.65	18.48	18.56		
40	PQ2 BPSK	50	0	18.62	18.58	18.61	20.5	0.0
40	PQ2 BPSK	50	28	18.63	18.75	18.62	20.5	0.0
40	PQ2 BPSK	50	56	18.66	18.51	18.51		
40	PQ2 BPSK	100	0	18.56	18.54	18.73	20.5	0.0
40	QPSK	1	1	18.52	18.72	18.53		
40	QPSK	1	53	18.56	18.80	18.53	20.5	0.0
40	QPSK	1	104	18.52	18.56	18.69		
40	QPSK	50	0	18.52	18.70	18.52	20.5	0.0
40	QPSK	50	28	18.57	18.78	18.55	20.5	0.0
40	QPSK	50	56	18.56	18.50	18.53	20.5	0.0
40	QPSK	100	0	18.58	18.69	18.67		
40	16QAM	1	1	18.56	18.72	18.59	20.5	0.0
40	64QAM	1	1	18.53	18.74	18.52	20.5	0.0
40	256QAM	1	1	18.59	18.71	18.50	20.5	0.0
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2585	2610		
20	QPSK	1	53	18.59	18.68	18.61	20.5	0.0
Channel				518002	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	40	18.53	18.64	18.56	20.5	0.0
Channel				518004	519000	522996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2573.02	2595	2614.98		
10	QPSK	1	28	18.56	18.78	18.69	20.5	0.0
Channel				518006	519000	523494	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2572.53	2595	2617.47		
5	QPSK	1	13	18.61	18.82	18.61	20.5	0.0

n38_Ant4 DSI1&4 For END C								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	518000	518996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PQ2 BPSK	1	1	15.63	15.62	15.56		
40	PQ2 BPSK	1	53	15.63	15.53	15.72	17.5	0.0
40	PQ2 BPSK	1	104	15.56	15.56	15.54		
40	PQ2 BPSK	50	0	15.71	15.62	15.52	17.5	0.0
40	PQ2 BPSK	50	28	15.50	15.54	15.69	17.5	0.0
40	PQ2 BPSK	50	56	15.56	15.63	15.52		
40	PQ2 BPSK	100	0	15.63	15.53	15.56	17.5	0.0
40	QPSK	1	1	15.58	15.53	15.61		
40	QPSK	1	53	15.51	15.76	15.53	17.5	0.0
40	QPSK	1	104	15.63	15.52	15.61		
40	QPSK	50	0	15.56	15.58	15.56	17.5	0.0
40	QPSK	50	28	15.63	15.73	15.57	17.5	0.0
40	QPSK	50	56	15.53	15.51	15.52	17.5	0.0
40	QPSK	100	0	15.51	15.60	15.51		
40	16QAM	1	1	15.58	15.58	15.58	17.5	0.0
40	64QAM	1	1	15.65	15.51	15.66	17.5	0.0
40	256QAM	1	1	15.73	15.53	15.63	17.5	0.0
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2585	2610		
20	QPSK	1	53	15.63	15.63	14.65	17.5	0.0
Channel				518002	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	40	15.52	15.61	15.64	17.5	0.0
Channel				519004	519000	522996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2574.02	2595	2614.98		
10	QPSK	1	28	15.71	15.56	15.66	17.5	0.0
Channel				518006	519000	523494	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2572.53	2595	2617.47		
5	QPSK	1	13	15.64	15.63	15.75	17.5	0.0

n41_Ant4 DSI1 For SA								
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				504204	518000	532596		
Frequency (MHz)				2521.02	2592.99	2664.99		
50	PQ2 BPSK	1	1	20.53	20.56	20.52		
50	PQ2 BPSK	1	135	21.13	21.26	21.10	22.5	0.0
50	PQ2 BPSK	1	268	20.56	20.78	20.53		
50	PQ2 BPSK	135	0	20.63	21.06	21.02	22.5	0.0
50	PQ2 BPSK	135	68	21.08	21.11	21.13	22.5	0.0
50	PQ2 BPSK	135	135	21.12	21.21	21.23		
50	PQ2 BPSK	270	0	21.30	21.00	20.97	22.5	0.0
50	QPSK	1	1	20.84	20.63	20.67		
50	QPSK	1	135	21.19	21.47	21.38	22.5	0.0
50	QPSK	1	268	20.61	20.56	20.63		
50	QPSK	135	0	21.21	21.21	21.27	22.5	0.0
50	QPSK	135	68	21.14	21.38	21.36	22.5	0.0
50	QPSK	135	135	21.30	21.21	21.13		
50	QPSK	270	0	21.05	21.38	21.36	22.5	0.0
50	16QAM	1	1	20.53	20.62	20.59	22.5	0.0
50	64QAM	1	1	20.56	20.63	20.63	22.5	0.0
50	256QAM	1	1	20.60	20.56	20.58	22.5	0.0
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2516.01	2592.99	2670		
40	PQ2 BPSK	1	108	21.37	21.28	21.40	22.5	0.0
Channel				502202	518598	535596	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98		
30	PQ2 BPSK	1	80	21.42	21.33	21.42	22.5	0.0
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2504.02	2592.99	2679.99		
20	QPSK	1	53	21.27	21.21	21.32	22.5	0.0
Channel				500700	518598	536496	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.5	2592.99	2682.48		
15	QPSK	1	40	21.24	21.37	21.32	22.5	0.0
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2688		
10	QPSK	1	28	21.30	21.31	21.29	22.5	0.0

n41_Ant4 DSI1 For ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				504204	518598	532998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	PI2 BPSK	1	1	17.56	17.64	17.52	19.5	0.0	
50	PI2 BPSK	1	135	18.19	18.13	17.85			
50	PI2 BPSK	1	268	17.63	17.63	17.63			
50	PI2 BPSK	135	0	17.93	18.01	17.53	19.5	0.0	
50	PI2 BPSK	135	68	18.17	18.16	18.11	19.5	0.0	
50	PI2 BPSK	135	135	18.14	18.24	18.22	19.5	0.0	
50	PI2 BPSK	270	0	18.34	17.97	17.96			
50	QPSK	1	1	17.81	17.83	17.63			
50	QPSK	1	135	18.08	18.40	18.25	19.5	0.0	
50	QPSK	1	268	17.56	17.63	17.59			
50	QPSK	135	0	18.19	18.29	18.34		0.0	
50	QPSK	135	68	18.23	18.44	18.20	19.5	0.0	
50	QPSK	135	135	18.21	18.20	18.20	19.5	0.0	
50	QPSK	270	0	18.13	18.42	18.23	19.5	0.0	
50	16QAM	1	1	17.89	17.83	17.63			
50	64QAM	1	1	17.69	17.82	17.59		0.0	
50	256QAM	1	1	17.63	17.59	17.63	19.5	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	PI2 BPSK	1	108	18.05	18.36	18.41	19.5	0.0	
Channel				522202	518598	535098	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	PI2 BPSK	1	80	18.21	18.39	18.36	19.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	53	18.23	18.40	18.33	19.5	0.0	
Channel				500700	518598	536498	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	40	18.01	18.40	18.33	19.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	26	18.12	18.52	18.29	19.5	0.0	

n41_Ant4 DSI4 For SA&ENDC									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				504204	518598	532998			
Frequency (MHz)				2521.02	2592.99	2664.99			
50	PI2 BPSK	1	1	18.63	18.57	18.78	20.5	0.0	
50	PI2 BPSK	1	135	18.14	18.18	18.83			
50	PI2 BPSK	1	268	18.58	18.63	18.98			
50	PI2 BPSK	135	0	18.83	19.01	19.03	20.5	0.0	
50	PI2 BPSK	135	68	19.21	19.23	18.92	20.5	0.0	
50	PI2 BPSK	135	135	19.08	19.23	19.18	20.5	0.0	
50	PI2 BPSK	270	0	18.32	18.84	18.84			
50	QPSK	1	1	18.36	18.56	18.69			
50	QPSK	1	135	19.02	19.57	19.26	20.5	0.0	
50	QPSK	1	268	18.69	18.53	18.67			
50	QPSK	135	0	19.20	19.27	19.28		0.0	
50	QPSK	135	68	19.18	19.20	19.22	20.5	0.0	
50	QPSK	135	135	19.16	19.28	19.28	20.5	0.0	
50	QPSK	270	0	19.10	19.28	19.25	20.5	0.0	
50	16QAM	1	1	18.63	18.69	18.58			
50	64QAM	1	1	18.63	18.63	18.59		0.0	
50	256QAM	1	1	18.64	18.58	18.69	20.5	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	PI2 BPSK	1	108	18.10	19.35	19.19	20.5	0.0	
Channel				522202	518598	535098	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	PI2 BPSK	1	80	19.20	19.36	19.30	20.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	53	19.17	19.44	19.35	20.5	0.0	
Channel				500700	518598	536498	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	40	18.17	19.43	19.38	20.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	26	19.11	19.49	19.33	20.5	0.0	



n77_Ants DSI1 For SA/DSI 4 For SA&ENDC									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648334	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	18.05	18.16	17.86	19.0	0.0	
50	PI2 BPSK	1	135	18.12	18.09	17.74			
50	PI2 BPSK	1	268	18.11	18.08	17.87			
50	PI2 BPSK	135	0	17.91	18.14	17.84	19.0	0.0	
50	PI2 BPSK	135	68	17.96	17.80	17.83	19.0	0.0	
50	PI2 BPSK	135	135	18.01	18.15	17.91	19.0	0.0	
50	PI2 BPSK	270	0	18.06	18.02	17.96	19.0	0.0	
50	QPSK	1	1	18.06	18.07	17.99	19.0	0.0	
50	QPSK	1	135	17.96	18.26	17.93			
50	QPSK	1	268	18.10	18.09	17.96			
50	QPSK	135	0	18.13	17.97	17.77	19.0	0.0	
50	QPSK	135	68	17.96	18.21	17.88	19.0	0.0	
50	QPSK	135	135	17.90	17.84	17.90	19.0	0.0	
50	QPSK	270	0	17.92	17.97	17.85	19.0	0.0	
50	16QAM	1	1	17.93	18.07	17.83			
50	64QAM	1	1	18.06	18.10	17.76			
50	256QAM	1	1	17.89	18.22	17.85	19.0	0.0	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	17.90	18.08	17.84	19.0	0.0	
Channel				647334	656000	664668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	26	17.97	18.22	17.86	19.0	0.0	
Channel				647168	656000	664834	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	17.92	18.17	17.80	19.0	0.0	
Channel				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	17.91	18.19	17.78	19.0	0.0	

par27Q n77_Ant5 DSI1 For SA/DSI 4 For SA&ENDC									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				631668	633334	635000			
Frequency (MHz)				3475.02	3500.01	3525			
50	PI2 BPSK	1	1	18.00	18.04	17.93	19.0	0.0	
50	PI2 BPSK	1	135	17.95	17.95	17.90			
50	PI2 BPSK	1	268	17.88	17.88	17.91			
50	PI2 BPSK	135	0	17.96	17.93	18.00	19.0	0.0	
50	PI2 BPSK	135	68	17.97	18.04	17.96	19.0	0.0	
50	PI2 BPSK	135	135	18.14	18.00	18.07	19.0	0.0	
50	PI2 BPSK	270	0	18.04	18.03	17.97	19.0	0.0	
50	QPSK	1	1	18.18	18.12	18.18			
50	QPSK	1	135	18.23	18.27	18.26			
50	QPSK	1	268	17.87	17.93	17.97	19.0	0.0	
50	QPSK	135	0	18.08	18.07	18.09			
50	QPSK	135	68	18.26	18.24	18.15			
50	QPSK	135	135	18.03	18.05	17.96	19.0	0.0	
50	QPSK	270	0	17.98	18.03	18.00	19.0	0.0	
50	16QAM	1	1	18.07	18.07	18.19			
50	64QAM	1	1	18.01	17.99	17.91			
50	256QAM	1	1	18.04	18.16	18.12	19.0	0.0	
Channel				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3525.98			
40	QPSK	1	53	18.13	18.04	17.87	19.0	0.0	
Channel				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	26	18.07	18.08	18.11	19.0	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49			
15	QPSK	1	19	18.04	17.97	18.08	19.0	0.0	
Channel				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3464.01	3500.01	3544.98			
10	QPSK	1	12	17.97	18.08	18.08	19.0	0.0	

n77_Ant5 DSI1 For ENDC									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				648534	656000	663668			
Frequency (MHz)				3725.01	3840	3955.02			
50	PI2 BPSK	1	1	14.87	15.13	14.93	18.0	0.0	
50	PI2 BPSK	1	135	14.98	14.91	14.81			
50	PI2 BPSK	1	268	15.04	14.98	14.85			
50	PI2 BPSK	135	0	14.99	15.01	14.98	18.0	0.0	
50	PI2 BPSK	135	68	14.86	14.78	14.68	18.0	0.0	
50	PI2 BPSK	135	135	14.97	15.09	15.09	18.0	0.0	
50	PI2 BPSK	270	0	15.08	14.92	14.88	18.0	0.0	
50	QPSK	1	1	14.78	15.13	15.04			
50	QPSK	1	135	14.82	15.15	14.89			
50	QPSK	1	268	15.05	15.04	14.84	18.0	0.0	
50	QPSK	135	0	14.91	14.85	14.84			
50	QPSK	135	68	15.05	15.09	14.95			
50	QPSK	135	135	14.93	14.95	14.98	18.0	0.0	
50	QPSK	270	0	14.86	15.04	14.99	18.0	0.0	
50	16QAM	1	1	14.88	15.00	14.97			
50	64QAM	1	1	14.96	14.84	14.76			
50	256QAM	1	1	14.85	15.05	14.85	18.0	0.0	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	14.72	15.06	14.77	18.0	0.0	
Channel				647334	656000	664668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	26	14.75	14.95	14.76	18.0	0.0	
Channel				647178	656000	664834	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	14.72	15.07	14.81	18.0	0.0	
Channel				647000	656000	665000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	14.63	15.01	14.69	18.0	0.0	

n77_Ant5 DS11 For ENDC

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000		
Frequency (MHz)				3475.02	3500.01	3525		
50	PB2 BPSK	1	1	14.87	14.89	14.89		
50	PB2 BPSK	1	135	15.02	15.03	14.99	16.0	0.0
50	PB2 BPSK	1	268	14.96	14.94	15.05		
50	PB2 BPSK	135	0	14.84	14.87	14.89	16.0	0.0
50	PB2 BPSK	135	68	14.85	14.87	14.84	16.0	0.0
50	PB2 BPSK	135	135	14.97	14.98	15.10	16.0	0.0
50	PB2 BPSK	270	0	15.02	14.98	15.00		
50	QPSK	1	1	14.96	15.02	15.01		
50	QPSK	1	135	15.17	15.21	15.12	16.0	0.0
50	QPSK	1	268	15.15	15.17	15.16		
50	QPSK	135	0	14.95	14.96	14.93	16.0	0.0
50	QPSK	135	68	14.96	14.90	14.84	16.0	0.0
50	QPSK	135	135	14.77	14.81	14.75	16.0	0.0
50	QPSK	270	0	15.00	15.04	15.01		
50	16QAM	1	1	14.90	14.80	14.90	16.0	0.0
50	64QAM	1	1	14.91	15.00	14.97	16.0	0.0
50	256QAM	1	1	15.04	15.17	15.09	16.0	0.0
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)
40	QPSK	1	53	15.10	14.94	14.89	16.0	0.0
Channel				630668	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)
20	QPSK	1	26	15.02	14.96	14.91	16.0	0.0
Channel				635550	633334	633336	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)
15	QPSK	1	19	15.03	14.96	14.97	16.0	0.0
Channel				630334	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)
10	QPSK	1	12	15.01	14.96	14.98	16.0	0.0

n78_Ant5 DS11 For SA&DSI 4 For SA&ENDC

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				646334	650000	651668		
Frequency (MHz)				3725.01	3750	3775.02		
50	PB2 BPSK	1	1	18.10	18.22	18.19		
50	PB2 BPSK	1	135	18.08	18.03	17.98	19.0	0.0
50	PB2 BPSK	1	268	18.01	18.00	18.07		
50	PB2 BPSK	135	0	18.01	17.84	18.07	19.0	0.0
50	PB2 BPSK	135	68	18.02	18.06	18.12	19.0	0.0
50	PB2 BPSK	135	135	18.04	18.16	18.04	19.0	0.0
50	PB2 BPSK	270	0	18.13	18.23	18.11		
50	QPSK	1	1	18.12	18.10	18.15		
50	QPSK	1	135	18.16	18.21	18.20	19.0	0.0
50	QPSK	1	268	18.15	18.23	18.22		
50	QPSK	135	0	17.95	17.93	17.91	19.0	0.0
50	QPSK	135	68	18.09	18.12	18.09	19.0	0.0
50	QPSK	135	135	17.86	17.97	17.91		
50	QPSK	270	0	18.02	18.07	18.04	19.0	0.0
50	16QAM	1	1	17.89	17.93	17.81	19.0	0.0
50	64QAM	1	1	18.21	18.15	18.23	19.0	0.0
50	256QAM	1	1	18.23	18.22	18.16	19.0	0.0
Channel				648000	650000	652000	Tune-up limit	MPR
Frequency (MHz)				3720	3750	3780	(dBm)	(dB)
40	QPSK	1	53	17.60	18.07	17.63	19.0	0.0
Channel				647334	650000	652668	Tune-up limit	MPR
Frequency (MHz)				3710.01	3750	3760.02	(dBm)	(dB)
20	QPSK	1	26	17.62	18.20	17.62	19.0	0.0
Channel				647668	650000	652134	Tune-up limit	MPR
Frequency (MHz)				3707.92	3750	3762.51	(dBm)	(dB)
15	QPSK	1	19	17.91	18.20	17.86	19.0	0.0
Channel				647000	650000	653000	Tune-up limit	MPR
Frequency (MHz)				3704	3750	3756	(dBm)	(dB)
10	QPSK	1	12	17.99	18.06	17.89	19.0	0.0

par27Q n78_Ant5 DS11 For SA&DSI 4 For SA&ENDC

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				631668	633334	635000		
Frequency (MHz)				3475.02	3500.01	3525		
50	PB2 BPSK	1	1	18.12	18.19	18.15		
50	PB2 BPSK	1	135	18.08	18.09	18.03	19.0	0.0
50	PB2 BPSK	1	268	18.04	18.06	18.12		
50	PB2 BPSK	135	0	18.10	18.13	18.14	19.0	0.0
50	PB2 BPSK	135	68	18.14	18.05	18.12	19.0	0.0
50	PB2 BPSK	135	135	18.22	18.11	18.17	19.0	0.0
50	PB2 BPSK	270	0	18.06	18.06	18.06		
50	QPSK	1	1	18.09	18.10	18.01		
50	QPSK	1	135	18.23	18.25	18.23	19.0	0.0
50	QPSK	1	268	18.15	18.04	18.10		
50	QPSK	135	0	17.99	17.90	17.88	19.0	0.0
50	QPSK	135	68	18.02	18.12	18.08	19.0	0.0
50	QPSK	135	135	17.98	17.96	18.08		
50	QPSK	270	0	18.09	18.12	18.02	19.0	0.0
50	16QAM	1	1	17.98	18.00	17.97	19.0	0.0
50	64QAM	1	1	18.14	18.14	18.14	19.0	0.0
50	256QAM	1	1	18.06	18.08	18.11	19.0	0.0
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)
40	QPSK	1	53	17.50	17.67	17.77	19.0	0.0
Channel				630668	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)
20	QPSK	1	26	17.67	17.60	17.77	19.0	0.0
Channel				635550	633334	633336	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)
15	QPSK	1	19	18.00	17.81	17.69	19.0	0.0
Channel				630334	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)
10	QPSK	1	12	17.93	17.94	17.81	19.0	0.0



n78_Ant5 DSI1 For ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)
Channel				648334	650000	651666		
Frequency (MHz)				3725.01	3750	3775.02		
50	Pl2 BPSK	1	1	14.80	14.85	14.74	16.0	0.0
50	Pl2 BPSK	1	135	14.92	14.91	15.02		
50	Pl2 BPSK	1	268	15.10	15.16	15.19		
50	Pl2 BPSK	135	0	14.90	14.87	14.94	16.0	0.0
50	Pl2 BPSK	135	68	14.86	14.81	14.79	16.0	0.0
50	Pl2 BPSK	135	135	15.16	15.16	15.20	16.0	0.0
50	Pl2 BPSK	270	0	15.13	15.11	15.11	16.0	0.0
50	QPSK	1	1	14.90	14.87	14.85		
50	QPSK	1	135	15.16	15.21	15.20		
50	QPSK	1	268	15.02	15.03	15.15	16.0	0.0
50	QPSK	135	0	14.97	15.02	14.96		
50	QPSK	135	68	14.95	15.04	14.94		
50	QPSK	135	135	14.92	14.84	14.78	16.0	0.0
50	QPSK	270	0	15.03	15.17	15.06	16.0	0.0
50	16QAM	1	1	14.72	14.72	14.70		
50	64QAM	1	1	15.11	15.15	15.01		
50	256QAM	1	1	15.04	15.10	15.08	16.0	0.0
Channel				648000	650000	650000	Tune-up limit	MPR
Frequency (MHz)				3720	3750	3780	(dbm)	(db)
40	QPSK	1	53	14.85	15.08	14.92	16.0	0.0
Channel				647334	650000	652666	Tune-up limit	MPR
Frequency (MHz)				3710.01	3750	3790.02	(dbm)	(db)
20	QPSK	1	26	14.95	15.01	14.94	16.0	0.0
Channel				647103	650000	652951	Tune-up limit	MPR
Frequency (MHz)				3707.52	3750	3792.51	(dbm)	(db)
15	QPSK	1	19	14.93	14.94	15.00	16.0	0.0
Channel				647000	650000	653000	Tune-up limit	MPR
Frequency (MHz)				3705	3750	3795	(dbm)	(db)
10	QPSK	1	12	14.96	14.97	14.93	16.0	0.0

Par27Q n78_Ant5 DSI1 For ENDC								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)
Channel				631668	633334	635000		
Frequency (MHz)				3475.02	3500.01	3525		
50	Pl2 BPSK	1	1	14.99	14.93	14.95	16.0	0.0
50	Pl2 BPSK	1	135	15.10	15.01	15.05		
50	Pl2 BPSK	1	268	14.84	14.94	14.84		
50	Pl2 BPSK	135	0	15.00	14.96	15.00	16.0	0.0
50	Pl2 BPSK	135	68	14.91	14.90	14.81	16.0	0.0
50	Pl2 BPSK	135	135	14.96	14.92	15.04	16.0	0.0
50	Pl2 BPSK	270	0	15.06	14.99	14.97	16.0	0.0
50	QPSK	1	1	14.85	14.87	14.86		
50	QPSK	1	135	15.07	15.15	15.11		
50	QPSK	1	268	14.99	14.96	15.00	16.0	0.0
50	QPSK	135	0	15.00	14.96	14.91		
50	QPSK	135	68	14.87	15.03	14.91		
50	QPSK	135	135	14.75	14.86	14.80	16.0	0.0
50	QPSK	270	0	15.03	15.10	14.95	16.0	0.0
50	16QAM	1	1	15.01	14.95	14.93		
50	16QAM	1	1	14.88	14.92	15.00		
50	256QAM	1	1	15.05	15.00	15.05	16.0	0.0
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.98	(dbm)	(db)
40	QPSK	1	53	14.59	14.91	14.84	16.0	0.0
Channel				630668	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dbm)	(db)
20	QPSK	1	26	15.04	14.87	14.87	16.0	0.0
Channel				630332	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.49	(dbm)	(db)
15	QPSK	1	19	15.03	14.90	14.91	16.0	0.0
Channel				630334	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3446.01	3500.01	3544.98	(dbm)	(db)
10	QPSK	1	12	15.05	14.98	14.94	16.0	0.0



For DFT-30

n7_Ant0 DSI3 For SA							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm) MPR (dB)
Channel				502000	507000	512000	
Frequency (MHz)				2510	2535	2560	
20	PI2 BPSK	1	1	16.01	16.02	16.14	
20	PI2 BPSK	1	26	15.78	16.09	16.00	17.5 0.0
20	PI2 BPSK	1	49	15.89	16.12	16.07	17.5 0.0
20	PI2 BPSK	25	0	15.85	16.04	15.93	17.5 0.0
20	PI2 BPSK	25	13	15.94	16.16	16.07	17.5 0.0
20	PI2 BPSK	25	26	15.80	16.15	15.98	17.5 0.0
20	PI2 BPSK	50	0	15.89	16.06	16.06	17.5 0.0
20	QPSK	1	1	16.00	16.17	16.14	
20	QPSK	1	26	16.02	16.16	16.09	17.5 0.0
20	QPSK	1	49	15.93	16.17	16.15	17.5 0.0
20	QPSK	25	0	15.93	16.12	15.97	17.5 0.0
20	QPSK	25	13	15.99	16.16	16.09	17.5 0.0
20	QPSK	25	26	15.84	16.15	16.08	17.5 0.0
20	QPSK	50	0	15.93	16.09	16.04	17.5 0.0
20	16QAM	1	1	15.96	16.17	15.95	17.5 0.0
20	64QAM	1	1	15.81	16.10	15.97	17.5 0.0
20	256QAM	1	1	15.96	15.99	16.09	17.5 0.0
Channel				501500	507000	512500	Tune-up limit (dBm) MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	
15	QPSK	1	40	16.00	15.99	16.03	17.5 0.0
Channel				501000	507000	513000	Tune-up limit (dBm) MPR (dB)
Frequency (MHz)				2505	2535	2565	
10	QPSK	1	26	16.04	16.11	16.10	17.5 0.0

n7_Ant0 DSI3 For NSA							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm) MPR (dB)
Channel				502000	507000	512000	
Frequency (MHz)				2510	2535	2560	
20	PI2 BPSK	1	1	12.91	13.09	13.11	
20	PI2 BPSK	1	26	12.72	12.99	12.90	14.5 0.0
20	PI2 BPSK	1	49	12.82	13.01	13.03	14.5 0.0
20	PI2 BPSK	25	0	12.86	13.09	12.98	14.5 0.0
20	PI2 BPSK	25	13	13.05	13.05	13.03	14.5 0.0
20	PI2 BPSK	25	26	12.72	13.15	13.04	14.5 0.0
20	PI2 BPSK	50	0	12.96	13.05	13.17	14.5 0.0
20	QPSK	1	1	13.03	13.24	13.17	
20	QPSK	1	26	13.11	13.26	13.05	14.5 0.0
20	QPSK	1	49	12.81	13.23	13.19	14.5 0.0
20	QPSK	25	0	12.83	13.05	13.01	14.5 0.0
20	QPSK	25	13	13.04	13.20	13.13	14.5 0.0
20	QPSK	25	26	12.80	13.12	13.16	14.5 0.0
20	QPSK	50	0	12.80	13.21	13.09	14.5 0.0
20	16QAM	1	1	12.90	13.25	12.94	14.5 0.0
20	64QAM	1	1	12.80	13.19	12.91	14.5 0.0
20	256QAM	1	1	12.85	12.98	13.10	14.5 0.0
Channel				501500	507000	512500	Tune-up limit (dBm) MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	
15	QPSK	1	40	13.02	13.10	12.96	14.5 0.0
Channel				501000	507000	513000	Tune-up limit (dBm) MPR (dB)
Frequency (MHz)				2505	2535	2565	
10	QPSK	1	26	13.01	13.13	12.99	14.5 0.0

n7_Ant0 DSI2 For SA							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm) MPR (dB)
Channel				502000	507000	512000	
Frequency (MHz)				2510	2535	2560	
20	PI2 BPSK	1	1	20.99	20.87	20.92	
20	PI2 BPSK	1	26	20.74	20.80	20.78	22.0 0.0
20	PI2 BPSK	1	49	20.80	20.80	21.07	22.0 0.0
20	PI2 BPSK	25	0	20.77	21.01	20.88	22.0 0.0
20	PI2 BPSK	25	13	20.80	21.03	20.85	22.0 0.0
20	PI2 BPSK	25	26	20.68	21.09	20.76	22.0 0.0
20	PI2 BPSK	50	0	20.84	21.04	20.99	22.0 0.0
20	QPSK	1	1	20.80	21.06	21.19	
20	QPSK	1	26	20.98	21.28	20.97	22.0 0.0
20	QPSK	1	49	20.52	21.24	20.94	22.0 0.0
20	QPSK	25	0	20.77	20.97	20.80	22.0 0.0
20	QPSK	25	13	21.01	21.20	20.98	22.0 0.0
20	QPSK	25	26	20.70	21.01	21.19	22.0 0.0
20	QPSK	50	0	20.55	21.20	21.06	22.0 0.0
20	16QAM	1	1	20.80	21.17	20.76	22.0 0.0
20	64QAM	1	1	20.32	20.25	20.07	21.0 1.0
20	256QAM	1	1	17.95	18.32	18.03	19.0 3.0
Channel				501500	507000	512500	Tune-up limit (dBm) MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5	
15	QPSK	1	40	20.88	21.21	20.94	22.0 0.0
Channel				501000	507000	513000	Tune-up limit (dBm) MPR (dB)
Frequency (MHz)				2505	2535	2565	
10	QPSK	1	26	20.93	21.27	20.85	22.0 0.0



n7_Ant0 DS12 For NSA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				50000	507000	510000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2510	2535	2560		
20	PI2 BPSK	1	1	18.10	17.77	17.94		
20	PI2 BPSK	1	26	17.69	17.83	17.71	19.0	0.0
20	PI2 BPSK	1	49	17.91	17.75	18.13		
20	PI2 BPSK	25	0	17.81	17.98	17.80	19.0	0.0
20	PI2 BPSK	25	13	17.77	18.04	17.74	19.0	0.0
20	PI2 BPSK	25	26	17.58	18.13	17.72	19.0	0.0
20	PI2 BPSK	50	0	17.67	18.03	18.07		
20	QPSK	1	1	17.82	17.98	18.13		
20	QPSK	1	26	17.99	18.38	17.96	19.0	0.0
20	QPSK	1	49	17.48	18.28	17.87		
20	QPSK	25	0	17.66	17.90	17.71	19.0	0.0
20	QPSK	25	13	17.97	18.29	17.98	19.0	0.0
20	QPSK	25	26	17.64	18.10	18.13	19.0	0.0
20	QPSK	50	0	17.56	18.29	17.97		
20	16QAM	1	1	17.92	18.12	17.89	19.0	0.0
20	16QAM	1	1	17.67	18.21	17.88	19.0	0.0
20	256QAM	1	1	17.86	18.21	17.93	19.0	0.0
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2563.5		
15	QPSK	1	40	17.67	18.37	17.87	19.0	0.0
Channel				510000	513000	515000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565		
10	QPSK	1	26	17.83	18.28	17.92	19.0	0.0



n38_Ant0 DS13 For SA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	519000	519996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PQ2 BPSK	1	1	14.16	14.07	14.10		
40	PQ2 BPSK	1	53	14.59	14.42	14.47	15.0	0.0
40	PQ2 BPSK	1	104	14.05	13.99	13.89	15.0	0.0
40	PQ2 BPSK	50	0	14.02	13.90	13.97	15.0	0.0
40	PQ2 BPSK	50	28	14.10	13.97	14.08	15.0	0.0
40	PQ2 BPSK	50	56	14.58	14.32	14.40		
40	PQ2 BPSK	100	0	14.06	13.96	13.96	15.0	0.0
40	QPSK	1	1	14.05	14.12	14.18		
40	QPSK	1	53	14.40	14.00	14.43	15.0	0.0
40	QPSK	1	104	14.09	14.04	14.11		
40	QPSK	50	0	13.96	14.08	13.89	15.0	0.0
40	QPSK	50	28	14.38	14.41	14.31	15.0	0.0
40	QPSK	50	56	14.00	13.87	13.97	15.0	0.0
40	QPSK	100	0	13.98	14.00	13.97		
40	16QAM	1	1	14.06	14.14	14.18	15.0	0.0
40	64QAM	1	1	14.24	14.49	14.25	15.0	0.0
40	256QAM	1	1	14.04	14.02	14.04	15.0	0.0
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2595	2610		
20	QPSK	1	26	14.32	14.59	14.29	15.0	0.0
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	19	14.31	14.47	14.28	15.0	0.0
Channel				518004	519000	522996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2593.02	2595	2614.08		
10	QPSK	1	12	14.24	14.50	14.30	15.0	0.0

n38_Ant0 DS13 For NSA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				518004	519000	519996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PQ2 BPSK	1	1	11.26	11.07	11.17		
40	PQ2 BPSK	1	53	11.57	11.41	11.39	12.0	0.0
40	PQ2 BPSK	1	104	11.04	10.93	10.89	12.0	0.0
40	PQ2 BPSK	50	0	11.16	11.65	11.37	12.0	0.0
40	PQ2 BPSK	50	28	11.23	11.61	11.39	12.0	0.0
40	PQ2 BPSK	50	56	11.59	11.37	11.45		
40	PQ2 BPSK	100	0	11.14	10.75	10.94	12.0	0.0
40	QPSK	1	1	11.14	11.07	11.16		
40	QPSK	1	53	11.33	11.66	11.42	12.0	0.0
40	QPSK	1	104	11.11	11.56	11.35		
40	QPSK	50	0	11.03	10.92	10.92	12.0	0.0
40	QPSK	50	28	11.15	11.64	11.42	12.0	0.0
40	QPSK	50	56	11.23	11.59	11.41	12.0	0.0
40	QPSK	100	0	11.32	11.44	11.25		
40	16QAM	1	1	11.17	11.13	11.24	12.0	0.0
40	64QAM	1	1	11.32	11.40	11.21	12.0	0.0
40	256QAM	1	1	11.19	11.62	11.28	12.0	0.0
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2580	2595	2610		
20	QPSK	1	26	11.19	11.54	11.27	12.0	0.0
Channel				518000	519000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	19	11.28	11.65	11.33	12.0	0.0
Channel				518004	519000	522996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2593.02	2595	2614.08		
10	QPSK	1	12	11.28	11.61	11.28	12.0	0.0

n41_Ant0 DS13 For SA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				520002	518598	520000		
Frequency (MHz)				2548.01	2592.99	2640		
100	PQ2 BPSK	1	1	16.02	16.02	16.31		
100	PQ2 BPSK	1	137	16.40	16.62	16.33	18.0	0.0
100	PQ2 BPSK	1	271	16.05	16.05	16.11		
100	PQ2 BPSK	135	0	16.36	16.50	16.53	18.0	0.0
100	PQ2 BPSK	135	69	16.56	16.59	16.58	18.0	0.0
100	PQ2 BPSK	135	138	16.37	16.63	16.38		
100	PQ2 BPSK	270	0	16.66	16.49	16.45	18.0	0.0
100	QPSK	1	1	16.05	16.01	16.04		
100	QPSK	1	137	16.45	16.88	16.31	18.0	0.0
100	QPSK	1	271	16.03	16.11	16.05		
100	QPSK	135	0	16.49	16.72	16.72	18.0	0.0
100	QPSK	135	69	16.33	16.75	16.27	18.0	0.0
100	QPSK	135	138	16.34	16.62	16.69		
100	QPSK	270	0	16.99	16.97	16.26	18.0	0.0
100	16QAM	1	1	16.39	16.50	16.68	18.0	0.0
100	64QAM	1	1	16.44	16.64	16.49	18.0	0.0
100	256QAM	1	1	16.24	16.48	16.44	18.0	0.0
Channel				508000	518598	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2541	2592.99	2644.98		
90	QPSK	1	123	16.31	16.71	16.20	18.0	0.0
Channel				507004	518598	529996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2538.02	2592.99	2649.99		
80	QPSK	1	109	16.23	16.69	16.23	18.0	0.0
Channel				505000	518598	531996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536	2592.99	2659.98		
60	QPSK	1	81	16.40	16.68	16.19	18.0	0.0
Channel				504004	518598	532996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2521.02	2592.99	2664.99		
50	QPSK	1	67	16.40	16.73	16.09	18.0	0.0
Channel				503002	518598	534000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2518.01	2592.99	2670		
40	QPSK	1	53	16.47	16.69	16.23	18.0	0.0
Channel				502000	518598	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98		
30	QPSK	1	39	16.31	16.77	16.25	18.0	0.0
Channel				501004	518598	535996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99		
20	QPSK	1	25	16.42	16.83	16.22	18.0	0.0
Channel				500000	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2501.01	2592.99	2685		
10	QPSK	1	12	16.32	16.71	16.18	18.0	0.0

n41_Ant0 DSI3 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				500200	518598	526000			
Frequency (MHz)				2546.01	2592.99	2640			
100	P12 BPSK	1	1	13.52	13.79	13.98			
100	P12 BPSK	1	137	13.79	14.24	13.95	15.5	0.0	
100	P12 BPSK	1	271	13.69	13.50	13.54			
100	P12 BPSK	135	0	13.86	14.07	13.97	15.5	0.0	
100	P12 BPSK	135	69	14.09	13.99	14.01	15.5	0.0	
100	P12 BPSK	135	138	13.91	14.06	13.99			
100	P12 BPSK	270	0	14.01	14.10	13.97	15.5	0.0	
100	QPSK	1	1	13.58	13.75	13.70			
100	QPSK	1	137	13.90	14.39	13.87	15.5	0.0	
100	QPSK	1	271	13.75	13.71	13.99			
100	QPSK	135	0	13.99	14.25	14.11	15.5	0.0	
100	QPSK	135	69	13.93	14.26	13.78	15.5	0.0	
100	QPSK	135	138	13.83	14.12	14.70	15.5	0.0	
100	QPSK	270	0	13.97	14.29	13.96			
100	16QAM	1	1	13.96	13.98	14.29	15.5	0.0	
100	64QAM	1	1	13.93	14.07	14.01	15.5	0.0	
100	256QAM	1	1	14.14	13.83	13.97	15.5	0.0	
Channel				508200	518598	528996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	13.83	14.29	13.68	15.5	0.0	
Channel				512204	518598	522208	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2640.99			
80	QPSK	1	109	13.77	14.23	13.83	15.5	0.0	
Channel				505200	518598	531996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	81	13.88	14.29	13.68	15.5	0.0	
Channel				504204	518598	532998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	67	13.88	14.29	13.66	15.5	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	53	13.69	14.30	13.87	15.5	0.0	
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	13.82	14.15	13.83	15.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	26	13.75	14.36	13.65	15.5	0.0	
Channel				500200	518598	536996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	19	13.82	14.20	13.88	15.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	12	13.77	14.30	13.70	15.5	0.0	

n41_Ant0 DSI2 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				500200	518598	526000			
Frequency (MHz)				2546.01	2592.99	2640			
100	P12 BPSK	1	1	21.98	22.06	22.04			
100	P12 BPSK	1	137	21.95	22.12	22.12	22.5	0.0	
100	P12 BPSK	1	271	21.91	21.92	21.78			
100	P12 BPSK	135	0	22.03	22.05	21.90	22.5	0.0	
100	P12 BPSK	135	69	22.00	22.03	21.89	22.5	0.0	
100	P12 BPSK	135	138	21.99	22.06	22.05			
100	P12 BPSK	270	0	21.93	22.06	21.96	22.5	0.0	
100	QPSK	1	1	21.94	22.10	22.09			
100	QPSK	1	137	21.88	22.16	21.78	22.5	0.0	
100	QPSK	1	271	21.94	22.01	21.98			
100	QPSK	135	0	21.88	22.03	21.82	22.5	0.0	
100	QPSK	135	69	22.00	22.10	22.06	22.5	0.0	
100	QPSK	135	138	22.04	22.08	22.03	22.5	0.0	
100	QPSK	270	0	21.92	22.00	21.84			
100	16QAM	1	1	21.78	21.96	21.82	22.5	0.0	
100	64QAM	1	1	21.79	21.87	21.69	22.5	0.0	
100	256QAM	1	1	20.51	20.68	20.52	21.0	1.5	
Channel				508200	518598	528996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	21.87	21.97	21.63	23.0	0.0	
Channel				512204	518598	532998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2649.99			
80	QPSK	1	109	21.89	22.15	21.66	23.0	0.0	
Channel				505200	518598	531996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2526	2592.99	2659.98			
60	QPSK	1	81	21.78	22.00	21.56	23.0	0.0	
Channel				504204	518598	532998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	67	21.73	22.14	21.66	23.0	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	53	21.72	22.04	21.74	23.0	0.0	
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	21.82	22.08	21.68	23.0	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	26	21.79	22.02	21.74	23.0	0.0	
Channel				500200	518598	536996	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2503.5	2592.99	2682.48			
15	QPSK	1	19	21.67	22.09	21.76	23.0	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	12	21.63	22.08	21.59	23.0	0.0	

n66_Ant1 DSI3 For SA&NSA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				346000	349000	352000	23.5	0.0
Frequency (MHz)				1730	1745	1760		
40	PI/2 BPSK	1	1	22.14	22.04	21.91	23.5	0.0
40	PI/2 BPSK	1	53	22.42	22.38	22.30		
40	PI/2 BPSK	1	104	22.18	22.38	22.10	23.5	0.0
40	PI/2 BPSK	50	0	21.90	21.96	22.16		
40	PI/2 BPSK	50	28	22.04	21.91	21.82	23.5	0.0
40	PI/2 BPSK	50	56	22.35	22.46	22.23		
40	PI/2 BPSK	100	0	22.16	22.35	22.07	23.5	0.0
40	QPSK	1	1	22.07	21.86	21.81		
40	QPSK	1	53	22.40	22.58	22.31	23.5	0.0
40	QPSK	1	104	22.21	22.38	22.04		
40	QPSK	50	0	21.79	21.77	21.95	23.5	0.0
40	QPSK	50	28	22.09	22.43	22.01		
40	QPSK	50	56	22.32	22.41	22.33	23.5	0.0
40	QPSK	100	0	21.98	22.38	22.02		
40	16QAM	1	1	22.00	21.99	22.17	23.5	0.0
40	64QAM	1	1	22.03	22.00	21.85		
40	256QAM	1	1	20.02	20.08	19.73	21.0	2.5
Channel				345000	349000	353000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1725	1745	1765		
30	QPSK	1	80	22.41	22.47	22.18	23.5	0.0
Channel				344500	349000	353500		
Frequency (MHz)				1722.5	1745	1767.5	Tune-up limit (dBm)	MPR (dB)
25	QPSK	1	67	22.37	22.52	22.24		
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1720	1745	1770		
20	QPSK	1	28	22.23	22.37	22.11	23.5	0.0
Channel				343500	349000	354500		
Frequency (MHz)				1717.5	1745	1772.5	Tune-up limit (dBm)	MPR (dB)
15	QPSK	1	19	22.22	22.41	22.12		
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				1715	1745	1775		
10	QPSK	1	12	22.34	22.46	22.24	23.5	0.0

n77_Ant1 DSI3 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch / Freq	Power Middle Ch / Freq	Power High Ch / Freq	Tune-up limit (dBm)	MPR (dB)	
Channel				650000	656000	662000	22.0	0.0	
Frequency (MHz)				3750	3840	3930			
100	PI/2 BPSK	1	1	20.31	20.35	20.09			
100	PI/2 BPSK	1	137	20.42	20.95	20.60	22.0	0.0	
100	PI/2 BPSK	1	271	20.02	20.06	20.16			
100	PI/2 BPSK	135	0	20.52	21.00	20.62			
100	PI/2 BPSK	135	69	20.45	20.90	20.60	22.0	0.0	
100	PI/2 BPSK	135	138	20.42	20.89	20.68			
100	PI/2 BPSK	270	0	20.58	20.88	20.77			
100	QPSK	1	1	20.12	20.24	20.15	22.0	0.0	
100	QPSK	1	137	20.59	21.04	20.81			
100	QPSK	1	271	20.23	20.02	20.08			
100	QPSK	135	0	20.46	20.99	20.71	22.0	0.0	
100	QPSK	135	69	20.45	21.01	20.70			
100	QPSK	135	138	20.58	20.90	20.74			
100	QPSK	270	0	20.46	20.96	20.72	22.0	0.0	
100	16QAM	1	1	20.13	20.01	20.13			
100	64QAM	1	1	20.28	20.00	20.13			
100	256QAM	1	1	19.63	19.57	19.53	21.5	0.0	
Channel				649668	656000	662334	Tune-up limit	MPR	
Frequency (MHz)				3745.02	3840	3935.01	(dBm)	(dB)	
90	QPSK	1	123	20.54	20.86	20.71	22.0	0.0	
Channel				649334	656000	662668	Tune-up limit	MPR	
Frequency (MHz)				3740.01	3840	3940.02	(dBm)	(dB)	
80	QPSK	1	109	20.49	20.85	20.68	22.0	0.0	
Channel				649000	656000	663000	Tune-up limit	MPR	
Frequency (MHz)				3735	3840	3945	(dBm)	(dB)	
70	QPSK	1	95	20.48	20.84	20.70	22.0	0.0	
Channel				648668	656000	663334	Tune-up limit	MPR	
Frequency (MHz)				3730.02	3840	3950.01	(dBm)	(dB)	
60	QPSK	1	81	20.54	21.02	20.70	22.0	0.0	
Channel				648334	656000	663668	Tune-up limit	MPR	
Frequency (MHz)				3725.01	3840	3955.02	(dBm)	(dB)	
50	QPSK	1	67	20.39	21.02	20.69	22.0	0.0	
Channel				648000	656000	664000	Tune-up limit	MPR	
Frequency (MHz)				3720	3840	3960	(dBm)	(dB)	
40	QPSK	1	53	20.40	20.84	20.67	22.0	0.0	
Channel				647334	656000	664668	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3840	3970.02	(dBm)	(dB)	
20	QPSK	1	26	20.60	20.89	20.66	22.0	0.0	
Channel				647168	656000	664834	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3840	3972.51	(dBm)	(dB)	
15	QPSK	1	19	20.59	20.85	20.72	22.0	0.0	
Channel				647000	656000	665000	Tune-up limit	MPR	
Frequency (MHz)				3705	3840	3975	(dBm)	(dB)	
10	QPSK	1	12	20.49	20.94	20.61	22.0	0.0	

Par27Q n77_Ant1 DS13 For SA&NSA								
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel					3500.01			
Frequency (MHz)								
100	PI/2 BPSK	1	1		20.28		22.0	0.0
100	PI/2 BPSK	1	137		20.84			
100	PI/2 BPSK	1	271		20.16			
100	PI/2 BPSK	135	0		20.68		22.0	0.0
100	PI/2 BPSK	135	69		20.71		22.0	0.0
100	PI/2 BPSK	135	138		20.62		22.0	0.0
100	PI/2 BPSK	270	0		20.78			
100	QPSK	1	1		20.09			
100	QPSK	1	137		20.94		22.0	0.0
100	QPSK	1	271		20.82			
100	QPSK	135	0		20.03			
100	QPSK	135	69		20.88		22.0	0.0
100	QPSK	135	138		20.67		22.0	0.0
100	QPSK	270	0		20.73			
100	16QAM	1	1		20.13			
100	64QAM	1	1		20.25		22.0	0.0
100	256QAM	1	1		19.63		21.5	0.5
Channel				633000	633334	633666	Tune-up limit	MPR
Frequency (MHz)				3495	3500.01	3504.99	(dBm)	(dB)
90	QPSK	1	123	20.74	20.69	20.63	22.0	0.0
Channel				632668	633334	634000	Tune-up limit	MPR
Frequency (MHz)				3490.02	3500.01	3510	(dBm)	(dB)
80	QPSK	1	109	20.78	20.64	20.83	22.0	0.0
Channel				632334	633334	634332	Tune-up limit	MPR
Frequency (MHz)				3485.01	3500.01	3514.98	(dBm)	(dB)
70	QPSK	1	95	20.74	20.73	20.75	22.0	0.0
Channel				632000	633334	634666	Tune-up limit	MPR
Frequency (MHz)				3480	3500.01	3519.99	(dBm)	(dB)
60	QPSK	1	81	20.66	20.69	20.64	22.0	0.0
Channel				631668	633334	635000	Tune-up limit	MPR
Frequency (MHz)				3475.02	3500.01	3525	(dBm)	(dB)
50	QPSK	1	67	20.67	20.76	20.81	22.0	0.0
Channel				631334	633334	635332	Tune-up limit	MPR
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)
40	QPSK	1	53	20.66	20.63	20.78	22.0	0.0
Channel				630668	633334	636000	Tune-up limit	MPR
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)
20	QPSK	1	26	20.69	20.81	20.73	22.0	0.0
Channel				630500	633334	636166	Tune-up limit	MPR
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)
15	QPSK	1	19	20.68	20.73	20.71	22.0	0.0
Channel				630334	633334	636332	Tune-up limit	MPR
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)
10	QPSK	1	12	20.70	20.71	20.74	22.0	0.0

n78_Ant1 DSI3 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				650000			22.0	0.0	
Frequency (MHz)				3750					
100	PI/2 BPSK	1	1	20.08					
100	PI/2 BPSK	1	137	20.79					
100	PI/2 BPSK	1	271	20.16			22.0	0.0	
100	PI/2 BPSK	135	0	20.75					
100	PI/2 BPSK	135	69	20.75					
100	PI/2 BPSK	135	138	20.59					
100	PI/2 BPSK	270	0	20.68			22.0	0.0	
100	QPSK	1	1	20.13					
100	QPSK	1	137	20.91					
100	QPSK	1	271	20.11					
100	QPSK	135	0	20.70			22.0	0.0	
100	QPSK	135	69	20.74					
100	QPSK	135	138	20.68					
100	QPSK	270	0	20.71					
100	16QAM	1	1	20.05			22.0	0.0	
100	64QAM	1	1	20.19					
100	256QAM	1	1	19.63					
Channel				649668	650000	650334	Tune-up limit	MPR	
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)	
90	QPSK	1	123	20.57	20.80	20.73	22.0	0.0	
Channel				649334	650000	650668	Tune-up limit	MPR	
Frequency (MHz)				3740.01	3750	3760.02	(dBm)	(dB)	
80	QPSK	1	109	20.65	20.87	20.71	22.0	0.0	
Channel				649000	650000	651000	Tune-up limit	MPR	
Frequency (MHz)				3735	3750	3765	(dBm)	(dB)	
70	QPSK	1	95	20.57	20.83	20.72	22.0	0.0	
Channel				648668	650000	651334	Tune-up limit	MPR	
Frequency (MHz)				3730.02	3750	3770.01	(dBm)	(dB)	
60	QPSK	1	81	20.65	20.83	20.63	22.0	0.0	
Channel				648334	650000	651668	Tune-up limit	MPR	
Frequency (MHz)				3725.01	3750	3775.02	(dBm)	(dB)	
50	QPSK	1	67	20.78	20.89	20.69	22.0	0.0	
Channel				648000	650000	652000	Tune-up limit	MPR	
Frequency (MHz)				3720	3750	3780	(dBm)	(dB)	
40	QPSK	1	53	20.77	20.86	20.64	22.0	0.0	
Channel				647334	650000	652668	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3750	3790.02	(dBm)	(dB)	
20	QPSK	1	26	20.70	20.87	20.65	22.0	0.0	
Channel				647168	650000	652834	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3750	3792.51	(dBm)	(dB)	
15	QPSK	1	19	20.63	20.85	20.80	22.0	0.0	
Channel				647000	650000	653000	Tune-up limit	MPR	
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)	
10	QPSK	1	12	20.62	20.89	20.72	22.0	0.0	

Par27Q n78_Ant1 DSI3 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				633334			22.0	0.0	
Frequency (MHz)				3500.01					
100	PI/2 BPSK	1	1	20.31					
100	PI/2 BPSK	1	137	20.78					
100	PI/2 BPSK	1	271	20.25			22.0	0.0	
100	PI/2 BPSK	135	0	20.56					
100	PI/2 BPSK	135	69	20.69					
100	PI/2 BPSK	135	138	20.53					
100	PI/2 BPSK	270	0	20.81			22.0	0.0	
100	QPSK	1	1	20.11					
100	QPSK	1	137	20.86					
100	QPSK	1	271	20.05					
100	QPSK	135	0	20.51			22.0	0.0	
100	QPSK	135	69	20.76					
100	QPSK	135	138	20.63					
100	QPSK	270	0	20.61					
100	16QAM	1	1	20.10			22.0	0.0	
100	64QAM	1	1	20.03					
100	256QAM	1	1	19.59					
Channel				633000	633334	633666	Tune-up limit	MPR	
Frequency (MHz)				3495	3500.01	3504.99	(dBm)	(dB)	
90	QPSK	1	123	20.79	20.68	20.56	22.0	0.0	
Channel				632668	633334	634000	Tune-up limit	MPR	
Frequency (MHz)				3490.02	3500.01	3510	(dBm)	(dB)	
80	QPSK	1	109	20.80	20.72	20.66	22.0	0.0	
Channel				632334	633334	634332	Tune-up limit	MPR	
Frequency (MHz)				3485.01	3500.01	3514.98	(dBm)	(dB)	
70	QPSK	1	95	20.81	20.76	20.58	22.0	0.0	
Channel				632000	633334	634666	Tune-up limit	MPR	
Frequency (MHz)				3480	3500.01	3519.99	(dBm)	(dB)	
60	QPSK	1	81	20.59	20.65	20.60	22.0	0.0	
Channel				631668	633334	635000	Tune-up limit	MPR	
Frequency (MHz)				3475.02	3500.01	3525	(dBm)	(dB)	
50	QPSK	1	67	20.60	20.85	20.71	22.0	0.0	
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3529.98	(dBm)	(dB)	
40	QPSK	1	53	20.72	20.81	20.64	22.0	0.0	
Channel				630668	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3460.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	20.67	20.72	20.58	22.0	0.0	
Channel				630500	633334	636166	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	20.62	20.70	20.72	22.0	0.0	
Channel				630334	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3455.01	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	20.65	20.74	20.53	22.0	0.0	

n7_Ant2 DSI4 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	18.00	18.35	18.11	19.5	0.0	
20	PI/2 BPSK	1	26	18.20	18.23	18.24			
20	PI/2 BPSK	1	49	18.16	18.23	18.12			
20	PI/2 BPSK	25	0	17.93	18.15	18.07	19.5	0.0	
20	PI/2 BPSK	25	13	18.06	18.26	18.31	19.5	0.0	
20	PI/2 BPSK	25	26	17.99	18.12	18.12	19.5	0.0	
20	PI/2 BPSK	50	0	18.11	18.28	18.05			
20	QPSK	1	1	18.26	18.43	18.32			
20	QPSK	1	26	18.10	18.50	18.03	19.5	0.0	
20	QPSK	1	49	17.97	18.37	18.11			
20	QPSK	25	0	18.08	18.30	18.23			
20	QPSK	25	13	18.04	18.34	18.03	19.5	0.0	
20	QPSK	25	26	18.08	18.15	18.10	19.5	0.0	
20	QPSK	50	0	18.17	18.30	18.29			
20	16QAM	1	1	17.94	18.24	18.21			
20	64QAM	1	1	18.28	18.29	18.19	19.5	0.0	
20	256QAM	1	1	18.20	18.13	18.02	19.5	0.0	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	18.06	18.25	18.11	19.5	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	18.03	18.13	18.06	19.5	0.0	

n7_Ant2 DSI4 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	PI/2 BPSK	1	1	15.09	15.30	15.21	16.5	0.0	
20	PI/2 BPSK	1	26	15.31	15.19	15.32			
20	PI/2 BPSK	1	49	15.08	15.18	15.11			
20	PI/2 BPSK	25	0	14.93	15.25	15.00	16.5	0.0	
20	PI/2 BPSK	25	13	14.97	15.24	15.28	16.5	0.0	
20	PI/2 BPSK	25	26	14.95	15.03	15.08	16.5	0.0	
20	PI/2 BPSK	50	0	15.07	15.19	14.98			
20	QPSK	1	1	15.24	15.43	15.28			
20	QPSK	1	26	15.01	15.51	15.12	16.5	0.0	
20	QPSK	1	49	14.97	15.30	15.11			
20	QPSK	25	0	15.10	15.24	15.18			
20	QPSK	25	13	15.02	15.28	14.98	16.5	0.0	
20	QPSK	25	26	15.08	15.25	15.04	16.5	0.0	
20	QPSK	50	0	15.16	15.32	15.17			
20	16QAM	1	1	14.99	15.21	15.31			
20	64QAM	1	1	15.24	15.23	15.07	16.5	0.0	
20	256QAM	1	1	15.23	15.23	15.11	16.5	0.0	
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	40	15.01	15.29	15.34	16.5	0.0	
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2505	2535	2565			
10	QPSK	1	26	15.11	15.31	15.28	16.5	0.0	



n38_Ant2 DSI4 For SA

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				516004	516000	516996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PV2 BPSK	1	1	15.41	15.53	15.44		
40	PV2 BPSK	1	53	15.62	15.91	15.88	17.0	0.0
40	PV2 BPSK	1	104	15.50	15.50	15.41	17.0	0.0
40	PV2 BPSK	50	0	15.46	15.61	15.44	17.0	0.0
40	PV2 BPSK	50	26	15.75	15.89	15.88	17.0	0.0
40	PV2 BPSK	50	56	15.44	15.45	15.23	17.0	0.0
40	PV2 BPSK	100	0	15.59	15.59	15.53	17.0	0.0
40	QPSK	1	1	15.60	15.51	15.62		
40	QPSK	1	53	15.80	15.98	15.88	17.0	0.0
40	QPSK	1	104	15.53	15.90	15.26		
40	QPSK	50	0	15.89	15.95	15.87	17.0	0.0
40	QPSK	50	26	15.53	15.96	15.24	17.0	0.0
40	QPSK	50	56	15.43	15.50	15.52	17.0	0.0
40	QPSK	100	0	15.86	15.97	15.77		
40	16QAM	1	1	15.47	15.45	15.49	17.0	0.0
40	16QAM	1	1	15.76	15.90	15.75	17.0	0.0
40	256QAM	1	1	15.48	15.42	15.41	17.0	0.0
Channel				516000	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2590	2595	2610		
20	QPSK	1	26	15.63	15.91	15.72	17.0	0.0
Channel				515202	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	19	15.63	15.88	15.63	17.0	0.0
Channel				515004	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2573.02	2595	2614.98		
10	QPSK	1	12	15.79	15.80	15.76	17.0	0.0

n38_Ant2 DSI4 For NSA

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				516004	516000	516996		
Frequency (MHz)				2590.02	2595	2599.98		
40	PV2 BPSK	1	1	12.49	12.47	12.37		
40	PV2 BPSK	1	53	12.89	13.01	12.82	14.0	0.0
40	PV2 BPSK	1	104	12.57	12.49	12.45	14.0	0.0
40	PV2 BPSK	50	0	12.48	12.53	12.34	14.0	0.0
40	PV2 BPSK	50	26	12.70	12.86	12.76	14.0	0.0
40	PV2 BPSK	50	56	12.40	12.49	12.31	14.0	0.0
40	PV2 BPSK	100	0	12.68	12.53	12.43		
40	QPSK	1	1	12.42	12.83	12.71		
40	QPSK	1	53	12.83	13.09	12.81	14.0	0.0
40	QPSK	1	104	12.47	13.01	12.33		
40	QPSK	50	0	12.86	12.90	12.78	14.0	0.0
40	QPSK	50	26	12.54	13.05	12.18	14.0	0.0
40	QPSK	50	56	12.53	12.60	12.44	14.0	0.0
40	QPSK	100	0	12.83	13.01	12.86		
40	16QAM	1	1	12.55	12.58	12.50	14.0	0.0
40	16QAM	1	1	12.86	13.01	12.70	14.0	0.0
40	256QAM	1	1	12.52	12.48	12.47	14.0	0.0
Channel				516000	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2590	2595	2610		
20	QPSK	1	26	12.77	13.02	12.80	14.0	0.0
Channel				515202	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2577.51	2595	2612.49		
15	QPSK	1	19	12.69	13.00	12.62	14.0	0.0
Channel				515004	516000	522000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2573.02	2595	2614.98		
10	QPSK	1	12	12.62	12.92	12.88	14.0	0.0

n41_Ant2 DSI4 For SA&NSA

BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)
Channel				530302	518598	530300		
Frequency (MHz)				2546.01	2592.99	2640		
100	PV2 BPSK	1	1	18.54	18.64	18.53		
100	PV2 BPSK	1	137	19.20	19.15	19.25	20.5	0.0
100	PV2 BPSK	1	271	18.52	18.57	18.58		
100	PV2 BPSK	135	0	18.96	19.08	18.99	20.5	0.0
100	PV2 BPSK	135	69	19.21	19.25	19.25	20.5	0.0
100	PV2 BPSK	135	138	18.62	18.68	18.65	20.5	0.0
100	PV2 BPSK	270	0	18.52	18.72	18.63		
100	QPSK	1	1	18.52	18.74	18.58		
100	QPSK	1	137	19.25	19.35	19.27	20.5	0.0
100	QPSK	1	271	18.58	18.51	18.53		
100	QPSK	135	0	18.58	18.61	18.55	20.5	0.0
100	QPSK	135	69	19.17	19.22	19.18	20.5	0.0
100	QPSK	135	138	18.62	18.55	18.58	20.5	0.0
100	QPSK	270	0	19.19	19.21	19.17		
100	16QAM	1	1	18.56	18.53	18.62	20.5	0.0
100	16QAM	1	1	18.63	18.71	18.65	20.5	0.0
100	256QAM	1	1	18.57	18.58	18.58	20.5	0.0
Channel				508200	518598	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2541	2592.99	2644.98		
90	QPSK	1	123	18.75	18.73	18.75	20.5	0.0
Channel				507204	518598	528996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2536.02	2592.99	2649.99		
80	QPSK	1	109	18.66	18.71	18.73	20.5	0.0
Channel				505200	518598	531996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2524	2592.99	2659.98		
60	QPSK	1	81	18.67	18.78	18.79	20.5	0.0
Channel				504204	518598	530996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2521.02	2592.99	2664.99		
50	QPSK	1	67	18.75	18.73	18.72	20.5	0.0
Channel				503202	518598	531000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2518.01	2592.99	2670		
40	QPSK	1	53	18.59	18.73	18.69	20.5	0.0
Channel				502200	518598	534996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2511	2592.99	2674.98		
30	QPSK	1	39	18.74	18.71	18.67	20.5	0.0
Channel				501204	518598	535996	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2506.02	2592.99	2679.99		
20	QPSK	1	26	18.59	18.76	18.71	20.5	0.0
Channel				500200	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.01	2592.99	2685		
15	QPSK	1	19	18.61	18.71	18.79	20.5	0.0
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2503.01	2592.99	2685		
10	QPSK	1	12	18.69	18.75	18.74	20.5	0.0



n77_Ant3 DSI4 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq. 650000	Power Middle Ch. / Freq. 650000	Power High Ch. / Freq. 650000	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	PI2 BPSK	1	1	22.24	22.38	22.50			
100	PI2 BPSK	1	137	22.50	22.46	22.07	23.5	0.0	
100	PI2 BPSK	1	271	22.29	22.55	22.15			
100	PI2 BPSK	135	0	22.28	22.35	22.25	23.5	0.0	
100	PI2 BPSK	135	69	22.30	22.38	22.38	23.5	0.0	
100	PI2 BPSK	135	138	22.50	22.52	22.21	23.5	0.0	
100	PI2 BPSK	270	0	22.29	22.46	22.35			
100	QPSK	1	1	22.43	22.47	22.46			
100	QPSK	1	137	22.58	22.56	22.26	23.5	0.0	
100	QPSK	1	271	22.42	22.55	22.34			
100	QPSK	135	0	22.39	22.45	22.18	23.5	0.0	
100	QPSK	135	69	22.47	22.56	22.10	23.5	0.0	
100	QPSK	135	138	22.42	22.42	22.24			
100	QPSK	270	0	22.37	22.53	22.14			
100	16QAM	1	1	22.24	22.41	22.31	23.5	0.0	
100	64QAM	1	1	22.04	22.11	21.81	23.0	0.5	
100	256QAM	1	1	20.20	20.10	19.74	21.0	2.5	
Channel									
Frequency (MHz)				649668	650000	652334	Tune-up limit	MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	123	22.42	22.38	22.22	23.5	0.0	
Channel									
Frequency (MHz)				649334	650000	652668	Tune-up limit	MPR (dB)	
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	109	22.40	22.45	22.25	23.5	0.0	
Channel									
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	95	22.41	22.50	22.18	23.5	0.0	
Channel									
Frequency (MHz)				648668	650000	653334	Tune-up limit	MPR (dB)	
Frequency (MHz)				3730.02	3840	3940.01			
60	QPSK	1	81	22.54	22.43	22.26	23.5	0.0	
Channel									
Frequency (MHz)				648334	650000	653668	Tune-up limit	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	67	22.37	22.40	22.09	23.5	0.0	
Channel									
Frequency (MHz)				648000	650000	654000	Tune-up limit	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	22.48	22.53	22.17	23.5	0.0	
Channel									
Frequency (MHz)				647334	650000	654668	Tune-up limit	MPR (dB)	
Frequency (MHz)				3715.01	3840	3970.02			
20	QPSK	1	26	22.51	22.57	22.21	23.5	0.0	
Channel									
Frequency (MHz)				647000	650000	655334	Tune-up limit	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	22.53	22.40	22.10	23.5	0.0	
Channel									
Frequency (MHz)				647000	650000	656000	Tune-up limit	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	22.42	22.38	22.28	23.5	0.0	

Par27Q n77_Ant3 DSI4 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)					3500.01				
100	PI2 BPSK	1	1	22.51	22.51				
100	PI2 BPSK	1	137	22.51	22.51		23.5	0.0	
100	PI2 BPSK	1	271	22.49	22.49				
100	PI2 BPSK	135	0	22.40	22.40		23.5	0.0	
100	PI2 BPSK	135	69	22.41	22.41		23.5	0.0	
100	PI2 BPSK	135	138	22.46	22.46		23.5	0.0	
100	PI2 BPSK	270	0	22.42	22.42				
100	QPSK	1	1	22.46	22.46				
100	QPSK	1	137	22.53	22.53		23.5	0.0	
100	QPSK	1	271	22.51	22.51				
100	QPSK	135	0	22.39	22.39		23.5	0.0	
100	QPSK	135	69	22.47	22.47		23.5	0.0	
100	QPSK	135	138	22.39	22.39		23.5	0.0	
100	QPSK	270	0	22.48	22.48				
100	16QAM	1	1	22.41	22.41		23.5	0.0	
100	64QAM	1	1	22.20	22.20		23.0	0.5	
100	256QAM	1	1	20.17	20.17		21.0	2.5	
Channel									
Frequency (MHz)				633000	633334	633666	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3495	3500.01	3504.99			
90	QPSK	1	123	22.31	22.49	22.37	23.5	0.0	
Channel									
Frequency (MHz)				632668	633334	633000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	109	22.36	22.47	22.34	23.5	0.0	
Channel									
Frequency (MHz)				632334	633334	634332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3485.01	3500.01	3514.98			
70	QPSK	1	95	22.24	22.47	22.44	23.5	0.0	
Channel									
Frequency (MHz)				632000	633334	634666	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3480	3500.01	3519.96			
60	QPSK	1	81	22.31	22.45	22.30	23.5	0.0	
Channel									
Frequency (MHz)				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3525			
50	QPSK	1	67	22.27	22.52	22.44	23.5	0.0	
Channel									
Frequency (MHz)				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3525.98			
40	QPSK	1	53	22.33	22.49	22.39	23.5	0.0	
Channel									
Frequency (MHz)				630668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	26	22.23	22.39	22.42	23.5	0.0	
Channel									
Frequency (MHz)				630300	633334	635666	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49			
15	QPSK	1	19	22.27	22.46	22.40	23.5	0.0	
Channel									
Frequency (MHz)				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3548.98			
10	QPSK	1	12	22.33	22.41	22.33	23.5	0.0	

n77_Ant3 DSI1 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	PI2 BPSK	1	1	21.28	21.35	21.28			
100	PI2 BPSK	1	137	21.43	21.51	21.10	22.5	0.0	
100	PI2 BPSK	1	271	21.36	21.54	21.06			
100	PI2 BPSK	135	0	21.34	21.44	21.26	22.5	0.0	
100	PI2 BPSK	135	69	21.24	21.42	21.34	22.5	0.0	
100	PI2 BPSK	135	138	21.56	21.52	21.47	22.5	0.0	
100	PI2 BPSK	270	0	21.22	21.50	21.44	22.5	0.0	
100	QPSK	1	1	21.45	21.47	21.45			
100	QPSK	1	117	21.38	21.63	21.45	22.5	0.0	
100	QPSK	1	271	21.36	21.53	21.11	22.5	0.0	
100	QPSK	135	0	21.32	21.38	21.45	22.5	0.0	
100	QPSK	135	69	21.42	21.56	21.69	22.5	0.0	
100	QPSK	135	138	21.43	21.36	21.23	22.5	0.0	
100	QPSK	270	0	21.37	21.58	21.14	22.5	0.0	
100	16QAM	1	1	21.31	21.38	21.26	22.5	0.0	
100	64QAM	1	1	21.50	21.18	20.84	22.5	0.0	
100	256QAM	1	1	19.16	19.07	19.09	21.0	1.5	
Channel									
Frequency (MHz)				3846.0	3860.0	3823.34	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	123	21.44	21.44	21.14	22.5	0.0	
Frequency (MHz)				3833.34	3850.0	3845.08	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	21.45	21.34	21.23	22.5	0.0	
Channel									
Frequency (MHz)				3735	3840	3945	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	95	21.42	21.40	21.28	22.5	0.0	
Channel									
Frequency (MHz)				3869.0	3869.0	3833.34	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	392	21.42	21.40	21.01	22.5	0.0	
60	QPSK	1	81	21.44	21.43	21.14	22.5	0.0	
Channel									
Frequency (MHz)				3833.34	3860.0	3856.08	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	77	21.45	21.39	21.05	22.5	0.0	
50	QPSK	1	67	21.48	21.29	21.16	22.5	0.0	
Channel									
Frequency (MHz)				3840.0	3860.0	3840.0	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	21.40	21.33	21.23	22.5	0.0	
Channel									
Frequency (MHz)				3873.34	3860.0	3846.08	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	21.45	21.33	21.28	22.5	0.0	
Channel									
Frequency (MHz)				3877.5	3860.0	3872.5	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	21.50	21.30	21.16	22.5	0.0	
Channel									
Frequency (MHz)				3870.0	3860.0	3870.0	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	21.42	21.45	21.26	22.5	0.0	

Par27Q n77_Ant3 DS1 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3500.01					
100	Pi2 BPSK	1	1	21.47			22.5	0.0	
100	Pi2 BPSK	1	137	21.45					
100	Pi2 BPSK	1	271	21.48					
100	Pi2 BPSK	135	0	21.34			22.5	0.0	
100	Pi2 BPSK	135	66	21.30			22.5	0.0	
100	Pi2 BPSK	135	138	21.49			22.5	0.0	
100	Pi2 BPSK	270	0	21.39			22.5	0.0	
100	QPSK	1	1	21.48					
100	QPSK	1	137	21.50					
100	QPSK	1	271	21.45			22.5	0.0	
100	QPSK	135	0	21.43					
100	QPSK	135	66	21.46					
100	QPSK	135	138	21.34			22.5	0.0	
100	QPSK	270	0	21.53			22.5	0.0	
100	16QAM	1	1	21.40					
100	64QAM	1	1	21.57					
100	256QAM	1	1	20.12			21.0	1.5	
Channel									
Frequency (MHz)				633000	633334	633666	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	3495	3500.01	3504.99	22.5	0.0	
Channel									
Frequency (MHz)				632668	633334	634000	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	3490.02	3500.01	3510	22.5	0.0	
Channel									
Frequency (MHz)				3485.01	3500.01	3514.98	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	95	21.34	21.32	21.15	22.5	0.0	
Channel									
Frequency (MHz)				632000	633334	634666	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	3490	3500.01	3510.99	22.5	0.0	
Channel									
Frequency (MHz)				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	3485.01	3500.01	3505	22.5	0.0	
Channel									
Frequency (MHz)				631334	633334	635333	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	21.45	21.50	21.21	22.5	0.0	
Channel									
Frequency (MHz)				630668	633334	636000	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	21.44	21.34	21.15	22.5	0.0	
Channel									
Frequency (MHz)				3467.5	3500.01	3542.49	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	21.44	21.43	21.20	22.5	0.0	
Channel									
Frequency (MHz)				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	21.38	21.45	21.14	22.5	0.0	

n78_Ant3 DS14 For SA&NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Mid Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750					
100	Pi2 BPSK	1	1	22.16					
100	Pi2 BPSK	1	137	22.30			23.5	0.0	
100	Pi2 BPSK	1	271	22.45					
100	Pi2 BPSK	135	0	22.24			23.5	0.0	
100	Pi2 BPSK	135	66	22.19			23.5	0.0	
100	Pi2 BPSK	135	138	22.38			23.5	0.0	
100	Pi2 BPSK	270	0	22.43			23.5	0.0	
100	QPSK	1	1	22.25					
100	QPSK	1	137	22.45			23.5	0.0	
100	QPSK	1	271	22.34					
100	QPSK	135	0	22.23			23.5	0.0	
100	QPSK	135	66	22.36			23.5	0.0	
100	QPSK	135	138	22.33			23.5	0.0	
100	QPSK	270	0	22.39			23.5	0.0	
100	16QAM	1	1	22.39			23.5	0.0	
100	64QAM	1	1	22.02			23.0	2.5	
100	256QAM	1	1	19.98			21.0	2.5	
Channel									
Frequency (MHz)				64668	65000	65034	Tune-up limit (dBm)	MPR (dB)	
90	QPSK	1	123	22.41	22.43	22.23	23.5	0.0	
Channel									
Frequency (MHz)				646134	650000	650668	Tune-up limit (dBm)	MPR (dB)	
80	QPSK	1	109	22.41	22.34	22.25	23.5	0.0	
Channel									
Frequency (MHz)				646000	650000	650200	Tune-up limit (dBm)	MPR (dB)	
70	QPSK	1	95	22.32	22.31	22.40	23.5	0.0	
Channel									
Frequency (MHz)				646668	650000	651334	Tune-up limit (dBm)	MPR (dB)	
60	QPSK	1	81	22.35	22.36	22.31	23.5	0.0	
Channel									
Frequency (MHz)				646134	650000	651668	Tune-up limit (dBm)	MPR (dB)	
50	QPSK	1	67	22.25	22.36	22.22	23.5	0.0	
Channel									
Frequency (MHz)				646000	650000	652000	Tune-up limit (dBm)	MPR (dB)	
40	QPSK	1	53	22.42	22.29	22.35	23.5	0.0	
Channel									
Frequency (MHz)				647134	650000	652668	Tune-up limit (dBm)	MPR (dB)	
20	QPSK	1	26	22.23	22.35	22.27	23.5	0.0	
Channel									
Frequency (MHz)				647000	650000	653000	Tune-up limit (dBm)	MPR (dB)	
15	QPSK	1	19	22.41	22.36	22.27	23.5	0.0	
Channel									
Frequency (MHz)				647000	650000	653000	Tune-up limit (dBm)	MPR (dB)	
10	QPSK	1	12	22.25	22.40	22.20	23.5	0.0	

Par27Q n78_Ant3 DS14 For SA&NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
100	Pi2 BPSK	1	1	22.12	3500.01		23.5	0.0	
100	Pi2 BPSK	1	137	22.23					
100	Pi2 BPSK	1	271	22.43					
100	Pi2 BPSK	135	0	22.22			23.5	0.0	
100	Pi2 BPSK	135	66	22.10			23.5	0.0	
100	Pi2 BPSK	135	138	22.33			23.5	0.0	
100	Pi2 BPSK	270	0	22.25			23.5	0.0	
100	QPSK	1	1	22.36					
100	QPSK	1	137	22.44					
100	QPSK	1	271	22.20			23.5	0.0	
100	QPSK	135	0	22.38					
100	QPSK	135	66	22.46					
100	QPSK	135	138	22.27			23.5	0.0	
100	QPSK	270	0	22.37			23.5	0.0	
100	16QAM	1	1	22.41					
100	64QAM	1	1	22.13					
100	256QAM	1	1	19.99			21.0	2.5	
Channel									
Frequency (MHz)									
90	QPSK	1	123	22.30	3500.01	3504.99	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
80	QPSK	1	109	22.20	3500.01	3504.99	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
70	QPSK	1	95	22.26	3500.01	3514.98	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
60	QPSK	1	81	22.26	3500.01	3524.99	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
50	QPSK	1	67	22.26	3500.01	3534.98	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
40	QPSK	1	53	22.14	3500.01	3544.98	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
20	QPSK	1	26	22.23	3500.01	3549.98	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
15	QPSK	1	19	22.29	3500.01	3554.98	Time-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)									
10	QPSK	1	12	22.17	3500.01	3559.98	Time-up limit (dBm)	MPR (dB)	

n78_Ant3 DS1 For NSA										
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)		
Channel										
Frequency (MHz)				3750						
100	P2 BPSK	1	1		21.19					
100	P2 BPSK	1	137		21.23		22.5	0.0		
100	P2 BPSK	1	271		21.33					
100	P2 BPSK	135	0		21.20		22.5	0.0		
100	P2 BPSK	135	69		21.17		22.5	0.0		
100	P2 BPSK	135	138		21.35		22.5	0.0		
100	P2 BPSK	270	0		21.24					
100	QPSK	1	1		21.33					
100	QPSK	1	137		21.05		22.5	0.0		
100	QPSK	1	271		21.16					
100	QPSK	135	0		21.51		22.5	0.0		
100	QPSK	135	69		21.55		22.5	0.0		
100	QPSK	135	138		21.28		22.5	0.0		
100	QPSK	270	0		21.42					
100	16QAM	1	1		21.35		22.5	0.0		
100	64QAM	1	1		21.47		22.5	0.0		
100	256QAM	1	1		19.75		21.0	1.5		
Channel				648668	650000	650334	Tune-up limit	MPR		
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)		
90	QPSK	1	123		21.30	21.35	21.30	22.5	0.0	
Channel				648334	650000	650668	Tune-up limit	MPR		
Frequency (MHz)				3740.01	3750	3760.02	(dBm)	(dB)		
80	QPSK	1	109		21.32	21.38	21.29	22.5	0.0	
Channel				650003	650000	651000	Tune-up limit	MPR		
Frequency (MHz)				3735	3750	3765	(dBm)	(dB)		
70	QPSK	1	95		21.23	21.44	21.30	22.5	0.0	
Channel				648668	650000	651334	Tune-up limit	MPR		
Frequency (MHz)				3730.02	3750	3770.01	(dBm)	(dB)		
60	QPSK	1	81		21.38	21.35	21.31	22.5	0.0	
Channel				648334	650000	651668	Tune-up limit	MPR		
Frequency (MHz)				3725.01	3750	3775.02	(dBm)	(dB)		
50	QPSK	1	67		21.58	21.47	21.34	22.5	0.0	
Channel				648000	650000	652000	Tune-up limit	MPR		
Frequency (MHz)				3720	3750	3780	(dBm)	(dB)		
40	QPSK	1	53		21.34	21.34	21.34	22.5	0.0	
Channel				647334	650000	652668	Tune-up limit	MPR		
Frequency (MHz)				3718.01	3750	3780.02	(dBm)	(dB)		
20	QPSK	1	26		21.25	21.40	21.28	22.5	0.0	
Channel				647168	650000	652334	Tune-up limit	MPR		
Frequency (MHz)				3707.52	3750	3792.51	(dBm)	(dB)		
15	QPSK	1	19		21.35	21.48	21.20	22.5	0.0	
Channel				647000	650000	653000	Tune-up limit	MPR		
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)		
10	QPSK	1	12		21.28	21.44	21.28	22.5	0.0	

Par27Q n78_Ant3 DS1 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)	
Channel									
Frequency (MHz)				633334		3500.01			
100	Pi2 BPSK	1	1		21.09				
100	Pi2 BPSK	1	137		21.21		22.5	0.0	
100	Pi2 BPSK	1	271		21.44				
100	Pi2 BPSK	135	0		21.20		22.5	0.0	
100	Pi2 BPSK	135	69		21.18		22.5	0.0	
100	Pi2 BPSK	135	138		21.33		22.5	0.0	
100	Pi2 BPSK	270	0		21.25		22.5	0.0	
100	QPSK	1	1		21.32				
100	QPSK	1	137		21.53		22.5	0.0	
100	QPSK	1	271		21.24				
100	QPSK	135	0		21.31		22.5	0.0	
100	QPSK	135	69		21.40		22.5	0.0	
100	QPSK	135	138		21.26		22.5	0.0	
100	QPSK	270	0		21.44		22.5	0.0	
100	16QAM	1	1		21.50		22.5	0.0	
100	64QAM	1	1		21.45		22.5	0.0	
100	256QAM	1	1		19.80		21.0	1.5	
Channel									
Frequency (MHz)				633000	633334	633668	Tune-up limit (dbm)	MPR (db)	
90	QPSK	1	123	3495	3500.01	3504.99			
Channel				632668	633334	634000	21.19	22.5	0.0
Frequency (MHz)				3490.02	3500.01	3510	Tune-up limit (dbm)	MPR (db)	
80	QPSK	1	109	21.22	21.39	21.35	22.5	0.0	
Channel				632334	633334	634332	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3485.01	3500.01	3514.98	Tune-up limit (dbm)	MPR (db)	
70	QPSK	1	95	21.31	21.40	21.20	22.5	0.0	
Channel				632000	633334	634668	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3480	3500.01	3519.96	Tune-up limit (dbm)	MPR (db)	
60	QPSK	1	81	21.25	21.41	21.35	22.5	0.0	
Channel				631668	633334	635000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3475.02	3500.01	3525	Tune-up limit (dbm)	MPR (db)	
50	QPSK	1	67	21.31	21.44	21.19	22.5	0.0	
Channel				631334	633334	635332	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3470.01	3500.01	3529.98	Tune-up limit (dbm)	MPR (db)	
40	QPSK	1	53	21.25	21.41	21.23	22.5	0.0	
Channel				630999	633334	635668	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3466.02	3500.01	3540	Tune-up limit (dbm)	MPR (db)	
20	QPSK	1	26	21.30	21.33	21.28	22.5	0.0	
Channel				630668	633334	636168	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3467.5	3500.01	3542.49	Tune-up limit (dbm)	MPR (db)	
15	QPSK	1	19	21.25	21.39	21.32	22.5	0.0	
Channel				630334	633334	636332	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				3465.01	3500.01	3544.99	Tune-up limit (dbm)	MPR (db)	
10	QPSK	1	12	21.24	21.48	21.24	22.5	0.0	



n7_Ant4 DSI4 For SA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	Pl2 BPSK	1	1	19.41	19.73	19.55			
20	Pl2 BPSK	1	26	19.58	19.63	19.48	21.0	0.0	
20	Pl2 BPSK	1	49	19.42	19.65	19.49			
20	Pl2 BPSK	25	0	19.56	19.63	19.47	21.0	0.0	
20	Pl2 BPSK	25	13	19.61	19.77	19.62	21.0	0.0	
20	Pl2 BPSK	25	26	19.24	19.52	19.57			
20	Pl2 BPSK	50	0	19.59	19.53	19.54	21.0	0.0	
20	QPSK	1	1	19.64	19.70	19.69			
20	QPSK	1	26	19.69	19.54	19.63	21.0	0.0	
20	QPSK	1	49	19.46	19.63	19.36			
20	QPSK	25	0	19.42	19.44	19.56	21.0	0.0	
20	QPSK	25	13	19.54	19.66	19.56	21.0	0.0	
20	QPSK	25	26	19.57	19.60	19.46			
20	QPSK	50	0	19.47	19.66	19.36	21.0	0.0	
20	16QAM	1	1	19.74	19.40	19.64	21.0	0.0	
20	16QAM	1	1	19.66	19.60	19.49	21.0	0.0	
20	256QAM	1	1	19.09	19.52	19.14	19.5	1.5	
Channel				501800	507000	512600	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	19	19.51	19.61	19.50	21.0	0.0	
Channel				507000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2565	2535	2565			
10	QPSK	1	12	19.65	19.72	19.43	21.0	0.0	

n7_Ant4 DSI1 For SA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	Pl2 BPSK	1	1	17.10	17.81	17.62			
20	Pl2 BPSK	1	26	17.76	17.84	17.82	19.0	0.0	
20	Pl2 BPSK	1	49	17.72	17.93	17.64			
20	Pl2 BPSK	25	0	17.88	17.93	17.71	19.0	0.0	
20	Pl2 BPSK	25	13	17.72	17.86	17.93	19.0	0.0	
20	Pl2 BPSK	25	26	17.56	17.88	17.85			
20	Pl2 BPSK	50	0	17.75	17.80	17.79	19.0	0.0	
20	QPSK	1	1	17.84	17.83	17.74			
20	QPSK	1	26	17.97	17.95	17.87	19.0	0.0	
20	QPSK	1	49	17.70	17.94	17.57			
20	QPSK	25	0	17.77	17.81	17.69	19.0	0.0	
20	QPSK	25	13	17.86	17.91	17.86	19.0	0.0	
20	QPSK	25	26	17.64	17.90	17.65			
20	QPSK	50	0	17.83	17.85	17.64	19.0	0.0	
20	16QAM	1	1	17.89	17.70	17.84	19.0	0.0	
20	16QAM	1	1	17.83	17.94	17.67	19.0	0.0	
20	256QAM	1	1	17.79	17.93	17.86	19.0	0.0	
Channel				501800	507000	512600	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	19	17.67	17.90	17.67	19.0	0.0	
Channel				507000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2565	2535	2565			
10	QPSK	1	12	17.71	17.84	17.79	19.0	0.0	

n7_Ant4 DSI4 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2510	2535	2560			
20	Pl2 BPSK	1	1	16.43	16.70	16.45			
20	Pl2 BPSK	1	26	16.61	16.59	16.53	18.0	0.0	
20	Pl2 BPSK	1	49	16.53	16.64	16.36			
20	Pl2 BPSK	25	0	16.62	16.77	16.53	18.0	0.0	
20	Pl2 BPSK	25	13	16.56	16.72	16.60	18.0	0.0	
20	Pl2 BPSK	25	26	16.28	16.62	16.61			
20	Pl2 BPSK	50	0	16.50	16.64	16.55	18.0	0.0	
20	QPSK	1	1	16.54	16.65	16.65			
20	QPSK	1	26	16.58	16.64	16.70	18.0	0.0	
20	QPSK	1	49	16.48	16.68	16.36			
20	QPSK	25	0	16.53	16.52	16.52	18.0	0.0	
20	QPSK	25	13	16.63	16.79	16.61	18.0	0.0	
20	QPSK	25	26	16.54	16.65	16.34			
20	QPSK	50	0	16.55	16.77	16.44	18.0	0.0	
20	16QAM	1	1	16.73	16.43	16.71	18.0	0.0	
20	16QAM	1	1	16.68	16.70	16.49	18.0	0.0	
20	256QAM	1	1	16.58	16.71	16.60	18.0	0.0	
Channel				501800	507000	512600	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2507.5	2535	2562.5			
15	QPSK	1	19	16.50	16.70	16.60	18.0	0.0	
Channel				507000	507000	513000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2565	2535	2565			
10	QPSK	1	12	16.55	16.72	16.48	18.0	0.0	

n7_Ant4 DSI1 For NSA

BW [MHz]	Modulation	Size	RB Offset	Power			Tune-up limit (dBm)	MPR (dB)
				Low Ch. / Freq. 500000	Mid Ch. / Freq. 507000	High Ch. / Freq. 510000		
Channel								
Frequency (MHz)				2510	2535	2560	Tune-up limit (dBm)	MPR (dB)
20	PB2 BPSK	1	1	14.50	14.57	14.54	16.0	0.0
20	PB2 BPSK	1	26	14.62	14.63	14.62		
20	PB2 BPSK	1	49	14.43	14.63	14.49	16.0	0.0
20	PB2 BPSK	25	0	14.65	14.77	14.47		
20	PB2 BPSK	25	13	14.50	14.75	14.70	16.0	0.0
20	PB2 BPSK	25	26	14.40	14.77	14.70		
20	PB2 BPSK	50	0	14.56	14.70	14.65	16.0	0.0
20	QPSK	1	1	14.61	14.65	14.55		
20	QPSK	1	26	14.75	14.63	14.60	16.0	0.0
20	QPSK	1	49	14.43	14.65	14.30		
20	QPSK	25	0	14.62	14.58	14.42	16.0	0.0
20	QPSK	25	13	14.66	14.72	14.56		
20	QPSK	25	26	14.40	14.71	14.50	16.0	0.0
20	QPSK	50	0	14.73	14.74	14.52		
20	16QAM	1	1	14.74	14.61	14.53	16.0	0.0
20	64QAM	1	1	14.66	14.70	14.46		
20	256QAM	1	1	14.68	14.70	14.70	16.0	0.0
Channel				501500	507000	512500		
Frequency (MHz)				2507.5	2535	2562.5	Tune-up limit (dBm)	MPR (dB)
15	QPSK	1	19	14.60	14.78	14.56	16.0	0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565		
10	QPSK	1	12	14.54	14.74	14.56	16.0	0.0

n7_Ant4 DSI2 For NSA

BW [MHz]	Modulation	RB Size	RB Offset	Power			Tune-up limit (dBm)	MPR (dB)
				Low Ch. / Freq.	Middle Ch. / Freq.	High Ch. / Freq.		
Channel				502000	507000	512000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2510	2535	2560		
20	PB2 BPSK	1	1	21.76	21.84	21.67	23.0	0.0
20	PB2 BPSK	1	26	21.83	21.92	21.77		
20	PB2 BPSK	1	49	21.71	21.94	21.81	23.0	0.0
20	PB2 BPSK	25	0	21.80	21.76	21.68		
20	PB2 BPSK	25	13	21.79	21.84	21.79	23.0	0.0
20	PB2 BPSK	25	26	21.78	21.89	21.85		
20	PB2 BPSK	50	0	21.84	21.95	21.72	23.0	0.0
20	QPSK	1	1	21.47	21.67	21.81		
20	QPSK	1	26	21.59	21.66	21.77	23.0	0.0
20	QPSK	1	49	21.80	21.80	21.94		
20	QPSK	25	0	21.82	21.81	21.70	23.0	0.0
20	QPSK	25	13	21.85	21.82	21.85		
20	QPSK	25	26	21.80	21.86	21.83	23.0	0.0
20	QPSK	50	0	21.68	21.90	21.82		
20	16QAM	1	1	21.80	21.80	21.90	23.0	0.0
20	64QAM	1	1	20.16	20.46	20.25		
20	256QAM	1	1	19.25	19.21	19.38	19.5	3.5
Channel				501500	507000	512500	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2507.5	2535	2562.5		
15	QPSK	1	19	21.60	21.88	21.61	23.0	0.0
Channel				501000	507000	513000	Tune-up limit (dBm)	MPR (dB)
Frequency (MHz)				2505	2535	2565		
10	QPSK	1	12	21.86	21.81	21.69	23.0	0.0

n66_Ant4 DSI1 For SA

BW [MHz]	Modulation	Size	RB Offset	Power			Tune-up limit (dBm)	MPR (dB)
				Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.		
				346000	349000	352000		
				1720	1745	1760		
40	PB2 BPSK	1	1	18.48	18.64	18.55	20.0	0.0
40	PB2 BPSK	1	53	18.41	18.67	18.61		
40	PB2 BPSK	1	104	18.53	18.55	18.46	20.0	0.0
40	PB2 BPSK	50	0	18.34	18.69	18.43		
40	PB2 BPSK	50	26	18.56	18.74	18.45	20.0	0.0
40	PB2 BPSK	50	56	18.33	18.60	18.48		
40	PB2 BPSK	100	0	18.41	18.72	18.47	20.0	0.0
40	QPSK	1	1	18.49	18.57	18.52		
40	QPSK	1	53	18.51	18.75	18.53	20.0	0.0
40	QPSK	1	104	18.39	18.54	18.50		
40	QPSK	50	0	18.33	18.72	18.45	20.0	0.0
40	QPSK	50	26	18.53	18.73	18.45		
40	QPSK	50	56	18.43	18.61	18.44	20.0	0.0
40	QPSK	100	0	18.48	18.60	18.52		
40	16QAM	1	1	18.42	18.52	18.58	20.0	0.0
40	64QAM	1	1	18.45	18.61	18.46		
40	256QAM	1	1	18.41	18.53	18.52	20.0	0.0
				345000	349000	353000		
				1725	1745	1765		
30	QPSK	1	39	18.42	18.73	18.53	20.0	0.0
				344500	349000	353500		
				1722.5	1745	1767.5		
25	QPSK	1	32	18.44	18.70	18.51	20.0	0.0
				343500	349000	354000		
				1720	1745	1770		
20	QPSK	1	26	18.45	18.60	18.54	20.0	0.0
				343000	349000	355000		
				1717.5	1745	1772.5		
15	QPSK	1	19	18.44	18.63	18.33	20.0	0.0
				343000	349000	355000		
				1718	1745	1775		
10	QPSK	1	12	18.50	18.57	18.54	20.0	0.0

n66_Ant4 DSI1 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				346000	349000	352000			
Frequency (MHz)				1730	1745	1760			
40	Pl2 BPSK	1	1	15.49	15.67	15.50	17.0		
40	Pl2 BPSK	1	53	15.36	15.64	15.61			
40	Pl2 BPSK	1	104	15.49	15.62	15.45			
40	Pl2 BPSK	50	0	15.35	15.68	15.43		0.0	
40	Pl2 BPSK	50	26	15.50	15.66	15.51	17.0	0.0	
40	Pl2 BPSK	50	56	15.35	15.69	15.38	17.0		
40	Pl2 BPSK	100	0	15.43	15.76	15.50		0.0	
40	QPSK	1	1	15.61	15.54	15.52			
40	QPSK	1	53	15.55	15.77	15.63		17.0	
40	QPSK	1	104	15.29	15.63	15.45	17.0		
40	QPSK	50	0	15.40	15.70	15.55		0.0	
40	QPSK	50	26	15.45	15.72	15.56		0.0	
40	QPSK	50	56	15.32	15.61	15.44			
40	QPSK	100	0	15.38	15.72	15.45	17.0	0.0	
40	16QAM	1	1	15.31	15.50	15.65		0.0	
40	16QAM	1	1	15.37	15.50	15.54		0.0	
40	256QAM	1	1	15.29	15.59	15.52		17.0	
Channel				346000	349000	353000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1725	1745	1765	(dBm)	(dB)	
30	QPSK	1	39	15.42	15.72	15.60	17.0	0.0	
Channel				344500	349000	353000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1722.5	1745	1767.5	(dBm)	(dB)	
25	QPSK	1	32	15.49	15.58	15.52	17.0	0.0	
Channel				344000	349000	354000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1720	1745	1770	(dBm)	(dB)	
20	QPSK	1	26	15.37	15.60	15.54	17.0	0.0	
Channel				343000	349000	354000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1717.5	1745	1772.5	(dBm)	(dB)	
15	QPSK	1	19	15.56	15.62	15.43	17.0	0.0	
Channel				343000	349000	355000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				1715	1745	1775	(dBm)	(dB)	
10	QPSK	1	12	15.59	15.64	15.60	17.0	0.0	

n66_Ant4 DS14 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dbm)	MPR (db)	
Channel				346000	349000	352000			
Frequency (MHz)				1720	1745	1760			
40	Pl2 BPSK	1	1	19.47	19.68	19.50	21.0		
40	Pl2 BPSK	1	53	19.35	19.60	19.69			
40	Pl2 BPSK	1	104	19.51	19.62	19.56			
40	Pl2 BPSK	50	0	19.43	19.57	19.39		0.0	
40	Pl2 BPSK	50	26	19.51	19.76	19.37	21.0	0.0	
40	Pl2 BPSK	50	56	19.27	19.53	19.56			
40	Pl2 BPSK	100	0	19.30	19.69	19.47		0.0	
40	QPSK	1	1	19.41	19.46	19.53			
40	QPSK	1	53	19.40	19.66	19.44	21.0	0.0	
40	QPSK	1	104	19.34	19.63	19.51			
40	QPSK	50	0	19.41	19.60	19.52		0.0	
40	QPSK	50	26	19.52	19.77	19.52		0.0	
40	QPSK	50	56	19.45	19.57	19.46	21.0	0.0	
40	QPSK	100	0	19.58	19.74	19.63			
40	16QAM	1	1	19.40	19.52	19.54		0.0	
40	16QAM	1	1	19.53	19.71	19.38		0.0	
40	256QAM	1	1	17.88	19.32	17.90	19.5	1.5	
Channel				346000	349000	353000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				1725	1745	1765	(dbm)	(db)	
30	QPSK	1	39	19.29	19.75	19.41	21.0	0.0	
Channel				344500	349000	353000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				1722.5	1745	1767.5	(dbm)	(db)	
25	QPSK	1	32	19.32	19.83	19.33	21.0	0.0	
Channel				344000	349000	354000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				1720	1745	1770	(dbm)	(db)	
20	QPSK	1	26	19.29	19.85	19.29	21.0	0.0	
Channel				343000	349000	354000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				1717.5	1745	1772.5	(dbm)	(db)	
15	QPSK	1	19	19.23	19.64	19.30	21.0	0.0	
Channel				343000	349000	355000	Tune-up limit (dbm)	MPR (db)	
Frequency (MHz)				1715	1745	1775	(dbm)	(db)	
10	QPSK	1	12	19.24	19.74	19.40	21.0	0.0	



n38_Ant4 DSI1&4 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519996			
Frequency (MHz)				2590.02	2595	2599.98			
40	PI2 BPSK	1	1	18.52	18.59	18.57			
40	PI2 BPSK	1	53	18.84	18.57	18.86	20.5	0.0	
40	PI2 BPSK	1	104	18.54	18.57	18.61	20.5	0.0	
40	PI2 BPSK	50	0	18.51	18.58	18.58	20.5	0.0	
40	PI2 BPSK	50	28	18.61	18.90	18.83	20.5	0.0	
40	PI2 BPSK	50	56	18.58	18.56	18.62			
40	PI2 BPSK	100	0	18.57	18.84	18.52	20.5	0.0	
40	QPSK	1	1	18.51	18.82	18.94			
40	QPSK	1	53	18.56	18.90	18.52	20.5	0.0	
40	QPSK	1	104	18.58	18.55	18.53			
40	QPSK	50	0	18.65	18.90	18.62	20.5	0.0	
40	QPSK	50	28	18.56	19.02	18.62	20.5	0.0	
40	QPSK	50	56	18.84	18.50	18.56	20.5	0.0	
40	QPSK	100	0	18.77	18.67	18.85			
40	16QAM	1	1	18.61	18.91	18.72	20.5	0.0	
40	64QAM	1	1	18.53	18.75	18.52	20.5	0.0	
40	256QAM	1	1	18.58	18.86	18.51	20.5	0.0	
Channel				518000	519000	522000	Tune-up limit	MPR	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	28	18.58	18.76	18.53	20.5	0.0	
Channel				518202	519200	522100	Tune-up limit	MPR	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	19	18.52	18.75	18.53	20.5	0.0	
Channel				518004	519000	522996	Tune-up limit	MPR	
Frequency (MHz)				2578.02	2595	2614.98			
10	QPSK	1	12	18.62	18.75	18.52	20.5	0.0	

n38_Ant4 DSI1&4 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				518004	519000	519998			
Frequency (MHz)				2590.02	2595	2599.98			
40	PI2 BPSK	1	1	15.64	15.79	15.62			
40	PI2 BPSK	1	53	15.56	15.72	15.70	17.5	0.0	
40	PI2 BPSK	1	104	15.52	15.71	15.63			
40	PI2 BPSK	50	0	15.68	15.67	15.77	17.5	0.0	
40	PI2 BPSK	50	28	15.64	15.62	15.68	17.5	0.0	
40	PI2 BPSK	50	56	15.62	15.68	15.54			
40	PI2 BPSK	100	0	15.76	15.65	15.75	17.5	0.0	
40	QPSK	1	1	15.91	15.56	15.65			
40	QPSK	1	53	15.65	15.83	15.63	17.5	0.0	
40	QPSK	1	104	15.62	15.57	15.56			
40	QPSK	50	0	15.50	15.80	15.55	17.5	0.0	
40	QPSK	50	28	15.65	15.74	15.55	17.5	0.0	
40	QPSK	50	56	15.53	15.52	15.68			
40	QPSK	100	0	15.52	15.66	15.57	17.5	0.0	
40	16QAM	1	1	15.54	15.62	15.62	17.5	0.0	
40	64QAM	1	1	15.53	15.51	15.57	17.5	0.0	
40	256QAM	1	1	15.72	15.78	15.59	17.5	0.0	
Channel				518000	519000	522000	Tune-up limit	MPR	
Frequency (MHz)				2580	2595	2610			
20	QPSK	1	26	15.58	15.79	15.72	17.5	0.0	
Channel				518202	519200	522100	Tune-up limit	MPR	
Frequency (MHz)				2577.51	2595	2612.49			
15	QPSK	1	19	15.56	15.80	15.64	17.5	0.0	
Channel				518004	519000	522996	Tune-up limit	MPR	
Frequency (MHz)				2578.02	2595	2614.98			
10	QPSK	1	12	15.52	15.77	15.63	17.5	0.0	

n41_Ant4 DSI1 For SA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				509002	518598	530000			
Frequency (MHz)				2548.01	2592.99	2640			
100	PI2 BPSK	1	1	20.92	20.87	20.74			
100	PI2 BPSK	1	137	21.33	21.37	21.21			
100	PI2 BPSK	1	271	20.79	20.78	20.84	22.5	0.0	
100	PI2 BPSK	135	0	21.13	21.21	21.27	22.5	0.0	
100	PI2 BPSK	135	69	21.36	21.32	21.29	22.5	0.0	
100	PI2 BPSK	135	138	21.33	21.35	21.35			
100	PI2 BPSK	270	0	21.42	21.18	21.22	22.5	0.0	
100	QPSK	1	1	20.72	20.85	20.83			
100	QPSK	1	137	21.36	21.58	21.50	22.5	0.0	
100	QPSK	1	271	20.77	20.78	20.91			
100	QPSK	135	0	21.53	21.51	21.52	22.5	0.0	
100	QPSK	135	69	21.38	21.58	21.55	22.5	0.0	
100	QPSK	135	138	21.42	21.46	21.44			
100	QPSK	270	0	21.39	21.53	21.44	22.5	0.0	
100	16QAM	1	1	21.01	20.85	20.82	22.5	0.0	
100	64QAM	1	1	20.91	20.86	20.82	22.5	0.0	
100	256QAM	1	1	21.19	20.93	20.85	22.5	0.0	
Channel				508000	518598	538996	Tune-up limit	MPR	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	21.31	21.49	21.42	22.5	0.0	
Channel				507004	518598	539996	Tune-up limit	MPR	
Frequency (MHz)				2538.02	2592.99	2649.99			
80	QPSK	1	109	21.43	21.52	21.56	22.5	0.0	
Channel				505000	518598	531996	Tune-up limit	MPR	
Frequency (MHz)				2526	2592.99	2639.98			
60	QPSK	1	81	21.39	21.54	21.56	22.5	0.0	
Channel				504004	518598	532996	Tune-up limit	MPR	
Frequency (MHz)				2521.02	2592.99	2634.99			
50	QPSK	1	67	21.35	21.51	21.48	22.5	0.0	
Channel				503002	518598	534000	Tune-up limit	MPR	
Frequency (MHz)				2518.01	2592.99	2670			
40	QPSK	1	53	21.27	21.50	21.53	22.5	0.0	
Channel				502000	518598	534996	Tune-up limit	MPR	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	21.45	21.49	21.45	22.5	0.0	
Channel				501004	518598	535996	Tune-up limit	MPR	
Frequency (MHz)				2506.02	2592.99	2679.99			
20	QPSK	1	26	21.44	21.53	21.41	22.5	0.0	
Channel				500000	518598	537000	Tune-up limit	MPR	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	12	21.41	21.51	21.48	22.5	0.0	

n41_Ant4 DS11 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				500200	518598	526900			
Frequency (MHz)				2546.01	2592.99	2640			
100	PI2 BPSK	1	1	17.81	17.58	17.58	19.5	0.0	
100	PI2 BPSK	1	137	18.41	18.45	18.15			
100	PI2 BPSK	1	271	17.78	17.51	17.58			
100	PI2 BPSK	135	0	18.13	18.25	18.19	19.5	0.0	
100	PI2 BPSK	135	69	18.35	18.31	18.25	19.5	0.0	
100	PI2 BPSK	135	138	18.38	18.36	18.44	19.5	0.0	
100	PI2 BPSK	270	0	18.46	18.13	18.20			
100	QPSK	1	1	17.85	17.52	17.53			
100	QPSK	1	137	18.32	18.62	18.50	19.5	0.0	
100	QPSK	1	271	17.74	17.57	17.53			
100	QPSK	135	0	18.44	18.51	18.56	19.5	0.0	
100	QPSK	135	69	18.40	18.57	18.51	19.5	0.0	
100	QPSK	135	138	18.48	18.40	18.38	19.5	0.0	
100	QPSK	270	0	18.28	18.51	18.45			
100	16QAM	1	1	17.53	17.57	17.61	19.5	0.0	
100	64QAM	1	1	17.62	17.56	17.64	19.5	0.0	
100	256QAM	1	1	17.71	17.68	17.73	19.5	0.0	
Channel				508200	518598	528998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	18.32	18.50	18.34	19.5	0.0	
Channel				512200	518598	529098	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2648.99			
80	QPSK	1	109	18.28	18.52	18.36	19.5	0.0	
Channel				505200	518598	531998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2526	2592.99	2658.98			
60	QPSK	1	81	18.34	18.53	18.51	19.5	0.0	
Channel				504204	518598	532998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	67	18.33	18.53	18.50	19.5	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	53	18.33	18.52	18.34	19.5	0.0	
Channel				502200	518598	534998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	18.27	18.47	18.38	19.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2678.99			
20	QPSK	1	26	18.38	18.50	18.34	19.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2682			
15	QPSK	1	19	18.39	18.46	18.39	19.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2682			
10	QPSK	1	12	18.30	18.55	18.35	19.5	0.0	

n41_Ant4 DS14 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				500200	518598	526900			
Frequency (MHz)				2546.01	2592.99	2640			
100	PI2 BPSK	1	1	18.71	18.59	18.74	20.5	0.0	
100	PI2 BPSK	1	137	19.28	19.43	19.13			
100	PI2 BPSK	1	271	18.52	18.52	18.66			
100	PI2 BPSK	135	0	19.06	19.17	19.22	20.5	0.0	
100	PI2 BPSK	135	69	19.44	19.39	19.20	20.5	0.0	
100	PI2 BPSK	135	138	19.39	19.37	19.42	20.5	0.0	
100	PI2 BPSK	270	0	19.43	19.10	19.20			
100	QPSK	1	1	18.61	18.58	18.59			
100	QPSK	1	137	19.32	19.64	19.47	20.5	0.0	
100	QPSK	1	271	18.54	18.53	18.58			
100	QPSK	135	0	19.52	19.51	19.44	20.5	0.0	
100	QPSK	135	69	19.30	19.55	19.49	20.5	0.0	
100	QPSK	135	138	19.41	19.47	19.48	20.5	0.0	
100	QPSK	270	0	19.39	19.52	19.50			
100	16QAM	1	1	18.81	18.62	18.66	20.5	0.0	
100	64QAM	1	1	18.68	18.68	18.76	20.5	0.0	
100	256QAM	1	1	18.80	18.62	18.57	20.5	0.0	
Channel				508200	518598	528998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2541	2592.99	2644.98			
90	QPSK	1	123	19.40	19.41	19.39	20.5	0.0	
Channel				512200	518598	529098	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2536.02	2592.99	2648.99			
80	QPSK	1	109	19.31	19.40	19.44	20.5	0.0	
Channel				505200	518598	531998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2526	2592.99	2658.98			
60	QPSK	1	81	19.26	19.54	19.50	20.5	0.0	
Channel				504204	518598	532998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2521.02	2592.99	2664.99			
50	QPSK	1	67	19.38	19.44	19.46	20.5	0.0	
Channel				503202	518598	534000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2516.01	2592.99	2670			
40	QPSK	1	53	19.37	19.54	19.38	20.5	0.0	
Channel				502200	518598	534998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2511	2592.99	2674.98			
30	QPSK	1	39	19.29	19.45	19.44	20.5	0.0	
Channel				501204	518598	535998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2506.02	2592.99	2678.99			
20	QPSK	1	26	19.24	19.57	19.40	20.5	0.0	
Channel				500200	518598	536998	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2682.48			
15	QPSK	1	19	19.25	19.45	19.37	20.5	0.0	
Channel				500202	518598	537000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				2501.01	2592.99	2685			
10	QPSK	1	12	19.27	19.53	19.45	20.5	0.0	



n77_Ant5 DS1 For SA / DSI 4 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low 650000	Power Middle 650000	Power High 650000	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	Pi2 BPSK	1	1	18.16	18.28	17.84			
100	Pi2 BPSK	1	137	18.16	18.12	17.85	19.0	0.0	
100	Pi2 BPSK	1	271	18.28	18.14	17.98			
100	Pi2 BPSK	135	0	17.86	18.20	17.95	19.0	0.0	
100	Pi2 BPSK	135	69	18.10	17.95	17.95	19.0	0.0	
100	Pi2 BPSK	135	138	18.04	18.28	17.97	19.0	0.0	
100	Pi2 BPSK	270	0	18.20	18.18	18.03			
100	QPSK	1	1	18.12	18.10	18.03			
100	QPSK	1	137	18.14	18.28	17.96	19.0	0.0	
100	QPSK	1	271	18.28	18.17	18.01			
100	QPSK	135	0	18.16	18.10	17.94	19.0	0.0	
100	QPSK	135	69	17.99	18.26	17.96	19.0	0.0	
100	QPSK	135	138	18.07	18.01	17.99	19.0	0.0	
100	QPSK	270	0	18.06	18.15	17.83			
100	16QAM	1	1	18.01	18.11	17.97	19.0	0.0	
100	64QAM	1	1	18.09	18.12	17.85	19.0	0.0	
100	256QAM	1	1	17.99	18.26	17.97	19.0	0.0	
Channel									
Frequency (MHz)				649868	650000	650234	Tune-up limit	MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	123	18.00	18.28	17.53	18.0	0.0	
Channel									
Frequency (MHz)				649334	650000	650668	Tune-up limit	MPR (dB)	
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	109	18.05	18.12	17.89	19.0	0.0	
Channel									
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	95	18.13	18.17	17.91	19.0	0.0	
Channel									
Frequency (MHz)				648668	650000	653334	Tune-up limit	MPR (dB)	
Frequency (MHz)				3730.02	3840	3940.01			
60	QPSK	1	81	17.98	18.21	17.87	19.0	0.0	
Channel									
Frequency (MHz)				648334	650000	653668	Tune-up limit	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	67	18.07	18.26	17.84	19.0	0.0	
Channel									
Frequency (MHz)				648000	650000	654000	Tune-up limit	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	18.07	18.17	17.81	19.0	0.0	
Channel									
Frequency (MHz)				647334	650000	654668	Tune-up limit	MPR (dB)	
Frequency (MHz)				3715.01	3840	3970.02			
20	QPSK	1	26	17.95	18.12	17.87	19.0	0.0	
Channel									
Frequency (MHz)				647000	650000	655334	Tune-up limit	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	18.12	18.28	17.79	19.0	0.0	
Channel									
Frequency (MHz)				647000	650000	656000	Tune-up limit	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	18.15	18.14	17.92	19.0	0.0	

par27Q n77_Ant5 DSI1 For SA / DSI 4 For SA&NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)					3500.01				
100	Pi2 BPSK	1	1	18.10					
100	Pi2 BPSK	1	137	18.02			19.0	0.0	
100	Pi2 BPSK	1	271	18.02					
100	Pi2 BPSK	135	0	18.06			19.0	0.0	
100	Pi2 BPSK	135	69	18.04			19.0	0.0	
100	Pi2 BPSK	135	138	18.17			19.0	0.0	
100	Pi2 BPSK	270	0	18.01					
100	QPSK	1	1	18.24					
100	QPSK	1	137	18.25			19.0	0.0	
100	QPSK	1	271	18.04					
100	QPSK	135	0	18.23			19.0	0.0	
100	QPSK	135	69	18.24			19.0	0.0	
100	QPSK	135	138	18.09			19.0	0.0	
100	QPSK	270	0	18.10					
100	16QAM	1	1	18.23			19.0	0.0	
100	64QAM	1	1	18.63			19.0	0.0	
100	256QAM	1	1	18.19			19.0	0.0	
Channel									
Frequency (MHz)				633000	633334	633668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3485	3500.01	3504.99			
90	QPSK	1	123	18.15	18.11	18.14	18.0	0.0	
Channel									
Frequency (MHz)				632668	633334	633000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3490.02	3500.01	3510			
80	QPSK	1	109	18.16	18.00	18.07	19.0	0.0	
Channel									
Frequency (MHz)				3485.01	3500.01	3514.98			
70	QPSK	1	95	18.11	18.08	18.05	19.0	0.0	
Channel									
Frequency (MHz)				632000	633334	633668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3480	3500.01	3505			
60	QPSK	1	81	18.23	18.07	18.13	19.0	0.0	
Channel									
Frequency (MHz)				631668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3475.02	3500.01	3505			
50	QPSK	1	67	18.21	18.15	18.08	19.0	0.0	
Channel									
Frequency (MHz)				631334	633334	635332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3470.01	3500.01	3525.98			
40	QPSK	1	53	18.12	18.01	18.21	19.0	0.0	
Channel									
Frequency (MHz)				630668	633334	635000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3460.02	3500.01	3540			
20	QPSK	1	26	18.15	18.05	18.07	19.0	0.0	
Channel									
Frequency (MHz)				630300	633334	635668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3457.5	3500.01	3542.49			
15	QPSK	1	19	18.04	18.10	18.01	19.0	0.0	
Channel									
Frequency (MHz)				630334	633334	636332	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3455.01	3500.01	3544.99			
10	QPSK	1	12	18.08	18.12	18.07	19.0	0.0	

n77_Ant5 DSI1 For NSA									
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch./ Freq.	Power Middle Ch./ Freq.	Power High Ch./ Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel									
Frequency (MHz)				3750	3840	3930			
100	Pi2 BPSK	1	1	18.05	18.20	18.04			
100	Pi2 BPSK	1	137	15.07	15.05	14.90	16.0	0.0	
100	Pi2 BPSK	1	271	16.10	15.07	14.99			
100	Pi2 BPSK	135	0	15.08	15.19	15.07	16.0	0.0	
100	Pi2 BPSK	135	69	15.01	14.91	14.80	16.0	0.0	
100	Pi2 BPSK	135	138	15.05	15.17	15.13			
100	Pi2 BPSK	270	0	15.12	15.00	15.05	16.0	0.0	
100	QPSK	1	1	14.80	15.23	15.10			
100	QPSK	1	137	14.98	15.27	14.90			
100	QPSK	1	271	15.13	15.18	15.02			
100	QPSK	135	0	15.05	15.03	14.94	16.0	0.0	
100	QPSK	135	69	15.12	15.14	15.07	16.0	0.0	
100	QPSK	135	138	15.08	15.10	15.05			
100	QPSK	270	0	15.03	15.05	15.03			
100	16QAM	1	1	15.05	15.02	15.10	16.0	0.0	
100	16QAM	1	1	15.12	14.90	14.92	16.0	0.0	
100	256QAM	1	1	14.94	15.09	14.95	16.0	0.0	
Channel				649688	660000	662334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3745.02	3840	3935.01			
90	QPSK	1	123	14.79	15.12	14.81	16.0	0.0	
Channel				645334	596000	650208	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3740.01	3840	3940.02			
80	QPSK	1	109	14.79	15.06	14.86	16.0	0.0	
Channel				645334	600000	645333	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3735	3840	3945			
70	QPSK	1	95	14.70	15.20	14.75	16.0	0.0	
Channel				649688	660000	653334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3730.01	3840	3950.01			
60	QPSK	1	81	14.74	15.07	14.77	16.0	0.0	
Channel				648334	650000	653608	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3725.01	3840	3955.02			
50	QPSK	1	67	14.72	15.09	14.85	16.0	0.0	
Channel				648000	656000	664000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3720	3840	3960			
40	QPSK	1	53	14.69	15.10	14.87	16.0	0.0	
Channel				647334	659000	646668	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3710.01	3840	3970.02			
20	QPSK	1	26	14.81	15.15	14.70	16.0	0.0	
Channel				647168	659000	646334	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3707.52	3840	3972.51			
15	QPSK	1	19	14.81	15.16	14.74	16.0	0.0	
Channel				647000	660000	662000	Tune-up limit (dBm)	MPR (dB)	
Frequency (MHz)				3705	3840	3975			
10	QPSK	1	12	14.83	15.13	14.75	16.0	0.0	



n77_Ant5 DS1I For NSA							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	
Channel							
Frequency (MHz)							
100	PQ2 BPSK	1	1		15.03		
100	PQ2 BPSK	1	137		15.15		16.0
100	PQ2 BPSK	1	271		15.00		
100	PQ2 BPSK	135	0		15.04		16.0
100	PQ2 BPSK	135	69		14.98		16.0
100	PQ2 BPSK	135	138		15.13		16.0
100	PQ2 BPSK	270	0		15.16		
100	QPSK	1	1		15.13		
100	QPSK	1	137		15.15		16.0
100	QPSK	1	271		15.15		
100	QPSK	135	0		14.99		16.0
100	QPSK	135	69		15.04		16.0
100	QPSK	135	138		14.96		
100	QPSK	270	0		15.03		
100	16QAM	1	1		15.00		16.0
100	64QAM	1	1		15.00		16.0
100	256QAM	1	1		15.13		16.0
Channel							
Frequency (MHz)							
90	QPSK	1	123	633000	633334	633666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
80	QPSK	1	109	632688	633334	634000	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
70	QPSK	1	95	632000	633334	634666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
60	QPSK	1	81	631688	633334	635000	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
50	QPSK	1	67	631334	633334	635332	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
40	QPSK	1	53	631000	633334	635666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
20	QPSK	1	26	630500	633334	636166	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
15	QPSK	1	19	630334	633334	636332	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
10	QPSK	1	12	630334	633334	636332	Tune-up limit (dBm) MPR (dB)

n78_Ant5 DS1I For SA / DS1 4 For SA&NSA							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	
Channel							
Frequency (MHz)							
100	PQ2 BPSK	1	1		18.19		
100	PQ2 BPSK	1	137		18.11		19.0
100	PQ2 BPSK	1	271		18.12		
100	PQ2 BPSK	135	0		18.11		19.0
100	PQ2 BPSK	135	69		18.10		19.0
100	PQ2 BPSK	135	138		18.21		19.0
100	PQ2 BPSK	270	0		18.18		
100	QPSK	1	1		18.14		
100	QPSK	1	137		18.27		19.0
100	QPSK	1	271		18.28		
100	QPSK	135	0		18.04		19.0
100	QPSK	135	69		18.16		19.0
100	QPSK	135	138		18.03		
100	QPSK	270	0		18.15		
100	16QAM	1	1		18.01		19.0
100	64QAM	1	1		18.23		19.0
100	256QAM	1	1		18.20		19.0
Channel							
Frequency (MHz)							
90	QPSK	1	123	649668	650000	650334	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
80	QPSK	1	109	649334	650000	650666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
70	QPSK	1	95	648668	650000	651334	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
60	QPSK	1	81	648334	650000	651666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
50	QPSK	1	67	648000	650000	652000	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
40	QPSK	1	53	647668	650000	652334	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
20	QPSK	1	26	647166	650000	652834	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
15	QPSK	1	19	647000	650000	653000	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
10	QPSK	1	12	647000	650000	653000	Tune-up limit (dBm) MPR (dB)

par27Q n78_Ant5 DS1I For SA / DS1 4 For SA&NSA							
BW [MHz]	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	
Channel							
Frequency (MHz)							
100	PQ2 BPSK	1	1		18.12		
100	PQ2 BPSK	1	137		18.11		19.0
100	PQ2 BPSK	1	271		18.08		
100	PQ2 BPSK	135	0		18.17		19.0
100	PQ2 BPSK	135	69		18.16		19.0
100	PQ2 BPSK	135	138		18.21		19.0
100	PQ2 BPSK	270	0		18.13		
100	QPSK	1	1		18.18		
100	QPSK	1	137		18.25		19.0
100	QPSK	1	271		18.22		
100	QPSK	135	0		17.97		19.0
100	QPSK	135	69		18.11		19.0
100	QPSK	135	138		18.09		
100	QPSK	270	0		18.23		
100	16QAM	1	1		18.02		19.0
100	64QAM	1	1		18.19		19.0
100	256QAM	1	1		18.20		19.0
Channel							
Frequency (MHz)							
90	QPSK	1	123	639000	639334	639666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
80	QPSK	1	109	638668	639334	639999	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
70	QPSK	1	95	638000	639334	640666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
60	QPSK	1	81	637500	639334	641166	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
50	QPSK	1	67	637000	639334	641666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
40	QPSK	1	53	636500	639334	642166	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
20	QPSK	1	26	636000	639334	642666	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
15	QPSK	1	19	635500	639334	643166	Tune-up limit (dBm) MPR (dB)
Channel							
Frequency (MHz)							
10	QPSK	1	12	635000	639334	643666	Tune-up limit (dBm) MPR (dB)

n78_Ant5 DSI1 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit (dBm)	MPR (dB)	
Channel				649668	650000	650334	Tune-up limit	MPR	
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)	
100	Pl2 BPSK	1	1	15.02	15.11	15.09	16.0	0.0	
100	Pl2 BPSK	1	137	15.06	15.06	15.15	16.0	0.0	
100	Pl2 BPSK	1	271	15.19	15.19	15.00	16.0	0.0	
100	Pl2 BPSK	135	0	15.02	15.02	15.04	16.0	0.0	
100	Pl2 BPSK	135	69	14.98	14.98	15.04	16.0	0.0	
100	Pl2 BPSK	135	138	15.17	15.17	15.13	16.0	0.0	
100	Pl2 BPSK	270	0	15.16	15.16	15.15	16.0	0.0	
100	QPSK	1	1	15.04	15.04	15.13	16.0	0.0	
100	QPSK	1	137	15.04	15.04	15.15	16.0	0.0	
100	QPSK	1	271	15.14	15.14	15.15	16.0	0.0	
100	QPSK	135	0	14.98	14.98	14.99	16.0	0.0	
100	QPSK	135	69	15.06	15.06	15.03	16.0	0.0	
100	QPSK	135	138	14.97	14.97	14.96	16.0	0.0	
100	QPSK	270	0	15.13	15.13	15.05	16.0	0.0	
100	16QAM	1	1	14.74	14.74	15.00	16.0	0.0	
100	16QAM	1	1	15.18	15.18	15.00	16.0	0.0	
100	256QAM	1	1	15.20	15.20	15.13	16.0	0.0	
Channel				649668	650000	650334	Tune-up limit	MPR	
Frequency (MHz)				3745.02	3750	3755.01	(dBm)	(dB)	
90	QPSK	1	123	15.02	15.11	15.09	16.0	0.0	
Channel				648334	650000	650668	Tune-up limit	MPR	
Frequency (MHz)				3740.01	3750	3760.02	(dBm)	(dB)	
80	QPSK	1	109	15.00	15.20	15.13	16.0	0.0	
Channel				648000	650000	651000	Tune-up limit	MPR	
Frequency (MHz)				3735	3750	3765	(dBm)	(dB)	
70	QPSK	1	95	15.02	15.03	15.19	16.0	0.0	
Channel				648668	650000	651334	Tune-up limit	MPR	
Frequency (MHz)				3740.02	3750	3760.02	(dBm)	(dB)	
60	QPSK	1	81	14.99	15.23	15.21	16.0	0.0	
Channel				648334	650000	651668	Tune-up limit	MPR	
Frequency (MHz)				3735.01	3750	3765.02	(dBm)	(dB)	
50	QPSK	1	67	15.08	15.07	15.06	16.0	0.0	
Channel				648000	650000	652000	Tune-up limit	MPR	
Frequency (MHz)				3720	3750	3785	(dBm)	(dB)	
40	QPSK	1	53	15.07	15.16	15.18	16.0	0.0	
Channel				647334	650000	652668	Tune-up limit	MPR	
Frequency (MHz)				3710.01	3750	3790.02	(dBm)	(dB)	
20	QPSK	1	26	15.10	15.22	15.04	16.0	0.0	
Channel				647168	650000	652834	Tune-up limit	MPR	
Frequency (MHz)				3707.52	3750	3792.51	(dBm)	(dB)	
15	QPSK	1	19	15.08	15.23	15.19	16.0	0.0	
Channel				647000	650000	653000	Tune-up limit	MPR	
Frequency (MHz)				3705	3750	3795	(dBm)	(dB)	
10	QPSK	1	12	14.88	15.11	15.13	16.0	0.0	

Par27Q n78_Ant5 DSI1 For NSA									
BW (MHz)	Modulation	RB Size	RB Offset	Power Low Ch. / Freq.	Power Middle Ch. / Freq.	Power High Ch. / Freq.	Tune-up limit	MPR (dB)	
Channel				639000	633334	633668	Tune-up limit	MPR	
Frequency (MHz)				3405	3500.01	3504.99	(dBm)	(dB)	
100	Pl2 BPSK	1	1	15.09	15.03	15.01	16.0	0.0	
100	Pl2 BPSK	1	137	15.15	15.15	15.01	16.0	0.0	
100	Pl2 BPSK	1	271	15.00	15.00	15.04	16.0	0.0	
100	Pl2 BPSK	135	0	15.04	15.04	15.04	16.0	0.0	
100	Pl2 BPSK	135	69	14.98	14.98	14.96	16.0	0.0	
100	Pl2 BPSK	135	138	15.13	15.13	15.13	16.0	0.0	
100	Pl2 BPSK	270	0	15.15	15.15	15.13	16.0	0.0	
100	QPSK	1	1	15.13	15.13	15.15	16.0	0.0	
100	QPSK	1	137	15.16	15.16	15.15	16.0	0.0	
100	QPSK	1	271	15.15	15.15	15.07	16.0	0.0	
100	QPSK	135	0	14.99	14.99	14.99	16.0	0.0	
100	QPSK	135	69	15.03	15.03	15.03	16.0	0.0	
100	QPSK	135	138	14.96	14.96	14.96	16.0	0.0	
100	QPSK	270	0	15.03	15.03	15.05	16.0	0.0	
100	16QAM	1	1	15.00	15.00	15.00	16.0	0.0	
100	16QAM	1	1	15.00	15.00	15.00	16.0	0.0	
100	256QAM	1	1	15.13	15.13	15.00	16.0	0.0	
Channel				639000	633334	633668	Tune-up limit	MPR	
Frequency (MHz)				3405	3500.01	3504.99	(dBm)	(dB)	
90	QPSK	1	123	15.09	15.03	15.01	16.0	0.0	
Channel				632668	633334	634000	Tune-up limit	MPR	
Frequency (MHz)				3400.02	3500.01	3510	(dBm)	(dB)	
80	QPSK	1	109	15.05	15.03	15.01	16.0	0.0	
Channel				632334	633334	634332	Tune-up limit	MPR	
Frequency (MHz)				3405.01	3500.01	3514.98	(dBm)	(dB)	
70	QPSK	1	95	14.95	15.03	14.93	16.0	0.0	
Channel				632000	633334	634668	Tune-up limit	MPR	
Frequency (MHz)				3400	3500.01	3519.96	(dBm)	(dB)	
60	QPSK	1	81	15.02	15.00	14.95	16.0	0.0	
Channel				631668	633334	635000	Tune-up limit	MPR	
Frequency (MHz)				3405.02	3500.01	3525	(dBm)	(dB)	
50	QPSK	1	67	15.10	14.98	14.99	16.0	0.0	
Channel				631334	633334	635332	Tune-up limit	MPR	
Frequency (MHz)				3470.01	3500.01	3528.98	(dBm)	(dB)	
40	QPSK	1	53	15.15	15.02	15.03	16.0	0.0	
Channel				632668	633334	636000	Tune-up limit	MPR	
Frequency (MHz)				3400.02	3500.01	3540	(dBm)	(dB)	
20	QPSK	1	26	15.13	15.06	15.04	16.0	0.0	
Channel				632334	633334	636168	Tune-up limit	MPR	
Frequency (MHz)				3457.5	3500.01	3542.49	(dBm)	(dB)	
15	QPSK	1	19	15.05	15.09	15.07	16.0	0.0	
Channel				630334	633334	636332	Tune-up limit	MPR	
Frequency (MHz)				3405.01	3500.01	3544.98	(dBm)	(dB)	
10	QPSK	1	12	15.06	14.99	15.05	16.0	0.0	

WLAN/Bluetooth Power

Full power						Head		
2.4GHz WLAN						Ant 6		
	Mode	Channel	Frequency (Mhz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle %
2.4GHz WLAN	802.11b 1Mbps	1	2412	19.50	20.50	16.44	16.50	100.00
		6	2437	19.00	20.00	16.01	16.50	
		11	2462	19.20	20.00	16.16	16.50	
	802.11g 6Mbps	1	2412	17.90	19.00	Not Required	16.50	100.00
		6	2437	17.80	19.00		16.50	
		11	2462	16.00	17.00		16.50	
	802.11n-HT20 MCS0	1	2412	17.80	19.00		16.50	100.00
		6	2437	17.60	18.50		16.50	
		11	2462	15.20	16.00		16.00	
	802.11n-HT40 MCS0	3	2422	15.80	17.00		16.50	100.00
		6	2437	16.80	18.00		16.50	
		9	2452	13.20	14.00		14.00	

Full power						Head		
5.2GHz WLAN						Ant 6		
	Mode	Channel	Frequency (Mhz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle %
5.2GHz WLAN	802.11a 6Mbps	36	5180	15.00	16.00	Not Required	11.50	100.00
		40	5200	15.10	16.00		11.50	
		44	5220	15.20	16.50		11.50	
		48	5240	15.40	16.50		11.50	
	802.11n-HT20 MCS0	36	5180	14.90	16.00		11.50	100.00
		40	5200	15.00	16.00		11.50	
		44	5220	15.10	16.00		11.50	
	802.11n-HT40 MCS0	48	5240	15.00	16.00		11.50	100.00
		36	5190	14.80	16.00		11.50	
		46	5230	15.00	16.00		11.50	
	802.11ac-VHT20 MCS0	36	5180	14.80	16.00		11.50	100.00
		40	5200	14.90	16.00		11.50	
		44	5220	15.00	16.00		11.50	
	802.11ac-VHT40 MCS0	48	5240	14.90	16.00		11.50	100.00
		38	5190	14.70	16.00		11.50	
		46	5230	14.90	16.00		11.50	
	802.11ac-VHT80 MCS0	42	5210	14.10	15.00		11.50	100.00

Full power						Head		
5.3GHz WLAN						Ant 6		
	Mode	Channel	Frequency (Mhz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle %
5.3GHz WLAN	802.11a 6Mbps	52	5260	16.00	19.00	Not Required	11.50	100.00
		56	5280	16.10	19.00		11.50	
		60	5300	16.10	19.00		11.50	
		64	5320	16.20	19.00		11.50	
	802.11n-HT20 MCS0	52	5260	16.50	17.50		11.50	100.00
		56	5280	16.60	17.50		11.50	
		60	5300	16.70	17.50		11.50	
		64	5320	16.70	17.50		11.50	
	802.11n-HT40 MCS0	54	5270	16.40	17.50		11.50	100.00
		62	5310	16.40	17.50		11.50	
		52	5260	16.30	17.50		11.50	
		56	5280	16.30	17.50		11.50	
	802.11ac-VHT20 MCS0	60	5300	16.30	17.50		11.50	100.00
		64	5320	16.50	17.50		11.50	
		54	5270	16.30	17.50		11.50	
		62	5310	16.30	17.50		11.50	
	802.11ac-VHT40 MCS0	58	5290	14.50	15.50	10.45	11.50	100.00

Full power						Head		
5.5GHz WLAN						Ant 6		
	Mode	Channel	Frequency (Mhz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle %
5.5GHz WLAN	802.11a 6Mbps	100	5500	18.00	19.00	Not Required	10.50	100.00
		116	5580	18.10	19.00		10.50	
		124	5620	18.00	19.00		10.50	
		132	5660	18.10	19.00		10.50	
		140	5700	15.40	16.50		10.50	
		144	5720	18.00	19.00		10.50	
	802.11n-HT20 MCS0	100	5500	16.50	17.50		10.50	100.00
		116	5580	16.60	17.50		10.50	
		124	5620	16.50	17.50		10.50	
		132	5660	16.60	17.50		10.50	
		140	5700	15.60	16.50		10.50	
		144	5720	16.60	17.50		10.50	
	802.11n-HT40 MCS0	102	5510	16.30	17.50		10.50	100.00
		110	5550	16.50	17.50		10.50	
		126	5630	16.50	17.50		10.50	
		134	5670	16.20	17.50		10.50	
		142	5710	16.50	17.50		10.50	
		100	5500	16.30	17.50		10.50	
	802.11ac-VHT20 MCS0	116	5580	16.30	17.50		10.50	100.00
		124	5620	16.30	17.50		10.50	
		132	5660	16.30	17.50		10.50	
		140	5700	15.50	16.50		10.50	
		144	5720	16.40	17.50		10.50	
		102	5510	16.20	17.50		10.50	
	802.11ac-VHT40 MCS0	110	5550	16.40	17.50		10.50	100.00
		126	5630	16.40	17.50		10.50	
		134	5670	16.10	17.00		10.50	
		142	5710	16.40	17.50		10.50	
		106	5630	15.00	16.00	9.42	10.50	
		122	5610	16.00	17.00	9.53	10.50	
	802.11ac-VHT80 MCS0	138	5690	16.10	17.00	9.61	10.50	100.00

Full power						Head		
5.8GHz WLAN						Ant 6		
	Mode	Channel	Frequency (Mhz)	Average power (dBm)	Tune-Up Limit	Average power (dBm)	Tune-Up Limit	Duty Cycle %
5.8GHz WLAN	802.11a 6Mbps	149	5745	15.30	16.50	Not Required	11.50	100.00
		157	5785	15.60	16.50		11.50	
		165	5825	15.70	16.50		11.50	
	802.11n-HT20 MCS0	149	5745	15.20	16.50		11.50	100.00
		157	5785	15.40	16.50		11.50	
		165	5825	15.50	16.50		11.50	
	802.11n-HT40 MCS0	151	5755	15.40	16.50		11.50	100.00
		159	5795	15.40	16.50		11.50	
		149	5745	15.10	16.50		11.50	
	802.11ac-VHT20 MCS0	157	5785	15.30	16.50		11.50	100.00
		165	5825	15.40	16.50		11.50	
		151	5755	15.30	16.50		11.50	
	802.11ac-VHT40 MCS0	159	5795	15.30	16.50		11.50	100.00
		155	5775	15.50	16.50	10.12	11.50	

BT BR/EDR

Mode	Channel	Frequency (MHz)	Average power (dBm)			Tune-up Limit
			1Mbps	2Mbps	3Mbps	
BR / EDR	CH 00	2402	9.16	8.56	8.27	10.00
	CH 39	2441	11.00	9.36	9.35	11.50
	CH 78	2480	9.32	8.70	8.73	10.00

BT LE

Mode	Channel	Frequency (MHz)	Average power (dBm)
			GFSK
LE	CH 00	2402	-4.90
	CH 19	2440	-3.20
	CH 39	2480	-3.80
Tune-up Limit			0

BT LE V5.0

Mode	Channel	Frequency (MHz)	Average power (dBm)
			1Mbps
LE	CH 00	2402	-4.70
	CH 19	2440	-2.70
	CH 39	2480	-3.70
Tune-up Limit			0