

FCC PART 22/24/27 TEST REPORT				
FCC Part 22 /Part 24/Part 27				
Report Reference No.:	HK1812211956E			
FCC ID:	2AHZ5QUEST			
Compiled by (position+printed name+signature):	File administrators Gary Qian	Googe Bian		
Supervised by (position+printed name+signature) :	Technique principal Eden Hu	Edan Hu		
Approved by (position+printed name+signature):	Manager Jason Zhou	Jason Zhou		
Testing Laboratory Name :	Shenzhen HUAK Testing Technolog	gy Co., Ltd.		
Address :	Heping Community, Fuhai Street, E	Bao'an District, Shenzhen, China		
Applicant's name:	Shenzhen Huafurui Technology Co	., Ltd.		
	Unit 1401 &1402, 14/F, Jin qi zhi	gu mansion (No. 4 building of		
Address :	Chong wen Garden), Crossing of th	he Liu xian street and Tang ling		
	FCC Part 22: PUBLIC MOBILE SEP///CES			
	FCC Part 24: PERSONAL COMMUNICATIONS SERVICES			
Standard :	ECC Part 27: MISCELLANEOUS W			
	SERVICES			
Shenzhen HUAK Testing Technology Co This publication may be reproduced in v HUAK Testing Technology Co., Ltd. is a HUAK Testing Technology Co., Ltd. ta resulting from the reader's interpretation	b., Ltd. All rights reserved. whole or in part for non-commercial cknowledged as copyright owner and akes no responsibility for and will of the reproduced material due to it	purposes as long as the Shenzhen d source of the material. Shenzhen not assume liability for damages s placement and context.		
Test item description :	Smart Phone			
Brand Name:	CUBOT			
Model	QUEST			
Ratings :	DC 3.85V From Battery; DC5V/2A			
Modulation :	GSM / GPRS :GMSK EGPRS: 8PS	SK		
	HSDPA:QPSK/16QAM; HSUPA:BP	SK; WCDMA:QPSK		
GPRS/EGPRS	Supported			
Hardware version:	A799_MAIN_PCB_V1.1			
Software version:	CUBOT_CUBOT_QUEST_8123C_	_V01_20181122		
Frequency	GSM 850MHz; PCS 1900MHz; UM	TS Band II;UMTS Band V;		
	UMTS Band IV			
Result :	PASS			



Test Report No. :	Ηk	(1812211956E
Equipment under Test	:	Smart Phone
Model /Type	:	QUEST
Applicant	:	Shenzhen Huafurui Technology Co., Ltd.
Address	:	Unit 1401 &1402, 14/F, Jin qi zhi gu mansion (No. 4 building of Chong wen Garden), Crossing of the Liu xian street and Tang ling road, Tao yuan street, Nan shan district, Shenzhen,P.R. China
Manufacturer	:	Shenzhen Huafurui Technology Co., Ltd.
Address	:	Unit 1401 &1402, 14/F, Jin qi zhi gu mansion (No. 4 building of Chong wen Garden), Crossing of the Liu xian street and Tang ling road, Tao yuan street, Nan shan district, Shenzhen,P.R. China
Factory's Name		Shenzhen Huafurui Technology Co., Ltd.
Address:		Unit 1401 &1402, 14/F, Jin qi zhi gu mansion (No. 4 building of Chong wen Garden), Crossing of the Liu xian street and Tang ling road, Tao yuan street, Nan shan district, Shenzhen,P.R. China
Date of Test		
Date (s) of performance of tests		Dec. 28, 2018~Jan. 09, 2019
Date of Issue		Feb. 18, 2019
Test Result		Pass

TEST REPORT

Test Result:

PASS

The test report merely corresponds to the test sample.

It is not permitted to copy extracts of these test result without the written permission of the test laboratory.

Testing Engineer

:

2

Technical Manager

Good Dian (Gary Qian) Edan Mu (Eden Hu)

ason Zhori

Authorized Signatory:

(Jason Zhou)



Revision	Issue Date	Revisions	Revised By
V1.0	Feb. 18, 2019	Initial Issue	Jason Zhou



TABLE OF CONTENTS

1.TEST STANDARDS	6
2.1 PRODUCT DESCRIPTION	7
2.2 RELATED SUBMITTAL(S) / GRANT (S)	9
2.3 TEST METHODOLOGY	9
2.4 TEST FACILITY	
2.6 SPECIAL ACCESSORIES	11
2.7 EQUIPMENT MODIFICATIONS	11
3. SYSTEM TEST CONFIGURATION	
3.1 EUT CONFIGURATION	
3.2 EUT EXERCISE	
3.3 CONFIGURATION OF EUT SYSTEM	
4. SUMMARY OF TEST RESULTS	
5. DESCRIPTION OF TEST MODES	
6. OUTPUT POWER	
6.1 CONDUCTED OUTPUT POWER	
6.2 RADIATED OUTPUT POWER	
6.2.1 MEASUREMENT METHOD	
6.2.2 PROVISIONS APPLICABLE	
6.3. PEAK-TO-AVERAGE RATIO	
6.3.1 MEASUREMENT METHOD	
6.3.2 PROVISIONS APPLICABLE	
6.3.3 MEASUREMENT RESULT	
7. OCCUPIED BANDWIDTH	
7.1 MEASUREMENT METHOD	
7.2 PROVISIONS APPLICABLE	
7.3 MEASUREMENT RESULT	
8. BAND EDGE	
8.1 MEASUREMENT METHOD	
8.2 PROVISIONS APPLICABLE	
8.3 MEASUREMENT RESULT	
9. SPURIOUS EMISSION	41
9.1 CONDUCTED SPURIOUS EMISSION	
9.2 RADIATED SPURIOUS EMISSION	
9.2.2 TEST SETUP	
10. FREQUENCY STABILITY	
10.1 MEASUREMENT METHOD	65
10.2 PROVISIONS APPLICABLE	



10.3 MEASUREMENT RESULT	. 67
APPENDIX A: PHOTOGRAPHS OF TEST SETUP	. 76



1.TEST STANDARDS

The tests were performed according to following standards:

FCC Part 22 (10-1-12 Edition): PRIVATE LAND MOBILE RADIO SERVICES.

FCC Part 24(10-1-12 Edition): PUBLIC MOBILE SERVICES

FCC Part 27(10-12-18 Edition): MISCELLANEOUS WIRELESS COMMUNICATIONS SERVICES

<u>TIA-603 E Mar. 2016:</u> Land Mobile FM or PM Communications Equipment Measurement and Performance Standards.

FCC Part 2: FREQUENCY ALLOCA-TIONS AND RADIO TREATY MAT-TERS; GENERAL RULES AND REG-ULATIONS

KDB971168 D01:v03r01MEASUREMENT GUIDANCE FOR CERTIFICATION OF LICENSED DIGITAL

TRANSMITTERS

ANSI C63.26:2015: Compliance Testing of Transmitters Used in Licensed Radio Services



2. SUMMARY

2.1 PRODUCT DESCRIPTION

A major technical description of EUT is described as following:

Product Designation:	Smart Phone	
	GSM 850 PCS1900 (U.S. Bands)	
	GSM 900 DCS 1800 (Non-U.S. Bands)	
Frequency Bands:	UMTS FDD Band II UMTS FDD Band IV	
	⊠UMTS FDD Band V (U.S. Bands)	
	UMTS FDD Band I UMTS FDD Band VIII (Non-U.S. Bands)	
Antenna Type	PIFA Antenna	
	GSM / GPRS :GMSK	
Type of Modulation	EGPRS: GMSK/8PSK	
	WCDMA : QPSK	
Antonna gain	GSM850:-1.02dBi; PCS1900: 0.7dBi;	
Antenna gain	WCDMA850: -1.02dBi; WCDMA 1700:0.5dBi; WCDMA1900:0.7dBi;	
Power Supply:	DC 3.85V by battery	
Battery parameter:	DC3.85V/6000mAh	
Dual Card:	GSM /WCDMA/LTE Card Slot	
GPRS Class	12	
Extreme Vol. Limits:	DC3.4 V to 4.4 V (Normal: DC3.85 V)	
Extreme Temp. Tolerance	-10℃ to +50℃	
*** Note: 1. The High Voltage DC	4.4V and Low Voltage DC3.4V were declared by manufacturer	
2. The EUT couldn't be operating normally with higher or lower voltage.		

*** Note:1.The maximum power levels are GSM for MCS-4: GMSK link, and RMC 12.2kbps mode for WCDMA band II, WCDMA band V, WCDMA band IV, only these modes were used for all tests.

2. We found out the test mode with the highest power level after we analyze all the data rates. So we chose worst caseas a representative.



GSM/WCDMA Card1 Slot :

	Maximum ERP/EIRP	Max. Average	
	(dBm)	Burst Power (dBm)	
GSM 850	32.18	33.70	
PCS 1900	29.56	31.27	
UMTS BAND II	20.73	21.94	
UMTS BAND V	20.54	23.60	
UMTS BAND IV	19.49	20.74	

GSM/WCDMA Card2 Slot :

	Maximum ERP/EIRP	Max. Average	
	(dBm)	Burst Power (dBm)	
GSM 850	30.59	32.19	
PCS 1900	28.44	30.44	
UMTS BAND II	19.36	20.59	
UMTS BAND V	18.99	23.12	
UMTS BAND IV	18.10	19.16	



2.2 RELATED SUBMITTAL(S) / GRANT (S)

This submittal(s) (test report) is intended for **FCC ID:2AHZ5QUEST**, filing to comply with the FCC Part 22H&24E requirements.

2.3 TEST METHODOLOGY

The radiated emission testing was performed according to the procedures of ANSI/TIA-603-E-2016, and KDB 971168 D01 Power Means License Digital Systems V03R01.



2.4 TEST FACILITY

Site	Shenzhen HUAK Testing Technology Co., Ltd.		
Location	1F, B2 Building, Junfeng Zhongcheng Zhizao Innovation Park, Fuhai Street, Bao'an		
Location	District, Shenzhen City, China		
Designation Number	CN1229		
Test Firm Registration Number : 616276			

ALL TEST EQUIPMENT LIST

Equipment	Manufacturer	Model	S/N	Cal. Date	Cal. Due
Receiver	R&S	ESCI 7	HKE-010	Dec. 27, 2018	Dec. 26, 2019
LISN	R&S	ENV216	HKE-002	Dec. 27, 2018	Dec. 26, 2019
Spectrum analyzer	Agilent	N9020A	HKE-048	Dec. 27, 2018	Dec. 26, 2019
Horn antenna	Schwarzbeck	9120D	HKE-013	Dec. 27, 2018	Dec. 26, 2019
Preamplifier	EMCI	EMC051845SE	HKE-015	Dec. 27, 2018	Dec. 26, 2019
Double-Ridged Waveguide Horn	ETS LINDGREN	3117	HKE-087	Dec. 27, 2018	Dec. 26, 2019
Broadband antenna Schwarzbeck		VULB 9163	HKE-012	Dec. 27, 2018	Dec. 26, 2019
Spectrum analyzer	Agilent	N9020A	HKE-048	Dec. 27, 2018	Dec. 26, 2019
Power Sensor	Agilent	E9300A	HKE-086	Dec. 27, 2018	Dec. 26, 2019
Wireless					
Communication	R&S	CMU200	HKE-026	Dec. 27, 2018	Dec. 26, 2019
Test Set					



2.6 SPECIAL ACCESSORIES

The battery wassupplied by the applicant were used as accessories and being tested with EUT intended for FCC grant together.

2.7 EQUIPMENT MODIFICATIONS

Not available for this EUT intended for grant.



3. SYSTEM TEST CONFIGURATION

3.1 EUT CONFIGURATION

The EUTconfiguration for testing is installed on RF field strength measurement to meet the Commission's requirement and operating in a manner which intends to maximize its emission characteristics in a continuous normal application.

3.2 EUT EXERCISE

The Transmitter was operated in the maximum output power mode through Communication Tester. The TX frequency was fixed which was for the purpose of the measurements.

3.3 CONFIGURATION OF EUT SYSTEM

Fig. 2-1 Configuration of EUT System



Table 2-1 Equipment Used in EUT System

ltem	Equipment	Model No.	ID or Specification	Remark
1	Smart Phone	QUEST	2AHZ5QUEST	EUT
2	Adapter	QUEST	DC 5.0V 2A	Accessory
3	Battery	QUEST	DC3.85V/ 4000mAh	Accessory
4	USB	N/A	N/A	Accessory

***Note: All the accessories have been used during the test. The following "EUT" in setup diagram means EUT system.



4. SUMMARY OF TEST RESULTS

ltem Number	Item Description		FCC Rules	Result
		Conducted	2 10/6	
1	Output Power	Output Power	2.1046	Deee
I	Output Power	Radiated	22.042(a) (2) / 24.222 (a) / 27.50(d) (4)	Pass
		Output Power	22.915(a) (2) / 24.252 (C)/ 27.50(d)(4)	
2	Peak-to-Average	Peak-to-Average	24.222(4)	Pass
2	Ratio	Ratio	24.232(u)	
		Conducted		
2	Spurious	Spurious Emission	2 1051/22 017(a)/24 228(a)/ 27 52(b)	Deec
3	Emission	Radiated	2.1031/22.917(a)/24.230(a)/ 27.53(1)	Pass
		Spurious Emission		
4	Frequency Stability		2.1053/22.917(a)/24.238(a)/27.53(h)	Pass
5	Occupied Bandwidth		2.1049	Pass
6	Band Edge		2.1051/22.917(a)/24.238(a)/ 27.53(h)	Pass



5. DESCRIPTION OF TEST MODES

During the testing, the EUT was controlled via Rhode & Schwarz Digital Radio Communication Tester (CMU 200)to ensure max power transmission and proper modulation. Three channels (The top channel, the middle channel and the bottom channel) were chosen for testing on both GSMand PCS frequency band. *****Note:** GSM/GPRS/EGPRS 850, GSM/GPRS/EGPRS 1900, WCDMA/HSPA band II, WCDMA/HSPA band V, WCDMA/HSPA band IV, mode have been tested during the test.

The worst condition was recorded in the test report if no other modes test data.



6. OUTPUT POWER

6.1 CONDUCTED OUTPUT POWER

6.1.1 MEASUREMENT METHOD

The transmitter output port was connected to base station.

The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator.

The path loss was compensated to the results for each measurement.

Measure the maximum burst average power and average power for othermodulation signal.

The EUT was setup for the max output power with pseudo random data modulation. Power was measured with Spectrum Analyzer. The measurements were performed on all modes(GSM/GPRS/EGPRS 850, GSM/GPRS/EGPRS1900, WCDMA/HSPA band II,WCDMA/HSPA band V, WCDMA/HSPA band IV)at 3 typical channels(the Top Channel, the Middle Channel and the Bottom Channel) for each band.



GSM 850:

Mode	Frequency (MHz)	Avg.Burst Power	Duty cycle Factor(dB)	Frame Power(dBm)
	824.2	33.44	-9	24.44
GSM850	836.6	33.64	-9	24.64
	848.8	33.70	-9	24.70
	824.2	33.50	-9	24.50
(1 Slot)	836.6	33.65	-9	24.65
(1 300)	848.8	33.69	-9	24.69
	824.2	32.69	-6	26.69
(2 Slot)	836.6	32.84	-6	26.84
	848.8	32.93	-6	26.93
	824.2	30.89	-4.26	26.63
(2 Slot)	836.6	31.06	-4.26	26.80
(3 Slot)	848.8	31.13	-4.26	26.87
0000050	824.2	29.69	-3	26.69
(4 Slot)	836.6	29.91	-3	26.91
(4 3101)	848.8	30.01	-3	27.01

Mada	Channel	Frequency	Avg.Burst Power
INIOGE		(MHz)	(dBm)
EDCE	128	824.2	26.37
EDGE (1 Slot)	190	836.6	26.55
(1 3101)	251	848.8	26.90
EDGE (2 Slot)	128	824.2	24.71
	190	836.6	24.89
	251	848.8	25.17
EDCE	128	824.2	22.11
EDGE	190	836.6	22.39
(3 5101)	251	848.8	22.75
FDOF	128	824.2	20.89
EDGE (4 Slot)	190	836.6	21.21
(4 0101)	251	848.8	21.53



PCS 1900:

Mode	Frequency (MHz)	Avg.Burst Power	Duty cycle Factor(dB)	Frame Power(dBm)
	1850.2	31.17	-9	22.17
GSM1900	1880	30.47	-9	21.47
	1909.8	30.70	-9	21.70
	1850.2	31.27	-9	22.27
(1 Slot)	1880	30.56	-9	21.56
(1 300)	1909.8	30.79	-9	21.79
	1850.2	30.51	-6	24.51
(2 Slot)	1880	29.79	-6	23.79
	1909.8	30.11	-6	24.11
	1850.2	28.81	-4.26	24.55
(2 Slot)	1880	28.10	-4.26	23.84
(3 Slot)	1909.8	28.40	-4.26	24.14
	1850.2	27.75	-3	24.75
(4 Slot)	1880	27.01	-3	24.01
(4 3101)	1909.8	27.37	-3	24.37

NA - da	Channel	Frequency	Avg.Burst Power
Mode		(MHz)	(dBm)
FDOF	512	1850.2	27.71
EDGE (1 Slot)	661	1880	27.09
(1 3101)	810	1909.8	26.88
EDGE (2 Slot)	512	1850.2	26.25
	661	1880	25.63
	810	1909.8	25.36
EDGE (3 Slot)	512	1850.2	24.04
	661	1880	23.37
	810	1909.8	23.01
5005	512	1850.2	22.70
EDGE (4 Slot)	661	1880	22.04
(4 3101)	810	1909.8	21.73



UMTS BAND II

Mode	Mode Frequency (MHz)		Avg.Burst Power
	1852.4	24	21.82
WCDMA1900 RMC	1880	24	21.43
	1907.6	24	21.94
	1852.4	24	20.71
WCDMA1900 AMR	1880	24	20.59
	1907.6	24	20.47
	1852.4	24	20.93
Cubtost 1	1880	24	20.57
Sublesi	1907.6	24	21.08
אסטא	1852.4	24	20.18
Subtect 2	1880	24	19.89
Sublesi 2	1907.6	24	20.26
	1852.4	24	20.11
FIGDER Subtest 2	1880	24	19.88
Subtest 3	1907.6	24	20.22
	1852.4	24	20.09
Cubtost 4	1880	24	19.84
Sublest 4	1907.6	24	20.16
	1852.4	24	18.71
Subtest 1	1880	24	18.28
Sublesi	1907.6	24	18.79
	1852.4	24	18.88
Cubtost 2	1880	24	18.42
Sublesi 2	1907.6	24	18.96
	1852.4	24	19.79
Cubtost 2	1880	24	19.34
Subtest 3	1907.6	24	19.83
	1852.4	24	18.44
	1880	24	18.00
Subtest 4	1907.6	24	18.53
	1852.4	24	17.73
	1880	24	17.38
C IZBIQUE	1907.6	24	18.13



UMTS BAND V

Mode	Frequency (MHz)	Reference power	Avg.Burst Power
	826.4	24	22.86
WCDMA850 RMC	836.4	24	23.60
	846.6	24	23.56
	826.4	24	22.25
WCDMA850	836.4	24	22.12
	846.6	24	22.31
	826.4	24	22.05
HODFA	836.4	24	22.31
Subtest	846.6	24	22.43
	826.4	24	21.35
HSDPA Outstast 0	836.4	24	21.54
Subtest 2	846.6	24	21.71
	826.4	24	21.29
HSDPA Outstast 0	836.4	24	21.62
Subtest 3	846.6	24	21.71
	826.4	24	21.23
HSDPA	836.4	24	21.60
Sublest 4	846.6	24	21.59
	826.4	24	19.83
HOUFA	836.4	24	20.14
Sublest	846.6	24	20.25
	826.4	24	19.90
	836.4	24	20.21
Sublest 2	846.6	24	20.35
	826.4	24	20.78
HOUFA	836.4	24	21.10
Subtest 3	846.6	24	21.25
	826.4	24	19.46
	836.4	24	19.74
Sublest 4	846.6	24	19.85
	826.4	24	19.01
	836.4	24	19.27
Sublest 5	846.6	24	19.40



UMTS BAND IV

Mode	Frequency (MHz)	Reference power	Avg.Burst Power
	1712.4	24	20.74
WCDMA 1700	1732.4	24	20.69
	1752.6	24	20.70
	1712.4	24	20.52
WCDMA 1700	1732.4	24	20.44
	1752.6	24	20.64
ЦСОВУ	1712.4	24	20.33
Subtect 1	1732.4	24	20.42
Sublest	1752.6	24	19.69
нерра	1712.4	24	19.81
Subtect 2	1732.4	24	19.77
Sublest 2	1752.6	24	19.46
нерра	1712.4	24	19.52
Subtest 2	1732.4	24	19.66
Subtest 3	1752.6	24	19.73
нерра	1712.4	24	20.44
Subtest 4	1732.4	24	20.52
	1752.6	24	20.42
	1712.4	24	20.11
Subtect 1	1732.4	24	20.21
Sublest	1752.6	24	20.33
	1712.4	24	20.54
Subtest 2	1732.4	24	20.39
Sublest 2	1752.6	24	20.42
	1712.4	24	20.44
	1732.4	24	20.36
Subtest 3	1752.6	24	20.42
	1712.4	24	19.33
	1732.4	24	19.87
Sudtest 4	1752.6	24	19.44
	1712.4	24	20.11
	1732.4	24	20.36
Sudtest 5	1752.6	24	20.42



According to 3GPP 25.101 sub-clause 6.2.2, the maximum output power is allowed to be reduced by following the table.

Table 6.1aA: UE maximum output power with HS-DPCCH and E-DCH

· · ·				
UE Transmit Channel Configuration	CM(db)	MPR(db)		
For all combinations of ,DPDCH,DPCCH	0< CM<2 5	MAX(CM-1,0)		
HS-DPDCH, E-DPDCH and E-DPCCH				
Note: CM=1 for $\beta c/\beta d=12/15$, $\beta hs/\beta c=24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH,				
E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.				

The device supports MPR to solve linearity issues (ACLR or SEM) due to the higher peak-to average ratios (PAR) of the HSUPA signal. This prevents saturating the full range of the TX DAC inside of device and provides a reduced power output to the RF transceiver chip according to the Cubic Metric (a function of the combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH).

When E-DPDCH channels are present the beta gains on those channels are reduced firsts to try to get the power under the allowed limit. If the beta gains are lowered as far as possible, then a hard limiting is applied at the maximum allowed level.

The SW currently recalculates the cubic metric every time the beta gains on the E-DPDCH are reduced. The cubic metric will likely get lower each time this is done .However, there is no reported reduction of maximum output power in the HSUPA mode since the device also provides a compensate for the power back-off by increasing the gain of TX_AGC in the transceiver (PA) device.

The end effect is that the DUT output power is identical to the case where there is no MPR in the device.



6.2 RADIATED OUTPUT POWER 6.2.1 MEASUREMENT METHOD

The measurements procedures specified in ANSI/TIA-603-E-2016 were applied.

1. Effective Radiated Power (ERP) and Equivalent Isotropic Radiated Power (EIRP) measurements are performed using the substitution method described in ANSI/TIA-603-E-2016 with the EUT transmitting into an integral antenna. Measurements on signal operating below 1GHz are performed using dipole antennas. Measurements on signals operating above 1GHz are performed using broadband horn antennas. All measurements are performed as RMS average measurements while the EUT operating at its maximum duty cycle, at maximum power, and at the approximate frequencies.

2. In an anechoic antenna test chamber, a half-wave dipole antenna for the frequency band of interest is placed at the reference centre of the chamber. An RF Signal source for the frequency band of interest is connected to the dipole with a cable that has been constructed to not interfere with the radiation pattern of the antenna. A known (measured) power (Pin) is applied to the input of the dipole, and the power received (Pr) at the chamber's probe antenna is recorded.

3. The substitution method is used. Substitution values at each frequency are measured before and saved to the test software. A "reference path loss" is established as ARpl=Pin + 2.15 - Pr. TheARpl is the attenuation of "reference path loss", and including the gain of receive antenna, the cable loss and the air loss. The measurement results are obtained as described below: Power=PMea+ARpl

4. The EUT is substituted for the dipole at the reference centre of the chamber and a scan is performed to obtain the radiation pattern.

5. From the radiation pattern, the co-ordinates where the maximum antenna gain occurs are identified.

6. The EUT is then put into continuously transmitting mode at its maximum power level.

7. Power mode measurements are performed with the receiving antenna placed at the coordinates determined in Step 3 to determine the output power as defined in Rule 24.232 (b) and (c). The "reference path loss" from Step1 is added to this result.

8. This value is EIRP since the measurement is calibrated using a half-wave dipole antenna of known gain (2.15 dBi) and known input power (Pin).

9. ERP can be calculated from EIRP by subtracting the gain of the dipole, ERP = EIRP -2.15dBi...



6.2.2 PROVISIONS APPLICABLE

Mode	FCC Part Section(s)	Nominal Peak Power
GSM/EDGE 850	22.913(a)(2)	<=38.45dBm (7W). ERP
GSM/EDGE 1900	24.232(c)	<=33dBm (2W). EIRP
UMTS BAND II	24.232(c)	<=33dBm (2W),EIRP
UMTS BANDV	22.913(a)(2)	<=38.45dBm (7W).ERP
UMTS BAND IV	27.50(d)(4)	<=30dBm (1W). EIRP



6.2.3 MEASUREMENT RESULT

Radiated Power (ERP) for GSM/EDGE 850					
		Re	Result		
Mode	Frequency	Max. Peak ERP	Polarization	Conclusion	
		(dBm)	Of Max. ERP		
	824.2	32.08	Horizontal	Pass	
	836.6	32.15	Horizontal	Pass	
COM	848.8	32.18	Horizontal	Pass	
GSIVI	824.2	30.25	Vertical	Pass	
	836.6	30.27	Vertical	Pass	
	848.8	30.59	Vertical	Pass	
	824.2	25.07	Horizontal	Pass	
	836.6	25.10	Horizontal	Pass	
FDOF	848.8	25.19	Horizontal	Pass	
EDGE	824.2	23.22	Vertical	Pass	
	836.6	23.43	Vertical	Pass	
	848.8	23.16	Vertical	Pass	

Radiated Power (E.I.R.P) for GSM/EDGE 1900					
		Res	Result		
Mode	Frequency	Max. Peak	Polarization	Conclusion	
		E.I.R.P.(dBm)	Of Max. E.I.R.P.		
	1850.2	29.56	Horizontal	Pass	
	1880.0	29.47	Horizontal	Pass	
COM	1909.8	29.33	Horizontal	Pass	
GSM	1850.2	27.43	Vertical	Pass	
	1880.0	27.28	Vertical	Pass	
	1909.8	27.39	Vertical	Pass	
	1850.2	25.99	Horizontal	Pass	
	1880.0	25.87	Horizontal	Pass	
EDCE	1909.8	25.69	Horizontal	Pass	
EDGE	1850.2	24.44	Vertical	Pass	
	1880.0	24.49	Vertical	Pass	
	1909.8	24.58	Vertical	Pass	



Radiated Power (E.I.R.P) for UMTS band II				
		Res		
Mode	Frequency	Max. Peak E.I.R.P	Polarization	Conclusion
		(dBm)	Of Max. E.I.R.P	Conclusion
	1852.4	20.28	Horizontal	Pass
	1880	20.44	Horizontal	Pass
LIMTS	1907.6	20.73	Horizontal	Pass
UNITS	1852.4	19.11	Vertical	Pass
	1880	19.14	Vertical	Pass
	1907.6	19.06	Vertical	Pass

Radiated Power (ERP) for UMTS band V					
Mode	Frequency	Max. Peak ERP (dBm)	Polarization	Conclusion	
			Of Max. ERP		
	826.4	20.37	Horizontal	Pass	
	836.4	20.54	Horizontal	Pass	
LIMTO	846.6	20.34	Horizontal	Pass	
UMIS	826.4	19.46	Vertical	Pass	
	836.4	19.39	Vertical	Pass	
	846.6	19.27	Vertical	Pass	

Radiated Power (E.I.R.P) for UMTS band IV				
		Result		
Mode	Frequency	Max. Peak E.I.R.P.	Polarization	Conclusion
		(dBm)	Of Max. E.I.R.P.	
UMTS	1712.4	19.49	Horizontal	Pass
	1732.4	19.35	Horizontal	Pass
	1752.6	19.42	Horizontal	Pass
	1712.4	18.55	Vertical	Pass
	1732.4	18.42	Vertical	Pass
	1752.6	18.70	Vertical	Pass

Note: Above is the worst mode data.



6.3. PEAK-TO-AVERAGE RATIO

6.3.1 MEASUREMENT METHOD

Use one of the procedures presented in 4.1 to measure the total peak power and record as PPk. Use one of the applicable procedures presented 4.2 to measure the total average power and record as PAvg. Both the peak and average power levels must be expressed in the same logarithmic units (e.g., dBm). Determine the PAPR from:

PAPR (dB) = PPk (dBm) - PAvg (dBm).

6.3.2 PROVISIONS APPLICABLE

This is the test for the Peak-to-Average Ratio from the EUT.

Power Complementary Cumulative Distribution Function (CCDF) curves provide a means for characterizing the power peaks of a digitally modulated signal on a statistical basis. A CCDF curve depicts the probability of the peak signal amplitude exceeding the average power level. Most contemporary measurement instrumentation include the capability to produce CCDF curves for an input signal provided that the instrument's resolution bandwidth can be set wide enough to accommodate the entire input signal bandwidth. In measuring transmissions in this band using an average power technique, the peak-to-average ratio (PAR) of the transmission may not exceed 13 dB.



6.3.3 MEASUREMENT RESULT

Modes	GSM850(GSM)		
Channel	128	190	251
Chaimer	(Low)	(Mid)	(High)
Frequency	924.2 926.6		040 0
(MHz)	024.2	030.0	040.0
Peak-To-Average Ratio (dB)/GSM	2.64	2.63	2.61
Peak-To-Average Ratio (dB)/EDGE	5.57	5.54	5.65

Modes	PCS1900 (GSM)		
Channel	512	661	810
Channel	(Low)	(Mid)	(High)
Frequency	1950 0	1990	4000.9
(MHz)	1030.2	1000	1909.0
Peak-To-Average Ratio (dB)/GSM	2.63	2.66	2.65
Peak-To-Average Ratio (dB)/EDGE	5.49	5.55	5.53

Modes	UMTS BAND II		
Channel	9262	9400	9538
Channel	(Low)	(Mid)	(High)
Frequency	1952 /	4000	4007.6
(MHz)	1052.4	1000	1907.0
Peak-To-Average Ratio (dB)	4.75	3.06	2.81

Modes	UMTS BAND V		
Channel	4132	4182	4233
Channel	(Low)	(Mid)	(High)
Frequency	806 A	926 A	946 6
(MHz)	020.4	030.4	040.0
Peak-To-Average Ratio (dB)	2.96	2.92	3.01



Modes	UMTS BAND IV		
Channel	8562	8662	8763
	(Low)	(Mid)	(High)
Frequency (MHz)	1712.4	1732.4	1752.6
Peak-To-Average Ratio (dB)	2.96	2.92	3.01



7. OCCUPIED BANDWIDTH

7.1 MEASUREMENT METHOD

1. The Occupied bandwidth, that is the frequency bandwidth such that, below its lower and above its upper Frequency limits, the mean power radiated are each equal to 0.5 percent of the total mean power radiated by a given emission shall be measured.

2. RBW=1~5% of the expected OBW, VBW>=3 x RBW, Detector=Peak, Trace mode=max hold, Sweep=auto couple, and the trace was allowed to stabilize.

7.2 PROVISIONS APPLICABLE

The emission bandwidth is defined as two points, one below the carrier center frequency and one above the carrier center frequency, outside of which all emissions are attenuated at least 26dB below the transmitter power



7.3 MEASUREMENT RESULT

Test Results

Test	Test	Test	Occupied Bandwidth	Emission Bandwidth	Vardiat
Band	Mode	Channel	(KHZ)	(KHZ)	verdict
GSM850 EDGE		LCH	247.1	317	PASS
	GSM	MCH	244.3	311	PASS
		HCH	245.6	308	PASS
	EDGE	LCH	250.8	315	PASS
		MCH	247.3	304	PASS
		НСН	249.2	310	PASS

Teat Band	Test	Test	Occupied Bandwidth	Emission Bandwidth	Vardiat
Test Band	Mode	Channel	(KHZ)	(KHZ)	verdict
GSM1900		LCH	246.3	315	PASS
	GSM	MCH	245.9	302	PASS
		HCH	242.9	306	PASS
		LCH	249.5	311	PASS
	EDGE	MCH	249.0	314	PASS
		НСН	248.9	309	PASS



For GSM

Test Band=GSM850/PCS1900

Test Mode=GSM/EDGE

















Test Band	Test	Test	Occupied Bandwidth	Emission Bandwidth	Verdict
	Mode	Channel	(KHZ)	(KHZ)	
		LCH	4162.7	4703	PASS
VVCDIVIA 950	UMTS	MCH	4162.4	4706	PASS
850		НСН	4170.3	4710	PASS

Test Band	Test	Test	Occupied Bandwidth	Emission Bandwidth	Verdict
	Mode	Channel	(KHZ)	(KHZ)	
		LCH	4168.4	4709	PASS
	UMTS	MCH	4169.1	4713	PASS
1700		HCH	4165.9	4702	PASS

Test Band	Test	Test	Occupied Bandwidth	Emission Bandwidth	Verdict
	Mode	Channel	(KHZ)	(KHZ)	
		LCH	4177.1	4728	PASS
1000	UMTS	MCH	4171.4	4726	PASS
1900		HCH	4179.6	4734	PASS



For WCDMA

Test Band=WCDMA850/WCDMA1700/WCDMA1900

Test Mode=UMTS















8. BAND EDGE

8.1 MEASUREMENT METHOD

1. All out of band emissions are measured with an analyzer spectrum connected to the antenna terminal of the EUT while the EUT at its maximum duty cycle, at maximum power, and at the approximate frequencies. All data rates were investigated to determine the worst case configuration

2. The test set up and general procedure is similar to conducted peak output power test. Only different for setting the measurement configuration of the measuring instrument of Spectrum Analyzer.

3. Start and stop frequency were set such that the band edge would be placed in the center of the plot.

4. Span was set large enough so as to capture all out of band emissions near the band edge.

5. RBW>1% of the emission bandwidth, VBW >=3 x RBW, Detector=RMS, Number of points>=2 x Span/RBW,

Trace mode=max hold, Sweep time=auto couple, and the trace was allowed to stabilize

8.2 PROVISIONS APPLICABLE

As Specified in FCC rules of 22.917(a), 24.238(a)and KDB 971168 D1 V03R01.



8.3 MEASUREMENT RESULT

Test Results

For GSM

Test Band=GSM850/GSM1900

Test Mode=GSM/EDGE













For WCDMA

Test Band=WCDMA850/WCDMA1700/WCDMA1900

Test Mode=UMTS









9. SPURIOUS EMISSION

9.1 CONDUCTED SPURIOUS EMISSION

9.1.1MEASUREMENT METHOD

The following steps outline the procedure used to measure the conducted emissions from the EUT. 1. The level of the carrier and the various conducted spurious and harmonic frequency is measured by means of a calibrated spectrum analyzer. The spectrum is scanned from the lowest frequency generated in the equipment up to a frequency including its 10th harmonic. All out of band emissions are measured with a spectrum analyzer connected to the antenna terminal of the EUT while the EUT is operating at maximum power, and at the approximate frequencies. All data rates were investigated to determine the worst case configuration.

2. Determine frequency range for measurements: From CFR 2.1057 the spectrum should be investigated from the lowest radio frequency generated in the equipment up to at least the 10th harmonic of the carrier frequency. For the equipment of PCS1900 band, this equates to a frequency range of 30 MHz to 19.1 GHz, data taken from 30 MHz to 20 GHz. For GSM850, data taken from 30 MHz to 9 GHz.

3. Determine EUT transmit frequencies: the following typical channelswere chosen to conducted emissions testing.



Typical Channels for testing of GSM 850		
Channel	Frequency (MHz)	
128	824.2	
190	836.6	
251	848.8	

Typical Channels for testing of PCS 1900		
Channel	Frequency (MHz)	
512	1850.2	
661	1880.0	
810	1909.8	

Typical Channels for testing of UMTS band II		
Channel	Frequency (MHz)	
9262	1852.4	
9400	1880	
9538	1907.6	

Typical Channels for testing of UMTS band V		
Channel	Frequency (MHz)	
4132	826.4	
4182	836.4	
4233	846.6	

Typical Channels for testing of UMTS band IV	
Channel	Frequency (MHz)
8562	1712.4
8662	1732.4
8763	1752.6



9.1.2 PROVISIONS APPLICABLE

On any frequency outside frequency band of the USPCS spectrum, the power of any emission shall be attenuated below the transmitter power (P, in Watts) by at least 43+10Log(P) dB. For all power levels +30 dBm to 0 dBm, this becomes a constant specification limit of -13 dBm.



9.1.3MEASUREMENT RESULT

Test Results

Test Band=GSM850/GSM1900

Test Mode=GSM/EDGE











