

# RF Exposure evaluation

**Product Name** : BT module  
**FCC ID** : 2ABN2-RSBR02ABR-01  
**Test Standard** : KDB447498D04 General RF Exposure Guidance v01

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th} \text{ (mW)} = ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20 \text{ cm}}$  is per Formula (B.1). The example values shown in Table B.2 are for illustration only.

Table B.2—Example Power Thresholds (mW)

| Frequency (MHz) | Distance (mm) |    |    |    |     |     |     |     |     |     |     |
|-----------------|---------------|----|----|----|-----|-----|-----|-----|-----|-----|-----|
|                 | 5             | 10 | 15 | 20 | 25  | 30  | 35  | 40  | 45  | 50  |     |
|                 | 300           | 39 | 65 | 88 | 110 | 129 | 148 | 166 | 184 | 201 | 217 |
|                 | 450           | 22 | 44 | 67 | 89  | 112 | 135 | 158 | 180 | 203 | 226 |
|                 | 835           | 9  | 25 | 44 | 66  | 90  | 116 | 145 | 175 | 207 | 240 |
|                 | 1900          | 3  | 12 | 26 | 44  | 66  | 92  | 122 | 157 | 195 | 236 |
|                 | 2450          | 3  | 10 | 22 | 38  | 59  | 83  | 111 | 143 | 179 | 219 |
|                 | 3600          | 2  | 8  | 18 | 32  | 49  | 71  | 96  | 125 | 158 | 195 |
|                 | 5800          | 1  | 6  | 14 | 25  | 40  | 58  | 80  | 106 | 136 | 169 |

Ant gain = -0.89 dBi

MAX output power : [-1.485dBm@2442MHz](#)

ERP=-1.485-0.89-2.15=-4.525dBm

WORSE CASE:

$10^{-0.1485} = 0.710\text{mW} < 2.715 \text{ mW}$

Then SAR evaluation is not required